

DH11

DH11 SPD SEL LOG TST
CZDHDD0

AH-FG23D-MC

1 OF 1 OCT 1985

COPYRIGHT© 1972-85

digital

MADE IN USA

.REM !

IDENTIFICATION

PRODUCT CODE: AC-8456D-MC

PRODUCT NAME: CZDHDDO DH11 SPD SEL LOG TST

DATE: 12-JUNE-1985

MAINTAINER: NAC SOFTWARE ENGINEERING

AUTHOR: MICHAEL DAVIS

THE INFORMATION IN THIS DOCUMENT IS SUBJECT TO CHANGE WITHOUT NOTICE AND SHOULD NOT BE CONSTRUED AS A COMMITMENT BY DIGITAL EQUIPMENT CORPORATION. DIGITAL EQUIPMENT CORPORATION ASSUMES NO RESPONSIBILITY FOR ANY ERRORS THAT MAY APPEAR IN THIS DOCUMENT.

NO RESPONSIBILITY FOR THE USE OR RELIABILITY OF SOFTWARE ON EQUIPMENT THAT IS NOT SUPPLIED BY DIGITAL OR ITS AFFILIATED COMPANIES

COPYRIGHT (C) 1972, 1976, 1985 BY DIGITAL EQUIPMENT CORPORATION, MAYNARD, MASSACHUSETTS.

1. ABSTRACT

THE DH11 SPEED SELECTION LOGIC TEST VERIFIES
THAT THE SPEED SELECTION FUNCTIONS
OF THE LINE PARAMETER REGISTER OPERATE PROPERLY
FOR EACH TRANSMITTER AND RECEIVER LINE. TRANSMITTER
TIMING IS CHECKED FIRST, AND THEN RECEIVER TIMING IS
TESTED. THE PROGRAM USES A RELATIVE TIMING COMPARISON
TO DETERMINE IF LINE SPEED SELECTION IS CORRECT.

NOTE: THE EXTERNAL CLOCK FUNCTIONS (SPEED CODES 16 AND 17)
ARE NOT TESTED.

1
2
3
4
5
6
7
8
9
10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55

- 2. REQUIREMENTS
 - 2.1 EQUIPMENT
 - PDP-11 FAMILY STANDARD COMPUTER WITH 4KW OF MEMORY
 - ASR-33 TELETYPE OR EQUIVALENT
 - DH11 ASYNCHRONOUS MULTIPLEXER
 - DM11 MAINTENANCE CARD INSTALLED
 - 2.2 STORAGE
 - THE PROGRAM LOADS INTO 4KW OF MEMORY
- 3. LOADING PROCEDURE
 - THE STANDART PROCEDURE FOR LOADING ABSOLUTE BINARY TAPES IS TO BE USED
- 4. STARTING PROCEDURE
 - 4.1 CONTROL SWITCH SETTINGS
 - 4.1.1 AFTER PROGRAM LOAD (INITIAL PROGRAM START)
 - ALL CONSOLE SWITCHES DOWN
 - 4.1.2 TO MODIFY DEVICE VECTOR AND CONTROL REGISTER ADDRESSES AFTER PROGRAM RESTART
 - SW00=1
 - 4.1.3 TO START PROGRAM AT SELECTED TEST AFTER PROGRAM RESTART
 - SW01=1
 - 4.2 STARTING ADDRESS
 - THE STARTING ADDRESS FOR ALL TESTS IS 000200
 - THE RESTART ADDRESS FOR ALL TESTS I 0002000
 - THE STARTING ADDRESS TO ENTER A SELECTED TEST IS 000200
 - 4.3 PROGRAM AND/OR OPERATOR ACTION
 - 4.3.1 INITIAL PROGRAM START
 - 4.3.1.1 LOAD PROGRAM INTO MEMORY
 - 4.3.1.2 LOAD ADDRESS 000200
 - 4.3.1.3 CLEAR CONSOLE SWITCHES
 - 4.3.1.4 PRESS START
 - 4.3.1.5 THE PROGRAM WILL TYPE "DH11 SPEED SELECTION LOGIC TEST" AND WILL THEN TYPE "VECTOR ADDRESS" AND WAIT FOR AN INPUT FROM THE TELETYPE KEYBOARD.

4.3 (CONT'D)

4.3.1.6 TYPE IN THE ADDRESS OF THE RECEIVER INTERRUPT VECTOR
FOR THE DH11 TO BE TESTED FOLLOWED BY <CARRIAGE RETURN>

NOTE: WORDS IN ANGLE BRACKETS, I.E. <CARRIAGE RETURN> MEAN THAT
THE TELETYPE KEY WITH THE NAMED FUNCTION SHOULD BE STRUCK

IF AN INCORRECT ADDRESS IS ENTERED, THE PROGRAM
WILL TYPE "?" AND WILL REPEAT THE SECOND MESSAGE OF 4.3.1.5
4.3.1.7 THE PROGRAM WILL TYPE "CONTROL REGISTER ADDRESS-"
AND WAIT FOR AN INPUT FROM THE TELETYPE KEYBOARD

4.3.1.8 TYPE IN THE ADDRESS OF THE SYSTEM CONTROL REGISTER OF THE
DH11 TO BE TESTED FOLLOWED BY <CARRIAGE RETURN>

IF AN INCORRECT ADDRESS IS TYPED, THE PROGRAM WILL TYPE
"?" AND WILL THEN REPEAT THE MESSAGE OF 4.3.1.7
4.3.1.9 THE PROGRAM WILL TYPE "R" TO INDICATE THAT IT IS
ABOUT TO START TESTING, AND THEN TESTING WILL BEGIN

4.3.2 PROGRAM RESTART WITH ALL SWITCHES DOWN

4.3.2.1 PERFORM 4.3.1.2 TO 4.3.1.5

4.3.2.2 THE PROGRAM WILL TYPE "DH11 SPEED SELECTION LOGIC TEST"
AND WILL THEN CONTINUE AS DESCRIBED IN 4.3.1.9

4.3.3 PROGRAM RESTART WITH SW00=1

4.3.3.1 LOAD ADDRESS 000200

4.3.3.2 SET SW01=1

4.3.3.3 PRESS START

4.3.3.4 THE PROGRAM WILL PERFORM AS DESCRIBED IN 4.3.1.5 TO 4.3.1.9

4.3.4 PROGRAM RESTART WITH SW01=1

4.3.4.1 LOAD ADDRESS 000200

4.3.4.2 SET SW01=1

4.3.4.3 PRESS START

4.3.4.4 THE PROGRAM WILL TYPE "DH11 SPEED SELECTION LOGIC TEST"
AND WILL THEN TYPE "TEST PC-" AND WILL WAIT FOR AN INPUT
FROM THE TELETYPE KEYBOARD

4.3.4.5 TYPE IN THE ADDRESS OF THE TEST AT WHICH THE PROGRAM IS TO
BE STARTED FOLLOWED BY <CARRIAGE RETURN>

4.3.4.6 THE PROGRAM WILL TYPE R TO INDICATE THAT IT HAS STARTED
AND WILL START TESTING AT THE SELECTED TEST.

NOTE: CARE MUST BE TAKEN WHEN THIS FEATURE IS USED, SINCE
THERE IS NO PROTECTION AGAINST SELECTING AN ADDRESS THAT
IS IN THE MIDDLE OF A TEST

NOTE: IF IT IS DESIRED TO LOOP ON THE TEST THAT IS SELECTED
SET SW14=1 BEFORE ENTERING THE TEST ADDRESS

5. OPERATING PROCEDURE

5.1 OPERATIONAL SWITCH SETTINGS

SW15=1, HALT ON ERROR
SW14=1, LOOP ON CURRENT TEST
SW13=1, SUPPRESS ERROR TYPEOUT
SW11=1, INHIBIT ITERATIONS
SW10=1, ESCAPE TO NEXT TEST ON ERROR
SW09=1, FREEZE VARIABLE PARAMETER IN CURRENT TEST
SW01=1, START PROGRAM AT SELECTED TEST
SW00=1, CHANGE PARAMETERS AT PROGRAM RESTART

5.2 SUBROUTINE ABSTRACTS

5.2.1 TRAPCATCHER (LOCATIONS 000000-000776)

THIS ROUTINE IS USED TO INTERCEPT UNEXPECTED INTERRUPTS AND TRAPS. THE AREA FROM 000000-000776 IS LOADED WITH THE FOLLOWING SEQUENCE

2
0
4
0
:
:
772
0
776
0

IF AN UNEXPECTED INTERRUPT OR TRAP OCCURS, THE PROGRAM WILL HALT WITH THE PC 2 GREATER THAN THE ADDRESS TO WHICH THE PROGRAM TRAPPED. THE PROCESSOR STACK MAY BE EXAMINED TO DETERMINE WHERE THE PROGRAM WAS WHEN THE TRAP OR INTERRUPT OCCURED.

5.2.2 START (PROGRAM INITIALIZATION)

THIS ROUTINE INITIALIZES ALL PROGRAM FLAGS AND COUNTERS, TYPES THE PROGRAM TITLE MESSAGE, AND INPUTS THE VECTOR AND CONTROL REGISTER ADDRESSES OF THE DH11 TO BE TESTED.

5.2.3 BEGIN (PROGRAM START AND RESTART)

THIS ROUTINE IS ENTERED IMMEDIATELY AFTER "START" AND EACH TIME A PROGRAM PASS HAS BEEN COMPLETED. THE ROUTINE SETS UP THE PROCESSOR STACK AND STATUS WORD AND THEN TRANSFERS CONTROL TO THE TEST AT WHICH TESTING WILL BEGIN. IF SW01=0 WHEN THIS ROUTINE IS ENTERED TESTING WILL START AT T1 (TEST 1). IF SW01=1 WHEN THIS ROUTINE IS ENTERED, TESTING WILL START AT THE PC ENTERED FROM THE TELETYPE KEYBOARD.

5.2.4 EOP (END OF PASS)

THIS ROUTINE IS ENTERED ONCE PER PASS AFTER ALL TESTS HAVE BEEN COMPLETED. THIS ROUTINE TYPES THE MAINDEC IDENTIFICATION CODE OF THE PROGRAM, CLEARS ERROR FLAGS AND UPDATES THE PASS COUNT. IF THE PROGRAM WAS LOADED UNDER ACT11 OR DDP, THE ROUTINE CHECKS FOR RETURN TO THE ACT11 OR DDP MONITOR. IF THE PROGRAM IS NOT UNDER MONITOR CONTROL, THE ROUTINE TRANSFERS TO BEGIN.

5.2.5 SCOPER (SCOPE LOOP AND ITERATION HANDLER)

THIS ROUTINE IS ENTERED EACH TIME A TEST IS COMPLETED. THE ROUTINE CHECKS FOR THE FOLLOWING UPON ENTRY
A) IF SW10=1, THE ROUTINE WILL TRANSFER TO THE NEXT TEST IN SEQUENCE, AFTER CLEARING ERROR FLAGS.
B) IF SW11=1, THE ROUTINE WILL TRANSFER TO THE NEXT TEST IN SEQUENCE, AFTER CLEARING ERROR FLAGS.
C) IF SW14=1, THE ROUTINE WILL LOOP ON THE CURRENT TEST REGARDLESS OF THE ITERATION COUNT.

IF NONE OF THE ABOVE IS TRUE, THE ROUTINE WILL ADD 1 TO THE COUNT OF TEST ITERATIONS, AND COMPARE THIS VALUE TO THE NUMBER OF ITERATIONS THAT SHOULD BE PERFORMED. IF THESE NUMBERS ARE EQUAL, THE ROUTINE WILL TRANSFER TO THE NEXT TEST IN SEQUENCE. IF THE NUMBERS ARE NOT EQUAL, THE TEST CURRENTLY IN PROGRESS WILL BE REPEATED.

5.2.6 SCOP1R (FREEZE ON CURRENT DATA)

THE CALL TO THIS ROUTINE FOLLOWS IMMEDIATELY AFTER THE CALL TO THE ERROR HANDLER IN THOSE TESTS THAT HAVE VARIABLE PARAMETERS. THIS ROUTINE IS ALWAYS ENTERED IN THOSE TESTS, WHETHER OR NOT AN ERROR OCCURS. IF SW09=1, THE ROUTINE WILL TRANSFER CONTROL BACK TO THE TEST AT A POINT WHICH WILL ALLOW REPEATING THE FUNCTION UNDER TEST CONTINUOUSLY WITH THE SAME DATA. IF THIS OPTION IS SELECTED, THE ROUTINE "SCOPER" IS NEVER ENTERED AND ITERATION COUNTS WILL NOT BE UPDATED.

5.2.7 ERRORS (ERROR HANDLER)

THIS ROUTINE IS ENTERED UPON ERROR DETECTION ONLY.
WITH ALL CONSOLE SWITCHES DOWN, THE ROUTINE PROCEEDS AS FOLLOWS:

- A) THE PC OF THE INSTRUCTION THAT CALLED THE ERROR HANDLER IS ACCESSED THRU THE STACK, AND THEN THE EMT INSTRUCTION ITSELF IS FETCHED. THE 8 LSB OF THE EMT INSTRUCTION ARE THE ERROR CODE. THIS CODE IS USED TO ACCESS A TABLE OF ERROR MESSAGES AND ERROR DATA STORAGE LOCATIONS.
- B) IF THE TEST THAT FAILED DID NOT FAIL PREVIOUSLY DURING THIS PASS, A COMPLETE ERROR REPORT IS MADE IF THE TEST THAT FAILED FAILED MOR THAT ONCE DURING THE CURRENT PASS, ONLY THE DATA RELATING TO THE FAILUER IS TYPED. IF SW13=1, NO ERROR TYPEOUT IS MADE.
- C) THE ROUTINE NOW CHECKS FOR HALT ON ERROR. IF SW15=1 THE PROGRAM WILL HALT WITH THE PC OF THE CALL TO THE ERROR ROUTINE IN R0. IF SW15=0, THE PROGRAM WILL NOT HALT, BUT WILL CHECK FOR ESCAPE TO NEXT TEST.
- D) IF SW10=0, THE ROUTINE WILL RETURN TO THE TEST IN PROGRESS. IF SW10=1, THE ROUTINE WILL ABORT THE CURRENT TEST, AND TRANSFER TO THE NEXT TEST IN SEQUENCE, THRU THE ROUTINE "SCOPER".

5.2.8 TRPSRV (TRAP DECODE AND DISPATCH)

THIS ROUTINE DECODES THE 8 LSB OF THE TRAP INSTRUCTION THAT CAUSED TH PROGRAM INTERRUPT, AND TRANSFERS CONTROL TO THE ROUTINE THRU THE TABLE "TRPTAB" USING THE 8 LSB OF THE TRAP INSTRUCTION AS AN OFFSET TO THE POINTER TO THE ROUTINE TO BE ENTERED.

1
2
3
4
5
6
7
8
9
10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55

5.3 PROGRAM AND OR OPERATOR ACTION

5.3.1 PROGRAM START WITH ALL SWITCHES DOWN

5.3.1.1 REFER TO SECTIONS 4.3.1 AND 4.3.2 FOR INITIAL PROGRAM BEHAVIOR.

5.3.1.2 AFTER "R" HAS BEEN TYPED BY THE PROGRAM, TEST EXECUTION WILL BEGIN. EACH TEST WILL BE REPEATED A SELECTED NUMBER OF ITERATIONS (SEE LISTING FOR EXACT NUMBER FOR EACH TEST) AND THEN THE PROGRAM WILL PROCEED TO THE NEXT TEST.

5.3.1.3 WHEN ALL ITERATIONS HAVE BEEN COMPLETED, THE PROGRAM WILL TYPE "CZDHD-D" AND THEN RESTART TESTING AT TEST 1 (LOCATION T1 IN THE PROGRAM).

5.3.1.4 IF AN ERROR OCCURS, THE PROGRAM WILL TYPE AN APPROPRIATE ERROR MESSAGE, AND THEN CONTINUE THE TEST IN PROGRESS.

5.3.2 PROGRAM START WITH SW00=1

THE PROGRAM WILL PERFORM AS DESCRIBED IN 4.3.1 AND 5.3.1

5.3.3 PROGRAM START WITH SW01=1

5.3.3.1 REFER TO SECTION 4.3.4 FOR INITIAL PROGRAM BEHAVIOR

5.3.3.2 TEST EXECUTION WILL START AT THE ADDRESS SPECIFIED AND WILL CONTINUE AS DESCRIBED IN 5.3.1.2

5.3.3.3 AFTER "CZDHD-D" HAS BEEN TYPED, THE PROGRAM WILL RESUME TESTING AT TEST 1

5.3.4 PROGRAM OPERATION WITH SW15=1

SAME AS 5.3.1, EXCEPT THAT IN THE CASE OF AN ERROR, THE PROGRAM WILL HALT AFTER THE ERROR TYPEOUT, AND THE PC+2 OF THE CALL TO THE ERROR ROUTINE WILL BE DISPLAYED IN R0.

5.3.5 PROGRAM OPERATION WITH SW13=1

SAME AS 5.3.1 EXCEPT THAT NO ERROR TYPEOUTS WILL OCCUR

5.3.6 PROGRAM OPERATION WITH SW11=1

SAME AS 5.3.1 EXCEPT THAT EACH TEST WILL BE REPEATED ONCE ONLY

5.3.7 PROGRAM OPERATION WITH SW10=1

SAME AS 5.3.1, EXCEPT THAT IN THE CASE OF AN ERROR THE CURRENT TEST WILL BE ABORTED, AND THE PROGRAM WILL PROCEED TO THE NEXT TEST IN SEQUENCE.

5. (CONT'D)

5.3.8 PROGRAM OPERATION WITH SW14=1, OR SW09=1

THESE FUNCTIONS ARE NORMALLY USED FOR TROUBLE SHOOTING.
SEE SECTION 6.3 FOR THEIR USE.

6. ERRORS

6.1 ERROR HALTS

THE ERROR MESSAGE FORMAT FOR ALL ERROR TYPEOUTS
IS AS FOLLOWS

PC+2 MESSAGE
HEADER (IF APPLICABLE)
DATA (IF APPLICABLE)

WHERE

PC+2 IS THE ADDRESS OF THE CALL TO THE ERROR HANDLER + 2
MESSAGE IS AN ASCII MESSAGE DESCRIBING (BRIEFLY) THE FAILURE
HEADER IS A DESCRIPTION OF THE DATA TO FOLLOW
DATA IS OCTAL INFORMATION RELATING TO THE CAUSE OF THE FAILURE
IF THE SAME ERROR OCCURS IN A GIVEN TEST ON THE SAME
PASS, AND IF DATA IS ASSOCIATED WITH THAT ERROR, ONLY
DATA IS TYPE ON SUCCEEDING ERROR TYPEOUTS

IF NO DATA IS ASSOCIATED WITH THE ERROR
THE COMPLETE ERROR MESSAGE IS TYPED.

6.1.1 ERROR DESCRIPTIONS

SEE LISTING FOR DETAILS OF ERRORS

6.2 ERROR RECOVERY

6.2.1 SW15=0

IF THE PROGRAM IS RUN WITH SW15=0, NO OPERATOR ACTION IS
REQUIRED TO CONTINUE TESTING

6.2.2 SW15=1

IF THE PROGRAM IS RUN WITH SW15=1, TO CONTINUE TESTING
AFTER THE PROGRAM HAS HALTED, PRESS THE PROCESSOR
CONSOLE CONTINUE SWITCH

6.2.3 ILLEGAL INTERRUPTS

IF AN INTERRUPT OCCURS TO A VECTOR ADDRESS NOT
SELECTED DURING PROGRAM INITIALIZATION, THE PROGRAM WILL
HALT IN THE TRAPCATCHER. THE ADDRESS AT WHICH
THE PROGRAM HALTS IS 2 GREATER THAN THE ADDRESS
TO WHICH THE INTERRUPT OCCURED. THE PROGRAM MUST BE
RESTARTED AT 200 TO RECOVER FROM THIS ERROR.

1
2
3
4
5
6
7
8
9
10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46

6.3 SCOPE LOOPING

6.3.1 TO SCOPE ON A SPECIFIC TEST, SET SW14=1 AND SW13=1
THIS WILL CAUSE THE PROGRAM TO CONTINUOUSLY LOOP ON THE
SAME TEST, AND WILL CAUSE ALL ERROR TYPEOUTS TO BE INHIBITED

6.3.2 TO SCOPE ON A SPECIFIC VALUE OF A PARAMETER WITHIN
A TEST, SET SW09=1 TO FREEZE THE DATA
(SEE LISTING FOR THOSE TESTS THAT INCORPORATE THIS FEATURE)

6. (CONT'D)

6.3.3 PROGRAM START TO SCOPE LOOP ON SELECTED TEST

PERFORM SECTION 4.3.4 WITH SW14=1

7. RESTRICTIONS

7.1 STARTING

THE DH11 TEST CARD MUST BE INSTALLED

7.2 RUNNING

NONE

8. MISCELLANEOUS

8.1 EXECUTION TIME

THE TIME FOR ONE PASS OF THE PROGRAM (END OF
TYPEOUT OF CZDHD-D TO END OF TYPEOUT OF CZDHD-D)
IS GIVEN FOR VARIOUS PROCESSORS IN THE TABLE BELOW

PROCESSOR	TIME
PDP-11/05,10	
PDP-11/20	
PDP-11/40	
PDP-11/45	

9. PROGRAM DESCRIPTION

TRANSMITTER LINE SPEED SELECTION IS TESTED ON A LINE BY LINE BASIS USING A RELATIVE TIMING TECHNIQUE TO DETERMINE IF SPEED SELECTION FOR A SELECTED LINE IS CORRECT.

THE TEST PROCEEDS AS FOLLOWS:

A SPEED OF 50 BAUD IS SET FOR A SELECTED LINE, AND A COUNT IS RECORDED FROM THE TIME THAT THE BAR BIT IS SET FOR THAT LINE TO THE TIME THAT TRANSMITTER DONE IS SET. THREE CHARACTERS ARE TRANSMITTED. AT THE SAME TIME, A TIMEOUT COUNTER IS STARTED. IF THE TIMEOUT COUNTER DECREMENTS TO 0 BEFORE TRANSMITTER DONE IS RECEIVED, AN ERROR MESSAGE IS REPORTED. IF THE TIMEOUT DOES NOT OCCUR, THE TIME COUNT IS STORED, AND THE NEXT LINE SPEED IS SELECTED. TRANSMISSION IS RESTARTED AND THE TIME COUNT, AND TIMEOUT ARE RESTARTED. WHEN TRANSMITTER DONE IS RECEIVED, THE TIME COUNTS FOR THE CURRENT SPEED AND THE PREVIOUS SPEED ARE COMPARED. IF THE TIME COUNT FOR THE CURRENT SPEED IS GREATER THAN OR EQUAL TO THE COUNT FOR THE PREVIOUS SPEED, A TIMING ERROR HAS OCCURED, SINCE A HIGHER SELECTED BAUD RATE SHOULD MEAN THAT THE NUMBER OF COUNTS RECORDED IS LESS THAN AT A LOWER BAUD RATE. THIS PROCEDURE IS REPEATED FOR ALL SPEED CODES 1-15.

THE NEXT GROUP OF TESTS VERIFIES THAT RECEIVER SPEED SELECTION IS CORRECT, BY USING A RELATIVE TIMING COMPARISON AS DESCRIBED ABOVE. A CHARACTER IS TRANSMITTED AS ABOVE AND THE TIME FROM THE START OF TRANSMISSION TO THE TIME THAT CHARACTER AVAILABLE IS RECEIVED IS RECORDED. ALSO, THE TIMEOUT COUNT IS DECREMENTED. IF THE TIMEOUT COUNTER DECREMENTS TO 0 BEFORE CHARACTER AVAILABLE OCCURS, AN ERROR HAS OCCURED. THE PROCEDURE IS REPEATED AT THE NEXT HIGHEST BAUD RATE AND A COMPARISON IS MADE AS IN THE TRANSMITTER TESTS IF THE TIME COUNT AT THE PRESENT BAUD RATE IS GREATER THAN OR EQUAL TO THE PREVIOUS BAUD RATE, AN ERROR HAS OCCURED.

10. LISTING

!

```
1      ; DHMAC-A - DH11 MACRO LIBRARY
2      ; COPYRIGHT 1985, DIGITAL EQUIPMENT CORP., MAYNARD, MASS. 01~54
3
4
5      .LIST  ME
6      .NLIST MC,MD,CMD
7
104
119
131
148
158
167
303
339
373
520
563
595
607
652
664
691
712
743      ; CMS REPLACEMENT HISTORY
744
745
746      ; *9 SKONETSKI 26-APR-1985 16:23:08 "FIXED TYPO CAUSING ASSEMBLY ERRORS"
747      ; *8 SKONETSKI 22-APR-1985 16:48:03 "TYPO ERROR IN VECTOR CHANGE CODE SOURCE FIXED"
748      ; *7 SKONETSKI 22-APR-1985 16:26:04 "ADDED CODE TO SET VECTORS FOR PWR FAIL, ERRORS, AND EMT
TRAPS."
749      ; *6 SKONETSKI 22-APR-1985 14:22:35 "FIXED BRANCH ERROR IN END OF PASS ROUTINE"
750      ; *5 SKONETSKI 22-APR-1985 08:28:54 "FIXED BUG (AN OCTASC MACRO CALL WAS WRONG) AND ADDED A
CLEAN END OF PASS
MESSAGE.
751      ; *4 SKONETSKI 18-APR-1985 14:20:15 "ADDED SOFTWARE SWITCH REG SUPPORT, PUT UNTESTED"
752      ; *3 SKONETSKI 12-APR-1985 10:34:52 "FIXED PROBLEMS WITH SPURIOUS CR/LFS"
753      ; *2 SKONETSKI 11-APR-1985 16:00:24 "ADDED MACRO FROM SYSMAC.SHL THAT SIZES FOR SOFTWARE SWI
TCH REGISTER"
754      ; *1 SKONETSKI 11-APR-1985 15:49:05 "LIBRARY FOR DH11 DIAGNOSTICS"
```

; 3

2
3
5 000CC0

.LIST ME
.NLIST MC,MD,CND
.HEADER +/1976,1985/,+/DH11 SPEED SELECTION LOGIC TEST/,+/CZDHD-D0/

;STARTING PROCEDURE
;LOAD PROGRAM
;LOAD ADDRESS 000200
;PRESS START
;PROGRAM WILL TYPE DH11 SPEED SELECTION LOGIC TEST
;PROGRAM WILL TYPE "VECTOR ADDRESS-"
;TYPE IN THE ADDRESS OF THE RECEIVER INTERRUPT VECTOR
;FOR THE DH11 TO BE TESTED, FOLLOWED BY <CARRIAGE RETURN>
;PROGRAM WILL TYPE "CONTROL REGISTER ADDRESS-"
;TYPE IN THE ADDRESS OF THE SYSTEM CONTROL REGISTER
;FOR THE DH11 TO BE TESTED, FOLLOWED BY <CARRIAGE RETURN>
;PROGRAM WILL TYPE "R" TO INDICATE THAT TESTING HAS STARTED
;AT THE END OF A PASS, PROGRAM WILL TYPE " CZDHD-D0 "
;AND THEN RESUM TESTING

; 3

000000

.TITLE CZDHD-D0
.ENABLE ABS
.NLIST MC,MD,CND
.LIST ME
.SYMBOLS

6 000000

;SWITCH REGISTER OPTIONS

100000
040000
020000
010000
004000
002000
001000
000400
000100
000040
000020
000010
000004
000002
000001

SW15=100000
SW14=40000
SW13=20000
SW12=10000
SW11=4000
SW10=2000
SW09=1000
SW08=400
SW06=100
SW05=40
SW04=20
SW03=10
SW02=4
SW01=2
SW00=1

;=1,HALT ON ERROR
;=1,LOOP ON CURRENT TEST
;=1,INHIBIT ERROR TYPEOUT

;=1,INHIBIT ITERATIONS
;=1,ESCAPE TO NEXT TEST ON ERROR
;=1,LOOP WITH CURRENT DATA

; 3

;RESTART PROGRAM AT SELECTED TEST
;RESELECT VECTOR AND CONTROL REGISTER
;ADDRESS AFTER PROGRAM RESTART

0

;REGISTER DEFINITIONS

000000	R0=#0	;GENERAL REGISTER
000001	R1=#1	;GENERAL REGISTER
000002	R2=#2	;GENERAL REGISTER
000003	R3=#3	;GENERAL REGISTER
000004	R4=#4	;GENERAL REGISTER
000005	R5=#5	;GENERAL REGISTER
000006	SP=#6	;PROCESSOR STACK POINTER
000007	PC=#7	;PROGRAM COUNTER

;LOCATION EQUIVALENCIES

	;SWR=177570	;CONSOLE SWITCH REGISTER	; 3
	;LIGHTS=177570	;PDP-11/45 DISPLAY REGISTER	; 4
177776	PS=177776	;PROCESSOR STATUS WORD	; 4
015120	STACK=ENDCOD+200	;START OF PROCESSOR STACK	; 3

;INSTRUCTION DEFINITIONS

005746	PUSH1SP=5746	;DECREMENT PROCESSOR STACK 1 WORD
005726	POP1SP=5726	;INCREMENT PROCESSOR STACK 1 WORD
010046	PUSHR0=10046	;SAVE R0 ON STACK
012600	POPR0=12600	;RESTORE R0 FROM STACK
024646	PUSH2SP=24646	;DECREMENT STACK TWICE
022626	POP2SP=22626	;INCREMENT STACK TWICE

```

;
.MACRO HLT      $A
          EMT    $A
.ENDM HLT
;

```

100000	BIT15=100000
040000	BIT14=40000
020000	BIT13=20000
010000	BIT12=10000
004000	BIT11=4000
002000	BIT10=2000
001000	BIT09=1000
000400	BIT08=400
000200	BIT07=200
000100	BIT06=100
000040	BIT05=40
000020	BIT04=20
000010	BIT03=10
000004	BIT02=4
000002	BIT01=2
000001	BIT00=1
	.CATCH

1 000000

; 3

000146	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000150	000152	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000152	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000154	000156	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000156	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000160	000162	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000162	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000164	000166	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000166	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000170	000172	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000172	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000174	000176	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000176	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000200	000202	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000202	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000204	000206	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000206	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000210	000212	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000212	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000214	000216	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000216	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000220	000222	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000222	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000224	000226	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000226	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000230	000232	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000232	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000234	000236	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000236	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000240	000242	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000242	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000244	000246	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000246	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000250	000252	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000252	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000254	000256	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000256	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000260	000262	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000262	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000264	000266	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000266	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000270	000272	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000272	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000274	000276	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000276	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000300	000302	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000302	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000304	000306	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000306	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000310	000312	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000312	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000314	000316	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000316	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000320	000322	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000322	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000324	000326	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000326	000000	HALT	;EXAMINE STACK TO FIND CAUSE

000330	000332	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000332	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000334	000336	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000336	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000340	000342	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000342	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000344	000346	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000346	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000350	000352	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000352	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000354	000356	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000356	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000360	000362	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000362	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000364	000366	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000366	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000370	000372	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000372	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000374	000376	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000376	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000400	000402	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000402	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000404	000406	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000406	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000410	000412	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000412	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000414	000416	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000416	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000420	000422	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000422	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000424	000426	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000426	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000430	000432	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000432	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000434	000436	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000436	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000440	000442	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000442	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000444	000446	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000446	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000450	000452	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000452	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000454	000456	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000456	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000460	000462	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000462	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000464	000466	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000466	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000470	000472	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000472	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000474	000476	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000476	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000500	000502	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000502	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000504	000506	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000506	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000510	000512	.+2	;UNEXPECTED TRAP TO THIS LOCATION

000512	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000514	000516	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000516	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000520	000522	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000522	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000524	000526	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000526	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000530	000532	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000532	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000534	000536	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000536	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000540	000542	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000542	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000544	000546	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000546	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000550	000552	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000552	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000554	000556	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000556	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000560	000562	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000562	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000564	000566	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000566	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000570	000572	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000572	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000574	000576	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000576	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000600	000602	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000602	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000604	000606	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000606	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000610	000612	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000612	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000614	000616	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000616	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000620	000622	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000622	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000624	000626	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000626	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000630	000632	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000632	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000634	000636	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000636	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000640	000642	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000642	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000644	000646	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000646	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000650	000652	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000652	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000654	000656	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000656	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000660	000662	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000662	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000664	000666	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000666	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000670	000672	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000672	000000	HALT	;EXAMINE STACK TO FIND CAUSE

000674	000676	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000676	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000700	000702	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000702	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000704	000706	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000706	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000710	000712	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000712	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000714	000716	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000716	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000720	000722	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000722	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000724	000726	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000726	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000730	000732	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000732	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000734	000736	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000736	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000740	000742	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000742	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000744	000746	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000746	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000750	000752	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000752	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000754	000756	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000756	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000760	000762	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000762	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000764	000766	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000766	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000770	000772	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000772	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000774	000776	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000776	000000	HALT	;EXAMINE STACK TO FIND CAUSE
1 001000		.SETVEC	

```

0          000200      000167 000600      .-200      ;STANDARD INTERRUPT VECTORS
          000200      000167 000600      JMP      START      ;GO TO START OF PROGRAM

1 000204          .TRPDEF

          ;DEFINITIONS FOR TRAP SUBROUTINE CALLS
          ;POINTERS TO SUBROUTINES CAN BE FOUND STARTING
          ;AT LOCATION "TRPTAB"

000204      TRPDEF SCOPE,+/SCOPE LOOP AND ITERATION HANDLER/
          104400      SCOPE=TRAP+Y      ;SCOPE LOOP AND ITERATION HANDLER
          000001      Y=Y+1

000204      TRPDEF TYPE,+/TELETYPE OUTPUT ROUTINE/
          104401      TYPE=TRAP+Y      ;TELETYPE OUTPUT ROUTINE
          000002      Y=Y+1

000204      TRPDEF OCTASC,+/OCTAL TO ASCII CONVERSION/
          104402      OCTASC=TRAP+Y      ;OCTAL TO ASCII CONVERSION
          000003      Y=Y+1

000204      TRPDEF INSTR,+/INPUT ASCII STRING/
          104403      INSTR=TRAP+Y      ;INPUT ASCII STRING
          000004      Y=Y+1

000204      TRPDEF INSTER,+/STRING INPUT ERROR/
          104404      INSTER=TRAP+Y      ;STRING INPUT ERROR
          000005      Y=Y+1

000204      TRPDEF PARAM,+/CONVERT STRING TO OCTAL, CHECK LIMITS/
          104405      PARAM=TRAP+Y      ;CONVERT STRING TO OCTAL, CHECK LIMITS
          000006      Y=Y+1

000204      TRPDEF SAVOSP,+/SAVE R0-R5, PC/
          104406      SAVOSP=TRAP+Y      ;SAVE R0-R5, PC
          000007      Y=Y+1

000204      TRPDEF RESO5,+/RESTORE R0-R5/
          104407      RESO5=TRAP+Y      ;RESTORE R0-R5
          000010      Y=Y+1

000204      TRPDEF SCOPE1,+/CHECK FOR FREEZE ON CURRENT DATA/
          104410      SCOPE1=TRAP+Y      ;CHECK FOR FREEZE ON CURRENT DATA
          000011      Y=Y+1

2          .MACRO CODEM1
3          MOV      DHSSR,DHSLR      ;SET UP ADDRESS OF SILO
4          INC      DHSLR      ;STATUS REGISTER HIGH BYTE
5          .ENDM CODEM1
6 000204      .START DHRVEC,3,4,DHSCR,0,177776,7,10,...,1

```



```

      .ENDC
      .IF NB
      TRACER: MOV    <>
              SXT    #1$,0#10
              MOV    R0
              MOV    #RTT,TRTRET
              BR     2$
      1$:     MOV    #RTI,TRTRET
              MOV    #12,0#10
              MOV    #TRTRET,0#16
      .ENDC
      .IF NB
      .IF B   <DHRVEC>
      .IFF    BR     VEC2
              TST    INIFLG
              BEQ    VEC2
      .ENDC
      VEC1:   BIT    #SW00,0SWR
              BEQ    BEGIN
      VEC2:   MOV    #300,R1
              MOV    #302,R2
              MOV    #4,R3
      1$:     MOV    R2,(R1)
              CLR    (R2)
              ADD    R3,R1
              ADD    R3,R2
              CMP    R1,#1000
              BNE    1$
              INSTR  MVECTOR
              PARAM  300
              770
              DHRVEC
      .BYTE   3
      .BYTE   4
              INSTR  MREGAD
              PARAM  0
              177776
              DHSCR
      .BYTE   7
      .BYTE   10
      .ENDC
      .IF NB
      .IF B   <1>
      CODEM1
      MOV    DHSSR,DHSLR
      INC    DHSLR
      .ENDC
      TST    INIFLG
      BNE    BEGIN
      COM    INIFLG
      .PROGRAM START
      .CHECK FOR PROGRAM START AT SELECTED ADDRESS

```

001162 000404

001164 032777 000001 177606

001172 001445

001174 012701 000300

001200 012702 000302

001204 012703 000004

001210 010211

001212 005012

001214 060301

001216 060302

001220 020127 001000

001224 001371

001226 104403

001230 014306

001232 104405

001234 000300

001236 000770

001240 014000

001242 003

001243 004

001244 104403

001246 014330

001250 104405

001252 000000

001254 177776

001256 013756

001260 007

001261 010

001262

001262 016767 012506 012506

001270 005267 012502

001274 005767 012550

001300 001002

001302 005167 012542

;SET UP ILLEGAL INSTRUCTION TRAP RETURN

;DO 11/40, 11/45 INSTRUCTION

;11/40,45 RTT RETURN FROM TRACE TRAP

;1105,10,20 RTI RETURN FROM TRACE TRAP

;RESTORE TRAPCATCHER

;SET UP TRACE TRAP VECTOR

; 3

;IF INITIALIZE FLAG=0

;GET VECTOR AND CSR ADDRESS

;IF SW00=1, GET NEW VECTOR ; 4

;AND CSR ; 4

; 4

; 4

;RESTORE TRAPCATCHER

;IN FLOATING VECTOR AREA

;INPUT ADDRESS OF DEVICE VECTOR

;MESSAGE "VECTOR ADDRESS-"

;CONVERT STRING TO OCTAL

;LOW LIMIT

;HIGH LIMIT ; 3

;LOCATIONS TO BE FILLED

;NUMBER OF LOCATIONS

;LSB MASK

;INPUT ADDRESS OF DEVICE CSR

;MESSAGE "CONTROL REGISTER ADDRESS-"

;CONVERT STRING TO OCTAL

;LOW LIMIT

;HIGH LIMIT

;LOCATIONS TO BE FILLED

;NUMBER OF LOCATIONS

;LSB MASK

;SET UP ADDRESS OF SILO

;STATUS REGISTER HIGH BYTE

;IF INITIALIZATION FLAG

;IS CLEARED

;SET IT

; 3

001306	012767	000340	176462	BEGIN:	MOV	#340,PS	;LOCK OUT INTERRUPTS	
001314	012706	015120			MOV	#STACK,SP	;SET UP PROCESSOR STACK	
001320	032777	000002	177452		BIT	#SW01,#SWR	;IF SW01=1	; 4
001326	001410				BEQ	1#	;GET PC FOR PROGRAM START	
001330	104403				INSTR		;GET PC	
001332	014517				MTSTPC		;MESSAGE "TEST PC"	
001334	104405				PARAM		;CONVERT STRING TO OCTAL	
001336	000000				0			
001340	017500				17500			
001342	014016				RETRN			
001344	001			.BYTE	1			
001345	001			.BYTE	1			
001346	000410				BR	2#		
001350	012767	001400	012440	1#:	MOV	#T1,RETRN	;NORMAL START, TEST 1	
001356	005767	012470			TST	STFLG	;IF LOOPING, BYPASS TYPEOUT	
001362	001004				BNE	3#		
001364	005167	012462			COM	STFLG		
001370	104401	014513		2#:	TYPE	,MR	;TYPE "R" TO INDICATE START	
001374	000177	012416		3#:	JMP	#RETRN	;START TESTING	; 3

```

3      000020      XLINE=LINE
4      000000      LINE=0
5      000000      XBIT=BITX
6      000001      BITX=1
8      000020      .REPT 20
9      SPEED \LINE,\BITX,3,+//,2000,+/TRANSMITTER/
10     .NLIST
11     LINE=LINE+1
12     BITX=BITX+BITX
13     .LIST
14     .ENDR
001400 SPEED \LINE,\BITX,3,+//,2000,+/TRANSMITTER/

;TRANSMITTER LINE SPEED SELECTION TEST
;TRANSMIT 3 CHARACTERS AT A SELECTED SPEED ON LINE 0
;VERIFY THAT TRANSMITTER DONE OCCURS AT THE SELECTED SPEED
;VERIFY THAT THE AMOUN OF TIME TAKEN IS LESS
;AT THIS SPEED THAN AT THE PREVIOUSLY SELECTED SPEED

001400 TS \XN,10,5+,1+
001400 012767 000340 176370 T1: MOV #340,PS ;DISABLE ALL INTERRUPTS
001406 012767 000010 012410 MOV #10,ICOUNT ;SET UP FOR 10 ITERATIONS
001414 012767 001620 012376 MOV #5+,ESCAPE ;SET UP TO ESCAPE TO NEXT TEST
001422 012767 001456 012372 .IF NB <1+> MOV #1+,FREEZ1 ;SET UP TO LOOP WITH DATA ; 3
001430 000002 .ENDC
001434 012705 000000 XN=XN+1 MOV #0,R5 ;LINE 0 WILL BE TESTED
001434 012700 002000 MOV #2000,R0 ;CONSTANT FOR SELECTION
001440 012701 000015 MOV #15,R1 ;OF INITIAL (LOWEST) SPEED
001444 012704 000001 MOV #1,R4 ;15 DIFFERENT SPEEDS WILL BE TESTED
001450 012767 177777 012402 MOV #1,TIME1 ;BINARY CODE FOR INITIAL SPEED
001456 012777 004000 012272 1+: MOV #BIT11,0DHSCR ;INITIALIZE COMPARISION VALUE
001464 010577 012266 MOV #5,0DHSCR ;CLEAR INTERFACE
001470 005077 012270 CLR 0DHBA ;SELECT LINE 0 FOR TESTING
001474 012777 177775 012264 MOV #3,0DHBC ;CLEAR BUS ADDRESS
001502 010077 012254 MOV R0,0DHLPR ;SET UP TO TRANSMIT
001506 005067 012350 CLR TIME2 ;3 CHARACTERS
001512 005067 012346 CLR TEMP1 ;SELECT LINE SPEED
001516 012767 000010 012342 MOV #10,TEMP2 ;CLEAR TRANSMITTER TIME TIMER
001524 012777 000001 012236 MOV #1,0DHBA ;SET UP NO CLOCK TIMER
001532 005777 012220 2+: TST 0DHSCR ;SET BAR BIT FOR LINE 0
001536 100412 BMI 3+ ;TO START TRANSMISSION
001540 005267 012316 INC TIME2 ;WAIT FOR TRANSMITTER
001544 005267 012314 INC TEMP1 ;TO FINISH
001550 001370 BNE 2+ ;UPDATE TRANSMITTER TIMER
001552 005367 012310 DEC TEMP2 ;UPDATE NO CLOCK TIMER
001556 001365 BNE 2+
001560 HLT 1 ;TRANSMITTER DID NOT FINISH, ERROR
001560 104001 EMT 1
001562 000405 BR 4+
001564 026767 012272 012266 3+: CMP TIME2,TIME1 ;VERIFY THAT TRANSMITTER
001572 103401 BLO 4+ ;WAS FASTER AT THIS SELECTED SPEED

```

```

001574      HLT      2      ;(NUMBER OF COUNTS IN TIME2
001574 104002    EMT      2      ;LESS THAN TIME1)
                                ;TRANSMITTER TIMING ERROR FOR
                                ;LINE 0
001576 104410    4$: SCOPE1      ;CHECK FOR FREEZE ON CURRENT DATA
001600 016767 012256 012252    MOV      TIME2,TIME1      ;SET UP FOR NEXT COMPARISION
001606 005204      INC      R4      ;SELECT NEXT SPEED
001610 062700 002000      ADD      #2000,R0
001614 005301      DEL      R1
001616 001317      BNE      1$
001620 104400    5$: SCOPE      ;CHECK FOR ITERATIONS, LOOP
      000001      LINE=LINE+1
      000002      BITX=BITX+BITX
001622      SPEED  \LINE,\BITX,3,+//,2000,+/TRANSMITTER/

      ;TRANSMITTER LINE SPEED SELECTION TEST
      ;TRANSMIT 3 CHARACTERS AT A SELECTED SPEED ON LINE 1
      ;VERIFY THAT TRANSMITTER DONE OCCURS AT THE SELECTED SPEED
      ;VERIFY THAT THE AMOUN OF TIME TAKEN IS LESS
      ;AT THIS SPEED THAN AT THE PREVIOUSLY SELECTED SPEED

001622      TS \XN,10,5$,1$
001622 012767 000340 176146    T2:  MOV      #340,PS      ;DISABLE ALL INTERRUPTS
001630 012767 000010 012166      MOV      #10,ICOUNT      ;SET UP FOR 10 ITERATIONS
001636 012767 002042 012154      MOV      #5$,ESCAPE      ;SET UP TO ESCAPE TO NEXT TEST
                                .IF NB <1$>
001644 012767 001700 012150      MOV      #1$,FREEZ1      ;SET UP TO LOOP WITH DATA      , 3
                                .ENDC
                                XN=XN+1
001652 012705 000001      MOV      #1,R5      ;LINE 1 WILL BE TESTED
001656 012700 002000      MOV      #2000,R0      ;CONSTANT FOR SELECTION
                                ;OF INITIAL (LOWEST) SPEED
001662 012701 000015      MOV      #15,R1      ;15 DIFFERENT SPEEDS WILL BE TESTED
001666 012704 000001      MOV      #1,R4      ;BINARY CODE FOR INITIAL SPEED
001672 012767 177777 012160      MOV      #-1,TIME1      ;INITIALIZE COMPARISION VALUE
001700 012777 004000 012050    1$: MOV      #BIT11,BDHSCR      ;CLEAR INTERFACE
001706 010577 012044      MOV      R5,BDHSCR      ;SELECT LINE 1 FOR TESTING
001712 005077 012046      CLR      BDHBA      ;CLEAR BUS ADDRESS
001716 012777 177775 012042      MOV      #-3,BDHBC      ;SET UP TO TRANSMIT
                                ;3 CHARACTERS
001724 010077 012032      MOV      R0,BDHLPR      ;SELECT LINE SPEED
001730 005067 012126      CLR      TIME2      ;CLEAR TRANSMITTER TIME TIMER
001734 005067 012124      CLR      TEMP1      ;SET UP NO CLOCK TIMER
001740 012767 000010 012120      MOV      #10,TEMP2
001746 012777 000002 012014      MOV      #2,BDHBA      ;SET BAR BIT FOR LINE 1
                                ;TO START TRANSMISSION
001754 005777 011776    2$: TST      BDHSCR      ;WAIT FOR TRANSMITTER
                                ;TO FINISH
001760 100412      BMI      3$
001762 005267 012074      INC      TIME2      ;UPDATE TRANSMITTER TIMER
001766 005267 012072      INC      TEMP1      ;UPDATE NO CLOCK TIMER
001772 001370      BNE      2$
001774 005367 012066      DEC      TEMP2
002000 001365      BNE      2$
002002      HLT      1      ;TRANSMITTER DID NOT FINISH, ERROR
002002 104001      EMT      1

```

```

002004 000405
002006 026767 012050 012044 3#: BR 4#
002014 103401 CMP TIME2,TIME1
BLO 4# ;VERIFY THAT TRANSMITTER
;WAS FASTER AT THIS SELECTED SPEED
;(NUMBER OF COUNTS IN TIME2
;LESS THAN TIME1)
;TRANSMITTER TIMING ERROR FOR

002016
002016 104002 HLT 2
EMT 2 ;LINE 1
;CHECK FOR FREEZE ON CURRENT DATA
;SET UP FOR NEXT COMPARISION
;SELECT NEXT SPEED

002020 104410
002022 016767 012034 012030 4#: SCOPE1
002030 005204 MOV TIME2,TIME1
002032 062700 002000 INC R4
002036 005301 ADD #2000,R0
002040 001317 DEC R1
002042 104400 BNE 1#
000002 ;CHECK FOR ITERATIONS, LOOP
000004
002044
SPEED \LINE,\BITX,3,+//,2000,+/TRANSMITTER/

;TRANSMITTER LINE SPEED SELECTION TEST
;TRANSMIT 3 CHARACTERS AT A SELECTED SPEED ON LINE 2
;VERIFY THAT TRANSMITTER DONE OCCURS AT THE SELECTED SPEED
;VERIFY THAT THE AMOUN OF TIME TAKEN IS LESS
;AT THIS SPEED THAN AT THE PREVIOUSLY SELECTED SPEED

002044 TS \XN,10,5#,1#
002044 012767 000340 175724 T3: MOV #340,PS
002052 012767 000010 011744 MOV #10,ICOUNT
002060 012767 002264 011732 MOV #5#,ESCAPE
;DISABLE ALL INTERRUPTS
;SET UP FOR 10 ITERATIONS
;SET UP TO ESCAPE TO NEXT TEST

002066 012767 002122 011726 .IF NB <1#> MOV #1#,FREEZ1
;SET UP TO LOOP WITH DATA , 3

000004 .ENDC
XN=XN+1

002074 012705 000002 MOV #2,R5
002100 012700 002000 MOV #2000,R0 ;LINE 2 WILL BE TESTED
;CONSTANT FOR SELECTION
;OF INITIAL (LOWEST) SPEED
;15 DIFFERENT SPEEDS WILL BE TESTED
;BINARY CODE FOR INITIAL SPEED
;INITIALIZE COMPARISION VALUE

002104 012701 000015 MOV #15,R1
002110 012704 000001 MOV #1,R4
002114 012767 177777 011736 MOV #-1,TIME1
002122 012777 004000 011626 1#: MOV #BIT11,0DHSCR
002130 010577 011622 MOV R5,0DHSCR
002134 005077 011624 CLR 0DHBA
002140 012777 177775 011620 MOV #-3,0DHBC
;CLEAR INTERFACE
;SELECT LINE 2 FOR TESTING
;CLEAR BUS ADDRESS
;SET UP TO TRANSMIT
;3 CHARACTERS
;SELECT LINE SPEED
;CLEAR TRANSMITTER TIME TIMER
;SET UP NO CLOCK TIMER

002146 010077 011610 MOV R0,0DHLPR
002152 005067 011704 CLR TIME2
002156 005067 011702 CLR TEMP1
002162 012767 000010 011676 MOV #10,TEMP2
002170 012777 000004 011572 MOV #4,0DHBAR
;SET BAR BIT FOR LINE 2
;TO START TRANSMISSION
;WAIT FOR TRANSMITTER
;TO FINISH

002176 005777 011554 2#: TST 0DHSCR

002202 100412 BHI 3#
002204 005267 011652 INC TIME2
002210 005267 011650 INC TEMP1
002214 001370 BNE 2#
002216 005367 011644 DEC TEMP2
;UPDATE TRANSMITTER TIMER
;UPDATE NO CLOCK TIMER

```

Address	Hex	Hex	Hex	Hex	Instruction	Comments
002222	001365				BNE 2	
002224					HLT 1	
002224	104001				EMT 1	;TRANSMITTER DID NOT FINISH, ERROR
002226	000405				BR 4	
002230	026767	011626	011622	3:	CMP TIME2,TIME1	;VERIFY THAT TRANSMITTER
002236	103401				BLO 4	;WAS FASTER AT THIS SELECTED SPEED
						; (NUMBER OF COUNTS IN TIME2
						; LESS THAN TIME1)
002240					HLT 2	;TRANSMITTER TIMING ERROR FOR
002240	104002				EMT 2	
						;LINE 2
002242	104410			4:	SCOPE1	;CHECK FOR FREEZE ON CURRENT DATA
002244	016767	011612	011606		MOV TIME2,TIME1	;SET UP FOR NEXT COMPARISON
002252	005204				INC R4	;SELECT NEXT SPEED
002254	062700	002000			ADD #2000,R0	
002260	005301				DEC R1	
002262	001317				BNE 1	
002264	104400			5:	SCOPE	;CHECK FOR ITERATIONS. LOOP
	000003				LINE=LINE+1	
	000010				BITX=BITX+BITX	
002266					SPEED \LINE,\BITX,3,↑//,2000,↑/TRANSMITTER/	
						;TRANSMITTER LINE SPEED SELECTION TEST
						;TRANSMIT 3 CHARACTERS AT A SELECTED SPEED ON LINE 3
						;VERIFY THAT TRANSMITTER DONE OCCURS AT THE SELECTED SPEED
						;VERIFY THAT THE AMOUN OF TIME TAKEN IS LESS
						;AT THIS SPEED THAN AT THE PREVIOUSLY SELECTED SPEED
002266					TS \XN,10,5,1	
002266	012767	000340	175502	T4:	MOV #340,PS	;DISABLE ALL INTERRUPTS
002274	012767	000010	011522		MOV #10,ICOUNT	;SET UP FOR 10 ITERATIONS
002302	012767	002506	011510		MOV #5,ESCAPE	;SET UP TO ESCAPE TO NEXT TEST
				.IF NB	<1>	
002310	012767	002344	011504		MOV #1,FREEZ1	;SET UP TO LOOP WITH DATA ; 3
	000005			.ENDC		
				XN=XN+1		
002316	012705	000003			MOV #3,R5	;LINE 3 WILL BE TESTED
002322	012700	002000			MOV #2000,R0	;CONSTANT FOR SELECTION
						;OF INITIAL (LOWEST) SPEED
002326	012701	000015			MOV #15,R1	;15 DIFFERENT SPEEDS WILL BE TESTED
002332	012704	000001			MOV #1,R4	;BINARY CODE FOR INITIAL SPEED
002336	012767	177777	011514		MOV #-1,TIME1	;INITIALIZE COMPARISON VALUE
002344	012777	004000	011404	1:	MOV #BIT11,0DHSCR	;CLEAR INTERFACE
002352	010577	011400			MOV R5,0DHSCR	;SELECT LINE 3 FOR TESTING
002356	005077	011402			CLR 0DH8A	;CLEAR BUS ADDRESS
002362	012777	177775	011376		MOV #-3,0DH8C	;SET UP TO TRANSMIT
						;3 CHARACTERS
002370	010077	011366			MOV R0,0DHLP	;SELECT LINE SPEED
002374	005067	011462			CLR TIME2	;CLEAR TRANSMITTER TIME TIMER
002400	005067	011460			CLR TEMP1	;SET UP NO CLOCK TIMER
002404	012767	000010	011454		MOV #10,TEMP2	
002412	012777	000010	011350		MOV #10,0DH8A	;SET BAR BIT FOR LINE 3
						;TO START TRANSMISSION
002420	005777	011332		2:	TST 0DHSCR	;WAIT FOR TRANSMITTER
						;TO FINISH
002424	100412				BMI 3	
002426	005267	011430			INC TIME2	;UPDATE TRANSMITTER TIMER

```

002432 005267 011426      INC      TEMP1      ;UPDATE NO CLOCK TIMER
002436 001370              BNE      2;
002440 005367 011422      DEC      TEMP2
002444 001365              BNE      2;
002446              HLT      1      ;TRANSMITTER DID NOT FINISH, ERROR
002446 104001              EMT      1
002450 000405              BR      4;
002452 026767 011404 011400 3;:  CMP      TIME2,TIME1      ;VERIFY THAT TRANSMITTER
002460 103401              BLC      4;      ;WAS FASTER AT THIS SELECTED SPEED
                                           ;(NUMBER OF COUNTS IN TIME2
                                           ;LESS THAN TIME1)
                                           ;TRANSMITTER TIMING ERROR FOR

002462              HLT      2
002462 104002              EMT      2

002464 104410 4;:          SCOPE1      ;LINE 3
002466 016767 011370 011364      MOV      TIME2,TIME1      ;CHECK FOR FREEZE ON CURRENT DATA
002474 005204              INC      R4      ;SET UP FOR NEXT COMPARISION
002476 062700 002000              ADD      @2000,R0      ;SELECT NEXT SPEED
002502 005301              DEC      R1
002504 001317              BNE      1;
002506 104400 5;:          SCOPE      ;CHECK FOR ITERATIONS, LOOP
000004      LINE=LINE+1
000020      BITX=BITX+BITX
002510      SPEED \LINE,\BITX,3,+//,2000,+/TRANSMITTER/

                                           ;TRANSMITTER LINE SPEED SELECTION TEST
                                           ;TRANSMIT 3 CHARACTERS AT A SELECTED SPEED ON LINE 4
                                           ;VERIFY THAT TRANSMITTER DONE OCCURS AT THE SELECTED SPEED
                                           ;VERIFY THAT THE AMOUN OF TIME TAKEN IS LESS
                                           ;AT THIS SPEED THAN AT THE PREVIOUSLY SELECTED SPEED

002510      TS \XN,10,5;1;
002510 012767 000340 175260      TS:      MOV      @340,PS      ;DISABLE ALL INTERRUPTS
002516 012767 000010 011300      MOV      @10,ICOUNT      ;SET UP FOR 10 ITERATIONS
002524 012767 002730 011266      MOV      @5;ESCAPE      ;SET UP TO ESCAPE TO NEXT TEST
                                           .IF NB <1;
002532 012767 002566 011262      MOV      @1;FREEZ1      ;SET UP TO LOOP WITH DATA      ; 3
                                           .ENDC
                                           XN=XN+1

002540 012705 000004      MOV      @4,R5      ;LINE 4 WILL BE TESTED
002544 012700 002000      MOV      @2000,R0      ;CONSTANT FOR SE' ECTION
                                           ;OF INITIAL (LOWEST) SPEED
002550 012701 000015      MOV      @15,R1      ;15 DIFFERENT SPEEDS WILL BE TESTED
002554 012704 000001      MOV      @1,R4      ;BINARY CODE FOR INITIAL SPEED
002560 012767 177777 011272      MOV      @-1,TIME1      ;INITIALIZE COMPARISION VALUE
002566 012777 004000 011162 1;:  MOV      @BIT11,@DHSCR      ;CLEAR INTERFACE
002574 010577 011156      MOV      R5,@DHSCR      ;SELECT LINE 4 FOR TESTING
002600 005077 011160      CLR      @DHBA      ;CLEAR BUS ADDRESS
002604 012777 177775 011154      MOV      @-3,@DHBC      ;SET UP TO TRANSMIT
                                           ;3 CHARACTERS
002612 010077 011144      MOV      R0,@DHLPR      ;SELECT LINE SPEED
002616 005067 011240      CLR      TIME2      ;CLEAR TRANSMITTER TIME TIMER
002622 005067 011236      CLR      TEMP1      ;SET UP NO CLOCK TIMER
002626 012767 000010 011232      MOV      @10,TEMP2
002634 012777 000020 011126      MOV      @20,@DHBAR      ;SET BAR BIT FOR LINE 4
                                           ;TO START TRANSMISSION
002642 005777 011110 2;:      TST      @DHSCR      ;WAIT FOR TRANSMITTER

```

```

002646 100412 BMI 3:
002650 005267 011206 INC TIME2
002654 005267 011204 INC TEMP1
002660 001370 BNE 2:
002662 005367 011200 DEC TEMP2
002666 001365 BNE 2:
002670 HLT 1
002670 104001 EMT 1
002672 000405 BR 4:
002674 026767 011162 011156 3: CMP TIME2,TIME1
002702 103401 BLO 4:

;TO FINISH
;UPDATE TRANSMITTER TIMER
;UPDATE NO CLOCK TIMER

;TRANSMITTER DID NOT FINISH, ERROR

;VERIFY THAT TRANSMITTER
;WAS FASTER AT THIS SELECTED SPEED
;(NUMBER OF COUNTS IN TIME2
;LESS THAN TIME1)
;TRANSMITTER TIMING ERROR FOR

002704 HLT 2
002704 104002 EMT 2

;LINE 4
;CHECK FOR FREEZE ON CURRENT DATA
;SET UP FOR NEXT COMPARISION
;SELECT NEXT SPEED

002706 104410 4: SCOPE1
002710 016767 011146 011142 MOV TIME2,TIME1
002716 005204 INC R4
002720 062700 002000 ADD #2000,R0
002724 005301 DEC R1
002726 001317 BNE 1:
002730 104400 5: SCOPE
000005 LINE=LINE+1
000040 BITX=BITX+BITX
002732 SPEED \LINE,\BITX,3,+/ /.2000,+/TRANSMITTER/

;TRANSMITTER LINE SPEED SELECTION TEST
;TRANSMIT 3 CHARACTERS AT A SELECTED SPEED ON LINE 5
;VERIFY THAT TRANSMITTER DONE OCCURS AT THE SELECTED SPEED
;VERIFY THAT THE AMOUN OF TIME TAKEN IS LESS
;AT THIS SPEED THAN AT THE PREVIOUSLY SELECTED SPEED

002732 TS \XN,10,5,1:
002732 012767 000340 175036 T6: MOV #340,PS
002740 012767 000010 011056 MOV #10,ICOUNT
002746 012767 003152 011044 MOV #5,ESCAPE
;DISABLE ALL INTERRUPTS
;SET UP FOR 10 ITERATIONS
;SET UP TO ESCAPE TO NEXT TEST

002754 012767 003010 011040 .IF NB <1: MOV #1,FREEZ1
;SET UP TO LOOP WITH DATA ; 3

.ENDC
XN=XN+1

002762 012705 000005 MOV #5,R5
002766 012700 002000 MOV #2000,R0
;LINE 5 WILL BE TESTED
;CONSTANT FOR SELECTION
;OF INITIAL (LOWEST) SPEED
;15 DIFFERENT SPEEDS WILL BE TESTED
;BINARY CODE FOR INITIAL SPEED
;INITIALIZE COMPARISION VALUE

002772 012701 000015 MOV #15,R1
002776 012704 000001 MOV #1,R4
003002 012767 177777 011050 MOV #-1,TIME1
003010 012777 004000 010740 1: MOV #BIT11,0DHSCR
003016 010577 010734 MOV R5,0DHSCR
003022 005077 010736 CLR 0DHBA
003026 012777 177775 010732 MOV #-3,0DHBC
;CLEAR INTERFACE
;SELECT LINE 5 FOR TESTING
;CLEAR BUS ADDRESS
;SET UP TO TRANSMIT
;3 CHARACTERS
;SELECT LINE SPEED
;CLEAR TRANSMITTER TIME TIMER
;SET UP NO CLOCK TIMER

003034 010077 010722 MOV R0,0DHLPR
003040 005067 011016 CLR TIME2
003044 005067 011014 CLR TEMP1
003050 012767 000010 011010 MOV #10,TEMP2

```

```

003056 012777 000040 010704      MOV      #40, @DHBAR      ;SET BAR BIT FOR LINE 5
003064 005777 010666      2$:    TST      @DHSCR          ;TO START TRANSMISSION
                                           ;WAIT FOR TRANSMITTER
                                           ;TO FINISH
003070 100412      BMI      3$
003072 005267 010764      INC      TIME2      ;UPDATE TRANSMITTER TIMER
003076 005267 010762      INC      TEMP1      ;UPDATE NO CLOCK TIMER
003102 001370      BNE      2$
003104 005367 010756      DEC      TEMP2
003110 001365      BNE      2$
003112      HLT      1      ;TRANSMITTER DID NOT FINISH, ERROR
003112 104001      EMT      1
003114 000405      BR      4$
003116 026767 010740 010734 3$:    CMP      TIME2, TIME1      ;VERIFY THAT TRANSMITTER
003124 103401      BLO      4$      ;WAS FASTER AT THIS SELECTED SPEED
                                           ;(NUMBER OF COUNTS IN TIME2
                                           ;LESS THAN TIME1)
                                           ;TRANSMITTER TIMING ERROR FOR

003126      HLT      2
003126 104002      EMT      2

003130 104410      4$:    SCOPE1      ;LINE 5
003132 016767 010724 010720      MOV      TIME2, TIME1      ;CHECK FOR FREEZE ON CURRENT DATA
003140 005204      INC      R4      ;SET UP FOR NEXT COMPARISON
003142 062700 002000      ADD      #2000, R0      ;SELECT NEXT SPEED
003146 005301      DEC      R1
003150 001317      BNE      1$
003152 104400      5$:    SCOPE      ;CHECK FOR ITERATIONS, LOOP
      000006      LINE=LINE+1
      000100      BITX=BITX+BITX
003154      SPEED \LINE, \BITX, 3, +//, 2000, +/TRANSMITTER/

      ;TRANSMITTER LINE SPEED SELECTION TEST
      ;TRANSMIT 3 CHARACTERS AT A SELECTED SPEED ON LINE 6
      ;VERIFY THAT TRANSMITTER DONE OCCURS AT THE SELECTED SPEED
      ;VERIFY THAT THE AMOUN OF TIME TAKEN IS LESS
      ;AT THIS SPEED THAN AT THE PREVIOUSLY SELECTED SPEED

003154      TS \XN, 10, 5$, 1$
003154 012767 000340 174614 T7:    MOV      #340, PS      ;DISABLE ALL INTERRUPTS
003162 012767 000010 010634      MOV      #10, ICOUNT      ;SET UP FOR 10 ITERATIONS
003170 012767 003374 010622      MOV      #5$, ESCAPE      ;SET UP TO ESCAPE TO NEXT TEST
                                           ;IF NB <1$>
003176 012767 003232 010616      MOV      #1$, FREEZ1      ;SET UP TO LOOP WITH DATA      ; 3
      .ENDC
      XN=XN+1
003204 012705 000006      MOV      #6, R5      ;LINE 6 WILL BE TESTED
003210 012700 002000      MOV      #2000, R0      ;CONSTANT FOR SELECTION
                                           ;OF INITIAL (LOWEST) SPEED
003214 012701 000015      MOV      #15, R1      ;15 DIFFERENT SPEEDS WILL BE TESTED
003220 012704 000001      MOV      #1, R4      ;BINARY CODE FOR INITIAL SPEED
003224 012767 177777 010626      MOV      #-1, TIME1      ;INITIALIZE COMPARISON VALUE
003232 012777 004000 010516 1$:    MOV      @BIT11, @DHSCR      ;CLEAR INTERFACE
003240 010577 010512      MOV      R5, @DHSCR      ;SELECT LINE 6 FOR TESTING
003244 005077 010514      CLR      @DHBA      ;CLEAR BUS ADDRESS
003250 012777 177775 010510      MOV      #-3, @DHBC      ;SET UP TO TRANSMIT
                                           ;3 CHARACTERS
003256 010077 010500      MOV      R0, @DHLPR      ;SELECT LINE SPEED

```

```

003262 005067 010574      CLR    TIME2      ;CLEAR TRANSMITTER TIME TIMER
003266 005067 010572      CLR    TEMP1      ;SET UP NO CLOCK TIMER
003272 012767 000010 010566  MOV    #10,TEMP2
003300 012777 000100 010462  MOV    #100,0DHBAR      ;SET BAR BIT FOR LINE 6
                                           ;TO START TRANSMISSION
003306 005777 010444      2$:    TST    0DHSCR      ;WAIT FOR TRANSMITTER
                                           ;TO FINISH

003312 100412      BMI    3$
003314 005267 010542      INC    TIME2      ;UPDATE TRANSMITTER TIMER
003320 005267 010540      INC    TEMP1      ;UPDATE NO CLOCK TIMER
003324 001370      BNE    2$
003326 005367 010534      DEC    TEMP2
003332 001365      BNE    2$
003334      HLT    1      ;TRANSMITTER DID NOT FINISH, ERROR
003334 104001      EMT    1
003336 000405      BR     4$
003340 026767 010516 010512 3$:    CMP    TIME2,TIME1
003346 103401      BLO    4$      ;VERIFY THAT TRANSMITTER
                                           ;WAS FASTER AT THIS SELECTED SPEED
                                           ;(NUMBER OF COUNTS IN TIME2
                                           ;LESS THAN TIME1)
                                           ;TRANSMITTER TIMING ERROR FOR

003350      HLT    2
003350 104002      EMT    2

                                           ;LINE 6
003352 104410      4$:    SCOPE1      ;CHECK FOR FREEZE ON CURRENT DATA
003354 016767 010502 010476  MOV    TIME2,TIME1      ;SET UP FOR NEXT COMPARISION
003362 005204      INC    R4      ;SELECT NEXT SPEED
003364 062700 002000      ADD    #2000,R0
003370 005301      DEC    R1
003372 001317      BNE    1$
003374 10440C      5$:    SCOPE      ;CHECK FOR ITERATIONS, LOOP
000007      LINE=LINE+1
000200      BITX=BITX+BITX
003376      SPEED \LINE,\BITX,3,+//,2000,+//TRANSMITTER/

                                           ;TRANSMITTER LINE SPEED SELECTION TEST
                                           ;TRANSMIT 3 CHARACTERS AT A SELECTED SPEED ON LINE 7
                                           ;VERIFY THAT TRANSMITTER DONE OCCURS AT THE SELECTED SPEED
                                           ;VERIFY THAT THE AMOUN OF TIME TAKEN IS LESS
                                           ;AT THIS SPEED THAN AT THE PREVIOUSLY SELECTED SPEED

003376      TS \XN,10,5$,1$
003376 012767 000340 174372 T10:    MOV    #340,PS      ;DISABLE ALL INTERRUPTS
003404 012767 000010 010412  MOV    #10,ICOUNT      ;SET UP FOR 10 ITERATIONS
003412 012767 003616 010400  MOV    #5$,ESCAPE      ;SET UP TO ESCAPE TO NEXT TEST

003420 012767 003454 010374  .IF NB <1$>
                                           ;SET UP TO LOOP WITH DATA      ; 3
                                           .ENDC
                                           XN=XN+1

003426 012705 000007      MOV    #7,R5      ;LINE 7 WILL BE TESTED
003432 012700 002000      MOV    #2000,R0      ;CONSTANT FOR SELECTION
                                           ;OF INITIAL (LOWEST) SPEED
003436 012701 000015      MOV    #15,R1      ;15 DIFFERENT SPEEDS WILL BE TESTED
003442 012704 000001      MOV    #1,R4      ;BINARY CODE FOR INITIAL SPEED
003446 012767 177777 010404  MOV    #-1,TIME1      ;INITIALIZE COMPARISION VALUE
003454 012777 004000 010274 1$:    MOV    #BIT11,0DHSCR      ;CLEAR INTERFACE
003462 010577 010270      MOV    R5,0DHSCR      ;SELECT LINE 7 FOR TESTING
003466 005077 010272      CLR    0DHBA      ;CLEAR BUS ADDRESS

```

```

003472 012777 177775 010266      MOV      3,0DHBC      ;SET UP TO TRANSMIT
                                ;3 CHARACTERS
003500 010077 010256      MOV      R0,0DHLPR      ;SELECT LINE SPEED
003504 005067 010352      CLR      TIME2          ;CLEAR TRANSMITTER TIME TIMER
003510 005067 010350      CLR      TEMP1          ;CLEAR CLOCK TIMER
003514 012767 000010 010344      MOV      10,TEMP2
003522 012777 000200 010240      MOV      200,0DHBAR      ;SET BAR BIT FOR LINE 7
                                ;TO START TRANSMISSION
                                ;WAIT FOR TRANSMITTER
                                ;TO FINISH
003530 005777 010222      2$:      TST      0DHSCR
003534 100412      BMI      3$
003536 005267 010320      INC      TIME2          ;UPDATE TRANSMITTER TIMER
003542 005267 010316      INC      TEMP1          ;UPDATE NO CLOCK TIMER
003546 001370      BNE      2$
003550 005367 010312      DEC      TEMP2
003554 001365      BNE      2$
003556      HLT      1          ;TRANSMITTER DID NOT FINISH, ERROR
003556 104001      EMT      1
003560 000405      BR      4$
003562 026767 010274 010270 3$:      CMP      TIME2,TIME1
003570 103401      BLO      4$          ;VERIFY THAT TRANSMITTER
                                ;WAS FASTER AT THIS SELECTED SPEED
                                ; (NUMBER OF COUNTS IN TIME2
                                ; LESS THAN TIME1)
                                ;TRANSMITTER TIMING ERROR FOR
003572      HLT      2
003572 104002      EMT      2
                                ;LINE 7
003574 104410      4$:      SCOPE1          ;CHECK FOR FREEZE ON CURRENT DATA
003576 016767 010260 010254      MOV      TIME2,TIME1      ;SET UP FOR NEXT COMPARISON
003604 005204      INC      R4          ;SELECT NEXT SPEED
003606 062700 002000      ADD      2000,R0
003612 005301      DEC      R1
003614 001317      BNE      1$
003616 104400      5$:      SCOPE          ;CHECK FOR ITERATIONS, LOOP
                                LINE=LINE+1
                                BITX=BITX+BITX
003620      SPEED      \LINE,\BITX,3,+//,2000,+//TRANSMITTER/

                                ;TRANSMITTER LINE SPEED SELECTION TEST
                                ;TRANSMIT 3 CHARACTERS AT A SELECTED SPEED ON LINE 10
                                ;VERIFY THAT TRANSMITTER DONE OCCURS AT THE SELECTED SPEED
                                ;VERIFY THAT THE AMOUN OF TIME TAKEN IS LESS
                                ;AT THIS SPEED THAN AT THE PREVIOUSLY SELECTED SPEED

003620      TS      \XN,10,5$,1$
003620 012767 000340 174150      T11:      MOV      340,PS          ;DISABLE ALL INTERRUPTS
003626 012767 000010 010170      MOV      10,ICOUNT      ;SET UP FOR 10 ITERATIONS
003634 012767 004040 010156      MOV      5$,ESCAPE      ;SET UP TO ESCAPE TO NEXT TEST
                                .IF NB      <1$>
003642 012767 003676 010152      MOV      1$,FREEZ1          ;SET UP TO LOOP WITH DATA      ; 3
                                .ENDC
                                XN=XN+1
003650 012705 000010      MOV      10,R5          ;LINE 10 WILL BE TESTED
003654 012700 002000      MOV      2000,R0          ;CONSTANT FOR SELECTION
                                ;OF INITIAL (LOWEST) SPEED
003660 012701 000015      MOV      15,R1          ;15 DIFFERENT SPEEDS WILL BE TESTED
003664 012704 000001      MOV      1,R4          ;BINARY CODE FOR INITIAL SPEED
003670 012767 177777 010162      MOV      -1,TIME1      ;INITIALIZE COMPARISON VALUE

```

```

003676 012777 004000 010052 1$: MOV #BIT11, @DHSCR ;CLEAR INTERFACE
003704 010577 010046 MOV R5, @DHSCR ;SELECT LINE 10 FOR TESTING
003710 005077 010050 CLR @DHEA ;CLEAR BUS ADDRESS
003714 012777 177775 010044 MOV #-3, @DHBC ;SET UP TO TRANSMIT
;3 CHARACTERS
003722 010077 010034 MOV R0, @DHLPR ;SELECT LINE SPEED
003726 005067 010130 CLR TIME2 ;CLEAR TRANSMITTER TIME TIMER
003732 005067 010126 CLR TEMP1 ;SET UP NO CLOCK TIMER
003736 012767 000010 010122 MOV #10, TEMP2
003744 012777 000400 010016 MOV #400, @DHBAR ;SET BAR BIT FOR LINE 10
;TO START TRANSMISSION
003752 005777 010000 2$: TST @DHSCR ;WAIT FOR TRANSMITTER
;TO FINISH
003756 100412 BMI 3$
003760 005267 010076 INC TIME2 ;UPDATE TRANSMITTER TIMER
003764 005267 010074 INC TEMP1 ;UPDATE NO CLOCK TIMER
003770 001370 BNE 2$
003772 005367 010070 DEC TEMP2
003776 001365 BNE 2$
004000 HLT 1 ;TRANSMITTER DID NOT FINISH, ERROR
004000 104001 EMT 1
004002 000405 BR 4$
004004 026767 010052 010046 3$: CMP TIME2, TIME1 ;VERIFY THAT TRANSMITTER
004012 103401 BLO 4$ ;WAS FASTER AT THIS SELECTED SPEED
;(NUMBER OF COUNTS IN TIME2
;LESS THAN TIME1)
;TRANSMITTER TIMING ERROR FOR
004014 HLT 2 ;LINE 10
004014 104002 EMT 2 ;CHECK FOR FREEZE ON CURRENT DATA
;SET UP FOR NEXT COMPARISON
;SELECT NEXT SPEED
004016 104410 4$: SCOPE1
004020 016767 010036 010032 MOV TIME2, TIME1
004026 005204 INC R4
004030 062700 002000 ADD #2000, R0
004034 005301 DEC R1
004036 001317 BNE 1$
004040 104400 5$: SCOPE ;CHECK FOR ITERATIONS, LOOP
004040 000011 LINE=LINE+1
004040 001000 BITX=BITX+BITX
004042 SPEED \LINE, \BITX, 3, +//, 2000, +//TRANSMITTER/
;TRANSMITTER LINE SPEED SELECTION TEST
;TRANSMIT 3 CHARACTERS AT A SELECTED SPEED ON LINE 11
;VERIFY THAT TRANSMITTER DONE OCCURS AT THE SELECTED SPEED
;VERIFY THAT THE AMOUN OF TIME TAKEN IS LESS
;AT THIS SPEED THAN AT THE PREVIOUSLY SELECTED SPEED
004042 TS \XN, 10, 5$, 1$
004042 012767 000340 173726 T12: MOV #340, PS ;DISABLE ALL INTERRUPTS
004050 012767 000010 007746 MOV #10, ICOUNT ;SET UP FOR 10 ITERATIONS
004056 012767 004262 007734 MOV #5$, ESCAPE ;SET UP TO ESCAPE TO NEXT TEST
;IF NB <1$>
004064 012767 004120 007730 MOV #1$, FREEZ1 ;SET UP TO LOOP WITH DATA ; 3
.ENDC
XN=XN+1
004072 000013
004072 012705 000011 MOV #11, R5 ;LINE 11 WILL BE TESTED
004076 012700 002000 MOV #2000, R0 ;CONSTANT FOR SELECTION
;OF INITIAL (LOWEST) SPEED

```

```

004102 012701 000015      MOV    #15,R1      ;15 DIFFERENT SPEEDS WILL BE TESTED
004106 012704 000001      MOV    #1,R4      ;BINARY CODE FOR INITIAL SPEED
004112 012767 177777 007740 1#:  MOV    #-1,TIME1    ;INITIALIZE COMPARISON VALUE
004120 012777 004000 007630  MOV    #BIT11,@DHSCR  ;CLEAR INTERFACE
004126 010577 007624      MOV    R5,@DHSCR  ;SELECT LINE 11 FOR TESTING
004132 005077 007626      CLR    @DHBA    ;CLEAR BUS ADDRESS
004136 012777 177775 007622  MOV    #-3,@DHBC  ;SET UP TO TRANSMIT
                                ;3 CHARACTERS
                                ;SELECT LINE SPEED
004144 010077 007612      MOV    R0,@DHLPR  ;CLEAR TRANSMITTER TIME TIMER
004150 005067 007706      CLR    TIME2
004154 005067 007704      CLR    TEMP1     ;SET UP NO CLOCK TIMER
004160 012767 000010 007700  MOV    #10,TEMP2
004166 012777 001000 007574  MOV    #1000,@DHBAR  ;SET BAR BIT FOR LINE 11
                                ;TO START TRANSMISSION
                                ;WAIT FOR TRANSMITTER
                                ;TO FINISH
004174 005777 007556      2#:  TST    @DHSCR
004200 100412      BMI    3#
004202 005267 007654      INC    TIME2     ;UPDATE TRANSMITTER TIMER
004206 005267 007652      INC    TEMP1     ;UPDATE NO CLOCK TIMER
004212 001370      BNE    2#
004214 005367 007646      DEC    TEMP2
004220 001365      BNE    2#
004222      HLT    1      ;TRANSMITTER DID NOT FINISH, ERROR
004222 104001      EMT    1
004224 000405      RR    4#
004226 026767 007630 007624 3#:  CMP    TIME2,TIME1  ;VERIFY THAT TRANSMITTER
004234 103401      BLO    4#                ;WAS FASTER AT THIS SELECTED SPEED
                                ;(NUMBER OF COUNTS IN TIME2
                                ;LESS THAN TIME1)
                                ;TRANSMITTER TIMING ERROR FOR
004236      HLT    2
004236 104002      EMT    2
                                ;LINE 11
                                ;CHECK FOR FREEZE ON CURRENT DATA
004240 104410      4#:  SCOPE1             ;SET UP FOR NEXT COMPARISON
004242 016767 007614 007610  MOV    TIME2,TIME1  ;SELECT NEXT SPEED
004250 005204      INC    R4
004252 062700 002000      ADD    #2000,R0
004256 005301      DEC    R1
004260 001317      BNE    1#
004262 104400      5#:  SCOPE             ;CHECK FOR ITERATIONS, LOOP
004262 000012      LINE=LINE+1
004262 002000      BITX=BITX,BITX
004264      SPEED  \LINE,\BITX,3,+//.2000,+//TRANSMITTER/

                                ;TRANSMITTER LINE SPEED SELECTION TEST
                                ;TRANSMIT 3 CHARACTERS AT A SELECTED SPEED ON LINE 12
                                ;VERIFY THAT TRANSMITTER DONE OCCURS AT THE SELECTED SPEED
                                ;VERIFY THAT THE AMOUN OF TIME TAKEN IS LESS
                                ;AT THIS SPEED THAN AT THE PREVIOUSLY SELECTED SPEED

004264      TS  \XN,10,5#.1#
004264 012767 000340 173504  T13:  MOV    #340,PS      ;DISABLE ALL INTERRUPTS
004272 012767 000010 007524  MOV    #10,ICOUNT  ;SET UP FOR 10 ITERATIONS
004300 012767 004504 007512  MOV    #5#,ESCAPE  ;SET UP TO ESCAPE TO NEXT TEST
                                ;IF NB <1#>
004306 012767 004342 007506  MOV    #1#,FREEZ1    ;SET UP TO LOOP WITH DATA
                                ; 3
                                .ENDC
                                XN=XN+1
000014

```

```

004314 012705 000012      MOV    #12,R5      ;LINE 12 WILL BE TESTED
004320 012700 002000      MOV    #2000,R0      ;CONSTANT FOR SELECTION
                                ;OF INITIAL (LOWEST) SPEED
004324 012701 000015      MOV    #15,R1      ;15 DIFFERENT SPEEDS WILL BE TESTED
004330 012704 000001      MOV    #1,R4      ;BINARY CODE FOR INITIAL SPEED
004334 012767 177777 007516 1#:  MOV    #-1,TIME1      ;INITIALIZE COMPARISON VALUE
004342 012777 004000 007406 1#:  MOV    #BIT11,0DHSCR      ;CLEAR INTERFACE
004350 010577 007402      MOV    R5,0DHSCR      ;SELECT LINE 12 FOR TESTING
004354 005077 007404      CLR     0DH8A      ;CLEAR PJS ADDRESS
004360 012777 177775 007400      MOV    #-3,0DH8C      ;SET UP TO TRANSMIT
                                ;3 CHARACTERS
004366 010077 007370      MOV    R0,0DHLPR      ;SELECT LINE SPEED
004372 005067 007464      CLR     TIME2      ;CLEAR TRANSMITTER TIME TIMER
004376 005067 007462      CLR     TEMP1      ;SET UP NO CLOCK TIMER
004402 012767 000010 007456      MOV    #10,TEMP2
004410 012777 002000 007352      MOV    #2000,0DH8A      ;SET BAR BIT FOR LINE 12
                                ;TO START TRANSMISSION
004416 005777 007334      2#:  TST     0DHSCR      ;WAIT FOR TRANSMITTER
                                ;TO FINISH
004422 100412      BMI     3#
004424 005267 007432      INC     TIME2      ;UPDATE TRANSMITTER TIMER
004430 005267 007430      INC     TEMP1      ;UPDATE NO CLOCK TIMER
004434 001370      BNE     2#
004436 005367 007424      DEC     TEMP2
004442 001365      BNE     2#
004444      HLT     1      ;TRANSMITTER DID NOT FINISH, ERROR
004444 104001      EMT     1
004446 000405      BR      4#
004450 026767 007406 007402 3#:  CMP    TIME2,TIME1      ;VERIFY THAT TRANSMITTER
004456 103401      BLO     4#      ;WAS FASTER AT THIS SELECTED SPEED
                                ;(NUMBER OF COUNTS IN TIME2
                                ;LESS THAN TIME1)
004460      HLT     2      ;TRANSMITTER TIMING ERROR FOR
004460 104002      EMT     2
004462 104410      4#:  SCOPE1      ;LINE 12
004464 016767 007372 007366      MOV    TIME2,TIME1      ;CHECK FOR FREEZE ON CURRENT DATA
004472 005204      INC     R4      ;SET UP FOR NEXT COMPARISON
004474 062700 002000      ADD     #2000,R0      ;SELECT NEXT SPEED
004500 005301      DEC     R1
004502 001317      BNE     1#
004504 104400      5#:  SCOPE      ;CHECK FOR ITERATIONS, LOOP
004504 000013      LINE=LINE+1
004506 004000      BITX=BITX+BITX
SPEED \LINE,\BITX,3,1///,2000,1//TRANSMITTER/

;TRANSMITTER LINE SPEED SELECTION TEST
;TRANSMIT 3 CHARACTERS AT A SELECTED SPEED ON LINE 13
;VERIFY THAT TRANSMITTER DONE OCCURS AT THE SELECTED SPEED
;VERIFY THAT THE AMOUN OF TIME TAKEN IS LESS
;AT THIS SPEED THAN AT THE PREVIOUSLY SELECTED SPEED

004506      TS \XN,10,5#,1#
004506 012767 000340 173262 T14:  MOV    #340,PS      ;DISABLE ALL INTERRUPTS
004514 012767 000010 007302      MOV    #10,ICOUNT      ;SET UP FOR 10 ITERATIONS
004522 012767 004726 007270      MOV    #5#,ESCAPE      ;SET UP TO ESCAPE TO NEXT TEST
      .IF NB <1#>

```

```

004530 012767 004564 007264      MOV    #11,FREEZ1      ;SET UP TO LOOP WITH DATA      ; 3
                                .ENDC
                                XN=XN+1
004536 012705 000013      MOV    #13,R5      ;LINE 13 WILL BE TESTED
004542 012700 002000      MOV    #2000,R0      ;CONSTANT FOR SELECTION
                                ;OF INITIAL (LOWEST) SPEED
                                ;15 DIFFERENT SPEEDS WILL BE TESTED
004546 012701 000015      MOV    #15,R1      ;BINARY CODE FOR INITIAL SPEED
004552 012704 000001      MOV    #1,R4      ;INITIALIZE COMPARISON VALUE
004556 012767 177777 007274      MOV    #-1,TIME1      ;CLEAR INTERFACE
004564 012777 004000 007164 1$:  MOV    @BIT11,@DHSCR      ;SELECT LINE 13 FOR TESTING
004572 010577 007160      MOV    R5,@DHSCR      ;CLEAR BUS ADDRESS
004576 005077 007162      CLR     @DHBA      ;SET UP TO TRANSMIT
004602 012777 177775 007156      MOV    #-3,@DHBC      ;3 CHARACTERS
                                ;SELECT LINE SPEED
004610 010077 007146      MOV    R0,@DHLPR      ;CLEAR TRANSMITTER TIME TIMER
004614 005067 007242      CLR     TIME2      ;SET UP NO CLOCK TIMER
004620 005067 007240      CLR     TEMP1
004624 012767 000010 007234      MOV    #10,TEMP2
004632 012777 004000 007130      MOV    #4000,@DHBAR      ;SET BAR BIT FOR LINE 13
                                ;TO START TRANSMISSION
004640 005777 007112      2$:  TST     @DHSCR      ;WAIT FOR TRANSMITTER
                                ;TO FINISH
004644 100412      BMI     3$
004646 005267 007210      INC     TIME2      ;UPDATE TRANSMITTER TIMER
004652 005267 007206      INC     TEMP1      ;UPDATE NO CLOCK TIMER
004656 001370      BNE     2$
004660 005367 007202      DEC     TEMP2
004664 001365      BNE     2$
004666      HLT     1      ;TRANSMITTER DID NOT FINISH, ERROR
004666 104001      EMT     1
004670 000405      BR      4$
004672 026767 007164 007160 3$:  CMP    TIME2,TIME1      ;VERIFY THAT TRANSMITTER
004700 103401      BLO     4$      ;WAS FASTER AT THIS SELECTED SPEED
                                ;(NUMBER OF COUNTS IN TIME2
                                ;LESS THAN TIME1)
                                ;TRANSMITTER TIMING ERROR FOR
004702      HLT     2
004702 104002      EMT     2
                                ;LINE 13
004704 104410      4$:  SCOPE1      ;CHECK FOR FREEZE ON CURRENT DATA
004706 016767 007150 007144      MOV    TIME2,TIME1      ;SET UP FOR NEXT COMPARISON
004714 005204      INC     R4      ;SELECT NEXT SPEED
004716 062700 002000      ADD     #2000,R0
004722 005301      DEC     R1
004724 001317      BNE     1$
004726 104400      5$:  SCOPE      ;CHECK FOR ITERATIONS, LOOP
                                LINE=LINE+1
                                BITX=BITX+BITX
004730 010000      SPEED  \LINE,\BITX.3,+//,2000,+//TRANSMITTER/
                                ;TRANSMITTER LINE SPEED SELECTION TEST
                                ;TRANSMIT 3 CHARACTERS AT A SELECTED SPEED ON LINE 14
                                ;VERIFY THAT TRANSMITTER DONE OCCURS AT THE SELECTED SPEED
                                ;VERIFY THAT THE AMOUN OF TIME TAKEN IS LESS
                                ;AT THIS SPEED THAN AT THE PREVIOUSLY SELECTED SPEED
004730      TS  \XN,10,5$,1$
004730 012767 000340 173040 T15:  MOV    #340,PS      ;DISABLE ALL INTERRUPTS

```

```

004736 012767 000010 007060      MOV    #10,ICOUNT      ;SET UP FOR 10 ITERATIONS
004744 012767 005150 007046      MOV    #5,ESCAPE      ;SET UP TO ESCAPE TO NEXT TEST
                                .IF NB <1>
004752 012767 005006 007042      MOV    #1,FREEZ1      ;SET UP TO LOOP WITH DATA      ; 3
                                .ENDC
                                XN=XN+1
004760 012705 000014              MOV    #14,R5      ;LINE 14 WILL BE TESTED
004764 012700 002000              MOV    #2000,R0      ;CONSTANT FOR SELECTION
                                ;OF INITIAL (LOWEST) SPEED
004770 012701 000015              MOV    #15,R1      ;15 DIFFERENT SPEEDS WILL BE TESTED
004774 012704 000001              MOV    #1,R4      ;BINARY CODE FOR INITIAL SPEED
005000 012767 177777 007052      MOV    #-1,TIME1      ;INITIALIZE COMPARISON VALUE
005006 012777 004000 006742 1$:  MOV    #BIT11,0DHSCR      ;CLEAR INTERFACE
005014 010577 006736              MOV    R5,0DHSCR      ;SELECT LINE 14 FOR TESTING
005020 005077 006740              CLR     0DH8A      ;CLEAR BUS ADDRESS
005024 012777 177775 006734      MOV    #-3,0DH8C      ;SET UP TO TRANSMIT
                                ;3 CHARACTERS
005032 010077 006724              MOV    R0,0DHLPR      ;SELECT LINE SPEED
005036 005067 007020              CLR     TIME2      ;CLEAR TRANSMITTER TIME TIMER
005042 005067 007016              CLR     TEMP1      ;SET UP NO CLOCK TIMER
005046 012767 000010 007012      MOV    #10,TEMP2
005054 012777 010000 006706      MOV    #10000,0DH8A      ;SET BAR BIT FOR LINE 14
                                ;TO START TRANSMISSION
005062 005777 006670              2$:  TST     0DHSCR      ;WAIT FOR TRANSMITTER
                                ;TO FINISH
005066 100412              BMI     3$
005070 005267 006766              INC     TIME2      ;UPDATE TRANSMITTER TIMER
005074 005267 006764              INC     TEMP1      ;UPDATE NO CLOCK TIMER
005100 001370              BNE     2$
005102 005367 006760              DEC     TEMP2
005106 001365              BNE     2$
005110              HLT     1      ;TRANSMITTER DID NOT FINISH, ERROR
005110 104001              EMT     1
005112 000405              BR      4$
005114 026767 006742 006736 3$:  CMP     TIME2,TIME1      ;VERIFY THAT TRANSMITTER
005122 103401              BLO     4$      ;WAS FASTER AT THIS SELECTED SPEED
                                ;(NUMBER OF COUNTS IN TIME2
                                ;LESS THAN TIME1)
005124              HLT     2      ;TRANSMITTER TIMING ERROR FOR
005124 104002              EMT     2
                                ;LINE 14
005126 104410              4$:  SCOPE1      ;CHECK FOR FREEZE ON CURRENT DATA
005130 016767 006726 006722      MOV    TIME?,TIME1      ;SET UP FOR NEXT COMPARISON
005136 005204              INC     R4      ;SELECT NEXT SPEED
005140 062700 002000              ADD    #2000,R0
005144 005301              DEC     R1
005146 001317              BNE     1$
005150 104400              5$:  SCOPE      ;CHECK FOR ITERATIONS, LOOP
                                LINE=LINE+1
                                BITX=BITX+BITX
005152              SPEED \LINE,\BITX,3,1//,2000,1//TRANSMITTER/

;TRANSMITTER LINE SPEED SELECTION TEST
;TRANSMIT 3 CHARACTERS AT A SELECTED SPEED ON LINE 15
;VERIFY THAT TRANSMITTER DONE OCCURS AT THE SELECTED SPEED
;VERIFY THAT THE AMOUN OF TIME TAKEN IS LESS
;AT THIS SPEED THAN AT THE PREVIOUSLY SELECTED SPEED

```

```

005152 TS \XN,10,54,14
005152 012767 000340 172616 T16: MOV #340,PS ;DISABLE ALL INTERRUPTS
005160 012767 000010 006636 MOV #10,ICOUNT ;SET UP FOR 10 ITERATIONS
005166 012767 005372 006624 MOV #54,ESCAPE ;SET UP TO ESCAPE TO NEXT TEST

005174 012767 005230 006620 .IF NB <14> MOV #14,FREEZ1 ;SET UP TO LOOP WITH DATA ; 3
000017 .ENDC
XN=XN+1

005202 012705 000015 MOV #15,R5 ;LINE 15 WILL BE TESTED
005206 012700 002000 MOV #2000,R0 ;CONSTANT FOR SELECTION
;OF INITIAL (LOWEST) SPEED
;15 DIFFERENT SPEEDS WILL BE TESTED
005212 012701 000015 MOV #15,R1 ;BINARY CODE FOR INITIAL SPEED
005216 012704 000001 MOV #1,R4 ;INITIALIZE COMPARISON VALUE
005222 012767 177777 006630 MOV #-1,TIME1 ;CLEAR INTERFACE
005230 012777 004000 006520 14: MOV #BIT11,0DHSCR ;SELECT LINE 15 FOR TESTING
005236 010577 006514 MOV R5,0DHSCR ;CLEAR BUS ADDRESS
005242 005077 006516 CLR 0DHBA ;SET UP TO TRANSMIT
005246 012777 177775 006512 MOV #-3,0DHBC ;3 CHARACTERS
;SELECT LINE SPEED
;CLEAR TRANSMITTER TIME TIMER
;SET UP NO CLOCK TIMER
005254 010077 006502 MOV R0,0DHLPR
005260 005067 006576 CLR TIME2
005264 005067 006574 CLR TEMP1
005270 012767 000010 006570 MOV #10,TEMP2
005276 012777 020000 006464 MOV #20000,0DHBAR ;SET BAR BIT FOR LINE 15
;TO START TRANSMISSION
;WAIT FOR TRANSMITTER
;TO FINISH
005304 005777 006446 24: TST 0DHSCR
;UPDATE TRANSMITTER TIMER
;UPDATE NO CLOCK TIMER
005310 100412 BHI 34
005312 005267 006544 INC TIME2
005316 005267 006542 INC TEMP1
005322 001370 BNE 24
005324 005367 006536 DEC TEMP2
005330 001365 BNE 24
005332 HLT 1 ;TRANSMITTER DID NOT FINISH, ERROR
005332 104001 EMT 1
005334 000405 BR 44
005336 026767 006520 006514 34: CMP TIME2,TIME1
005344 103401 BLO 44 ;VERIFY THAT TRANSMITTER
;WAS FASTER AT THIS SELECTED SPEED
;(NUMBER OF COUNTS IN TIME2
;LESS THAN TIME1)
;TRANSMITTER TIMING ERROR FOR
005346 HLT 2
005346 104002 EMT 2
;LINE 15
;CHECK FOR FREEZE ON CURRENT DATA
;SET UP FOR NEXT COMPARISON
;SELECT NEXT SPEED
005350 104410 44: SCOPE1
005352 016767 006504 006500 MOV TIME2,TIME1
005360 005204 INC R4
005362 062700 002000 ADD #2000,R0
005366 005301 DEC R1
005370 001317 BNE 14
005372 104400 54: SCOPE ;CHECK FOR ITERATIONS, LOOP
000016 LINE=LINE+1
040000 BITX=BITX+BITX
005374 SPEED \LINE,\BITX,3,+//,2000,+/TRANSMITTER/

;TRANSMITTER LINE SPEED SELECTION TEST
;TRANSMIT 3 CHARACTERS AT A SELECTED SPEED ON LINE 16

```

;VERIFY THAT TRANSMITTER DONE OCCURS AT THE SELECTED SPEED
 ;VERIFY THAT THE AMOUNT OF TIME TAKEN IS LESS
 ;AT THIS SPEED THAN AT THE PREVIOUSLY SELECTED SPEED

```

005374      TS \XN,10,50.10
005374 012767 000340 172374 T17: MOV #340,PS ;DISABLE ALL INTERRUPTS
005402 012767 000010 006414 MOV #10,ICOUNT ;SET UP FOR 10 ITERATIONS
005410 012767 005614 006402 MOV #50,ESCAPE ;SET UP TO ESCAPE TO NEXT TEST

005416 012767 005452 006376 .IF NB <10> MOV #10,FREEZ1 ;SET UP TO LOOP WITH DATA ; 3
      .ENDC
      XN=XN+1

005424 012705 000016      MOV #16,R5 ;LINE 16 WILL BE TESTED
005430 012700 002000      MOV #2000,R0 ;CONSTANT FOR SELECTION
      ;OF INITIAL (LOWEST) SPEED
      ;15 DIFFERENT SPEEDS WILL BE TESTED
      ;BINARY CODE FOR INITIAL SPEED
      ;INITIALIZE COMPARISON VALUE
005434 012701 000015      MOV #15,R1 ;CLEAR INTERFACE
005440 012704 000001      MOV #1,R4 ;SELECT LINE 16 FOR TESTING
005444 012767 177777 006406 10: MOV #1,TIME1 ;CLEAR BUS ADDRESS
005452 012777 004000 006276 10: MOV #BIT11,0DHSCR ;SET UP TO TRANSMIT
005460 010577 006272      MOV R5,0DHSCR ;3 CHARACTERS
005464 005077 006274      CLR 0DHBA ;SELECT LINE SPEED
005470 012777 177775 006270      MOV #3,0DHBC ;CLEAR TRANSMITTER TIME TIMER
      ;SET UP NO CLOCK TIMER
      ;SET BAR BIT FOR LINE 16
      ;TO START TRANSMISSION
      ;WAIT FOR TRANSMITTER
      ;TO FINISH
005476 010077 006260      MOV R0,0DHLPB
005502 005067 006354      CLR TIME2
005506 005067 006352      CLR TEMP1
005512 012767 000010 006346      MOV #10,TEMP2
005520 012777 040000 006242      MOV #40000,0DHBA

005526 005777 006224      20: TST 0DHSCR
      ;UPDATE TRANSMITTER TIMER
      ;UPDATE NO CLOCK TIMER
005532 100412      BMI 30
005534 005267 006322      INC TIME2
005540 005267 006320      INC TEMP1
005544 001370      BNE 20
005546 005367 006314      DEC TEMP2
005552 001365      BNE 20
005554      HLT 1 ;TRANSMITTER DID NOT FINISH, ERROR
005554 104001      EMT 1
005556 000405      BR 40
005560 026767 006276 006272 30: CMP TIME2,TIME1
005566 103401      BLO 40
      ;VERIFY THAT TRANSMITTER
      ;WAS FASTER AT THIS SELECTED SPEED
      ;(NUMBER OF COUNTS IN TIME2
      ;LESS THAN TIME1)
      ;TRANSMITTER TIMING ERROR FOR

005570      HLT 2
005570 104002      EMT 2

005572 104410      40: SCOPE1
005574 016767 006262 006256      MOV TIME2,TIME1
005602 005204      INC R4
005604 062700 002000      ADD #2000,R0
005610 005301      DEC R1
005612 001317      BNE 10
005614 104400      50: SCOPE
      ;CHECK FOR ITERATIONS, LOOP
      LINE=LINE+1
      BITX=BITX+BITX
      SPEED \LINE,\BITX,3,+//,2000,+//TRANSMITTER/
005616

```

```

;TRANSMITTER LINE SPEED SELECTION TEST
;TRANSMIT 3 CHARACTERS AT A SELECTED SPEED ON LINE 17
;VERIFY THAT TRANSMITTER DONE OCCURS AT THE SELECTED SPEED
;VERIFY THAT THE AMOUN OF TIME TAKEN IS LESS
;AT THIS SPEED THAN AT THE PREVIOUSLY SELECTED SPEED

```

Address	Hex	Hex	Hex	Label	Assembly	Comments
005616	012767	000340	172152	TS \XN,10,5,1		
005616	012767	000010	006172	T20:	MOV #340,PS	;DISABLE ALL INTERRUPTS
005624	012767	006036	006160		MOV #10,ICOUNT	;SET UP FOR 10 ITERATIONS
005632	012767	006036	006160		MOV #5,ESCAPE	;SET UP TO ESCAPE TO NEXT TEST
005640	012767	005674	006154	.IF NB <1>	MOV #1,FREEZ1	;SET UP TO LOOP WITH DATA ; 3
	000021			.ENDC		
	000021			XN=XN+1		
005646	012705	000017			MOV #17,R5	;LINE 17 WILL BE TESTED
005652	012700	002000			MOV #2000,R0	;CONSTANT FOR SELECTION
005656	012701	000015			MOV #15,R1	;OF INITIAL (LOWEST) SPEED
005662	012704	000001			MOV #1,R4	;15 DIFFERENT SPEEDS WILL BE TESTED
005666	012767	177777	006164		MOV #-1,TIME1	;BINARY CODE FOR INITIAL SPEED
005674	012777	004000	006054	1:	MOV #BIT11,SDHSCR	;INITIALIZE COMPARISON VALUE
005702	010577	006050			MOV R5,SDHSCR	;CLEAR INTERFACE
005706	005077	006052			CLR SDHBA	;SELECT LINE 17 FOR TESTING
005712	012777	177775	006046		MOV #-3,SDHBC	;CLEAR BUS ADDRESS
005720	010077	006036			MOV R0,SDHLPR	;SET UP TO TRANSMIT
005724	005067	006132			CLR TIME2	;3 CHARACTERS
005730	005067	006130			CLR TEMP1	;SELECT LINE SPEED
005734	012767	000010	006124		MOV #10,TEMP2	;CLEAR TRANSMITTER TIME TIMER
005742	012777	100000	006020		MOV #100000,SDHBAR	;SET UP NO CLOCK TIMER
005750	005777	006002		2:	TST SDHSCR	;SET BAR BIT FOR LINE 17
005754	100412				BMI 3:	;TO START TRANSMISSION
005756	005267	006100			INC TIME2	;WAIT FOR TRANSMITTER
005762	005267	006076			INC TEMP1	;TO FINISH
005766	001370				BNE 2:	
005770	005367	006072			DEC TEMP2	
005774	001365				BNE 2:	
005776					HLT 1	
005776	104001				EMT 1	;TRANSMITTER DID NOT FINISH, ERROR
006000	000405				BR 4:	
006002	026767	006054	006050	3:	CMP TIME2,TIME1	;UPDATE TRANSMITTER TIMER
006010	103401				BLO 4:	;UPDATE NO CLOCK TIMER
006012					HLT 2	
006012	104002				EMT 2	;TRANSMITTER TIMING ERROR FOR
006014	104410			4:	SCOPE1	;LINE 17
006016	016767	006040	006034		MOV TIME2,TIME1	;CHECK FOR FREEZE ON CURRENT DATA
006024	005204				INC R4	;SET UP FOR NEXT COMPARISON
006026	062700	002000			ADD #2000,R0	;SELECT NEXT SPEED
006032	005701				DEC R1	
006034	001317				BNE 1:	
006036	104400			5:	SCOPE	;CHECK FOR ITERATIONS. LOOP

```

000020      LINE=LINE+1
000000      BITX=BITX+BITX
16 000020      XLINE=LINE
17 000000      LINE=0
18 000000      XBIT=BITX
19 000001      BITX=1
21 000020      .REPT 20
22      SPEED \LINE,\BITX,1,+B/,2100,+RECEIVER/
23      .NLIST
24      LINE=LINE+1
25      BITX=BITX+BITX
26      .LIST
27      .ENDR
006040      SPEED \LINE,\BITX,1,+B/,2100,+RECEIVER/

;RECEIVER LINE SPEED SELECTION TEST
;TRANSMIT 1 CHARACTERS AT A SELECTED SPEED ON LINE 0
;VERIFY THAT RECEIVER DONE OCCURS AT THE SELECTED SPEED
;VERIFY THAT THE AMOUN OF TIME TAKEN IS LESS
;AT THIS SPEED THAN AT THE PREVIOUSLY SELECTED SPEED

006040      TS \XN,10,5+,1+
006040 012767 000340 171730 T21:  MOV  #340,PS          ;DISABLE ALL INTERRUPTS
006046 012767 000010 005750      MOV  #10,ICOUNT      ;SET UP FOR 10 ITERATIONS
006054 012767 006260 005736      MOV  #5+,ESCAPE      ;SET UP TO ESCAPE TO NEXT TEST
;IF NB <1+>
006062 012767 006116 005732      MOV  #1+,FREEZ1      ;SET UP TO LOOP WITH DATA      ; 3
;ENDC
XN=XN+1
006070 000022
006074 012705 000000      MOV  #0,R5          ;LINE 0 WILL BE TESTED
006074 012700 002100      MOV  #2100,R0      ;CONSTANT FOR SELECTION
;OF INITIAL (LOWEST) SPEED
;15 DIFFERENT SPEEDS WILL BE TESTED
006100 012701 000015      MOV  #15,R1      ;BINARY CODE FOR INITIAL SPEED
006104 012704 000001      MOV  #1,R4      ;INITIALIZE COMPARISION VALUE
006110 012767 177777 005742      MOV  #-1,TIME1      ;CLEAR INTERFACE
006116 012777 004000 005632 1+:  MOV  #BIT11,SDHSCR      ;SELECT LINE 0 FOR TESTING
006124 010577 005626      MOV  R5,SDHSCR      ;CLEAR BUS ADDRESS
006130 005077 005630      CLR  SDHBA      ;SET UP TO TRANSMIT
006134 012777 177777 005624      MOV  #-1,SDHBC      ;1 CHARACTERS
;SELECT LINE SPEED
;CLEAR RECEIVER TIME TIMER
;SET UP NO CLOCK TIMER
006142 010077 005614      MOV  R0,SDHLPR
006146 005067 005710      CLR  TIME2
006152 005067 005706      CLR  TEMP1
006156 012767 000010 005702      MOV  #10,TEMP2
006164 012777 000001 005576      MOV  #1,SDHBAR      ;SET BAR BIT FOR LINE 0
;TO START TRANSMISSION
;WAIT FOR RECEIVER
;TO FINISH
006172 105777 005560      2+:  TSTB  SDHSCR
006176 100412
006200 005267 005656      BMI  3+
006204 005267 005654      INC  TIME2          ;UPDATE RECEIVER TIMER
006210 001370      INC  TEMP1          ;UPDATE NO CLOCK TIMER
006212 005367 005650      BNE  2+
006216 001365      DEC  TEMP2
006220      BNE  2+
006220      HLT  1          ;RECEIVER DID NOT FINISH, ERROR
006220      EMT  1
006222 000405      BR  4+

```

```

006224 026767 005632 005626 34:  CMP      TIME2,TIME1      ;VERIFY THAT RECEIVER
006232 103401                      BLO      44              ;WAS FASTER AT THIS SELECTED SPEED
                                           ;(NUMBER OF COUNTS IN TIME2
006234                      HLT      2              ;LESS THAN TIME1)
006234 104002                      EMT      2              ;RECEIVER TIMING ERROR FOR
                                           ;LINE 0
006236 104410                      44:  SCOPE1              ;CHECK FOR FREEZE ON CURRENT DATA
006240 016767 005616 005612      MOV      TIME2,TIME1      ;SET UP FOR NEXT COMPARISON
006246 005204                      INC      R4              ;SELECT NEXT SPEED
006250 062700 002100      ADD      #2100,R0
006254 005301                      DEC      R1
006256 001317                      BNE     14
006260 104400                      54:  SCOPE              ;CHECK FOR ITERATIONS, LOOP
      000001      LINE=LINE+1
      000002      BITX=BITX+BITX
006262      SPEED  \LINE,\BITX,1,+/B/,2100,+/RECEIVER/

      ;RECEIVER LINE SPEED SELECTION TEST
      ;TRANSMIT 1 CHARACTERS AT A SELECTED SPEED ON LINE 1
      ;VERIFY THAT RECEIVER DONE OCCURS AT THE SELECTED SPEED
      ;VERIFY THAT THE AMOUN OF TIME TAKEN IS LESS
      ;AT THIS SPEED THAN AT THE PREVIOUSLY SELECTED SPEED

006262      TS \XN,10,54,14
006262 012767 000340 171506      T22:  MOV      #340,PS      ;DISABLE ALL INTERRUPTS
006270 012767 000010 005526      MOV      #10,ICOUNT      ;SET UP FOR 10 ITERATIONS
006276 012767 006502 005514      MOV      #54,ESCAPE      ;SET UP TO ESCAPE TO NEXT TEST
                                           ;IF NB <14>
006304 012767 006340 005510      MOV      #14,FREEZ1      ;SET UP TO LOOP WITH DATA      ; 3
      .ENDC
      XN=XN+1
006312 012705 000001      MOV      #1,R5      ;LINE 1 WILL BE TESTED
006316 012700 002100      MOV      #2100,R0      ;CONSTANT FOR SELECTION
                                           ;OF INITIAL (LOWEST) SPEED
006322 012701 000015      MOV      #15,R1      ;15 DIFFERENT SPEEDS WILL BE TESTED
006326 012704 000001      MOV      #1,R4      ;BINARY CODE FOR INITIAL SPEED
006332 012767 177777 005520      MOV      #-1,TIME1      ;INITIALIZE COMPARISON VALUE
006340 012777 004000 005410      14:  MOV      @BIT11,@DHSCR      ;CLEAR INTERFACE
006346 010577 005404      MOV      R5,@DHSCR      ;SELECT LINE 1 FOR TESTING
006352 005077 005406      CLR      @DHBA      ;CLEAR BUS ADDRESS
006356 012777 177777 005402      MOV      #-1,@DHBC      ;SET UP TO TRANSMI
                                           ;1 CHARACTERS
006364 010077 005372      MOV      R0,@DHLPR      ;SELECT LINE SPEED
006370 005067 005466      CLR      TIME2      ;CLEAR RECEIVER TIME TIMER
006374 005067 005464      CLR      TEMP1      ;SET UP NO CLOCK TIMER
006400 012767 000010 005460      MOV      #10,TEMP2
006406 012777 000002 005354      MOV      #2,@DHBA
                                           ;SET BAR BIT FOR LINE 1
006414 105777 005336      24:  TSTB      @DHSCR      ;TO START TRANSMISSION
                                           ;WAIT FOR RECEIVER
                                           ;TO FINISH
006420 100412      BMI      34
006422 005267 005434      INC      TIME2      ;UPDATE RECEIVER TIMER
006426 005267 005432      INC      TEMP1      ;UPDATE NO CLOCK TIMER
006432 001370      BNE     24
006434 005367 005426      DEC      TEMP2
006440 001365      BNE     24

```

```

006442          HLT      1          ;RECEIVER DID NOT FINISH, ERROR
006442 104001    EMT      1
006444 000405    BR       4$
006446 026767 005410 005404 3$: CMP      TIME2,TIME1      ;VERIFY THAT RECEIVER
006454 103401    BLO      4$          ;WAS FASTER AT THIS SELECTED SPEED
                                           ;(NUMBER OF COUNTS IN TIME2
                                           ;LESS THAN TIME1)
006456          HLT      2          ;RECEIVER TIMING ERROR FOR
006456 104002    EMT      2
                                           ;LINE 1
006460 104410    4$: SCOPE1      ;CHECK FOR FREEZE ON CURRENT DATA
006462 016767 005374 005370 MOV      TIME2,TIME1      ;SET UP FOR NEXT COMPARISION
006470 005204    INC      R4          ;SELECT NEXT SPEED
006472 062700 002100 ADD      #2100,R4
006476 005301    DEC      R1
006500 001317    BNE      1$
006502 104400    5$: SCOPE          ;CHECK FOR ITERATIONS, LOOP
006502 000002    LINE=LINE+1
006502 000004    BITX=BITX+BITX
006504          SPEED \LINE,\BITX,1,↑/B/,2100,↑/RECEIVER/

;RECEIVER LINE SPEED SELECTION TEST
;TRANSMIT 1 CHARACTERS AT A SELECTED SPEED ON LINE 2
;VERIFY THAT RECEIVER DONE OCCURS AT THE SELECTED SPEED
;VERIFY THAT THE AMOUN OF TIME TAKEN IS LESS
;AT THIS SPEED THAN AT THE PREVIOUSLY SELECTED SPEED

006504          TS \XN,10,5$,1$
006504 012767 000340 171264 T23: MOV      #340,PS          ;DISABLE ALL INTERRUPTS
006512 012767 000010 005304 MOV      #10,ICOUNT        ;SET UP FOR 10 ITERATIONS
006520 012767 006724 005272 MOV      #5$,ESCAPE        ;SET UP TO ESCAPE TO NEXT TEST
                                           .IF NB <1$>
006526 012767 006562 005266 MOV      #1$,FREEZ1        ;SET UP TO LOOP WITH DATA      ; 3
                                           .ENDC
006526 000024    XN=XN+1
006534 012705 000002 MOV      #2,R5          ;LINE 2 WILL BE TESTED
006540 012700 002100 MOV      #2100,R0        ;CONSTANT FOR SELECTION
                                           ;OF INITIAL (LOWEST) SPEED
006544 012701 000015 MOV      #15,R1        ;15 DIFFERENT SPEEDS WILL BE TESTED
006550 012704 000001 MOV      #1,R4          ;BINARY CODE FOR INITIAL SPEED
006554 012767 177777 005276 MOV      #-1,TIME1      ;INITIALIZE COMPARISION VALUE
006562 012777 004000 005166 1$: MOV      #BIT11,0DHSCR    ;CLEAR INTERFACE
006570 010577 005162 MOV      R5,0DHSCR        ;SELECT LINE 2 FOR TESTING
006574 005077 005164 CLR      0DH8A          ;CLEAR BUS ADDRESS
006600 012777 177777 005160 MOV      #-1,0DH8C        ;SET UP TO TRANSMIT
                                           ;1 CHARACTERS
006606 010077 005150 MOV      R0,0DHLPR        ;SELECT LINE SPEED
006612 005067 005244 CLR      TIME2          ;CLEAR RECEIVER TIME TIMER
006616 005067 005242 CLR      TEMP1          ;SET UP NO CLOCK TIMER
006622 012767 000010 005236 MOV      #10,TEMP2
006630 012777 000004 005132 MOV      #4,0DH8AR
                                           ;SET BAR BIT FOR LINE 2
006636 105777 005114 2$: TSTB      0DHSCR        ;TO START TRANSMISSION
                                           ;WAIT FOR RECEIVER
                                           ;TO FINISH
006642 100412    BMI      3$
006644 005267 005212 INC      TIME2          ;UPDATE RECEIVER TIMER
006650 005267 005210 INC      TEMP1          ;UPDATE NO CLOCK TIMER

```

```

006654 001370      BNE      2$
006656 005367 005204 DEC      TEMP2
006662 001365      BNE      2$
006664      HLT      1          ;RECEIVER DID NOT FINISH. ERROR
006666 104001      EMT      1
006666 000405      BR      4$
006670 026767 005166 005162 3$: CMP      TIME2,TIME1
006676 103401      BLO      4$          ;VERIFY THAT RECEIVER
                                        ;WAS FASTER AT THIS SELECTED SPEED
                                        ;(NUMBER OF COUNTS IN TIME2
                                        ;LESS THAN TIME1)
                                        ;RECEIVER TIMING ERROR FOR

006700      HLT      2
006700 104002      EMT      2

006702 104410      4$: SCOPE1
006704 016767 005152 005146 MOV      TIME2,TIME1
006712 005204      INC      R4
006714 062700 002100 ADD      #2100,R0
006720 005301      DEC      R1
006722 001317      BNE      1$
006724 104400      5$: SCOPE
000003 LINE=LINE+1
000010 BITX=BITX+BITX          ;CHECK FOR ITERATIONS. LOOP
006726 SPEED \LINE,\BITX,1,+/B/,2100,+/RECEIVER/

;RECEIVER LINE SPEED SELECTION TEST
;TRANSMIT 1 CHARACTERS AT A SELECTED SPEED ON LINE 3
;VERIFY THAT RECEIVER DONE OCCURS AT THE SELECTED SPEED
;VERIFY THAT THE AMOUN OF TIME TAKEN IS LESS
;AT THIS SPEED THAN AT THE PREVIOUSLY SELECTED SPEED

006726 TS \XN,10,5$,1$
006726 012767 000340 171042 T24: MOV      #340,PS
006734 012767 000010 005062 MOV      #10,ICOUNT
006742 012767 007146 005050 MOV      #5$,ESCAPE          ;DISABLE ALL INTERRUPTS
                                        ;SET UP FOR 10 ITERATIONS
                                        ;SET UP TO ESCAPE TO NEXT TEST

006750 012767 007004 005044 .IF NB <1$> MOV      #1$,FREEZ1          ;SET UP TO LOOP WITH DATA ; 3
                                        .ENDC
                                        XN=XN+1

006756 012705 000003 MOV      #3,R5          ;LINE 3 WILL BE TESTED
006762 012700 002100 MOV      #2100,R0          ;CONSTANT FOR SELECTION
                                        ;OF INITIAL (LOWEST) SPEED
                                        ;15 DIFFERENT SPEEDS WILL BE TESTED
006766 012701 000015 MOV      #15,R1          ;BINARY CODE FOR INITIAL SPEED
006772 012704 000001 MOV      #1,R4          ;INITIALIZE COMPARISION VALUE
006776 012767 177777 005054 MOV      #-1,TIME1
007004 012777 004000 004744 1$: MOV      #BIT11,@DHSCR
007012 010577 004740 MOV      R5,@DHSCR
007016 005077 004742 CLR      @DHBA
007022 012777 177777 004736 MOV      #-1,@DHBC
                                        ;CLEAR INTERFACE
                                        ;SELECT LINE 3 FOR TESTING
                                        ;CLEAR BUS ADDRESS
                                        ;SET UP TO TRANSMIT
                                        ;1 CHARACTERS
007030 010077 004726 MOV      R0,@DHLPR
007034 005067 005022 CLR      TIME2
007040 005067 005020 CLR      TEMP1
007044 012767 000010 005014 MOV      #10,TEMP2
007052 012777 000010 004710 MOV      #10,@DHBAR
                                        ;SELECT LINE SPEED
                                        ;CLEAR RECEIVER TIME TIMER
                                        ;SET UP NO CLOCK TIMER

007060 105777 004672 2$: TSTB      @DHSCR          ;SET BAR BIT FOR LINE 3
                                        ;TO START TRANSMISSION
                                        ;WAIT FOR RECEIVER
                                        ;TO FINISH

```

```

007064 100412      BMI      3$
007066 005267 004770      INC      TIME2      ;UPDATE RECEIVER TIMER
007072 005267 004766      INC      TEMP1      ;UPDATE NO CLOCK TIMER
007076 001370      BNE      2$
007100 005367 004762      DEC      TEMP2
007104 001365      BNE      2$
007106      HLT      1      ;RECEIVER DID NOT FINISH, ERROR
007106 104001      EMT      1
007110 000405      BR      4$
007112 026767 004744 004740 3$: CMP      TIME2,TIME1      ;VERIFY THAT RECEIVER
007120 103401      BLO      4$      ;WAS FASTER AT THIS SELECTED SPEED
                                           ;(NUMBER OF COUNTS IN TIME2
                                           ;LESS THAN TIME1)
                                           ;RECEIVER TIMING ERROR FOR

007122      HLT      2
007122 104002      EMT      2

007124 104410      4$: SCOPE1      ;LINE 3
007126 016767 004730 004724      MOV      TIME2,TIME1      ;CHECK FOR FREEZE ON CURRENT DATA
007134 005204      INC      R4      ;SET UP FOR NEXT COMPARISION
007136 062700 002100      ADD      #2100,R0      ;SELECT NEXT SPEED
007142 005301      DEC      R1
007144 001317      BNE      1$
007146 104400      5$: SCOPE      ;CHECK FOR ITERATIONS, LOOP
      000004      LINE=LINE+1
      000020      BITX=BITX+BITX
007150      SPEED \LINE,\BITX.1,↑/B/,2100,↑/RECEIVER/

      ;RECEIVER LINE SPEED SELECTION TEST
      ;TRANSMIT 1 CHARACTERS AT A SELECTED SPEED ON LINE 4
      ;VERIFY THAT RECEIVER DONE OCCURS AT THE SELECTED SPEED
      ;VERIFY THAT THE AMOUN OF TIME TAKEN IS LESS
      ;AT THIS SPEED THAN AT THE PREVIOUSLY SELECTED SPEED

007150      TS \XN,10,5$,1$
007150 012767 000340 170620 T25: MOV      #340,PS      ;DISABLE ALL INTERRUPTS
007156 012767 000010 004640      MOV      #10,ICOUNT      ;SET UP FOR 10 ITERATIONS
007164 012767 007370 004626      MOV      #5$,ESCAPE      ;SET UP TO ESCAPE TO NEXT TEST

      .IF NB <1$>
007172 012767 007226 004622      MOV      #1$,FREEZ1      ;SET UP TO LOOP WITH DATA      ; 3
      .ENDC
      XN=XN+1

007200 012705 000004      MOV      #4,R5      ;LINE 4 WILL BE TESTED
007204 012700 002100      MOV      #2100,R0      ;CONSTANT FOR SELECTION
                                           ;OF INITIAL (LOWEST) SPEED
007210 012701 000015      MOV      #15,R1      ;15 DIFFERENT SPEEDS WILL BE TESTED
007214 012704 000001      MOV      #1,R4      ;BINARY CODE FOR INITIAL SPEED
007220 012767 177777 004632      MOV      #-1,TIME1      ;INITIALIZE COMPARISION VALUE
007226 012777 004000 004522 1$: MOV      #BIT11,0DHSCR      ;CLEAR INTERFACE
007234 010577 004516      MOV      R5,0DHSCR      ;SELECT LINE 4 FOR TESTING
007240 005077 004520      CLR      0DH8A      ;CLEAR BUS ADDRESS
007244 012777 177777 004514      MOV      #-1,0DH8C      ;SET UP TO TRANSMIT
                                           ;1 CHARACTERS
007252 010077 004504      MOV      R0,0DHLPR      ;SELECT LINE SPEED
007256 005067 004600      CLR      TIME2      ;CLEAR RECEIVER TIME TIMER
007262 005067 004576      CLR      TEMP1      ;SET UP NO CLOCK TIMER
007266 012767 000010 004572      MOV      #10,TEMP2
007274 012777 000020 004466      MOV      #20,0DH8AR      ;SET BAR BIT FOR LINE 4

```

```

007302 105777 004450      2$:  TSTB  @DHSCR      ;TO START TRANSMISSION
                                           ;WAIT FOR RECEIVER
                                           ;TO FINISH
007306 100412      BMI  3$
007310 005267 004546      INC  TIME2      ;UPDATE RECEIVER TIMER
007314 005267 004544      INC  TEMP1      ;UPDATE NO CLOCK TIMER
007320 001370      BNE  2$
007322 005367 004540      DEC  TEMP2
007326 001365      BNE  2$
007330      HLT  1      ;RECEIVER DID NOT FINISH, ERROR
007330 104001      EMT  1
007332 000405      BR  4$
007334 026767 004522 004516 3$:  CMP  TIME2,TIME1      ;VERIFY THAT RECEIVER
007342 103401      BLO  4$      ;WAS FASTER AT THIS SELECTED SPEED
                                           ;(NUMBER OF COUNTS IN TIME2
                                           ;LESS THAN TIME1)
                                           ;RECEIVER TIMING ERROR FOR

007344      HLT  2
007344 104002      EMT  2

007346 104410      4$:  SCOPE1      ;LINE 4
007350 016767 004506 004502      MOV  TIME2,TIME1      ;CHECK FOR FREEZE ON CURRENT DATA
007356 005204      INC  R4      ;SET UP FOR NEXT COMPARISION
007360 062700 002100      ADD  @2100,R0      ;SELECT NEXT SPEED
007364 005301      DEC  R1
007366 001317      BNE  1$
007370 104400      5$:  SCOPE      ;CHECK FOR ITERATIONS, LOOP
      000005      LINE=LINE+1
      000040      BITX=BITX+BITX
007372      SPEED  \LINE,\BITX,1,+/B/,2100,+/RECEIVER/

      ;RECEIVER LINE SPEED SELECTION TEST
      ;TRANSMIT 1 CHARACTERS AT A SELECTED SPEED ON LINE 5
      ;VERIFY THAT RECEIVER DONE OCCURS AT THE SELECTED SPEED
      ;VERIFY THAT THE AMOUN OF TIME TAKEN IS LESS
      ;AT THIS SPEED THAN AT THE PREVIOUSLY SELECTED SPEED

007372      TS  \XN,10,5$,1$
007372 012767 000340 170376 T26:  MOV  #340,PS      ;DISABLE ALL INTERRUPTS
007400 012767 000010 004416      MOV  #10,ICOUNT      ;SET UP FOR 10 ITERATIONS
007406 012767 007612 004404      MOV  #5$,ESCAPE      ;SET UP TO ESCAPE TO NEXT TEST

007414 012767 007450 004400      .IF NB  <1$>
      MOV  #1$,FREEZ1      ;SET UP TO LOOP WITH DATA      ; 3
      .ENDC
      XN=XN+1

007422 012705 000005      MOV  #5,R5      ;LINE 5 WILL BE TESTED
007426 012700 002100      MOV  @2100,R0      ;CONSTANT FOR SELECTION
                                           ;OF INITIAL (LOWEST) SPEED
007432 012701 000015      MOV  #15,R1      ;15 DIFFERENT SPEEDS WILL BE TESTED
007436 012704 000001      MOV  #1,R4      ;BINARY CODE FOR INITIAL SPEED
007442 012767 177777 004410      MOV  #-1,TIME1      ;INITIALIZE COMPARISION VALUE
007450 012777 004000 004300 1$:  MOV  @BIT11,@DHSCR      ;CLEAR INTERFACE
007456 010577 004274      MOV  R5,@DHSCR      ;SELECT LINE 5 FOR TESTING
007462 005077 004276      CLR  @DHBA      ;CLEAR BUS ADDRESS
007466 012777 177777 004272      MOV  #-1,@DHBC      ;SET UP TO TRANSMIT
                                           ;1 CHARACTERS
007474 010077 004262      MOV  R0,@DHLPR      ;SELECT LINE SPEED
007500 005067 004356      CLR  TIME2      ;CLEAR RECEIVER TIME TIMER

```

```

007504 005067 004354          CLR      TEMP1          ;SET UP NO CLOCK TIMER
007510 012767 000010 004350    MOV      #10,TEMP2
007516 012777 000040 004244    MOV      #40,0DH8AR      ;SET BAR BIT FOR LINE 5
                                           ;TO START TRANSMISSION
007524 105777 004226          2$:    TSTB      0DHSCR      ;WAIT FOR RECEIVER
                                           ;TO FINISH

007530 100412          BMI      3$
007532 005267 004324          INC      TIME2          ;UPDATE RECEIVER TIMER
007536 005267 004322          INC      TEMP1          ;UPDATE NO CLOCK TIMER
007542 001370          BNE      2$
007544 005367 004316          DEC      TEMP2
007550 001365          BNE      2$
007552          HLT      1          ;RECEIVER DID NOT FINISH, ERROR
007552 104001          EMT      1
007554 000405          BR      4$
007556 026767 004300 004274 3$:    CMP      TIME2,TIME1
007564 103401          BLO      4$          ;VERIFY THAT RECEIVER
                                           ;WAS FASTER AT THIS SELECTED SPEED
                                           ;(NUMBER OF COUNTS IN TIME2
                                           ;LESS THAN TIME1)
                                           ;RECEIVER TIMING ERROR FOR

007566          HLT      2
007566 104002          EMT      2          ;LINE 5
                                           ;CHECK FOR FREEZE ON CURRENT DATA
                                           ;SET UP FOR NEXT COMPARISION
                                           ;SELECT NEXT SPEED

007570 104410          4$:    SCOPE1
007572 016767 004264 004260    MOV      TIME2,TIME1
007600 005204          INC      R4
007602 062700 002100          ADD      #2100,R0
007606 005301          DEC      R1
007610 001317          BNE      1$
007612 104400          5$:    SCOPE
007612 000606          LINE=LINE+1
007612 000100          BITX=BITX+BITX
007614          SPEED \LINE,\BITX,1,†/B/,2100,†/RECEIVER/

                                           ;RECEIVER LINE SPEED SELECTION TEST
                                           ;TRANSMIT 1 CHARACTERS AT A SELECTED SPEED ON LINE 6
                                           ;VERIFY THAT RECEIVER DONE OCCURS AT THE SELECTED SPEED
                                           ;VERIFY THAT THE AMOUN OF TIME TAKEN IS LESS
                                           ;AT THIS SPEED THAN AT THE PREVIOUSLY SELECTED SPEED

007614          TS \XN,10,5$,1$
007614 012767 000340 170154    T27:    MOV      #340,PS          ;DISABLE ALL INTERRUPTS
007622 012767 000010 004174    MOV      #10,ICOUNT      ;SET UP FOR 10 ITERATIONS
007630 012767 010034 004162    MOV      #5$,ESCAPE      ;SET UP TO ESCAPE TO NEXT TEST

007636 012767 007672 004156    .IF NB <1$>
                                MOV      #1$,FREEZ1      ;SET UP TO LOOP WITH DATA
                                .ENDC
                                XN=XN+1
                                ; 3

007644 012705 000006          MOV      #6,R5          ;LINE 6 WILL BE TESTED
007650 012700 002100          MOV      #2100,R0          ;CONSTANT FOR SELECTION
                                           ;OF INITIAL (LOWEST) SPEED
007654 012701 000015          MOV      #15,R1          ;15 DIFFERENT SPEEDS WILL BE TESTED
007660 012704 000001          MOV      #1,R4          ;BINARY CODE FOR INITIAL SPEED
007664 012767 177777 004166    MOV      #-1,TIME1      ;INITIALIZE COMPARISION VALUE
007672 012777 004000 004056 1$:    MOV      #BIT11,0DHSCR ;CLEAR INTERFACE
007700 010577 004052          MOV      R5,0DHSCR      ;SELECT LINE 6 FOR TESTING
007704 005077 004054          CLR      0DH8A          ;CLEAR BUS ADDRESS
007710 012777 177777 004050    MOV      #-1,0DH8C      ;SET UP TO TRANSMIT

```

```

007716 010077 004040      MOV    R0,0DHLPR      ;1 CHARACTERS
007722 005067 004134      CLR    TIME2        ;SELECT LINE SPEED
007726 005067 004132      CLR    TEMP1        ;CLEAR RECEIVER TIME TIMER
007732 012767 000010 004126  MOV    #10,TEMP2    ;SET UP NO CLOCK TIMER
007740 012777 000100 004022  MOV    #100,0DHBAR

007746 105777 004004      2$:  TSTB    0DHSCR      ;SET BAR BIT FOR LINE 6
                                           ;TO START TRANSMISSION
                                           ;WAIT FOR RECEIVER
                                           ;TO FINISH

007752 100412      BMI    3$
007754 005267 004102      INC    TIME2        ;UPDATE RECEIVER TIMER
007760 005267 004100      INC    TEMP1        ;UPDATE NO CLOCK TIMER
007764 001370      BNE    2$
007766 005367 004074      DEC    TEMP2
007772 001365      BNE    2$
007774      HLT    1
007774 104001      EMT    1
007776 000405      BR     4$
010000 026767 004056 004052 3$:  CMP    TIME2,TIME1
010006 103401      BLO    4$

                                           ;RECEIVER DID NOT FINISH, ERROR

010010      HLT    2
010010 104002      EMT    2

                                           ;LINE 6
010012 104410      4$:  SCOPE1
010014 016767 004042 004036  MOV    TIME2,TIME1
010022 005204      INC    R4
010024 062700 002100      ADD    #2100,R0
010030 005301      DEC    R1
010032 001317      BNE    1$
010034 104400      5$:  SCOPE
010036 000007      LINE=LINE+1
010036 000200      BITX=BITX+BITX
                                           ;CHECK FOR ITERATIONS, LOOP
                                           SPEED \LINE,\BITX,1,↑/8/,2100,↑/RECEIVER/

                                           ;RECEIVER LINE SPEED SELECTION TEST
                                           ;TRANSMIT 1 CHARACTERS AT A SELECTED SPEED ON LINE 7
                                           ;VERIFY THAT RECEIVER DONE OCCURS AT THE SELECTED SPEED
                                           ;VERIFY THAT THE AMOUN OF TIME TAKEN IS LESS
                                           ;AT THIS SPEED THAN AT THE PREVIOUSLY SELECTED SPEED

010036      TS \XN,10,5$,1$
010036 012767 000340 167732 T30:  MOV    #340,PS      ;DISABLE ALL INTERRUPTS
010044 012767 000010 003752  MOV    #10,ICOUNT    ;SET UP FOR 10 ITERATIONS
010052 012767 010256 003740  MOV    #5$,ESCAPE    ;SET UP TO ESCAPE TO NEXT TEST

010060 012767 010114 003734  .IF NB <1$>
                                           ;SET UP TO LOOP WITH DATA      : 3
                                           .ENDC
XN=XN+1
010066 012705 000007      MOV    #7,R5      ;LINE 7 WILL BE TESTED
010072 012700 002100      MOV    #2100,R0    ;CONSTANT FOR SELECTION
                                           ;OF INITIAL (LOWEST) SPEED
010076 012701 000015      MOV    #15,R1      ;15 DIFFERENT SPEEDS WILL BE TESTED
010102 012704 000001      MOV    #1,R4      ;BINARY CODE FOR INITIAL SPEED
010106 012767 177777 003744  MOV    #-1,TIME1  ;INITIALIZE COMPARISION VALJE
010114 012777 004000 003634 1$:  MOV    #BIT11,0DHSCR ;CLEAR INTERFACE

```

```

010122 010577 003630      MOV    R5,0DHSCR      ;SELECT LINE 7 FOR TESTING
010126 005077 003632      CLR    0DH8A        ;CLEAR BUS ADDRESS
010132 012777 177777 003626  MOV    0-1,0DH8C    ;SET UP TO TRANSMIT
                                           ;1 CHARACTERS
010140 010077 003616      MOV    R0,0DHLPR    ;SELECT LINE SPEED
010144 005067 003712      CLR    TIME2        ;CLEAR RECEIVER TIME TIMER
010150 005067 003710      CLR    TEMP1        ;SET UP NO CLOCK TIMER
010154 012767 000010 003704  MOV    010,TEMP2
010162 012777 000200 003600  MOV    0200,0DH8AR
                                           ;SET BAR BIT FOR LINE 7
                                           ;TO START TRANSMISSION
010170 105777 003562      2$: TSTB    0DHSCR    ;WAIT FOR RECEIVER
                                           ;TO FINISH

010174 100412      BMI    3$
010176 005267 003660      INC    TIME2        ;UPDATE RECEIVER TIMER
010202 005267 003656      INC    TEMP1        ;UPDATE NO CLOCK TIMER
010206 001370      BNE    2$
010210 005367 003652      DEC    TEMP2
010214 001365      BNE    2$
010216      HLT    1
                                           ;RECEIVER DID NOT FINISH, ERROR
010216 104001      EMT    1
010220 000405      BR     4$
010222 026767 003634 003630 3$: CMP    TIME2,TIME1
010230 103401      BLO    4$
                                           ;VERIFY THAT RECEIVER
                                           ;WAS FASTER AT THIS SELECTED SPEED
                                           ;(NUMBER OF COUNTS IN TIME2
                                           ;LESS THAN TIME1)
                                           ;RECEIVER TIMING ERROR FOR

010232      HLT    2
010232 104002      EMT    2
                                           ;LINE 7
010234 104410      4$: SCOPE1
010236 016767 003620 003614  MOV    TIME2,TIME1 ;CHECK FOR FREEZE ON CURRENT DATA
010244 005204      INC    R4                  ;SET UP FOR NEXT COMPARISON
010246 062700 002100      ADD    02100,R0      ;SELECT NEXT SPEED
010252 005301      DEC    R1
010254 001317      BNE    1$
010256 104400      5$: SCOPE
010256 000010      LINE=LINE+1
010256 000400      BITX=BITX+BITX
010260      SPEED  \LINE,\BITX,1,1/0/,2100,1/RECEIVER/
                                           ;CHECK FOR ITERATIONS, LOOP

                                           ;RECEIVER LINE SPEED SELECTION TEST
                                           ;TRANSMIT 1 CHARACTERS AT A SELECTED SPEED ON LINE 10
                                           ;VERIFY THAT RECEIVER DONE OCCURS AT THE SELECTED SPEED
                                           ;VERIFY THAT THE AMOUN OF TIME TAKEN IS LESS
                                           ;AT THIS SPEED THAN AT THE PREVIOUSLY SELECTED SPEED

010260      TS \XN,10,5$,1$
010260 012767 000340 167510 T31: MOV    0340,PS      ;DISABLE ALL INTERRUPTS
010266 012767 000010 003530  MOV    010,ICOUNT    ;SET UP FOR 10 ITERATIONS
010274 012767 010500 003516  MOV    05$,ESCAPE  ;SET UP TO ESCAPE TO NEXT TEST

010302 012767 010336 003512  .IF NB <1$>
                                           ;SET UP TO LOOP WITH DATA
                                           ; 3
010302 012767 010336 003512  MOV    01$,FREEZ1
010302 000032      .ENDC
010302 000032      XN=XN+1
010310 012705 000010      MOV    010,R5      ;LINE 10 WILL BE TESTED
010314 012700 002100      MOV    02100,R0    ;CONSTANT FOR SELECTION
                                           ;OF INITIAL (LOWEST) SPEED
010320 012701 000015      MOV    015,R1      ;15 DIFFERENT SPEEDS WILL BE TESTED

```

```

010324 012704 000001      MOV    #1,R4      ;BINARY CODE FOR INITIAL SPEED
010330 012767 177777 003522  MOV    #-1,TIME1    ;INITIALIZE COMPARISON VALUE
010336 012777 004000 003412 1$:  MOV    @BIT11,@DHSCR  ;CLEAR INTERFACE
010344 010577 003406      MOV    R5,@DHSCR    ;SELECT LINE 10 FOR TESTING
010350 005077 003410      CLR     @DHBA      ;CLEAR BUS ADDRESS
010354 012777 177777 003404  MOV    #-1,@DHBC    ;SET UP TO TRANSMIT
                                           ;1 CHARACTERS
010362 010077 003374      MOV    R0,@DHLPR    ;SELECT LINE SPEED
010366 005067 003470      CLR     TIME2       ;CLEAR RECEIVER TIME TIMER
010372 005067 003466      CLR     TEMP1       ;SET UP NO CLOCK TIMER
010376 012767 000010 003462  MOV    #10,TEMP2
010404 012777 000400 003356  MOV    #400,@DHBAR  ;SET BAR BIT FOR LINE 10
                                           ;TO START TRANSMISSION
010412 105777 003340      2$:  TSTB    @DHSCR    ;WAIT FOR RECEIVER
                                           ;TO FINISH
010416 100412      BMI     3$
010420 005267 003436      INC     TIME2       ;UPDATE RECEIVER TIMER
010424 005267 003434      INC     TEMP1       ;UPDATE NO CLOCK TIMER
010430 001370      BNE     2$
010432 005367 003430      DEC     TEMP2
010436 001365      BNE     2$
010440      HLT     1      ;RECEIVER DID NOT FINISH, ERROR
010440 104001      EMT     1
010442 000405      BR      4$
010444 026767 003412 003406 3$:  CMP    TIME2,TIME1  ;VERIFY THAT RECEIVER
010452 103401      BLO     4$                ;WAS FASTER AT THIS SELECTED SPEED
                                           ; (NUMBER OF COUNTS IN TIME2
                                           ; LESS THAN TIME1)
                                           ;RECEIVER TIMING ERROR FOR
010454      HLT     2
010454 104002      EMT     2
                                           ;LINE 10
010456 104410      4$:  SCOPE1    ;CHECK FOR FREEZE ON CURRENT DATA
010460 016767 003376 003372  MOV    TIME2,TIME1  ;SET UP FOR NEXT COMPARISON
010466 005204      INC     R4                ;SELECT NEXT SPEED
010470 062700 002100      ADD     @2100,R0
010474 005301      DEC     R1
010476 001317      BNE     1$
010500 104400      5$:  SCOPE      ;CHECK FOR ITERATIONS, LOOP
010500 000011      LINE=LINE+1
010502 001000      BITX=BITX+BITX
SPEED \LINE,\BITX,1,+/@/.2100,+/RECEIVER/

;RECEIVER LINE SPEED SELECTION TEST
;TRANSMIT 1 CHARACTERS AT A SELECTED SPEED ON LINE 11
;VERIFY THAT RECEIVER DONE OCCURS AT THE SELECTED SPEED
;VERIFY THAT THE AMOUN OF TIME TAKEN IS LESS
;AT THIS SPEED THAN AT THE PREVIOUSLY SELECTED SPEED

010502      TS \XN,10,5$,1$
010502 012767 000340 167266 T32:  MOV    #340,PS      ;DISABLE ALL INTERRUPTS
010510 012767 000010 003306  MOV    #10,ICOUNT   ;SET UP FOR 10 ITERATIONS
010516 012767 010722 003274  MOV    #5$,ESCAPE  ;SET UP TO ESCAPE TO NEXT TEST
                                           ; 3
010524 012767 010560 003270  .IF NB  <1$>
                                           ;SET UP TO LOOP WITH DATA
010524 000033      .ENDC
010532 012705 000011      XN=XN+1
MOV    #11,R5      ;LINE 11 WILL BE TESTED

```

```

010536 012700 002100      MOV      #2100,R0      ;CONSTANT FOR SELECTION
                                ;OF INITIAL (LOWEST) SPEED
010542 012701 000015      MOV      #15,R1      ;15 DIFFERENT SPEEDS WILL BE TESTED
010546 012704 000001      MOV      #1,R4      ;BINARY CODE FOR INITIAL SPEED
010552 012767 177777 003300 1#:      MOV      #-1,TIME1 ;INITIALIZE COMPARISON VALUE
010560 012777 004000 003170      MOV      #BIT11,0DHSCR ;CLEAR INTERFACE
010566 010577 003164      MOV      R5,0DHSCR ;SELECT LINE 11 FOR TESTING
010572 005077 003166      CLR      0DHBA      ;CLEAR BUS ADDRESS
010576 012777 177777 003162      MOV      #-1,0DHBC ;SET UP TO TRANSMIT
                                ;1 CHARACTERS
010604 010077 003152      MOV      R0,0DHLPR ;SELECT LINE SPEED
010610 005067 003246      CLR      TIME2      ;CLEAR RECEIVER TIME TIMER
010614 005067 003244      CLR      TEMP1      ;SET UP NO CLOCK TIMER
010620 012767 000010 003240      MOV      #10,TEMP2
010626 012777 001000 003134      MOV      #1000,0DHBAR ;SET BAR BIT FOR LINE 11
                                ;TO START TRANSMISSION
010634 105777 003116      2#:      TSTB      0DHSCR ;WAIT FOR RECEIVER
                                ;TO FINISH
010640 100412      BMI      3#
010642 005267 003214      INC      TIME2      ;UPDATE RECEIVER TIMER
010646 005267 003212      INC      TEMP1      ;UPDATE NO CLOCK TIMER
010652 001370      BNE      2#
010654 005367 003206      DEC      TEMP2
010660 001365      BNE      2#
010662      HLT      1
010662 104001      EMT      1      ;RECEIVER DID NOT FINISH, ERROR
010664 000405      BR      4#
010666 026767 003170 003164 3#:      CMP      TIME2,TIME1
010674 103401      BLO      4#      ;VERIFY THAT RECEIVER
                                ;WAS FASTER AT THIS SELECTED SPEED
                                ; (NUMBER OF COUNTS IN TIME2
                                ; LESS THAN TIME1)
                                ;RECEIVER TIMING ERROR FOR
010676      HLT      2
010676 104002      EMT      2
                                ;LINE 11
010700 104410      4#:      SCOPE1      ;CHECK FOR FREEZE ON CURRENT DATA
010702 016767 003154 003150      MOV      TIME2,TIME1 ;SET UP FOR NEXT COMPARISON
010710 005204      INC      R4      ;SELECT NEXT SPEED
010712 062700 002100      ADD      #2100,R0
010716 005301      DEC      R1
010720 001317      BNE      1#
010722 104400      5#:      SCOPE      ;CHECK FOR ITERATIONS, LOOP
                                LINE=LINE+1
                                BITX=BITX+BITX
010724      SPEED \LINE,\BITX,1,↑/B/,2100,↑/RECEIVER/

                                ;RECEIVER LINE SPEED SELECTION TEST
                                ;TRANSMIT 1 CHARACTERS AT A SELECTED SPEED ON LINE 12
                                ;VERIFY THAT RECEIVER DONE OCCURS AT THE SELECTED SPEED
                                ;VERIFY THAT THE AMOUN OF TIME TAKEN IS LESS
                                ;AT THIS SPEED THAN AT THE PREVIOUSLY SELECTED SPEED

010724      TS \XP' 10,5#,1#
010724 012767 000340 167044 T33:      MOV      #340,PS      ;DISABLE ALL INTERRUPTS
010732 012767 000010 003064      MOV      #10,ICOUNT ;SET UP FOR 10 ITERATIONS
010740 012767 011144 003052      MOV      #5#,ESCAPE ;SET UP TO ESCAPE TO NEXT TEST
                                .IF NB <1#>
010746 012767 011002 003046      MOV      #1#,FREEZ1 ;SET UP TO LOOP WITH DATA

```

```

      .ENDC
      XN=XN+1
010754 000034      MOV    #12,R5      ;LINE 12 WILL BE TESTED
010760 012705 000012      MOV    #2100,R0      ;CONSTANT FOR SELECTION
      002100      ;OF INITIAL (LOWEST) SPEED
010764 012701 000015      MOV    #15,R1      ;15 DIFFERENT SPEEDS WILL BE TESTED
010770 012704 000001      MOV    #1,R4      ;BINARY CODE FOR INITIAL SPEED
010774 012767 177777 003056      MOV    #-1,TIME1      ;INITIALIZE COMPARISON VALUE
011002 012777 004000 002746 1$:      MOV    #BIT11,SDHSCR      ;CLEAR INTERFACE
011010 010577 002742      MOV    R5,SDHSCR      ;SELECT LINE 12 FOR TESTING
011014 005077 002744      CLR    SDHBA      ;CLEAR BUS ADDRESS
011020 012777 177777 002740      MOV    #-1,SDHBC      ;SET UP TO TRANSMIT
      ;1 CHARACTERS
      ;SELECT LINE SPEED
011026 010077 002730      MOV    R0,SDHLPR      ;CLEAR RECEIVER TIME TIMER
011032 005067 003024      CLR    TIME2      ;SET UP NO CLOCK TIMER
011036 005067 003022      CLR    TEMP1
011042 012767 000010 003016      MOV    #10,TEMP2
011050 012777 002000 002712      MOV    #2000,SDHBAR      ;SET BAR BIT FOR LINE 12
      ;TO START TRANSMISSION
011056 105777 002674      2$:      TSTB    SDHSCR      ;WAIT FOR RECEIVER
      ;TO FINISH
011062 100412      BMI    3$
011064 005267 002772      INC    TIME2      ;UPDATE RECEIVER TIMER
011070 005267 002770      INC    TEMP1      ;UPDATE NO CLOCK TIMER
011074 001370      BNE    2$
011076 005367 002764      DEC    TEMP2
011102 001365      BNE    2$
011104      HLT    1      ;RECEIVER DID NOT FINISH, ERROR
011104 104001      EMT    1
011106 000405      BR    4$
011110 026767 002746 002742 3$:      CMP    TIME2,TIME1      ;VERIFY THAT RECEIVER
011116 103401      BLO    4$      ;WAS FASTER AT THIS SELECTED SPEED
      ;(NUMBER OF COUNTS IN TIME2
      ;LESS THAN TIME1)
      ;RECEIVER TIMING ERROR FOR
011120      HLT    2
011120 104002      EMT    2
      ;LINE 12
011122 104410      4$:      SCOPE1      ;CHECK FOR FREEZE ON CURRENT DATA
011124 016767 002732 002726      MOV    TIME2,TIME1      ;SET UP FOR NEXT COMPARISON
011132 005204      INC    R4      ;SELECT NEXT SPEED
011134 062700 002100      ADD    #2100,R0
011140 005301      DEC    R1
011142 001317      BNE    1$
011144 104400      5$:      SCOPE      ;CHECK FOR ITERATIONS, LOOP
      LINE=LINE+1
      BITX=BITX+BITX
011146 004000      SPEED \LINE,\BITX,1,+/B/,2100,+/RECEIVER/
      ;RECEIVER LINE SPEED SELECTION TEST
      ;TRANSMIT 1 CHARACTERS AT A SELECTED SPEED ON LINE 13
      ;VERIFY THAT RECEIVER DONE OCCURS AT THE SELECTED SPEED
      ;VERIFY THAT THE AMOUN OF TIME TAKEN IS LESS
      ;AT THIS SPEED THAN AT THE PREVIOUSLY SELECTED SPEED
011146      TS \XN,10,5$,1$
011146 012767 000340 166622 T34:      MOV    #340,PS      ;DISABLE ALL INTERRUPTS
011154 012767 000010 002642      MOV    #10,ICOUNT      ;SET UP FOR 10 ITERATIONS

```

```

011162 012767 011366 002630      MOV    #51,ESCAPE      ;SET UP TO ESCAPE TO NEXT TEST
                                .IF NB <11>
011170 012767 011224 002624      MOV    #11,FREEZ1      ;SET UP TO LOOP WITH DATA      ; 3
                                .ENDC
                                XN=XN+1
011176 012705 000013      MOV    #13,R5      ;LINE 13 WILL BE TESTED
011202 012700 002100      MOV    #2100,R0      ;CONSTANT FOR SELECTION
                                ;OF INITIAL (LOWEST) SPEED
011206 012701 000015      MOV    #15,R1      ;15 DIFFERENT SPEEDS WILL BE TESTED
011212 012704 000001      MOV    #1,R4      ;BINARY CODE FOR INITIAL SPEED
011216 012767 177777 002634      MOV    #-1,TIME1      ;INITIALIZE COMPARISON VALUE
011224 012777 004000 002524 11:  MOV    #BIT11,SDHSCR      ;CLEAR INTERFACE
011232 010577 002520      MOV    R5,SDHSCR      ;SELECT LINE 13 FOR TESTING
011236 005077 002522      CLR    SDHBA      ;CLEAR BUS ADDRESS
011242 012777 177777 002516      MOV    #-1,SDHBC      ;SET UP TO TRANSMIT
                                ;1 CHARACTERS
011250 010077 002506      MOV    R0,SDHLPR      ;SELECT LINE SPEED
011254 005067 002602      CLR    TIME2      ;CLEAR RECEIVER TIME TIMER
011260 005067 002600      CLR    TEMP1      ;SET UP NO CLOCK TIMER
011264 012767 000010 002574      MOV    #10,TEMP2
011272 012777 004000 002470      MOV    #4000,SDHBA      ;SET BAR BIT FOR LINE 13
                                ;TO START TRANSMISSION
011300 105777 002452      21:  TSTB    SDHSCR      ;WAIT FOR RECEIVER
                                ;TO FINISH
011304 100412      BMI    31
011306 005267 002550      INC    TIME2      ;UPDATE RECEIVER TIMER
011312 005267 002546      INC    TEMP1      ;UPDATE NO CLOCK TIMER
011316 001370      BNE    21
011320 005367 002542      DEC    TEMP2
011324 001365      BNE    21
011326      HLT    1      ;RECEIVER DID NOT FINISH, ERROR
011326 104001      EMT    1
011330 000405      BR    41
011332 026767 002524 002520 31:  CMP    TIME2,TIME1      ;VERIFY THAT RECEIVER
011340 103401      BLO    41      ;WAS FASTER AT THIS SELECTED SPEED
                                ;(NUMBER OF COUNTS IN TIME2
                                ;LESS THAN TIME1)
                                ;RECEIVER TIMING ERROR FOR
011342      HLT    2
011342 104002      EMT    2
                                ;LINE 13
011344 104410      41:  SCOPE1      ;CHECK FOR FREEZE ON CURRENT DATA
011346 016767 002510 002504      MOV    TIME2,TIME1      ;SET UP FOR NEXT COMPARISON
011354 005204      INC    R4      ;SELECT NEXT SPEED
011356 062700 002100      ADD    #2100,R0
011362 005301      DEC    R1
011364 001317      BNE    11
011366 104400      51:  SCOPE      ;CHECK FOR ITERATIONS, LOOP
                                LINE=LINE+1
                                BITX=BITX+BITX
011370      SPEED \LINE,\BITX,1,1/B/,2100,1/RECEIVER/

;RECEIVER LINE SPEED SELECTION TEST
;TRANSMIT 1 CHARACTERS AT A SELECTED SPEED ON LINE 14
;VERIFY THAT RECEIVER DONE OCCURS AT THE SELECTED SPEED
;VERIFY THAT THE AMOUN OF TIME TAKEN IS LESS
;AT THIS SPEED THAN AT THE PREVIOUSLY SELECTED SPEED

```

```

011370      TS \XN,10,5,1,1
011370 012767 000340 166400 T35:  MOV    #340,PS          ;DISABLE ALL INTERRUPTS
011376 012767 000010 002420      MOV    #10,ICOUNT      ;SET UP FOR 10 ITERATIONS
011404 012767 011610 002406      MOV    #5,ESCAPE       ;SET UP TO ESCAPE TO NEXT TEST

011412 012767 011446 002402      .IF NB <1>
                                MOV    #1,FREEZ1        ;SET UP TO LOOP WITH DATA      ; 3
                                .ENDC
                                XN=XN+1

011420 012705 000014      MOV    #14,R5          ;LINE 14 WILL BE TESTED
011424 012700 002100      MOV    #2100,R0        ;CONSTANT FOR SELECTION
                                                ;OF INITIAL (LOWEST) SPEED
011430 012701 000015      MOV    #15,R1          ;15 DIFFERENT SPEEDS WILL BE TESTED
011434 012704 000001      MOV    #1,R4          ;BINARY CODE FOR INITIAL SPEED
011440 012767 177777 002412      MOV    #1,TIME1     ;INITIALIZE COMPARISON VALUE
011446 012777 004000 002302 1#:  MOV    #BIT11,0DHSCR ;CLEAR INTERFACE
011454 010577 002276      MOV    R5,0DHSCR        ;SELECT LINE 14 FOR TESTING
011460 005077 002300      CLR    0DHBA          ;CLEAR BUS ADDRESS
011464 012777 177777 002274      MOV    #1,0DHBC    ;SET UP TO TRANSMIT
                                                ;1 CHARACTERS
011472 010077 002264      MOV    R0,0DHLP        ;SELECT LINE SPEED
011476 005067 002360      CLR    TIME2          ;CLEAR RECEIVER TIME TIMER
011502 005067 002356      CLR    TEMP1          ;SET UP NO CLOCK TIMER
011506 012767 000010 002352      MOV    #10,TEMP2
011514 012777 010000 002246      MOV    #10000,0DHBA ;SET BAR BIT FOR LINE 14
                                                ;TO START TRANSMISSION
011522 105777 002230      2#:  TSTB    0DHSCR      ;WAIT FOR RECEIVER
                                                ;TO FINISH

011526 100412      BMI    3#
011530 005267 002326      INC    TIME2          ;UPDATE RECEIVER TIMER
011534 005267 002324      INC    TEMP1          ;UPDATE NO CLOCK TIMER
011540 001370      BNE    2#
011542 005367 002320      DEC    TEMP2
011546 001365      BNE    2#
011550      HLT    1
011550 104001      EMT    1
011552 000405      BR    4#
011554 026767 002302 002276 3#:  CMP    TIME2,TIME1 ;VERIFY THAT RECEIVER
011562 103401      BLO    4#                    ;WAS FASTER AT THIS SELECTED SPEED
                                                ; (NUMBER OF COUNTS IN TIME2
                                                ; LESS THAN TIME1)
                                                ;RECEIVER TIMING ERROR FOR

011564      HLT    2
011564 104002      EMT    2

011566 104410      4#:  SCOPE1
011570 016767 002266 002262      MOV    TIME2,TIME1 ;LINE 14
011576 005204      INC    R4                    ;CHECK FOR FREEZE ON CURRENT DATA
011600 062700 002100      ADD    #2100,R0        ;SET UP FOR NEXT COMPARISON
011604 005301      DEC    R1                    ;SELECT NEXT SPEED
011606 001317      BNE    1#
011610 104400      5#:  SCOPE
                                LINE=LINE+1
                                BITX=BITX+BITX
                                SPEED \LINE,\BITX,1,+/B/,2100,+/RECEIVER/

011612      ;RECEIVER LINE SPEED SELECTION TEST
                                ;TRANSMIT 1 CHARACTERS AT A SELECTED SPEED ON LINE 15
                                ;VERIFY THAT RECEIVER DONE OCCURS AT THE SELECTED SPEED

```

;VERIFY THAT THE AMOUN OF TIME TAKEN IS LESS
;AT THIS SPEED THAN AT THE PREVIOUSLY SELECTED SPEED

```

011612      TS \XN,10,5,1;
011612 012767 000340 166156 T36: MOV #340,PS ;DISABLE ALL INTERRUPTS
011620 012767 000010 002176 MOV #10,ICOUNT ;SET UP FOR 10 ITERATIONS
011626 012767 012032 002164 MOV #5,ESCAPE ;SET UP TO ESCAPE TO NEXT TEST

011634 012767 011670 002160 .IF NB <1; MOV #1,FREEZ1 ;SET UP TO LOOP WITH DATA ; 3
                                .ENDC
                                XN=XN+1

011642 012705 000015 MOV #15,R5 ;LINE 15 WILL BE TESTED
011646 012700 002100 MOV #2100,R0 ;CONSTANT FOR SELECTION
                                ;OF INITIAL (LOWEST) SPEED
                                ;15 DIFFERENT SPEEDS WILL BE TESTED
011652 012701 000015 MOV #15,R1 ;BINARY CODE FOR INITIAL SPEED
011656 012704 000001 MOV #1,R4 ;INITIALIZE COMPARISION VALUE
011662 012767 177777 002170 MOV #1,TIME1 ;CLEAR INTERFACE
011670 012777 004000 002060 1;: MOV #BIT11,SDHSCR ;SELECT LINE 15 FOR TESTING
011676 010577 002054 MOV R5,SDHSCR ;CLEAR BUS ADDRESS
011702 005077 002056 CLR SDHBA ;SET UP TO TRANSMIT
011706 012777 177777 002052 MOV #1,SDHBC ;1 CHARACTERS
                                ;SELECT LINE SPEED
011714 010077 002042 MOV R0,SDHLPR ;CLEAR RECEIVER TIME TIMER
011720 005067 002136 CLR TIME2 ;SET UP NO CLOCK TIMER
011724 005067 002134 CLR TEMP1
011730 012767 000010 002130 MOV #10,TEMP2
011736 012777 020000 002024 MOV #20000,SDHBAR ;SET BAR BIT FOR LINE 15
                                ;TO START TRANSMISSION
011744 105777 002006 2;: TSTB SDHSCR ;WAIT FOR RECEIVER
                                ;TO FINISH

011750 100412 BMI 3;
011752 005267 002104 INC TIME2 ;UPDATE RECEIVER TIMER
011756 005267 002102 INC TEMP1 ;UPDATE NO CLOCK TIMER
011762 001370 BNE 2;
011764 005367 002076 DEC TEMP2
011770 001365 BNE 2;
011772 HLT 1 ;RECEIVER DID NOT FINISH, ERROR
011772 104001 EMT 1
011774 000405 BR 4;
011776 026767 002060 002054 3;: CMP TIME2,TIME1 ;VERIFY THAT RECEIVER
012004 103401 BLO 4; ;WAS FASTER AT THIS SELECTED SPEED
                                ;(NUMBER OF COUNTS IN TIME2
                                ;LESS THAN TIME1)
                                ;RECEIVER TIMING ERROR FOR

012006 HLT 2
012006 104002 EMT 2

012010 104410 4;: SCOPE1 ;LINE 15
012012 016767 002044 002040 MOV TIME2,TIME1 ;CHECK FOR FREEZE ON CURRENT DATA
012020 005204 INC R4 ;SET UP FOR NEXT COMPARISION
012022 062700 002100 ADD #2100,R0 ;SELECT NEXT SPEED
012026 005301 DEC R1
012030 001317 BNE 1;
012032 104400 5;: SCOPE ;CHECK FOR ITERATIONS, LOOP
                                LINE=LINE+1
                                BITX=BITX+BITX
012034 SPEED \LINE,\BITX,1,+/B/,2100,+/RECEIVER/

```

```

;RECEIVER LINE SPEED SELECTION TEST
;TRANSMIT 1 CHARACTERS AT A SELECTED SPEED ON LINE 16
;VERIFY THAT RECEIVER DONE OCCURS AT THE SELECTED SPEED
;VERIFY THAT THE AMOUN OF TIME TAKEN IS LESS
;AT THIS SPEED THAN AT THE PREVIOUSLY SELECTED SPEED

```

012034				TS \XN,10,5\$,1\$		
012034	012767	000340	165734	T37: MOV	#340,PS	;DISABLE ALL INTERRUPTS
012042	012767	000010	001754	MOV	#10,ICOUNT	;SET UP FOR 10 ITERATIONS
012050	012767	012254	001742	MOV	#5\$,ESCAPE	;SET UP TO ESCAPE TO NEXT TEST
				.IF NB	<1\$>	
012056	012767	012112	001736	MOV	#1\$,FREEZ1	;SET UP TO LOOP WITH DATA ; 3
	000040			.ENDC		
				XN=XN+1		
012064	012705	000016		MOV	#16,R5	;LINE 16 WILL BE TESTED
012070	012700	002100		MOV	#2100,R0	;CONSTANT FOR SELECTION
						;OF INITIAL (LOWEST) SPEED
012074	012701	000015		MOV	#15,R1	;15 DIFFERENT SPEEDS WILL BE TESTED
012100	012704	000001		MOV	#1,R4	;BINARY CODE FOR INITIAL SPEED
012104	012767	177777	001746	MOV	#-1,TIME1	;INITIALIZE COMPARISION VALUE
012112	012777	004000	001636	1\$: MOV	#BIT11,0DHSCR	;CLEAR INTERFACE
012120	010577	001632		MOV	R5,0DHSCR	;SELECT LINE 16 FOR TESTING
012124	005077	001634		CLR	0DHBA	;CLEAR BUS ADDRESS
012130	012777	177777	001630	MOV	#-1,0DHBC	;SET UP TO TRANSMIT
						;1 CHARACTERS
012136	010077	001620		MOV	R0,0DHLPR	;SELECT LINE SPEED
012142	005067	001714		CLR	TIME2	;CLEAR RECEIVER TIME TIMER
012146	005067	001712		CLR	TEMP1	;SET UP NO CLOCK TIMER
012152	012767	000010	001706	MOV	#10,TEMP2	
012160	012777	040000	001602	MOV	#40000,0DHBAR	;SET BAR BIT FOR LINE 16
						;TO START TRANSMISSION
012166	105777	001564		2\$: TSTB	0DHSCR	;WAIT FOR RECEIVER
						;TO FINISH
012172	100412			BMI	3\$	
012174	005267	001662		INC	TIME2	;UPDATE RECEIVER TIMER
012200	005267	001660		INC	TEMP1	;UPDATE NO CLOCK TIMER
012204	001370			BNE	2\$	
012206	005367	001654		DEC	TEMP2	
012212	001365			BNE	2\$	
012214				HLT	1	;RECEIVER DID NOT FINISH, ERROR
012214	104001			EMT	1	
012216	000405			BR	4\$	
012220	026767	001636	001632	3\$: CMP	TIME2,TIME1	;VERIFY THAT RECEIVER
012226	103401			BLO	4\$	;WAS FASTER AT THIS SELECTED SPEED
						; (NUMBER OF COUNTS IN TIME2
						;LESS THAN TIME1)
						;RECEIVER TIMING ERROR FOR
012230				HLT	2	
012230	104002			EMT	2	
						;LINE 16
012232	104410			4\$: SCOPE1		;CHECK FOR FREEZE ON CURRENT DATA
012234	016767	001622	001616	MOV	TIME2,TIME1	;SET UP FOR NEXT COMPARISION
012242	005204			INC	R4	;SELECT NEXT SPEED
012244	062700	002100		ADD	#2100,R0	
012250	005301			DEC	R1	
012252	001317			BNE	1\$	
012254	104400			5\$: SCOPE		;CHECK FOR ITERATIONS, LOOP
	000017			LINE=LINE+1		

012256 100000

BITX=BITX+BITX
SPEED \LINE,\BITX,1,+/B/,2100,+/RECEIVER/

;RECEIVER LINE SPEED SELECTION TEST
;TRANSMIT 1 CHARACTERS AT A SELECTED SPEED ON LINE 17
;VERIFY THAT RECEIVER DONE OCCURS AT THE SELECTED SPEED
;VERIFY THAT THE AMOUN OF TIME TAKEN IS LESS
;AT THIS SPEED THAN AT THE PREVIOUSLY SELECTED SPEED

012256				TS \XN,10,5\$,1\$		
012256	012767	000340	165512	T40: MOV	#340,PS	;DISABLE ALL INTERRUPTS
012264	012767	000010	001532	MOV	#10,ICOUNT	;SET UP FOR 10 ITERATIONS
012272	012767	012476	001520	MOV	#5\$,ESCAPE	;SET UP TO ESCAPE TO NEXT TEST
				.IF NB	<1\$>	
012300	012767	012334	001514	MOV	#1\$,FREEZ1	;SET UP TO LOOP WITH DATA ; 3
				.ENDC		
		000041		XN=XN+1		
012306	012705	000017		MOV	#17,R5	;LINE 17 WILL BE TESTED
012312	012700	002100		MOV	#2100,R0	;CONSTANT FOR SELECTION
						;OF INITIAL (LOWEST) SPEED
012316	012701	000015		MOV	#15,R1	;15 DIFFERENT SPEEDS WILL BE TESTED
012322	012704	000001		MOV	#1,R4	;BINARY CODE FOR INITIAL SPEED
012326	012767	177777	001524	MOV	#-1,TIME1	;INITIALIZE COMPARISION VALUE
012334	012777	004000	001414	1\$: MOV	#BIT11,@DHSCR	;CLEAR INTERFACE
012342	010577	001410		MOV	R5,@DHSCR	;SELECT LINE 17 FOR TESTING
012346	005077	001412		CLR	@DHBA	;CLEAR BUS ADDRESS
012352	012777	177777	001406	MOV	#-1,@DHBC	;SET UP TO TRANSMIT
						;1 CHARACTERS
012360	010077	001376		MOV	R0,@DHLPR	;SELECT LINE SPEED
012364	005067	001472		CLR	TIME2	;CLEAR RECEIVER TIME TIMER
012370	005067	001470		CLR	TEMP1	;SET UP NO CLOCK TIMER
012374	012767	000010	001464	MOV	#10,TEMP2	
012402	012777	100000	001360	MOV	#100000,@DHBAR	;SET BAR BIT FOR LINE 17
						;TO START TRANSMISSION
012410	105777	001342		2\$: TSTB	@DHSCR	;WAIT FOR RECEIVER
						;TO FINISH
012414	100412			BMI	3\$	
012416	005267	001440		INC	TIME2	;UPDATE RECEIVER TIMER
012422	005267	001436		INC	TEMP1	;UPDATE NO CLOCK TIMER
012426	001370			BNE	2\$	
012430	005367	001432		DEC	TEMP2	
012434	001365			BNE	2\$	
012436				HLT	1	;RECEIVER DID NOT FINISH. ERROR
012436	104001			EMT	1	
012440	000405			BR	4\$	

012442	026767	001414	001410	3\$:	CMP	TIME2,TIME1		
012450	103401				BLO	4\$		
								;VERIFY THAT RECEIVER
								;WAS FASTER AT THIS SELECTED SPEED
								;(NUMBER OF COUNTS IN TIME2
								;LESS THAN TIME1)
012452					HLT	2		;RECEIVER TIMING ERROR FOR
012452	104002				EMT	2		
012454	104410			4\$:	SCOPE1			;LINE 17
012456	016767	001400	001374		MOV	TIME2,TIME1		;CHECK FOR FREEZE ON CURRENT DATA
012464	005204				INC	R4		;SET UP FOR NEXT COMPARISION
012466	062700	002100			ADD	#2100,R0		;SELECT NEXT SPEED
012472	005301				DEC	R1		
012474	001317				BNE	1\$		
012476	104400			5\$:	SCOPE			
	000020			LINE=LINE+1				;CHECK FOR ITERATIONS, LOOP
	000000			BITX=BITX+BITX				

1 012500

.EOP +/BEGIN/

;END OF PASS
 ;TYPE NAME OF TEST
 ;UPDATE PASS COUNT
 ;CHECK FOR EXIT TO ACT-11
 ;RESTART TEST

012500	104401			EOP:	TYPE		;TYPE NAME OF TEST	
012502	014460				MEPASS			
012504	005067	001344			CLR	LAST	;CLEAR LAST ERROR PC	
012510	005067	001274			CLR	ERRFLG	;CLEAR ERROR FLAG	
012514	005267	001272			INC	PASCNT	;UPDATE PASS COUNT	
012520	005767	166256			TST	LIGHTS	; ARE WE USING LIGHTS?	: 4
012524	001005				BNE	2#	; BRANCH IF WE ARE	: 6
012526	104401				TYPE		; TYPE PASCOUNT MESSAGE	: 5
012530	014473				PASTXT			: 5
012532	104402				OCTASC		; PRINT PASCOUNT	: 4
012534	012572				PASARG			: 4
012536	000403				BR	3#	; CONTINUE	: 4 ; 6
012540				2#:				: 4
012540	016767	001246	166234		MOV	PASCNT,LIGHTS	;DISPLAY PASS COUNT	: 4
012546				3#:				: 4
012546	013701	000042			MOV	0042,R1	;CHECK FOR ACT-11 OR DDP	
012552	001405				BEQ	RESTR	;IF NOT, CONTINUE TESTING	
012554	000005				RESET			
012556	004711			LOGICAL:		JSR PC,(R1)		
012560	000240				NOP			
012562	000240				NOP			
012564	000240				NOP			
012566	000167	166514		RESTR:	JMP	BEGIN		
012572	000001			PASARG:	.WORD	1	; PARAMETERS TO PRINT PASCOUNT	: 5
012574	006	002			.BYTE	6,2		: 5
012576	014012				.WORD	PASCNT,		: 5
2 012600				.SCOPE				
							;CHECK FOR LOOP ON CURRENT TEST	: 3
							;CHECK FOR ITERATION SUPPRESSION	
012600	032777	002000	166172	SCOPER:	BIT	#SW10,BSWR		: 4
012606	001030				BNE	4#		
012610	032777	040000	166162	1#:	BIT	#SW14,BSWR		: 4
012616	001021				BNE	3#		
012620	032777	004000	166152		BIT	#SW11,BSWR		: 4
012626	001006				BNE	2#		
012630	005267	001172			INC	LPCNT		
012634	026767	001166	001162		CMP	LPCNT,ICOUNT		
012642	001007				BNE	3#		
012644	005067	001156		2#:	CLR	LPCNT		
012650	005067	001134			CLR	ERRFLG		
012654	011667	001136			MOV	(SP),RETRN		
012660	000002				RTI			
012662	016716	001130		3#:	MOV	RETRN,(SP)		
012666	000002				RTI			
012670	005767	001114		4#:	TST	ERRFLG		
012674	001745				BEQ	1#		
012676	000762				BR	2#		

3 012700

.SCOP1

;CHECK FOR FREEZE ON CURRENT DATA

012700	032777	001000	166072	SCOP1R:	BIT	#SW09,0SWR
012706	001402				BEQ	1\$
012710	016716	001106			MOV	FREEZ1,(SP)
012714	000002			1\$:	RT1	

; 4

1 012716

.ERROR

;ERROR HANDLER

```

012716 032777 020000 166054 ERRORS: BIT    #SW13, @SWR
012724 001055          BNE    HALTS
012726 021667 001122      CMP    (SP), LAST
012732 001404          BEQ    1$
012734 011667 001114      MOV    (SP), LAST
012740 005067 001044      CLR    ERRFLG
012744 104406          1$: SAV05P
012746 011605          MOV    (SP), R5
012750 162705 000002      SUB    #2, R5
012754 011504          MOV    (R5), R4
012756 006304          ASL    R4
012760 006304          ASL    R4
012762 042704 177001      BIC    #177001, R4
012766 062704 014672      ADD    @ERRTAB, R4
012772 012467 000040      MOV    (R4)+, ERRMSG
012776 011467 000052      MOV    (R4), DATABP
013002 005767 001002      TST    ERRFLG
013006 001403          BEQ    TYPMSG
013010 005767 000040      TST    DATABP
013014 001011          BNE    TYPDAT
013016 104401          TYPMSG: TYPE
013020 014370          MCRLF
013022 104402          OCTASC
013024 013122          ERTAB0
013026 012767 000001 000754 MOV    #1, ERRFLG
013034 104401          TYPE
013036 000000          ERRMSG: 0
013040 005767 000010      TYPDAT: TST    DATABP
013044 001404          BEQ    RESREG
013046 104401          TYPE
013050 014370          MCRLF
013052 104402          OCTASC
013054 000000          DATABP: 0
013056 104407          RESREG: RES05
013060 005777 165714      HALTS: TST    @SWR
013064 100005          BPL    EXITER
013066 010046          PUSHRO
013070 016600 000002      MOV    2(SP), R0
013074 000000          HALT
013076 012600          POPRO
013100 005267 000710      EXITER: INC    ERRCNT
013104 032777 002000 165666 BIT    #SW10, @SWR
013112 001402          BEQ    1$
013114 016716 000700      MOV    ESCAPE, (SP)
013120 000002          1$: RTI
013122 000001          ERTAB0: 1
013124 006      002      .BYTE 6, 2
013126 014046          SAVPC

```

013130

.TRPSRV

;TRAP DISPATCH SERVICE
;ARGUMENT OF TRAP IS EXTRACTED
;AND USED AS OFFSET TO OBTAIN POINTER
;TO SELECTED SUBROUTINE

; 3

013130 011646
013132 162716 000002
013136 017616 000000
013142 006316
013144 042716 177001
013150 062716 014612
013154 017616 000000
013160 000136
2 013162

TRPSRV: MOV (SP),-(SP) ;GET PC OF RETURN
SUB #2,(SP) ;=PC OF TRAP
MOV @2(SP),(SP) ;GET TRP
TRPOK: ASL (SP) ;MULTIPLY TRAP ARG BY 2
BIC #177001,(SP) ;CLEAR UNWANTED BITS
ADD @TRPTAB,(SP) ;POINTER TO SUBROUTINE ADDRESS
MOV @2(SP),(SP) ;SUBROUTINE ADDRESS
JMP @2(SP)+ ;GO TO SUBROUTINE

.SAVREG

;SAVE PC OF TEST THAT FAILED AND R0-R5

013162 016667 000004 000656 SV05P: MOV 4(SP),SAVPC

;SAVE R0-R5

013170 010567 000646
013174 010467 000640
013200 010367 000632
013204 010267 000624
013210 010167 000616
013214 010067 000610
013220 000002
3 013222

SV05: MOV R5,SAVR5
MOV R4,SAVR4
MOV R3,SAVR3
MOV R2,SAVR2
MOV R1,SAVR1
MOV R0,SAVR0
RTI

; 3

.RESREG

;RESTORE R0-R5

013222 016700 000602
013226 016701 000600
013232 016702 000576
013236 016703 000574
013242 016704 000572
013246 016705 000570
013252 000002

RS05: MOV SAVR0,R0
MOV SAVR1,R1
MOV SAVR2,R2
MOV SAVR3,R3
MOV SAVR4,R4
MOV SAVR5,R5
RTI

1 013254

.TYPER

;TELETYPE OUTPUT ROUTINE

013254	017605	000000		TYPER:	MOV	8(SP),R5	
013260	062716	000002			ADD	82,(SP)	; 3
013264	105777	000462		14:	TSTB	8TPCSR	
013270	100375				BPL	14	
013272	105715				TSTB	(R5)	
013274	001001				BNE	24	
013276	000002				RTI		
013300	112577	000450		24:	MOVB	(R5)+,8TPDBR	
013304	000767				BR	14	
2 013306				.INSTRG			

;ASCII STRING INPUT ROUTINE

013306	017667	000000	000006	INSTRG:	MOV	8(SP),MSG	
013314	062716	000002			ADD	82,(SP)	
013320	104401			INSTR1:	TYPE		
013322	000000			MSG:	0		
013324	012704	014634			MOV	8INBUF,R4	
013330	012703	000007			MOV	87,R3	
013334	105777	000406		14:	TSTB	8TKCSR	
013340	100375				BPL	14	
013342	117714	000402			MOVB	8TKDBR,(R4)	
013346	142714	000200			BICB	8200,(R4)	
013352	122427	000015			CMPB	(R4)+,815	
013356	001413				BEQ	INSTR2	
013360	117777	000364	000366		MOVB	8TKDBR,8TPDBR	
013366	105777	000360		24:	TSTB	8TPCSR	
013372	100375				BPL	24	
013374	005303				DEC	R3	
013376	001356				BNE	14	
013400	104401			INSTRE:	TYPE		
013402	014364				MOVM		
013404	000745				BR	INSTR1	
013406	000002			INSTR2:	RTI		

1 013410

.PARAMS

;CONVERT ASCII STRING TO OCTAL

, 3

013410 011675
 013412 012567 000146
 013416 012567 000144
 013422 012567 000142
 013426 112567 000140
 013432 112567 000135
 013436 010516
 013440 005005
 013442 012704 014634
 013446 122714 000015
 013452 001420
 013454 121427 000060
 013460 002415
 013462 121427 000067
 013466 003012
 013470 142714 000060
 013474 152405
 013476 122714 000015
 013502 001406
 013504 006305
 013506 006305
 013510 006305
 013512 000760
 013514 104404
 013516 000750

PARAMS: MOV (SP),R5
 MOV (R5)+,LOLIM
 MOV (R5)+,HILIM
 MOV (R5)+,DEVADR
 MOV (R5)+,LOBITS
 MOV (R5)+,ADRCNT
 MOV R5,(SP)
 PARAM1: CLR R5
 MOV #INBUF,R4
 CMPB #15,(R4)
 BEQ PARERR
 14: CMPB (R4),#60
 BLT PARERR
 CMPB (R4),#67
 BGT PARERR
 BICB #60,(R4)
 BISB (R4)+,R5
 CMPB #15,(R4)
 BEQ LIMITS
 ASL R5
 ASL R5
 ASL R5
 BR 14
 PARERR: INSTER
 BR PARAM1

;TEST TO SEE IF NUMBER IS WITHIN LIMITS

013520 020567 000042
 013524 101373
 013526 020567 000032
 013532 103770
 013534 136705 000032
 013540 001365

LIMITS: CMP R5,HILIM
 BHI PARERR
 CMP R5,LOLIM
 BLO PARERR
 BITB LOBITS,R5
 BNE PARERR

, 3

;STORE NUMBER AT SPECIFIED ADDRESS

013542 016704 000022
 013546 010524
 013550 062705 000002
 013554 105367 000013
 013560 001372
 013562 000002
 013564 000000
 013566 000000
 013570 000000
 013572 000000
 013573

14: MOV DEVADR,R4
 MOV R5,(R4)+
 ADD #2,R5
 DECB ADRCNT
 BNE 14
 RTI
 LOLIM: 0
 HILIM: 0
 DEVADR: 0
 LOBITS: 0
 ADRCNT=LOBITS+1

013574

.OCTASC

;CONVERT OCTAL NUMBER TO ASCII AND OUTPUT TO TELEPRINTER

013574 017601 000000
 013600 062716 000002
 013604 012167 000130
 013610 112167 000126
 013614 112167 000123
 013620 013167 000120
 013624 016704 000114
 013630 116705 000106
 013634 012700 014646
 013640 010403
 013642 042703 177770
 013646 062703 000260
 013652 110320
 013654 006204
 013656 006204
 013660 006204
 013662 005305
 013664 001365
 013666 012703 014660
 013672 114023
 013674 105367 000042
 013700 001374
 013702 105767 000035
 013706 001405
 013710 112723 000240
 013714 105367 000023
 013720 001373
 013722 105013
 013724 104401
 013726 014660
 013730 005367 000004
 013734 001325
 013736 000002
 013740 000000
 013742 000000
 013743 013743
 013744 000000

OCTASN: MOV @ (SP), R1
 ADD @2, (SP)
 MOV (R1)+, WRDCNT
 1+: MOV (R1)+, CHRCNT
 MOV (R1)+, SPACNT
 MOV @ (R1)+, BINWRD
 2+: MOV BINWRD, R4
 MOV CHRCNT, R5
 MOV @TEMP, R0
 3+: MOV R4, R3
 BIC @177770, R3
 ADD @260, R3
 MOV R3, (R0)+
 ASR R4
 ASR R4
 ASR R4
 DEC R5
 BNE 3+
 MOV @MDATA, R3
 4+: MOV -(R0), (R3)+
 DECB CHRCNT
 BNE 4+
 TSTB SPACNT
 BEQ 6+
 5+: MOV @240, (R3)+
 DECB SPACNT
 BNE 5+
 6+: CLRB (R3)
 TYPE
 MDATA
 DEC WRDCNT
 BNE 1+
 RTI
 WRDCNT: 0
 CHRCNT: 0
 SPACNT=CHRCNT+1
 BINWRD: 0

; 5

; 3

```

013746      .POINT  +/DHSCR,DHNRC,DHLPR,DMBA,DMBC,DMBAR,DMBCR,DHSSR,DHSLR,DHRVEC,DHRLVL,DHTVEC,DHTLVL/
               ;INDIRECT POINTERS
               ; 3

013746 177560    TKCSR: 177560
013750 177562    TKDBR: 177562
013752 177564    TPCSR: 177564
013754 177566    TPDDBR: 177566
               .IRP  A      <DHSCR,DHNRC,DHLPR,DMBA,DMBC,DMBAR,DMBCR,DHSSR,DHSLR,DHRVEC,DHRLVL,DHTVEC,DH
TLVL >
               A: 0
               .ENDM
013756 000000    DHSCR: 0
013760 000000    DHNRC: 0
013762 000000    DHLPR: 0
013764 000000    DMBA: 0
013766 000000    DMBC: 0
013770 000000    DMBAR: 0
013772 000000    DMBCR: 0
013774 000000    DHSSR: 0
013776 000000    DHSLR: 0
014000 000000    DHRVEC: 0
014002 000000    DHRLVL: 0
014004 000000    DHTVEC: 0
014006 000000    DHTLVL: 0
2 014010      .VARIA +/TCONST,TIME1,TIME2,TEMP1,TEMP2/
               ;PROGRAM VARIABLES

014010 000000    ERRFLG: 0      ;ERROR FLAG
014012 000000    PASCNT: 0      ;PASS COUNT
014014 000000    ERRCNT: 0      ;ERROR COUNT
014016 000000    RETRN: 0       ;SCOPE RETURN ADDRESS FOR TEST LOOPING
014020 000000    ESCAPE: 0      ;ADDRESS FOR ERROR ESCAPE
014022 000000    FREEZ1: 0      ;DATA LOOPING RETURN ADDRESS
014024 000000    ICOUNT: 0      ;ITERATION COUNT FOR TEST IN PROGRESS
014026 000000    LPCNT: 0       ;NUMBER OF ITERATIONS THIS TEST
014030 000000    SAVR0: 0       ;R0 SAVE AREA
014032 000000    SAVR1: 0       ;R1 SAVE AREA
014034 000000    SAVR2: 0       ;R2 SAVE AREA
014036 000000    SAVR3: 0       ;R3 SAVE ARE
014040 000000    SAVR4: 0       ;R4 SAVE AREA
014042 000000    SAVR5: 0       ;R5 SAVE AREA
014044 000000    SAVSP: 0       ;STACK POINTER SAVE AREA
014046 000000    SAVPC: 0       ;CALLING ROUTINE SAVE AREA
014050 000000    INIFLG: 0      ;PROGRAM INITIALIZATION FLAG
014052 000000    STFLG: 0       ;PROGRAM START FLAG
014054 000000    LAST: 0        ;LAST ERROR PC
               .IRP  A      <TCONST,TIME1,TIME2,TEMP1,TEMP2>
               A: 0
               .ENDM
014056 000000    TCONST: 0
014060 000000    TIME1: 0
014062 000000    TIME2: 0
014064 000000    TEMP1: 0
014066 000000    TEMP2: 0

```

1 014070

.PFAIL

;ENTER HERE ON POWER FAILURE

014070	010046			PFAIL:	MOV	R0,-(SP)		;SAVE R0-R5 ON PROCESSOR STACK
014072	010146				MOV	R1,-(SP)		
014074	010246				MOV	R2,-(SP)		
014076	010346				MOV	R3,-(SP)		
014100	010446				MOV	R4,-(SP)		
014102	010546				MOV	R5,-(SP)		
014104	016746	163714			MOV	24,-(SP)		
014110	010667	177730			MOV	SP,SAVSP		;SAVE STACK POINTER
014114	012767	014126	163702		MOV	#RESTART,24		;SET UP FOR POWER UP TRAP
014122	000000				HALT			;HALT ON POWER DOWN NORMAL
014124	000777				BR	.		

;PROCESSOR WILL TRAP HERE WHEN POWER IS RESTORED

014126	016706	177712		RESTAR:	MOV	SAVSP,SP		;RESTORE STACK POINTER
014132	012605				MOV	(SP)+,R5		;RESTORE R0-R5
014134	012604				MOV	(SP)+,R4		
014136	012603				MOV	(SP)+,R3		
014140	012602				MOV	(SP)+,R2		
014142	012601				MOV	(SP)+,R1		
014144	012600				MOV	(SP)+,R0		
014146	012767	014070	163650		MOV	#PFAIL,24		;SET UP FOR POWER FAILURE
014154	012767	000340	163614		MOV	#340,PS		
014162	012706	015120			MOV	#STACK,SP		
014166	005067	000454			CLR	TEMP		
014172	005267	000450			INC	TEMP		
014176	001375				BNE	.-4		
014200	104401				TYPE			; 5
014202	014370				MCRLF			; 5
014204	104402				OCTASC			
014206	014230				PFTAB			
014210	104401				TYPE			
014212	014373				MPFAIL			
014214	005067	177570			CLR	ERRFLG		
014220	005067	177630			CLR	LAST		
014224	000177	177566			JMP	#RETRN		
014230	000001			PFTAB:	1			
014232	000006	000002			6.2			
014236	014016				RETRN			

014240				.MSG	↑/DH11 SPEED SELECTION LOGIC TEST/,↑/CZDHD-D0/
014240	015	012	012	MTITLE:	.ASCIZ <15><12><12>/DH11 SPEED SELECTION LOGIC TEST /<15><12>
014243	104	110	061		
014246	061	040	123		
014251	120	105	105		
014254	104	040	123		
014257	105	114	105		
014262	103	124	111		
014265	117	116	040		
014270	114	117	107		
014273	111	103	040		
014276	124	105	123		
014301	124	040	015		
014304	012	000			
014306	015	012	126	MVECTOR:	.ASCIZ <15><12>/VECTOR ADDRESS-/
014311	105	103	124		
014314	117	122	040		
014317	101	104	104		
014322	122	105	123		
014325	123	055	000		
014330	015	012	103	MREGAD:	.ASCIZ <15><12>/CONTROL REGISTER ADDRESS-/
014333	117	116	124		
014336	122	117	114		
014341	040	122	105		
014344	107	111	123		
014347	124	105	122		
014352	040	101	104		
014355	104	122	105		
014360	123	123	055		
014363	000				
014364	040	040	077	MQM:	.ASCIZ / ?/
014367	000				
014370	015	012	000	MCRLF:	.ASCIZ <15><12>
014373	040	040	120	MPFAIL:	.ASCIZ / POWER FAILURE, PROGRAM RESTART AT TEST IN PROGRESS/
014376	117	127	105		
014401	122	040	106		
014404	101	111	114		
014407	125	122	105		
014412	054	040	120		
014415	122	117	107		
014420	122	101	115		
014423	040	122	105		
014426	123	124	101		
014431	122	124	040		
014434	101	124	040		
014437	124	105	123		
014442	124	040	111		
014445	116	040	120		
014450	122	117	107		
014453	122	105	123		
014456	123	000			
014460	015	012	103	MEPASS:	.ASCIZ <15><12>/CZDHD-D0/
014463	132	104	110		
014466	104	055	104		
014471	060	000			
014473	015	012	120	PASTXT:	.ASCIZ <15><12>/PASS COUNT = /

	014476	101	123	123	
	014501	040	103	117	
	014504	125	116	124	
	014507	040	075	040	
	014512	000			
	014513	015	012	122	MR: .ASCIZ <15><12>/R/
	014516	000			
	014517	015	012	124	MTSTPC: .ASCIZ <15><12>/TEST PC-/
	014522	105	123	124	
	014525	040	120	103	
	014530	055	000		
					.EVEN
2	014532	116	117	040	EM1: .ASCIZ /NO CLOCK/<15><12>/LINE SPEED/
	014535	103	114	117	
	014540	103	113	015	
	014543	012	114	111	
	014546	116	105	040	
	014551	040	123	120	
	014554	105	105	104	
	014557	000			
3	014560	124	111	115	EM2: .ASCIZ /TIMING ERROR/<15><12>/LINE SPEED/
	014563	111	116	107	
	014566	040	105	122	
	014571	122	117	122	
	014574	015	012	114	
	014577	111	116	105	
	014602	040	040	123	
	014605	120	105	105	
	014610	104	000		

4
5 014612 .EVEN
.TRPTAB

;TABLE OF POINTERS FOR TRAP DECODING

014612	012600	TRPTAB: SCOPER
014614	013254	TYPER
014616	013574	OCTASN
014620	013306	INSTRG
014622	013400	INSTRE
014624	013410	PARAMS
014626	013162	SV05P
014630	013222	RS05
014632	012700	SCOP1R
6 014634		.BUFFER

;BUFFERS FOR INPUT-OUTPUT

014634	000000	INBUF: 0
	014646	.+.10
014646	000000	TEMP: 0
	014660	.+.10
014660	000000	MDATA: 0
	014672	.+.10
7 014672		.ERRTAB

;TABLE OF POINTERS TO ERROR MESSAGES AND DATA

```
014672
8 014672 000000
9 014674 000000
10 014676 014532
11 014700 014706
12 014702 014560
13 014704 014706
14
15
16
17 014706 000002
18 014710 002 004
19 014712 014042
20 014714 002 000
21 014716 014040
22 014720
014720 000000
23 000001
```

ERRTAB:

0 ;NO MESSAGE
0 ;NO DATA
ET1: EM1 ;NO CLOCK ERROR
DT1
ET2: EM2 ;TIMING ERROR
DT1

;DATA TABLES FOR ERROR OUTPUT

DT1: 2 ;2 DATA WORDS WILL BE TYPED
.BYTE 2.4 ;TWO DIGITS, 4 SPACES
SAVR5 ;LINE UNDER TEST
.BYTE 2.0 ;TWO DIGITS, NO SPACES
SAVR4 ;SELECTED SPEED

.ENDCOD
ENDCOD: 0
.END

ADRCNT = 013573	EOP 012500	MTSTPC 014517	SPACNT = 013743	T10 003376
BEGIN 001306	ERRCNT 014014	MVECTO 014306	STACK = 015120	T11 003620
BINWRD 013744	ERRFLG 014010	N = 000001	START 001004	T12 004042
BITX = 000000	ERRMSG 013036	OCTASC = 104402	STFLG 014052	T13 004264
BIT00 = 000001	ERRORS 012716	OCTASN 013574	SV05 013170	T14 004506
BIT01 = 000002	ERRTAB 014672	PARAM = 104405	SV05P 013162	T15 004730
BIT02 = 000004	ERTAB0 013122	PARAMS 013410	SWR 001000	T16 005152
BIT03 = 000010	ESCAPE 014020	PARAM1 013440	SW00 = 000001	T17 005374
BIT04 = 000020	ET1 014676	PARERR 013514	SW01 = 000002	T2 001622
BIT05 = 000040	ET2 014702	PASARG 012572	SW02 = 000004	T20 005616
BIT06 = 000100	EXITER 013100	PASCNT 014012	SW03 = 000010	T21 006040
BIT07 = 000200	FREEZ1 014022	PASTXT 014473	SW04 = 000020	T22 006262
BIT08 = 000400	HALTS 013060	PFAIL 014070	SW05 = 000040	T23 006504
BIT09 = 001000	HILIM 013566	PFTAB 014230	SW06 = 000100	T24 006726
BIT10 = 002000	ICOUNT 014024	POPRO = 012600	SW08 = 000400	T25 007150
BIT11 = 004000	INBUF 014634	POP1SP = 005726	SW09 = 001000	T26 007372
BIT12 = 010000	INIFLG 014050	POP2SP = 022626	SW10 = 002000	T27 007614
BIT13 = 020000	INSTER = 104404	PS = 177776	SW11 = 004000	T3 002044
BIT14 = 040000	INSTR = 104403	PUSHRO = 010046	SW12 = 010000	T30 010036
BIT15 = 100000	INSTRE 013400	PUSH1S = 005746	SW13 = 020000	T31 010260
CHRCNT 013742	INSTRG 013306	PUSH2S = 024646	SW14 = 040000	T32 010502
DATABP 013054	INSTR1 013320	RESREG 013056	SW15 = 100000	T33 010724
DEADDR 013570	INSTR2 013406	RESTAR 014126	TCONST 014056	T34 011146
DHBA 013764	LAST 014054	RESTRT 012566	TEMP 014646	T35 011370
DHBAR 013770	LIGHTS 001002	RES05 = 104407	TEMP1 014064	T36 011612
DHBC 013766	LIMITS 013520	RETRN 014016	TEMP2 014066	T37 012034
DHBCR 013772	LINE = 000020	RS05 013222	TIME1 014060	T4 002266
DHLPR 013762	LOBITS 013572	SAVPC 014046	TIME2 014062	T40 012256
DHMRC 013760	LOGICA 012556	SAVR0 014030	TKCSR 013746	T5 002510
DHRLVL 014002	LOLIM 013564	SAVR1 014032	TKDBR 013750	T6 002732
DHRVEC 014000	LPCNT 014026	SAVR2 014034	TPCSR 013752	T7 003154
DHSCR 013756	MCRLF 014370	SAVR3 014036	TPDBR 013754	VEC1 001164
DHSLR 013776	MDATA 014660	SAVR4 014040	TRPOK 013142	VEC2 001174
DHSSR 013774	MEPASS 014460	SAVR5 014042	TRPSRV 013130	WRDCNT 013740
DHTLVL 014006	MPFAIL 014373	SAVSP 014044	TRPTAB 014612	X = 000000
DHTVEC 014004	MQM 014364	SAV05P = 104406	TYPDAT 013040	XBIT = 000000
DT1 014706	MR 014513	SCOPE = 104400	TYPE = 104401	XLIN = 000020
EM1 014532	MREGAD 014330	SCOPEP 012600	TYPER 013254	XN = 000041
EM2 014560	MSG 013322	SCOPE1 = 104410	TYPMSG 013016	Y = 000011
ENDCOD 014720	MTITLE 014240	SCOP1R 012700	T1 001400	

. ABS. 014722 000
000000 001
ERRORS DETECTED: 0

VIRTUAL MEMORY USED: 17664 WORDS (69 PAGES)
DYNAMIC MEMORY AVAILABLE FOR 71 PAGES
CZDHD.BIN,CZDHD.SEQ=CZDHD.DOC,DHMACA.MAC,CZDHD.P11