

DU11

OFF-LINE RECEIVER TESTS
MD-11-DZDUB-C

EP-DZDUB-C-DL-A

NOV 1976

COPYRIGHT © 1976

original

FICHE 1 OF 1

MADE IN USA

The image shows a microfiche card. The left side contains a grid of frames, each containing a small, illegible image or document snippet. The right side of the card is a large, blank, light-colored area.

SDJUB-C MACY11 27.1006 01-007-76 09:17 PAGE 1
HELLO.P11 03-AUG-76 00:00

SEC 0001

THE INFORMATION IN THIS DOCUMENT IS SUBJECT TO CHANGE WITHOUT NOTICE AND SHOULD NOT BE CONSTRUED AS A COMMITMENT BY DIGITAL EQUIPMENT CORPORATION. DIGITAL EQUIPMENT CORPORATION ASSUMES NO RESPONSIBILITY FOR ANY ERRORS THAT MAY APPEAR IN THIS DOCUMENT.

THE SOFTWARE DESCRIBED IN THIS DOCUMENT IS FURNISHED UNDER A LICENSE AND MAY ONLY BE USED OR COPIED IN ACCORDANCE WITH THE TERMS OF SUCH LICENSE.

DIGITAL EQUIPMENT CORPORATION ASSUMES NO RESPONSIBILITY FOR THE USE OF RELIABILITY OF ITS SOFTWARE ON EQUIPMENT THAT IS NOT SUPPLIED BY DIGITAL.

COPYRIGHT (C) 1973, 1976 BY DIGITAL EQUIPMENT CORPORATION

GENERAL DESCRIPTION

THIS DIAGNOSTIC CAN CHAIN 16 DUII'S. THIS MEANS THAT 16 DEVICES CAN BE SEQUENTIALLY EXERCISED. THE DIAGNOSTIC MAKES ONE PASS BEFORE PROCEEDING TO THE NEXT DEVICE, AND CONTINUES EXERCISING ALL DEVICES IN THIS FASHION UNTIL HALTED.

2. REQUIREMENTS

PDP-11 FAMILY STANDARD COMPUTER WITH OR WITHOUT HARDWARE SWITCH REGISTER (LOC. 177570)

DU11 SYNCHRONOUS/ISOCRONOUS OPTION

ONE CONSOLE TELETYPE OR EQUIVALENT

2.2 STORAGE

3. LOADING PROCEDURE

THE STANDARD PROCEDURE FOR LOADING ABSOLUTE BINARY TAPES IS TO BE USED.

STARTING ADDRESS FOR ABSOLUTE LOADER

4K	017500
8K	037500
12K	057500
16K	077500
20K	117500
24K	137500
28K	157500

4. STARTING PROCEDURE

4.1 CONTROL SWITCH SETTINGS

NOTE: SOFTWARE SWITCH REGISTER IS DEFINED AS LOC. 176, WHILE THE SOFTWARE DISPLAY REGISTER IS DEFINED AS LOC. 174.

4.1.1 AFTER PROGRAM LOAD (INITIAL PROGRAM START) ALL CONSOLE SWITCHES DOWN

4.1.2 TO MODIFY DEVICE VECTOR AND CONTROL REGISTER ADDRESSES AFTER PROGRAM RESTART OR TO RUN MULTIPLE DEVICES

SW00=1

4.1.3 TO START PROGRAM AT SELECTED TEST AFTER A PROGRAM RESTART

(ONLY IN SINGLE DEVICE TESTS)
 SW01=1

- 4.1.4 TO LOCK ON SELECTED TEST AFTER A PROGRAM RESTART
 (ONLY IN SINGLE DEVICE TESTS)

SW02=1
 NOTE1: IN GENERAL SW01 WILL BE USED WHEN SW02=1 IS USED
 NOTE2: WITHOUT SW01=1 "LOCK ON TEST" WILL DEFAULT TO TEST 1
 4.2 STARTING ADDRESS

THE STARTING ADDRESS FOR ALL TESTS IS 000200

THE RETARTING ADDRESS FOR ALL TESTS IS 000200
 THE STARTING ADDRESS TO ENTER A SELECTED TEST IS 000200
 THE STARTING ADDRESS TO LOCK ON TEST IS 000200

- 4.3 PROGRAM AND/OR OPERATOR ACTION

- 4.3.1 INITIAL PROGRAM START

4.3.1.1 LOAD PROGRAM INTO MEMORY WITH ABSOLUTE LOADER

4.3.1.2 LOAD ADDRESS 000200

4.3.1.3 CLEAR CONSOLE SWITCHES

4.3.1.4 PRESS START

NOTE: IF THE SOFTWARE SWITCH REGISTER IS SELECTED THEN THE FOLLOWING
 WILL BE TYPED AFTER THE PROGRAM IDENTIFIES ITSELF:
 SWR=XXXXXX NEW= (REFER TO SECTION 5. FOR OPERATOR'S OPTION)

4.3.1.7 THE PROGRAM WILL TYPE "R" TO INDICATE THAT IT IS ABOUT
 TO START TESTING ,AND THEN TESTING WILL BEGIN

- 4.3.2 PROGRAM RESTART WITH ALL SWITCHES DOWN

4.3.2.1 THE PROGRAM WILL TYPE "R" AND WILL COMMENCE TESTING

- 4.3.3 PROGRAM RESTART WITH SW00=1

4.3.3.1 LOAD ADDRESS 000200

4.3.3.2 SET SW00=1

4.3.3.3 PRESS START

NOTE: IF THE SOFTWARE SWITCH REGISTER IS SELECTED THEN THE FOLLOWING
 WILL BE TYPED AFTER THE PROGRAM IDENTIFIES ITSELF:
 SWR=XXXXXX NEW= (REFER TO SECTION 5. FOR OPERATOR'S OPTION)

4.3.3.4 THE PROGRAM WILL TYPE " 1ST DEVICE: RECEIVER CONTROL REGISTER

ADDRESS" AND WAIT FOR AN INPUT FROM THE TELETYPE KEYBOARD

- 4.3.3.5 TYPE IN THE ADDRESS OF THE FIRST RECEIVER CONTROL REGISTER ADDRESS OF THE DUI1 TO BE TESTED FOLLOWED BY A <CARRIAGE RETURN>

IF AN INCORRECT ADDRESS IS TYPED ,THE PROGRAM WILL TYPE "?" AND WILL THEN REPEAT THE MESSAGE OF 4.3.3.4

- 4.3.3.6 THE PROGRAM WILL TYPE "VECTOR ADDRESS-" AND WAIT FOR AN INPUT FROM THE TELETYPE KEYBOARD

- 4.3.3.7 TYPE IN THE BASE RECEIVER INTERRUPT VECTOR ADDRESS FOR THE DUI1 TO BE TESTED FOLLOWED BY A <CARRIAGE RETURN>

IF AN INCORRECT ADDRESS IS TYPED ,THE PROGRAM WILL TYPE "?" AND WILL THEN REPEAT THE MESSAGE OF 4.3.3.6

- 4.3.3.8 THE PROGRAM WILL TYPE "ARE YOU RUNNING MULTIPLE DEVICES ?" (Y OR N)-" AND WAIT FOR AN INPUT FROM THE TELETYPE KEYBOARD

- 4.3.3.9 TYPE IN THE APPROPRIATE ANSWER YES OR NO FOLLOWED BY A <CARRIAGE RETURN>

IF AN INCORRECT ANSWER IS GIVEN, THE PROGRAM WILL TYPE "?" AND WILL THEN REPEAT THE MESSAGE OF 4.3.3.8

IF A "NO" ANSWER IS GIVEN: JUMP TO SECTION 4.3.3.12
 IF A "YES" ANSWER IS GIVEN:THE NEXT QUESTION IS ASKED

- 4.3.3.10 THE PROGRAM WILL TYPE "LAST DEVICE:RECEIVER CONTROL REGISTER ADDRESS-" AND WAIT FOR AN INPUT FROM THE TELETYPE KEYBOARD

- 4.3.3.11 TYPE IN THE ADDRESS OF THE LAST RECEIVER CONTROL REGISTER ADDRESS OF THE DUI1 TO BE TESTED FOLLOWED BY A <CARRIAGE RETURN>

IF AN INCORRECT ANSWER IS TYPED ,THE PROGRAM WILL TYPE "?" AND WILL THEN REPEAT THE MESSAGE OF 4.3.3.10
 NOTE:ALL ADDRESSES SHALL BE CONTIGUOUS

- 4.3.3.11.1 IF AN "OUT OF RANGE" ADDRESS IS TYPED
 IE. MORE THAN 16 (10) DEVICES AWAY (UPWARDS).....THE PROGRAM WILL TYPE "OUT OF RANGE:RETYPE LAST DEVICE RXCSR ADDRESS-" AND WAIT FOR AN INPUT FROM THE TELETYPE KEYBOARD

- 4.3.3.11.2 TYPE IN THE ADDRESS OF THE LAST RECEIVER CONTROL REGISTER ADDRESS OF THE DUI1 TO BE TESTED FOLLOWED BY A <CARRIAGE RETURN>

IF AN INCORRECT ANSWER IS TYPED ,THE PROGRAM WILL TYPE "?"

AND WILL REPEAT THE MESSAGE OF 4.3.3.11.1

IF A DEVICE ADDRESS LOWER THAN 1ST DEVICE ADDRESS IS TYPED.....
....SCHOOLS OUT.....THERE IS NO PROTECTION FOR THIS.
THE PROGRAM WILL DEFAULT TO TWO DEVICES ACTIVE (UPWARDS FROM
1ST DEVICE ADDRESS).THE SAME APPLIES TO IDENTICAL ADDRESSES
TYPED FOR FIRST AND LAST DEVICE.
OBSERVE LOCATION 2 ACTREG: SEE SECTION 7.2

4.3.3.12 THE PROGRAM WILL TYPE "DU PRIORITY LEVEL-" AND
WAIT FOR AN INPUT FROM THE TELETYPE KEYBOARD

4.3.3.13 TYPE IN THE APPROPRIATE DEVICE PRIORITY LEVEL OF THE
DU11 OR DU11'S TO BE TESTED FOLLOWED BY A <CARRIAGE RETURN>
(NOTE THAT ALL MULTIPLE DEVICES MUST BE AT THE SAME PRIORITY
LEVEL). IE "5"

IF AN INCORRECT LEVEL IS TYPED ,THE PROGRAM WILL TYPE "?"
AND REPEAT THE MESSAGE OF 4.3.3.12

4.3.3.14 THE PROGRAM WILL TYPE "# OF SYNC CHARS
SELECTED (1 OR 2)-" AND WAIT FOR AN INPUT FROM THE TELETYPE
KEYBOARD

4.3.3.15 TYPE IN THE APPROPRIATE ANSWER "1" OR "2" FOLLOWED
BY A <CARRIAGE RETURN>.(NOTE:ALL MULTIPLE DEVICES MUST
BE THE SAME)

IF AN INCORRECT ANSWER IS TYPED ,THE PROGRAM WILL TYPE "?"
AND WILL REPEAT THE MESSAGE OF 4.3.3.14

4.3.3.16 THE PROGRAM WILL TYPE " IS SEC XMIT JUMPER #6 IN ? (Y OR N)-"
AND WAIT FOR AN INPUT FROM THE TELETYPE KEYBOARD

4.3.3.17 TYPE IN THE APPROPRIATE ANSWER YES OR NO FOLLOWED
BY A <CARRIAGE RETURN>.(NOTE THAT ALL MULTIPLE DEVICES
MUST BE THE SAME)

IF AN INCORRECT ANSWER IS TYPED ,THE PROGRAM WILL TYPE "?"
AND WILL REPEAT THE MESSAGE OF 4.3.3.16

4.3.3.18 THE PROGRAM WILL TYPE "IS SEC REC JUMPER # 5 IN ?
(Y OR N)-" AND WAIT FOR AN INPUT FROM THE TELETYPE KEYBOARD

4.3.3.19 TYPE IN THE APPROPRIATE ANSWER YES OR NO FOLLOWED
BY A <CARRIAGE RETURN>. (NOTE: ALL MULTIPLE DEVICES MUST BE THE SAME)

IF AN INCORRECT ANSWER IS TYPED ,THE PROGRAM WILL TYPE "?"
AND WILL REPEAT THE MESSAGE OF 4.3.3.18

4.3.3.20 THE PROGRAM WILL TYPE "IS OPT CLR ENABLE JUMPER

* 4 IN ? (Y OR N)-" AND WAIT FOR AN INPUT FROM THE TELETYPE KEYBOARD

4.3.3.21 TYPE IN THE APPROPRIATE ANSWER YES OR NO FOLLOWED BY A <CARRIAGE RETURN>. (NOTE: ALL MULTIPLE DEVICES MUST BE THE SAME)

IF AN INCORRECT ANSWER IS TYPED ,THE PROGRAM WILL TYPE "?" AND WILL REPEAT THE MESSAGE OF 4.3.3.20

4.3.3.22 THE PROGRAM WILL TYPE "ARE YOU RUNNING IN MAINT. MODE EXTERNAL ? ANDDO YOU HAVE THE EXTERNAL MODEM BYPASS JUMPER CONNECTOR ON ? (Y OR N)-" AND WAIT FOR AN INPUT FROM THE TELETYPE KEYBOARD

4.3.3.23 TYPE IN THE APPROPRIATE ANSWER YES OR NO FOLLOWED BY A <CARRIAGE RETURN>. (NOTE: ALL MULTIPLE DEVICES MUST BE THE SAME)

IF AN INCORRECT ANSWER IS TYPED ,THE PROGRAM WILL TYPE "?" AND WILL REPEAT THE MESSAGE OF 4.3.3.22

4.3.3.24 THE PROGRAM WILL TYPE "R" TO INDICATE THAT IT HAS STARTED AND WILL COMMENCE TESTING AT TEST 1

4.3.4 PROGRAM RESTART WITH SW01=1
NOTE: THIS WILL ONLY WORK WHEN A SINGLE DEVICE IS SELECTED
,,,IT WILL NOT WORK IF MULTIPLE DEVICES ARE SELECTED

IF MULTIPLE DEVICES WERE PREVIOUSLY SELECTED, LOAD 000200,
AND SELECT SW00=1 AND ANSWER "NO" TO THE MULTIPLE DEVICE QUESTION
SEE 4.3.3

4.3.4.1 LOAD 000200

4.3.4.2 SET SW01=1

4.3.4.3 PRESS START
NOTE: IF THE SOFTWARE SWITCH REGISTER IS SELECTED THEN THE FOLLOWING
WILL BE TYPED AFTER THE PROGRAM IDENTIFIES ITSELF:
SWR=XXXXXX NEW= (REFER TO SECTION 5. FOR OPERATOR'S OPTION)

4.3.4.4 THE PROGRAM WILL TYPE "TEST PC-" AND WAIT FOR AN INPUT FROM THE TELETYPE KEYBOARD

4.3.4.5 TYPE IN THE ADDRESS OF THE TEST AT WHICH THE PROGRAM IS TO BE STARTED FOLLOWED BY A <CARRIAGE RETURN>

4.3.4.6 THE PROGRAM WILL TYPE "R" TO INDICATE THAT IT HAS STARTED TESTING AT THE SELECTED TEST

NOTE: CARE MUST BE TAKEN WHEN THIS FEATURE IS USED
SINCE THERE IS NO PROTECTION AGAINST SELECTING AN ADDRESS
THAT IS IN THE MIDDLE OF A TEST

4.3.5 PROGRAM RESTART WITH SW02 =1
NOTE: THIS WILL ONLY WORK WHEN A SINGLE DEVICE IS SELECTED

SEE NOTE IN 4.3.4 FOR MORE DETAILS

4.3.5.1 LOAD ADDRESS 000200

4.3.5.2 SET SW02 =1

NOTE: IT MAY BE ADVANTAGEOUS TO SET SW01=1 (OPTIONAL)

4.3.5.3 PRESS START

NOTE: IF THE SOFTWARE SWITCH REGISTER IS SELECTED THEN THE FOLLOWING
WILL BE TYPED AFTER THE PROGRAM IDENTIFIES ITSELF:

SWR=XXXXXX NEW= (REFER TO SECTION 5. FOR OPERATOR'S OPTION)

4.3.5.4 THE PROGRAM WILL TYPE "LOCK ON SELECTED TEST ? (Y OR N)-"
AND WAIT FOR AN INPUT FROM THE TELETYPE KEYBOARD

4.3.5.5 TYPE IN THE APPROPRIATE ANSWER YES OR NO FOLLOWED BY A
<CARRIAGE RETURN>

IF A NO ANSWER IS GIVEN: THIS LOCK ON TEST WILL BE IGNORED
AND THE PROGRAM WILL TYPE "R" TO INDICATE THAT IT HAS STARTED
TESTING AT TEST 1

4.3.5.6 IF A YES ANSWER WAS GIVEN: THE PROGRAM WILL ACT AS FOLLOWS...
THE PROGRAM WILL TYPE "R" TO INDICATE THAT IT HAS STARTED
TESTING AT TEST 1 AND WILL REMAIN IN TEST 1 UNTIL HALTED
OR IF ANY KEY IS STRUCK ON THE TELETYPE THE PROGRAM
WILL FREEZE ON THE NEXT TEST UNTIL A KEY IS STRUCK ON
THE TELETYPE AND SO FORTH THRU THE PROGRAM. IF SW01 =1 IT
WILL PERFORM AS IN SECTION 4.3.4 ALLOWING ONE TO FREEZE
ON A SELECTED TEST RATHER THAN DEFAULTING TO TEST 1

5. OPERATING PROCEDURE

IF THE DIAGNOSTIC IS RUN ON A CPU WITHOUT A SWITCH
REGISTER THEN A SOFTWARE SWITCH REGISTER IS USED WHICH ALLOWS
THE USER THE SAME SWITCH OPTIONS AS THE HARDWARE SWITCH REGISTER.
IF THE HARDWARE SWITCH REGISTER DOES NOT EXIST OR IF ONE DOES
AND IT CONTAINS ALL ONES (177777) THEN THE SOFTWARE SWITCH
REGISTER (LOC. 176) IS USED.

CONTROL:

THIS PROGRAM ALSO SUPPORTS THE DYNAMIC LOADING OF THE SOFTWARE SWITCH
REGISTER (LOC. 176) FROM THE TTY. THIS CAN BE ACCOMPLISHED BY
DOING THE FOLLOWING:

- 1) TYPE CONTROL G (<G>); THIS WILL ALLOW THE TTY TO ENTER DATA INTO
LOC. 176 AT SELECTED POINTS WITHIN THE PROGRAM.
- 2) THE MACHINE WILL THEN TYPE: SWR=XXXXXXNEW= (XXXXXX IS THE OCTAL CONTENTS
OF THE SOFTWARE SWITCH REGISTER.)
- 3) AFTER THE ''NEW='' HAS BEEN TYPED THEN THE OPERATOR CAN DO ONE
OF THE FOLLOWING AT THE TTY:

A) TYPE A NUMBER TO BE LOADED INTO LOC. 176 FOLLOWED BY A <CR>.
(ONLY NUMBERS BETWEEN 0-7 WILL BE ACCEPTED AND ONLY 6 NUMBERS
WILL BE ALLOWED)
IF A <CR> IS THE FIRST KEY DEPRESSED THE SOFTWARE SWITCH
REGISTER CONTENTS WILL NOT BE CHANGED.

B) IF A CONTROL U <↑U> IS DEPRESSED THEN THE PROGRAM WILL SEND YOU
BACK TO STEP 2.

5.1 OPERATIONAL SWITCH SETTINGS
SW15 =1 HALT ON ERROR
SW14 =1 LOOP ON CURRENT TEST
SW13 =1 INHIBIT ERROR TIMEOUT
SW11 =1 INHIBIT ITERATIONS
SW10 =1 ESCAPE TO NEXT TEST ON ERROR
SW08 =1 LOOP ON ERROR
SW02 =1 LOCK ON TEST
SW01 =1 RESTART PROGRAM AT SELECTED TEST
SW00 =1 RESELECT VECTOR AND CONTROL REGISTER ADDRESSES
&PARAMETERS AFTER A PROGRAM RESTART
TO INHIBIT "END OF PASS" TIMEOUT - TURN TELETYPE OFF

6. ERRORS

6.1 ERROR HALTS
THERE ARE FOUR DISTINCT ERROR TIMEOUTS

NOTE: IF THE SOFTWARE SWITCH REGISTER IS TO BE CHANGED AFTER A HALT
THE THE OPERATOR IS REQUIRED TO TYPE A <↑G> BEFORE DEPRESSING CONTINUE.
THE FOLLOWING WILL BE TYPED:
SWR=XXXXXX NEW= (REFER TO SECTION 5. FOR OPERATOR OPTION)

6.1.1 PC+2 = ERROR PC
WHERE PC +2 IS THE ADDRESS OF THE CALL TO THE ERROR HANDLER +2
REFER TO THE ABOVE "HLT" IN DIAGNOSTIC FOR ERROR DESCRIPTION
CHECK ADDRESS 2 RXCSR: TO LOCATE THE DEVICE PRESENTLY UNDER
TEST WHEN RUNNING MULTIPLE DEVICES

6.1.2 PC +2 = REGISTER ERROR PC
REGISTER EXPECTED ACTUAL
16XXXX YYYYYY ZZZZZZ
WHERE 16XXXX IS THE ADDRESS OF THE FAILING DEVICE REGISTER
WHERE YYYYYY IS THE EXPECTED CONTENTS OF THAT REGISTER
WHERE ZZZZZZ IS THE ACTUAL CONTENTS OF THAT REGISTER

6.1.3 PC +2 = RECEIVER ERROR PC
REGISTER EXPECTED ACTUAL
16XXXX YYYYYY ZZZZZZ
WHERE 16XXXX IS THE ADDRESS OF THE FAILING RECEIVER (RXDBUF) REGISTER

WHERE YYYYYY IS THE EXPECTED DATA CONTENTS OF THAT REGISTER

WHERE ZZZZZZ IS THE ACTUAL DATA CONTENTS OF THAT REGISTER

6.1.4 PC +2 = TRANSMITTER ERROR PC
 REGISTER EXPECTED ACTUAL
 16XXXX YYYYYY ZZZZZZ

WHERE 16XXXX IS THE ADDRESS OF THE FAILING TRANSMITTER (TXCSR) REGISTER

WHERE YYYYYY IS THE EXPECTED CONTENTS OF THAT REGISTER

WHERE ZZZZZZ IS THE ACTUAL CONTENTS OF THAT REGISTER

6.1.5 ERROR DESCRIPTIONS
 SEE LISTINGS FOR DETAILS OF ERRORS

6.2 ERROR RECOVERY

6.2.1 SW15 =0
 IF THE PROGRAM IS RUN WITH SW15 =0 ,NO OPERATOR ACTION IS
 REQUIRED TO CONTINUE TESTING

6.2.2 SW15 =1
 IF THE PROGRAM IS RUN WITH SW15 =1 ,TO CONTINUE TESTING
 AFTER THE PROGRAM HAS HALTED ,PRESS THE PROCESSOR
 CONSOLE "CONTINUE SWITCH"

NOTE: THE PC + 2 OF THE "HLT" WILL BE DISPLAYED IN THE DATA LIGHTS

6.2.3 ILLEGAL INTERRUPTS
 IF AN INTERRUPT OCCURS TO A VECTOR ADDRESS NOT SELECTED
 DURING PROGRAM INITIALIZATION, THE PROGRAM WILL HALT IN
 THE TRAPCATCHER. THE ADDRESS AT WHICH THE PROGRAM
 HALTS IS 2 GREATER THAN THE ADDRESS TO WHICH THE INTERRUPT
 OCCURED. THE PROGRAM MUST BE RESTARTED AT 000200 TO
 RECOVER FROM THIS ERROR.

6.2.4 ADDITIONAL TROUBLESHOOTING AIDS ERRCNT: & PASCNT:
 CHECK THESE TWO TAG LOCATIONS FOR TOTAL # OF ERRORS AND PASSES RESPECTIVELY.
 LOADING 000200 AND RESTARTING WILL CLEAR THESE LOCATIONS.

6.3 END OF PASS ROUTINE
 THIS TYPEOUT IS MENTIONED HERE FOR CONVENIENCE
 IT IS IN THE FORM:

END OF PASS TAPE Y
 16XXXX = DEVICE

WHERE Y IS THE TAPE LOADED

WHERE 16XXXX IS THE DEVICE'S BASE REGISTER ADDRESS

TO INHIBIT THIS TYPEOUT - TURN TELETYPE OFF

7. RESTRICTIONS

7.1 MULTIPLE DEVICES

UP TO 16(10) DEVICES MAY BE TESTED. HOWEVER, THEY
MUST HAVE CONTIGUOUS ADDRESSES AND VECTORS

NOTE: IF ALL DEVICES UNDER TEST HAVE THE SAME INTERRUPT VECTOR
YOU CAN CHANGE "ZERO: ADD #10,BASEIV ;NEXT BLOCK
(VECTORS)" TO "ZERO: ADD #0,BASEIV";
THEREBY THE VECTOR ADDRESSES WILL NOT BE
UPDATED AFTER EACH PASS.

7.2 DISQUALIFYING DEVICES WHEN RUNNING MULTIPLE DEVICES

WHEN RUNNING MULTIPLE DEVICES AN ACTIVE BIT IS SET
FOR EACH DEVICE RUNNING UNDER TEST IE. BIT 0 FOR
DEVICE 0 BIT 15 FOR DEVICE 15
TO DISQUALIFY DEVICES:

7.2.1 IF DEVICE 0 IS TO BE DISQUALIFIED, SIMPLY RESTART
PROGRAM WITH SW00 =1 AND OMIT THE FIRST DEVICE.7.2.2 IF HOWEVER, DEVICES 1 THRU 15 OR ANY COMBINATION THEREOF
ARE TO BE DISQUALIFIED....LOAD THE LOCATION OF ACTREG:
OBSERVE THE ACTIVE BITS (ACTIVE =1, NONACTIVE = 0)
AND DEPOSIT 0 WHERE THOSE DEVICES ARE TO BE DISQUALIFIED

7.2.2.1 TO RESTART...LOAD 000200 IN SWR AND DEPRESS START....
THE PROGRAM WILL CONTINUE WITH THE DEVICE IT WAS IN BEFORE HALTING.

7.2.2.2ORLOAD 000200 WITH SW00 =1 AND DEPRESS START....
ANSWER THE QUESTION :1ST DEVICE : ETC.
.....THE PROGRAM WILL CONTINUE WITH DEVICE 0

7.2.2.3 IF ALL DEVICES ARE DISQUALIFIED BY MISTAKE THE PROGRAM
WILL TYPEOUT AN ERROR MESSAGE.....LOAD & START AT 000200

7.3 CABLE DELAYS

NOTE: EXTERNAL LOOP BACK TESTS ONLY (MODEM CABLE WITH H315 CONNECTOR ON)

7.3.1 TO PROVIDE SUFFICIENT DELAY FOR CLOCK SIGNAL OVER THE CABLE,
LOCATION "HOLD:" MUST BE MODIFIED TO ACCOMODATE FOR FASTER MACHINES.
PRESENTLY "HOLD:" =20 IS SUFFICIENT TIME ON AN 11/20 MACHINE.
IF RUNNING ON AN 11/40 OR AN 11/45 "HOLD:" MUST BE PATCHED TO 40

BASICALLY DON'T TRY TO EXCEED 10K TO 12K RATE USING THE EIA DRIVERS

7.4 TO USE THE "XOR" TESTER, THE BRANCH AROUND THE "XOR"
CODE MUST BE PATCHED TO A "NOP". (SEE LISTINGS FOR DETAILS)

8. DEFAULT PARAMETERS:

1ST DEVICE: RECEIVER CONTROL REGISTER ADDRESS- RXCSR: 160040

VECTOR ADDRESS-

DURIV: 770

L01

DZDUB-C MACY11 27(1036) 31-OCT-76 09:17 PAGE 11
HELLO.P11 03-AUG-76 00:00

SEQ 0011

ARE YOU RUNNING MULTIPLE DEVICES ?- NO MULTD: 0
LAST DEVICE: RECEIVER CONTROL REGISTER ADDRESS- LASTADD: 0
DJ PRIORITY LEVEL- LEVEL 5 DUPRT: LEVEL 5
OF SYNC CHARS SELECTED - 2 SYNCNO: 377
IS SEC XMIT JUMPER # 6 IN ?- YES SEXMIT: 377
IS SEC REC JUMPER # 5 IN ?- YES SEREC: 377
IS OPT CLR ENABLE JUMPER # 4 IN ?- YES OPTCLR: 377
DO YOU HAVE THE EXTERNAL MODEM BYPASS JUMPER
CONNECTOR ON (H315)- YES JMRBY: 377

9. PROGRAM DESCRIPTION
10. FLOW CHARTS: RECEIVER FLOW, TRANSMITTER FLOW, TRANSMITTER & RECEIVER FLOW
11. LISTINGS

MO1

DZDUB-C MACY11 27(1006) 01-OCT-76 09:17 PAGE 15
DZDUBC.P11 21-MAY-76 00:00

SEQ 0012

552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584

.ENABLE ABS

;DU11 DZDUB-C TAPE B
;COPYRIGHT 1973, DIGITAL EQUIPMENT CORP., MAYNARD, MASS. 01754

;STARTING PROCEDURE
;LOAD PROGRAM
;PRESS START
;PROGRAM WILL TYPE "DU11 DZDUB-C TAPE B "
;PROGRAM WILL TYPE "R" TO INDICATE THAT TESTING HAS STARTED
;AT THE END OF A PASS, PROGRAM WILL TYPE "END OF PASS TAPE B"
;AND THEN RESUME TESTING

;SWITCH REGISTER OPTIONS

100000
040000
020000
010000
004000
002000
001000
000400
000100
000040
000020
000010
000004
000002
000001

SW15=100000 ;=1,HALT ON ERROR.
SW14=40000 ;=1,LOOP ON CURRENT TEST
SW13=20000 ;=1,INHIBIT ERROR TYPEOUT
SW12=10000
SW11=4000 ;=1,INHIBIT ITERATIONS
SW10=2000 ;=1,ESCAPE TO NEXT TEST ON ERROR
SW09=1000 ;=1,LOOP WITH CURRENT DATA
SW08=400 ;=1,LOOP ON ERROR
SW06=100
SW05=40
SW04=20
SW03=10
SW02=4
SW01=2
SW00=1
;LOCK ON TEST SELECT
;RESTART PROGRAM AT SELECTED TEST
;RESELECT VECTOR AND CONTROL REGISTER
;ADDRESS AFTER PROGRAM RESTART

```

585
586
587
588      000000      R0=%0      ;GENERAL REGISTER
589      000001      R1=%1      ;GENERAL REGISTER
590      000002      R2=%2      ;GENERAL REGISTER
591      000003      R3=%3      ;GENERAL REGISTER
592      000004      R4=%4      ;GENERAL REGISTER
593      000005      R5=%5      ;GENERAL REGISTER
594      000006      SP=%6      ;PROCESSOR STACK POINTER
595      000007      PC=%7      ;PROGRAM COUNTER
596
597      ;LOCATION EQUIVALENCIES
598
599      177570      DSWR=177570 ;HARDWARE SWITCH REGISTER LOC.
600      177570      DLIGHTS=177570 ;HARDWARE DISPLAY REGISTER LOC.
601      177776      PS=177776 ;PROCESSOR STATUS WORD
602      001100      STACK=1100 ;START OF PROCESSOR STACK
603
604      ;INSTRUCTION DEFINITIONS
605
606      005746      PUSH1SP=5746 ;DECREMENT PROCESSOR STACK 1 WORD =TST -(SP)
607      005726      POP1SP=5726 ;INCREMENT PROCESSOR STACK 1 WORD =TST (SP)+
608      010046      PUSHRO=10046 ;SAVE RO ON STACK =MOV RO, -(SP)
609      012600      POPRO=12600 ;RESTORE RO FROM STACK =MOV (SP)+, RO
610      024646      PUSH2SP=24646 ;DECREMENT STACK TWICE =CMP -(SP), -(SP)
611      022626      POP2SP=22626 ;INCREMENT STACK TWICE =CMP (SP)+, (SP)+
612      .EQUIV EMT,HLT ;BASIC DEFINITION OF ERROR CALL
613
614
615      100000      BIT15=100000
616      040000      BIT14=40000
617      020000      BIT13=20000
618      010000      BIT12=10000
619      004000      BIT11=4000
620      002000      BIT10=2000
621      001000      BIT9=1000
622      000400      BIT8=400
623      000200      BIT7=200
624      000100      BIT6=100
625      000040      BIT5=40
626      000020      BIT4=20
627      000010      BIT3=10
628      000004      BIT2=4
629      000002      BIT1=2
630      000001      BIT0=1
631
632      ;PROCESSOR LEVELS
633      000340      LEVEL7=340
634      000300      LEVEL6=300
635      000240      LEVEL5=240
636      000200      LEVEL4=200
637      000140      LEVEL3=140
638      000100      LEVEL2=100
639      000040      LEVEL1=040
640      000000      LEVEL0=000

```

```

641      :REGISTER DEFINITIONS
642      :RXCSR BIT DEFINITIONS
643      100000 DSC=BIT15 :DATA SET CHANGE
644      040000 RING=BIT14 :RING
645      020000 CTS=BIT13 :CLR TO SEND
646      010000 CARDET=BIT12 :CARRIER DETECT
647      004000 RECACT=BIT11 :REC ACTIVE
648      002000 SRD=BIT10 :SEC REC DATA
649      001000 DSR=BIT9 :DATA SET RDY
650      000400 STPSYN=BIT8 :STRIP SYNC
651      000200 RXDONE=BIT7 :REC DONE
652      000100 RINTEN=BIT6 :REC INTR ENABLE
653      000040 DSINTE=BIT5 :DSC INTR ENABLE
654      000020 SYN SCH=BIT4 :SYNC SEARCH
655      000010 STD=BIT3 :SEC XMIT DATA
656      000004 RTS=BIT2 :REQ TO SEND
657      000002 DTR=BIT1 :DATA TERM RDY
658      000001 VOID=BIT0
659      :RXDBUF BIT DEFINITIONS
660      100000 RXERR=BIT15 :REC ERROR
661      040000 OVRRLN=BIT14 :OVERRUN
662      020000 FRMERR=BIT13 :FRAME ERROR
663      010000 PARERR=BIT12 :PARITY ERROR
664      :PARCSR BIT DEFINITIONS
665      001000 PAREN=BIT9 :PARITY ENABLE
666      000400 EVPAR=BIT8 :EVEN PARITY SENSE
667      :PARCSR WRD DEFINITIONS
668      030000 SYNINT=30000 :SYNC EXTERNAL MODE
669      020000 SYNEXT=20000 :SYNC INTERNAL MODE
670      000000 ISYN00=0 :ISOC MODE
671      000020 FIVE=0 :WORD LENGTH 5 BITS
672      002000 SIX=2000 :WORD LENGTH 6 BITS
673      004000 SEVEN=4000 :WORD LENGTH 7 BITS
674      006000 EIGHT=6000 :WORD LENGTH 8 BITS
675      000000 NOPAR=0 :NO PARITY
676      001000 ODDPAR=1000 :ODD PARITY
677      001400 EVEPAR=1400 :EVEN PARITY
678      :TXCSR BIT DEFINITIONS
679      100000 DNA=BIT15 :DATA NOT AVAILABLE
680      040000 MTDATA=BIT14 :MAINT DATA
681      020000 CLK=BIT13 :CLK
682      002000 BITW=BIT10 :BIT WINDOW
683      000400 MRESET=BIT8 :MASTER RESET
684      000200 TXDONE=BIT7 :XMIT DONE
685      000100 TXINTE=BIT6 :XMIT INTR ENABLE
686      000040 DNAINTE=BIT5 :DNA INTR ENAB
687      000020 SEND=BIT4 :SEND
688      000010 HDXEN=BIT3 :HDX/FDX
689      000001 BREAK=BIT0 :BREAK
690      :TXCSR WRD DEFINITIONS
691      000000 USER=0 :USER MODE
692      004000 MINT=4000 :MAINT INT MODE
693      010000 MEXT=10000 :MAINT EXT MODE
694      014000 SYSTST=14000 :SYSTEM TEST MODE
695      :TRAPCATCHER FOR ILLEGAL INTERRUPTS

```

```

696                                     ;STANDARD INTERRUPT VECTORS
697
698
699      . = 24
700      000024 015006      .PFAIL      ;POWER FAIL HANDLER
701      000026 000340      340      ;SERVICE AT LEVEL 7
702      000030 014536      .HLT      ;ERROR HANDLER
703      000032 000340      340      ;SERVICE AT LEVEL 7
704      000034 014504      .TRPSRV   ;GENERAL HANDLER DISPATCH SERVICE
705      000036 000340      340      ;SERVICE AT LEVEL 7
706
707      ;SOFTWARE SWITCH REGISTER
708
709      . = 174
710      000174 000000      DISPREG: .WORD 0      ;SOFTWARE DISPLAY REG.
711      000176 000000      SWREG:  .WORD 0      ;SOFTWARE SWITCH REGISTER
712      000200 000167 001054      JMP      .START      ;GO TO START OF PROGRAM
713
714
715
716      . = 1100
717
718      ;INDIRECT POINTERS
719
720      001100 177570      SWR:      177570      ;SWITCH REGISTER POINTER
721      001102 177570      LIGHTS: 177570      ;DISPLAY REGISTER POINTER
722      001104 177560      TKCSR:   177560      ;TELETYPE KEYBOARD CONTROL REGISTER
723      001106 177562      TKDBR:   177562      ;TELETYPE KEYBOARD DATA BUFFER
724      001110 177564      TPCSR:   177564      ;TELEPRINTER CONTROL REGISTER
725      001112 177566      TPDBR:   177566      ;TELEPRINTER DATA BUFFER
726
727      ;PROGRAM CONTROL PARAMETERS
728
729      001114 000000      RTRN:     0      ;SCOPE ADDRESS FOR LOOP ON TEST
730      001116 000000      NEXT:     0      ;ADDRESS OF NEXT TEST TO BE EXECUTED
731      001120 000000      LOCK:     0      ;ADDRESS FOR LOCK ON CURRENT DATA
732      001122 000000      ICCUNT:   0      ;NUMBER OF ITERATIONS THAT CURRENT TEST WILL BE EXECUTED
733      001124 000000      LPCNT:    0      ;NUMBER OF ITERATIONS COMPLETED
734      001126 000000      TSTNO:    0      ;NUMBER OF TEST IN PROGRESS
735      001130 000000      PASCNT:    0      ;NUMBER OF PASSES COMPLETED
736      001132 000000      ERRCNT:    0      ;TOTAL NUMBER OF ERRORS
737      001134 000000      LSTERR:    0      ;PC OF LAST ERROR CALL
738
739      ;PROGRAM VARIABLES
740
741      001136 000020      HOLD:      20      ;TEMPORARY STORAGE=DELAY TIME FOR CABLES
742      001140 000000      SHIFT:    0      ;TEMPORARY STORAGE= # OF SHIFTS PER CHAR
743      001142 000000      COUNT:    0      ;TEMPORARY STORAGE= # OF TIMES A CHAR WILL BE SENT
744      001144 000000      TEMP1:    0      ;TEMPORARY STORAGE
745      001146 000000      TEMP2:    0      ;TEMPORARY STORAGE
746      001150 000000      TEMP3:    0      ;TEMPORARY STORAGE
747      001152 000000      TEMP4:    0      ;TEMPORARY STORAGE
748      001154 000000      TEMP5:    0      ;TEMPORARY STORAGE
749      001156 000000      SAVR0:    0      ;R0 STORAGE
750      001160 000000      SAVR1:    0      ;R1 STORAGE
751      001162 000000      SAVR2:    0      ;R2 STORAGE

```

D02

02DUB-C MACY11 27(1006) 01-OCT-76 09:17 PAGE 19
02DUBC.P11 21-MAY-76 00:00

SEG 0016

752 001164 000000
753 001166 000000
754 001170 000000
755 001172 000000
756 001174 000000

SAVR3: 0
SAVR4: 0
SAVR5: 0
SAVSP: 0
SAVPC: 0

:R3 STORAGE
:R4 STORAGE
:R5 STORAGE
:STACK POINTER STORAGE
:PROGRAM COUNTER STORAGE

```

757          ;PROGRAM CONVERSATIONAL PARAMETERS
758 001176 377 SYNCNO: .BYTE 377 ;# OF SYNC CHARS REQ'D FOR SYNC'ZATION
759 001177 377 SEXMIT: .BYTE 377 ;SEC XMIT JUMPER "IN"
760 001200 377 SEPEC: .BYTE 377 ;SEC REC JUMPER "IN"
761 001201 377 OPTCLR: .BYTE 377 ;OPTIONAL JUMPER CLR "IN"
762 001202 000 MULTD: .BYTE 0 ;NO MULTIPLE DEVICE FLAG
763 001203 377 JMRBY: .BYTE 377 ;EXTERNAL MODEM BYPASS JUMPER "IN"
764          .EVEN
765
766          ;PROGRAM MULTIPLE DEVICE PARAMETERS
767 001204 000000 BASEADD: 0 ;PROG CONTROLLED 1ST DEVICE ADDR
768 001206 000000 KEEPADD: 0 ;SAVED 1ST DEVICE ADDR
769 001210 000000 LASTADD: 0 ;LAST DEVICE RXCSR ADDR
770 001212 000000 BASEIV: 0 ;PROG CONTROLLED IV
771 001214 000000 KEEPIV: 0 ;SAVED INTR VECTOR
772 001216 000000 ACTREG: 0 ;ACTIVE REGISTER, MODIFY THIS
773          ;LOCATION TO DISQUALIFY OR QUALIFY
774          ;DEVICES (1= RUN, 0= DON'T RUN)
775 001220 000000 ROTADD: 0 ;ROTATING POINTER FOR ACTREG. POINTS
776          ;TO DEVICE PRESENTLY UNDER TEST WHEN RUNNING MULTIPLE DE
777
778          ;PROGRAM CONTROL FLAGS
779
780 001222 000 INIFLG: .BYTE 0 ;PROGRAM INITIALIZATION FLAG
781 001223 000 STFLG: .BYTE 0 ;TEST START FLAG
782 001224 000 ERRFLG: .BYTE 0 ;ERROR OCCURED FLAG
783 001225 000 LOKFLG: .BYTE 0 ;LOCK ON CURRENT TEST FLAG
784
785          ;DEFINITIONS FOR TRAP SUBROUTINE CALLS
786          ;POINTERS TO SUBROUTINES CAN BE FOUND
787          ;IN THE TABLE IMMEDIATLY FOLLOWING THE DEFINITIONS
788
789 001226 .TRPTAB:
790          ;*****
791          ;*****
792          SCOPE=TRAP+0 ;CALL TO SCOPE LOOP AND ITERATION HANDLER
793 001226 013270 .SCOPE
794          SCOPI=TRAP+1 ;CALL TO LOOP ON CURRENT DATA HANDLER
795 001230 013454 .SCOP1
796          TYPE=TRAP+2 ;CALL TO TELETYPE OUTPUT ROUTINE
797 001232 013474 .TYPE
798          INSTR=TRAP+3 ;CALL TO ASCII STRING INPUT ROUTINE
799 001234 013534 .INSTR
800          INSTER=TRAP+4 ;CALL TO INPUT ERROR HANDLER
801 001236 013652 .INSTER
802          PARAM=TRAP+5 ;CALL TO NUMERICAL DATA INPUT ROUTINE
803 001240 013704 .PARAM
804          SAVOS=TRAP+6 ;CALL TO REGISTER SAVE ROUTINE
805 001242 014120 .SAVOS
806          RESOS=TRAP+7 ;CALL TO REGISTER RESTORE ROUTINE
807 001244 014160 .RESOS
808          CONVRT=TRAP+10 ;CALL TO DATA OUTPUT ROUTINE
809 001246 014212 .CONVRT
810          CNVRT=TRAP+11 ;CALL TO DATA OUTPUT ROUTINE WITHOUT CR/LF
811 001250 014216 .CNVRT
812          SETFLG=TRAP+12 ;CALL TO FLAG SET ROUTINE

```

```

813 001252 014436 .SETFLG
814 104413 CKSWR=TRAP+13 ;CALL TO ALLOW SWREG TO BE LOADED FROM TTY
815 001254 015152 .CKSWR
816 104414 CNTLU=TRAP+14 ;CALL TO ALLOW LOADING OF SWREG FROM TTY
817 001256 015226 .CNTLU
818 ;*****
819 ;*****
820
821 ;PROGRAM INITIALIZATION
822 ;LOCK OUT INTERRUPTS
823 ;SET UP PROCESSOR STACK
824 ;SET UP POWER FAIL VECTOR
825 ;CLEAR PROGRAM CONTROL FLAGS AND COUNTS
826 ;TYPE TITLE MESSAGE
827
828 001260 012767 000340 176510 .START: MOV #340,PS ;LOCK OUT INTERRUPTS
829 001266 012706 001100 MOV #STACK,SP ;SET UP STACK
830 001272 012737 015006 000024 MOV #.PFAIL,2#24 ;SET UP POWER FAIL VECTOR
831 001300 005067 177620 CLR LPCNT ;CLEAR # OF ITERATION COMPLETED LOCATION
832 001304 105067 177713 CLRB STFLG ;CLEAR START FLAG
833 001310 005067 177614 CLR PASCNT ;CLEAR PASS COUNT
834 001314 105067 177704 CLRB ERRFLG ;CLEAR ERROR FLAG
835 001320 005067 177606 CLR ERRCNT ;CLEAR ERROR COUNT
836 001324 005067 177604 CLR LSTERR ;CLEAR LAST ERROR POINTER
837 001330 012767 000001 177570 MOV #1,TSTNO ;SET UP FOR TEST 1
838 001336 012767 001260 177550 MOV #.START,RTRN ;SET UP FOR POWER FAIL BEFORE
839 ;TESTING STARTS
840 001344 105767 177652 TSTB INIFLG ;HAS INITIALIZATION BEEN PERFORMED
841 001350 001004 BNE ONCE
842 001352 104402 015326 TYPE ,MTITLE ;TYPE TITLE MESSAGE
843 001356 105167 177640 COMB INIFLG ;IF NOT SET FLAG AND DO
844 001362 012767 177570 177510 ONCE: MOV #DSWR,SWR ;RELOAD HARDWARE SWITCH REGISTER INTO POINTER
845 001370 012767 177570 177504 MOV #DLIGHTS,LIGHTS ;RELOAD HARDWARE DISPLAY REGISTER INTO POINTER
846 001376 013746 000006 MOV 2#6,-(SP) ;SAVE VECTORS
847 001402 013746 000004 MOV 2#4,-(SP)
848 001406 012737 001426 000004 MOV #645,2#4 ;SET UP FOR TIMEOUT
849 001414 022777 177777 177456 CMP #-1,2SWR ;REFERENCE HARDWARE SWITCH REGISTER
850 001422 001402 BEQ 655
851 001424 000407 BR 665
852 001426 022626 645: CMP (SP)+,(SP)+ ;ADJUST STACK
853 001430 012767 000176 177442 655: MOV #SWREG,SWR ;POINT TO SOFTWARE SWITCH REG
854 001436 012767 000174 177436 MOV #DISPREG,LIGHTS ;POINT TO SOFT DISPLAY REG
855 001444 012637 000004 665: MOV (SP)+,2#4 ;RESTORE VECTORS
856 001450 012637 000006 MOV (SP)+,2#6
857 001454 005737 000042 TST 2#42 ;UNDER MONITOR
858 001460 001005 BNE 675
859 001462 022767 000176 177410 CMP #SWREG,SWR ;IS SWREG USED
860 001470 001001 BNE 675
861 001472 104414 CNTLU
862 001474 032777 000001 177376 675: BIT #SW00,2SWR ;RESELECT VECTOR & CONTROL REG?
863 001502 001002 BNE 15
864 001504 000167 000446 JMP .BEGIN
865 001510 012700 000300 15: MOV #300,R0 ;RESTORE VECTOR AREA TO TRAPCATCHER
866 001514 012701 000302 MOV #302,R1 ;START AT LOCATION 300
867 001520 012702 000004 MOV #4,R2
868 001524 010110 25: MOV R1,(R0)

```

869	001526	005011			CLR	(R1)	
870	001530	060200			ADD	R2,R0	
871	001532	060201			ADD	R2,R1	
872	001534	022701	001000		CMP	#1000,R1	;END AT LOCATION 776
873	001540	002771			BLT	25	
874	001542	104403			INSTR		;OUTPUT MESSAGE & GET INPUT STRING
875	001544	015402			MREGAD		;MESSAGE
876	001546	104405			PARAM		;CONVERT STRING
877	001550	160000			160000		;LOW LIMIT
878	001552	167776			167776		;HIGH LIMIT
879	001554	017236			DUBASE		;STORE AT THIS LOCATION
880	001556	001			1		;MASK
881	001557	001			1		;HOW MANY TIMES + 2
882	001560	016767	015452	177420	MOV	DUBASE,KEEPPAD	;SAVE
883	001566	004767	015312		JSR	PC,DUADDR	
884	001572	016767	177410	177404	MOV	KEEPPAD,BASEADD	;RESTORE FOR ROTATION
885	001600	104403			INSTR		;OUTPUT MESSAGE & GET INPUT STRING
886	001602	015360			MVECTO		;MESSAGE
887	001604	104405			PARAM		;CONVERT STRING
888	001606	000300			300		;LOW LIMIT
889	001610	000776			776		;HIGH LIMIT
890	001612	017560			DURIV		;STORE AT THIS LOCATION
891	001614	001			1		;MASK
892	001615	004			4		;HOW MANY TIMES + 2
893	001616	016767	015736	177370	MOV	DURIV,KEEPIV	;SAVE
894	001624	016767	015730	177360	MOV	DURIV,BASEIV	;SET UP FOR ROTATION
895	001632	104403			INSTR		;OUTPUT MESSAGE & GET INPUT STRING
896	001634	015463			MMULT		;MESSAGE
897	001636	104412			SETFLG		;SET FLAG BASED UPON INPUT STRING
898	001640	001202			MULTD		;THIS FLAG
899	001642	105767	177334		TSTB	MULTD	;ARE THERE MULTIPLE DEVICES
900							;ON THE SYSTEM ?
901	001646	100406			BMI	BBB	;YES,ASK NEXT QUESTION
902	001650	005067	177342		CLR	ACTREG	
903	001654	005067	177340		CLR	ROTADD	
904	001660	000167	000140		JMP	OUTMUL	;JUMP AROUND NEXT QUESTION
905	001664				BBB:		
906	001664	104403			INSTR		;OUTPUT MESSAGE & GET INPUT STRING
907	001666	015542			MLASTD		;MESSAGE
908	001670	104405			PARAM		;CONVERT STRING
909	001672	160000			160000		;LOW LIMIT
910	001674	167776			167776		;HIGH LIMIT
911	001676	001210			LASTADD		;STORE AT THIS LOCATION
912	001700	001			1		;MASK
913	001701	001			1		;HOW MANY TIMES + 2
914					THE FOLLOWING ROUTINE SETS UP ACTREG FOR THE FIRST TIME		
915	001702	012767	000001	177310	15:	MOV	#1,ROTADD ;SET UP POINTER
916	001710	005067	177302		CLR	ACTREG	;CLR ACTIVE REGISTER
917	001714	056767	177300	177274	25:	BIS	ROTADD,ACTREG ;MAKE THIS DEVICE ACTIVE
918	001722	000241			CLC		
919	001724	006167	177270		ROL	ROTADD	;SET UP POINTER
920	001730	103421			BCS	35	;ARE YOU OUT OF RANGE ?
921	001732	062767	000010	177244	ADD	#10,BASEADD	;SET UP BASE ADDRESS
922	001740	026767	177244	177236	CMP	LASTADD,BASEADD	;IS THIS THE LAST DEVICE ?
923	001746	101362			BHI	25	;NO DO IT AGAIN
924	001750	056767	177244	177240	BIS	ROTADD,ACTREG	;THIS ASSUMES THAT THERE ARE AT

H02

DZDUB-C MACY11 27(1006) 01-OCT-76 09:17 PAGE 23
 DZDUBC.P11 21-MAY-76 00:00

SEQ 0020

```

925                                     :LEAST TWO DEVICES WHEN YOU ANSWER YES TO
926                                     :MULTIPLE DEVICE QUESTION
927 001756 012767 000001 177234 4$: MOV      #1,ROTADD      ;SET UP FOR LATER USE IN END OF PASS ROUTINE
928 001764 016767 177216 177212      MOV      KEEPADD,BASEADD ;DITTO
929 001772 000414      BR          OUTMUL      ;CONTINUE QUESTIONS
930 001774 016767 177206 177202 3$: MOV      KEEPADD,BASEADD ;RESTORE
931 002002 104403      INSTR                     ;OUTPUT MESSAGE & GET INPUT STRING
932 002004 015725      MRRANGE                    ;MESSAGE
933 002006 104405      PARAM                     ;CONVERT STRING
934 002010 160000      160000                    ;LOW LIMIT
935 002012 167776      167776                    ;HIGH LIMIT
936 002014 001210      LASTADD                   ;STORE AT THIS LOCATION
937 002016 001        .BYTE 1                   ;MASK
938 002017 001        .BYTE 1                   ;HOW MANY TIMES + 2
939 002020 000167 177656      JMP          1$      ;DO IT AGAIN
940 002024      OUTMUL:
941 002024 104403      INSTR                     ;OUTPUT MESSAGE & GET INPUT STRING
942 002026 016211      MLEVEL                    ;MESSAGE
943 002030 104405      PARAM                     ;CONVERT STRING
944 002032 000004      4                        ;LOW LIMIT
945 002034 000007      7                        ;HIGH LIMIT
946 002036 017100      DUPRT                     ;STORE AT THIS LOCATION
947 002040 000        .BYTE 0                   ;MASK
948 002041 001        .BYTE 1                   ;HOW MANY TIMES + 2
949 002042 004767 014762      JSR      PC,DULEV
950                                     ;COMPARE THE FIRST CHARACTER IN THE TELETYPE INPUT
951                                     ;BUFFER TO THE CHARACTERS "1" AND "2"
952                                     ;IF THE CHARACTER IS "1" CLEAR THE FLAG
953                                     ;IF THE CHARACTER IS "2" SET THE FLAG
954 002046      AAA:
955 002046 104403      INSTR                     ;OUTPUT MESSAGE & GET INPUT STRING
956 002050 016236      MSYNC                    ;MESSAGE
957 002052 122767 000061 014610 3$: CMPB      #'1,INBUF      ;IS IT "1" ?
958 002060 001003      BNE          1$
959 002062 105067 177110      CLRB      SYNCNO      ;000
960 002066 000412      BR          4$
961 002070 122767 000062 014572 1$: CMPB      #'2,INBUF      ;IS IT "2" ?
962 002076 001004      BNE          2$
963 002100 112767 177777 177070      MOVB      #-1,SYNCNO      ;377
964 002106 000402      BR          4$
965 002110 104404      2$: INSTR                     ;RETRY
966 002112 000757      BR          3$
967 002114 000240      4$: NOP
968 002116 104403      INSTR                     ;OUTPUT MESSAGE & GET INPUT STRING
969 002120 016304      MWIRE6                    ;MESSAGE
970 002122 104412      SETFLG                    ;SET FLAG BASED UPON INPUT STRING
971 002124 001177      SEXMIT                    ;THIS FLAG
972 002126 104403      INSTR                     ;OUTPUT MESSAGE & GET INPUT STRING
973 002130 016352      MWIRE5                    ;MESSAGE
974 002132 104412      SETFLG                    ;SET FLAG BASED UPON INPUT STRING
975 002134 001200      SEREC                    ;THIS FLAG
976 002136 104403      INSTR                     ;OUTPUT MESSAGE & GET INPUT STRING
977 002140 016417      MWIRE4                    ;MESSAGE
978 002142 104412      SETFLG                    ;SET FLAG BASED UPON INPUT STRING
979 002144 001201      OPTCLR                    ;THIS FLAG
980 002146 104403      INSTR                     ;OUTPUT MESSAGE & GET INPUT STRING

```

DZDUB-C MACY11 27(1036) 01-OCT-76 09:17 PAGE 24
 DZDUBC.P11 21-MAY-76 00:00

SEQ 0021

```

981 002150 016473      NEXTJ      ;MESSAGE
982 002152 104412      SETFLG      ;SET FLAG BASED UPON INPUT STRING
983 002154 001203      JMRBY       ;THIS FLAG
984
985                      ;TEST START AND RESTART
986
987 002156 012767 000340 175612 .BEGIN: MOV    #340,PS      ;LOCK OUT INTERRUPTS
988 002164 012706 001100      MOV    #STACK,SP      ;SET UP STACK
989 002170 005737 000042      TST    #42            ;IS PROGRAM UNDER MONITOR CONTROL
990 002174 001056      BNE    3$
991 002176 105767 177000      TSTB    MULTD      ;DON'T ALLOW LOCK ON TEST IF RUNNING
992                      ;MULTIPLE DEVICES
993 002202 001407      BEQ    5$      ;IF NO TEST FOR LOCK ON TEST
994 002204 016767 011240 011140      MOV    BRW,TTST      ;RESTORE NORMAL SCOPE LOOP
995 002212 016767 011234 011134      MOV    BRX,TTST+2      ;DITTO
996 002220 000444      BR     3$      ;JUMP AROUND IF YES
997 002222 032777 000004 176650 5$: BIT    #BIT2,ASWR      ;CHECK FOR LOCK ON TEST
998 002230 001416      BEQ    1$
999 002232 104403      INSTR          ;OUTPUT MESSAGE & GET INPUT STRING
1000 002234 016146      MLOCK          ;MESSAGE
1001 002236 104412      SETFLG      ;SET FLAG BASED UPON INPUT STRING
1002 002240 001225      LOKFLG      ;THIS FLAG
1003 002242 105767 176757      TSTB    LOKFLG      ;IS LOCK ON TEST OPTION SELECTED
1004 002246 001407      BEQ    1$
1005 002250 012767 000240 011074      MOV    #NOP,TTST
1006 002256 012767 000240 011070      MOV    #NOP,TTST+2
1007 002264 000406      BR     2$      ;SET UP TO LOCK
1008 002266 016767 011156 011056 1$: MOV    BRW,TTST
1009 002274 016767 011152 011052      MOV    BRX,TTST+2
1010 002302 032777 000002 176570 2$: BIT    #SW01,ASWR      ;LOCK NOT SELECTED, SET UP FOR NORMAL SCOPE LOOP
1011 002310 001410      BEQ    3$      ;IF SW01=1, GET STARTING PC
1012 002312 104403      INSTR          ;OUTPUT MESSAGE & GET INPUT STRING
1013 002314 016133      MTSTPC          ;MESSAGE
1014 002316 104405      PARAM          ;CONVERT STRING
1015 002320 002350      TST1          ;LOW LIMIT
1016 002322 012512      TLAST          ;HIGH LIMIT
1017 002324 001114      RTRN          ;STOP AT THIS LOCATION
1018 002326 001      .BYTE          ;MASK
1019 002327 001      .BYTE          ;HOW MANY TIMES + 2
1020 002330 000403      BR     4$
1021 002332 012767 002350 176554 3$: MOV    #TST1,RTRN      ;START AT TEST 1
1022 002340 104402 016127 4$: TYPE    MR          ;TYPE R
1023 002344 000177 176544      JMP     @RTRN      ;START TESTING
1024
1025                      ;: THIS TEST VERIFYS WORD LENGTH SELECT OF THE
1026                      ;: RECEIVER SECTION, IT USES THE ERROR FLAGS
1027                      ;: TO DETERMINE THAT IT WAS SELECTED CORRECTLY
1028                      ;: (OVRUN, RXERR)
1029                      ;: MODE: ISYMOD
1030                      ;: LENGTH: SIX
1031                      ;: CHAR: 25
1032
1033 002350 012767 000001 176550 TST1: MOV    #1,TSTNO      ;SAVE THIS
1034 002356 012767 002612 176532      MOV    #TST2,NEXT      ;GO TO THIS TEST WHEN THRU
1035 002364 052777 000400 015156      BIS    #MRESET,@TXCSR ;MASTER RESET
1036 002372 012777 000000 015144      MOV    #ISYMOD,@PARCSR ;SET THE MODE

```

```

1037 002400 052777 000400 015142      BIS      #MRESET, @TXCSR ;MASTER RESET
1038
1039                                     ;SET MAINT DATA, CLK BREAK, & MAINTENANCE MODE
1040 002406 012777 064001 015134      MOV      #MTDATA!CLK!MINT!BREAK, @TXCSR
1041
1042                                     ;SET MODE, # OF BITS, PARITY SENSE, & LOAD SYNC REG
1043 002414 012777 002000 015122      MOV      #ISYMOD!SIX!NOPAR!0, @PARCSR
1044 002422 052777 000020 015104      BIS      #SYNSCH, @RXCSR ;SET SYNC SEARCH
1045                                     ;POKE CLK TO GET RECEIVER INTO SYNCROIZATION....
1046 002430 042777 020000 015112      BIC      #CLK, @TXCSR ;POKE CLK DOWN
1047 002436 052777 020000 015104      BIS      #CLK, @TXCSR ;POKE CLK UP
1048                                     ;POKE CLK TO GET LOGIC INTO SYNCRONIZATION
1049 002444 042777 020000 015076      BIC      #CLK, @TXCSR ;POKE CLK DOWN
1050 002452 052777 020000 015070      BIS      #CLK, @TXCSR ;POKE CLK UP
1051 002460 016703 015054               MOV      RXDBUF, R3 ;SET UP FOR ERROR MESSAGE
1052 002464 012700 000025               MOV      #25, R0 ;EXPECTED
1053 002470 012767 000010 176442      MOV      #8, SHIFT ;# OF SHIFTS
1054 002476 012767 000252 176440      MOV      #252, TEMP1 ;DATA CHAR
1055 002504 004767 014530               JSR      PC, RPOKE ;SHIFT IN THIS CHAR
1056 002510 105777 015020               TSTB    @RXCSR ;RXDONE
1057 002514 100401                       BMI     64$
1058 002516 104000                       HLT
1059                                     ;RXDONE SHOULD BE SET
1060 002520 017701 015014               64$: MOV     @RXDBUF, R1 ;ACTUAL
1061 002524 020001                       CMP     R0, R1 ;COMPARE EXPECTED VS. ACTUAL
1062 002526 001401                       BEQ     65$
1063 002530 104002                       HLT     2 ;RECEIVED DATA DID NOT MATCH
1064                                     ;EXPECTED DATA - CHECK MAINT DATA
1065                                     ;OR RECEIVER LOGIC
1066 002532                                     65$:
1067 002532 012767 000010 176400      MOV     #8, SHIFT ;# OF SHIFTS
1068 002540 012767 000252 176376      MOV     #252, TEMP1 ;DATA CHAR
1069 002546 004767 014466               JSR     PC, RPOKE ;SHIFT IN THIS CHAR
1070                                     ;NOW SHIFT IN A SECOND CHARACTER WITHOUT READING RXDBUF
1071 002552 012767 000010 176360      MOV     #8, SHIFT ;# OF SHIFTS
1072 002560 012767 000252 176356      MOV     #252, TEMP1 ;DATA CHAR
1073 002566 004767 014446               JSR     PC, RPOKE ;SHIFT IN THIS CHAR
1074 002572 012700 140025               MOV     #140000!25, R0 ;EXPECTED DATA PLUS
1075                                     ;RXERR & OVRUN
1076 002576 017701 014736               MOV     @RXDBUF, R1 ;ACTUAL
1077 002602 020001                       CMP     R0, R1 ;COMPARE EXP VS. ACT
1078 002604 001401                       BEQ     66$
1079 002606 104002                       HLT     2 ;SPECIFICALLY LOOK AT RXERR &
1080                                     ;OVRUN BITS...THEY BOTH SHOULD BE SET
1081 002610                                     66$:
1082 002610 104400
1083                                     SCOPE
1084                                     ;;THIS TEST VERIFYS WORD LENGTH SELECT OF THE
1085                                     ;;RECEIVER SECTION, IT USES THE ERROR FLAGS
1086                                     ;;TO DETERMINE THAT IT WAS SELECTED CORRECTLY
1087                                     ;;(OVRUN, RXERR)
1088                                     ;;MODE: ISYMOD
1089                                     ;;LENGTH: SIX
1090                                     ;;CHAR: 52
1091 002612 012767 000002 176306      TST2: MOV     #2, TSTNO ;SAVE THIS
1092 002620 012767 003054 176270      MOV     #TST3, NEXT ;GO TO THIS TEST WHEN THRU

```

K02

DZDUB-C MACY11 27(1006) 01-OCT-76 09:17 PAGE 26
 DZDUBC.P11 21-MAY-76 00:00

SEQ 0023

```

1093 002626 052777 000400 014714      BIS      #MRESET, @TXCSR ; MASTER RESET
1094 002634 012777 000000 014702      MOV      #ISYMOD, @PARCSR ; SET THE MODE
1095 002642 052777 000400 014700      BIS      #MRESET, @TXCSR ; MASTER RESET
1096
1097                                     ; SET MAINT DATA, CLK, BREAK, & MAINTENANCE MODE
1098 002650 012777 064001 014672      MOV      #MTDATA!CLK!MINT!BREAK, @TXCSR
1099
1100                                     ; SET MODE, # OF BITS, PARITY SENSE, & LOAD SYNC REG
1101 002656 012777 002000 014660      MOV      #ISYMOD!SIX!NOPAR!0, @PARCSR
1102 002664 052777 000020 014642      BIS      #SYNSCH, @RXCSR ; SET SYNC SEARCH
1103                                     ; POKE CLK TO GET RECEIVER INTO SYNCROIZATION....
1104 002672 042777 020000 014650      BIC      #CLK, @TXCSR ; POKE CLK DOWN
1105 002700 052777 020000 014642      BIS      #CLK, @TXCSR ; POKE CLK UP
1106                                     ; POKE CLK TO GET LOGIC INTO SYNCRONIZATION
1107 002706 042777 020000 014634      BIC      #CLK, @TXCSR ; POKE CLK DOWN
1108 002714 052777 020000 014626      BIS      #CLK, @TXCSR ; POKE CLK UP
1109 002722 016703 014612              MOV      RXDBUF, R3 ; SET UP FOR ERROR MESSAGE
1110 002726 012700 000052              MOV      #52, R0 ; EXPECTED
1111 002732 012767 000010 176200      MOV      #8, SHIFT ; # OF SHIFTS
1112 002740 012767 000324 176176      MOV      #324, TEMP1 ; DATA CHAR
1113 002746 004767 014266              JSR      PC, RPOKE ; SHIFT IN THIS CHAR
1114 002752 105777 014556              TSTB    @RXCSR ; RXDONE
1115 002756 100401                    BMI      64$
1116 002760 104000                    HLT
1117 002762                    64$:
1118 002762 017701 014552              MOV      @RXDBUF, R1 ; ACTUAL
1119 002766 020001                    CMP      R0, R1 ; COMPARE EXPECTED VS. ACTUAL
1120 002770 001401                    BEQ      65$
1121 002772 104002                    HLT      2 ; RECEIVED DATA DID NOT MATCH
1122                                     ; EXPECTED DATA - CHECK MAINT DATA
1123                                     ; OR RECEIVER LOGIC
1124
1125 002774                    65$:
1126 002774 012767 000010 176136      MOV      #8, SHIFT ; # OF SHIFTS
1127 003002 012767 000324 176134      MOV      #324, TEMP1 ; DATA CHAR
1128 003010 004767 014224              JSR      PC, RPOKE ; SHIFT IN THIS CHAR
1129                                     ; NOW SHIFT IN A SECOND CHARACTER WITHOUT READING RXDBUF
1130 003014 012767 000010 176116      MOV      #8, SHIFT ; # OF SHIFTS
1131 003022 012767 000324 176114      MOV      #324, TEMP1 ; DATA CHAR
1132 003030 004767 014204              JSR      PC, RPOKE ; SHIFT IN THIS CHAR
1133 003034 012700 140052              MOV      #140000!52, R0 ; EXPECTED DATA PLUS
1134                                     ; RXERR & OVRUN
1135 003040 017701 014474              MOV      @RXDBUF, R1 ; ACTUAL
1136 003044 020001                    CMP      R0, R1 ; COMPARE EXP VS. ACT
1137 003046 001401                    BEQ      66$
1138 003050 104002                    HLT      2 ; SPECIFICALLY LOOK AT RXERR &
1139                                     ; OVRUN BITS...THEY BOTH SHOULD BE SET
1140
1141 003052                    66$:
1142 003052 104400
1143                                     SCOPE
1144                                     ;; THIS TEST VERIFYS WORD LENGTH SELECT OF THE
1145                                     ;; RECEIVER SECTION, IT USES THE ERROR FLAGS
1146                                     ;; TO DETERMINE THAT IT WAS SELECTED CORRECTLY
1147                                     ;; (OVRUN, RXERR)
1148                                     ;; MODE: ISYMOD
1149                                     ;; LENGTH: SIX
1150                                     ;; CHAR: 77
1151                                     ;;

```

```

1149 003054 012767 000003 176044 TST3: MOV #3,TSTNO ;SAVE THIS
1150 003062 012767 003316 176026 MOV #TST4,NEXT ;GO TO THIS TEST WHEN THRU
1151 003070 052777 000400 014452 BIS #MRESET,@TXCSR ;MASTER RESET
1152 003076 012777 000000 014440 MOV #ISYMOD,@PARCSR ;SET THE MODE
1153 003104 052777 000400 014436 BIS #MRESET,@TXCSR ;MASTER RESET
1154
1155 ;SET MAINT DATA,CLK BREAK,&MAINTENANCE MODE
1156 003112 012777 064001 014430 MOV #MTDATA!CLK!MINT!BREAK,@TXCSR
1157
1158 ;SET MODE ,# OF BITS,PARITY SENSE,&LOAD SYNC REG
1159 003120 012777 002000 014416 MOV #ISYMOD!SIX!NOPAR!0,@PARCSR
1160 003126 052777 000020 014400 BIS #SYNSCH,@RXCSR ;SET SYNC SEARCH
1161 ;POKE CLK TO GET RECEIVER INTO SYNCROIZATION....
1162 003134 042777 020000 014406 BIC #CLK,@TXCSR ;POKE CLK DOWN
1163 003142 052777 020000 014400 BIS #CLK,@TXCSR ;POKE CLK UP
1164 ;POKE CLK TO GET LOGIC INTO SYNCRONIZATION
1165 003150 042777 020000 014372 BIC #CLK,@TXCSR ;POKE CLK DOWN
1166 003156 052777 020000 014364 BIS #CLK,@TXCSR ;POKE CLK UP
1167 003164 016703 014350 MOV RXDBUF,R3 ;SET UP FOR ERROR MESSAGE
1168 003170 012700 000077 MOV #77,R0 ;EXPECTED
1169 003174 012767 000010 175736 MOV #8,SHIFT ;# OF SHIFTS
1170 003202 012767 000376 175734 MOV #376,TEMP1 ;DATA CHAR
1171 003210 004767 014024 JSR PC,RPOKE ;SHIFT IN THIS CHAR
1172 003214 105777 014314 TSTB @RXCSR ;RXDONE
1173 003220 100401 BMI 64$
1174 003222 104000 HLT ;RXDONE SHOULD BE SET
1175
1176 003224 017701 014310 64$: MOV @RXDBUF,R1 ;ACTUAL
1177 003230 020001 CMP R0,R1 ;COMPARE EXPECTED VS. ACTUAL
1178 003232 001401 BEQ 65$
1179 003234 104002 HLT 2 ;RECEIVED DATA DID NOT MATCH
1180 ;EXPECTED DATA - CHECK MAINT DATA
1181 ;OR RECEIVER LOGIC
1182
1183 003236 012767 000010 175674 65$: MOV #8,SHIFT ;# OF SHIFTS
1184 003244 012767 000376 175672 MOV #376,TEMP1 ;DATA CHAR
1185 003252 004767 013762 JSR PC,RPOKE ;SHIFT IN THIS CHAR
1186 ;NOW SHIFT IN A SECOND CHARACTER WITHOUT READING RXDBUF
1187 003256 012767 000010 175654 MOV #8,SHIFT ;# OF SHIFTS
1188 003264 012767 000376 175652 MOV #376,TEMP1 ;DATA CHAR
1189 003272 004767 013742 JSR PC,RPOKE ;SHIFT IN THIS CHAR
1190 003276 012700 140077 MOV #140000!77,R0 ;EXPECTED DATA PLUS
1191 ;RXERR & OVRUN
1192 003302 017701 014232 MOV @RXDBUF,R1 ;ACTUAL
1193 003306 020001 CMP R0,R1 ;COMPARE EXP VS. ACT
1194 003310 001401 BEQ 66$
1195 003312 104002 HLT 2 ;SPECIFICALLY LOOK AT RXERR &
1196 ;OVRUN BITS...THEY BOTH SHOULD BE SET
1197
1198 003314 104400 66$: SCOPE
1199 ;THIS TEST VERIFYS WORD LENGTH SELECT OF THE
1200 ;RECEIVER SECTION,IT USES THE ERROR FLAGS
1201 ;TO DETERMINE THAT IT WAS SELECTED CORRECTLY
1202 ; (OVRUN,RXERR)
1203 ;MODE:ISYMOD
1204 ;LENGTH:SIX

```

```

1205                                     ;;CHAR:0
1206                                     ;;
1207 003316 012767 000004 175602 TST4: MOV #4,TSTNO ;SAVE THIS
1208 003324 012767 003560 175564 MOV #TST5,NEXT ;GO TO THIS TEST WHEN THRU
1209 003332 052777 000400 014210 BIS #MRESET,@TXCSR ;MASTER RESET
1210 003340 012777 000000 014176 MOV #ISYMOD,@PARCSR ;SET THE MODE
1211 003346 052777 000400 014174 BIS #MRESET,@TXCSR ;MASTER RESET
1212
1213 ;SET MAINT DATA,CLK,BREAK,&MAINTENANCE MODE
1214 003354 012777 064001 014166 MOV #MTDATA!CLK!MINT!BREAK,@TXCSR
1215
1216 ;SET MODE # OF BITS,PARITY SENSE &LOAD SYNC REG
1217 003362 012777 002000 014154 MOV #ISYMOD!SIX!NOPAR!0,@PARCSR
1218 003370 052777 000020 014136 BIS #SYNSCH,@RXCSR ;SET SYNC SEARCH
1219 ;POKE CLK TO GET RECEIVER INTO SYNCHRONIZATION....
1220 003376 042777 020000 014144 BIC #CLK,@TXCSR ;POKE CLK DOWN
1221 003404 052777 020000 014136 BIS #CLK,@TXCSR ;POKE CLK UP
1222 ;POKE CLK TO GET LOGIC INTO SYNCHRONIZATION
1223 003412 042777 020000 014130 BIC #CLK,@TXCSR ;POKE CLK DOWN
1224 003420 052777 020000 014122 BIS #CLK,@TXCSR ;POKE CLK UP
1225 003426 016703 014106 MOV RXDBUF,R3 ;SET UP FOR ERROR MESSAGE
1226 003432 012703 000000 MOV #0,R0 ;EXPECTED
1227 003436 012767 000010 175474 MOV #8,SHIFT ;# OF SHIFTS
1228 003444 012767 000200 175472 MOV #200,TEMP1 ;DATA CHAR
1229 003452 004767 013552 JSR PC,RPOKE ;SHIFT IN THIS CHAR
1230 003456 105777 014052 TSTB @RXCSR ;RXDONE
1231 003462 100401 BMI 64$
1232 003464 104000 HLT ;RXDONE SHOULD BE SET
1233 64$:
1234 003466 017701 014046 MOV @RXDBUF,R1 ;ACTUAL
1235 003472 020001 CMP R0,R1 ;COMPARE EXPECTED VS. ACTUAL
1236 003474 001401 BEQ 65$
1237 003476 104002 HLT 2 ;RECEIVED DATA DID NOT MATCH
1238 ;EXPECTED DATA - CHECK MAINT DATA
1239 ;OR RECEIVER LOGIC
1240 65$:
1241 003500 012767 000010 175432 MOV #8,SHIFT ;# OF SHIFTS
1242 003506 012767 000200 175430 MOV #200,TEMP1 ;DATA CHAR
1243 003514 004767 013520 JSR PC,RPOKE ;SHIFT IN THIS CHAR
1244 ;NOW SHIFT IN A SECOND CHARACTER WITHOUT READING RXDBUF
1245 003520 012767 000010 175412 MOV #8,SHIFT ;# OF SHIFTS
1246 003526 012767 000200 175410 MOV #200,TEMP1 ;DATA CHAR
1247 003534 004767 013500 JSR PC,RPOKE ;SHIFT IN THIS CHAR
1248 003540 012700 140000 MOV #140000!0,R0 ;EXPECTED DATA PLUS
1249 ;RXERR & OVRUN
1250 003544 017701 013770 MOV @RXDBUF,R1 ;ACTUAL
1251 003550 020001 CMP R0,R1 ;COMPARE EXP VS. ACT
1252 003552 001401 BEQ 66$
1253 003554 104002 HLT 2 ;SPECIFICALLY LOOK AT RXERR &
1254 ;OVRUN BITS...THEY BOTH SHOULD BE SET
1255 66$:
1256 003556 104400 SCOPE
1257 ;;THIS TEST VERIFYS WORD LENGTH SELECT OF THE
1258 ;;RECEIVER SECTION,IT USES THE ERROR FLAGS
1259 ;;TO DETERMINE THAT IT WAS SELECTED CORRECTLY
1260 ;;(OVRUN,RXERR)

```

```

1261      ;;MODE:ISYMOD
1262      ;;LENGTH:SEVEN
1263      ;;CHAR:125
1264
1265      003560 012767 000005 175340 TST5:  MOV    #5,TSTNO      ;SAVE THIS
1266      003566 012767 004022 175322      MOV    #TST6,NEXT      ;GO TO THIS TEST WHEN THRU
1267      003574 052777 000400 013746      BIS    #MRESET,@TXCSR ;MASTER RESET
1268      003602 012777 000000 013734      MOV    #ISYMOD,@PARCSR ;SET THE MODE
1269      003610 052777 000400 013732      BIS    #MRESET,@TXCSR ;MASTER RESET
1270
1271      ;SET MAINT DATA,CLK,BREAK,&MAINTENANCE MODE
1272      003616 012777 064001 013724      MOV    #MTDATA!CLK!MINT!BREAK,@TXCSR
1273
1274      ;SET MODE , # OF BITS,PARITY SENSE,&LOAD SYNC REG
1275      003624 012777 004000 013712      MOV    #ISYMOD!SEVEN!NOPAR!0,@PARCSR
1276      003632 052777 000020 013674      BIS    #SYNSCH,@RXCSR ;SET SYNC SEARCH
1277      ;POKE CLK TO GET RECEIVER INTO SYNCROIZATION....
1278      003640 042777 020000 013702      BIC    #CLK,@TXCSR ;POKE CLK DOWN
1279      003646 052777 020000 013674      BIS    #CLK,@TXCSR ;POKE CLK UP
1280      ;POKE CLK TO GET LOGIC INTO SYNCRONIZATION
1281      003654 042777 020000 013666      BIC    #CLK,@TXCSR ;POKE CLK DOWN
1282      003662 052777 020000 013660      BIS    #CLK,@TXCSR ;POKE CLK UP
1283      003670 016703 013644      MOV    RXDBUF,R3 ;SET UP FOR ERROR MESSAGE
1284      003674 012700 000125      MOV    #125,R0 ;EXPECTED
1285      003700 012767 000011 175232      MOV    #9,SHIFT ;# OF SHIFTS
1286      003706 012767 000652 175230      MOV    #652,TEMP1 ;DATA CHAR
1287      003714 004767 013220      JSR    PC,RPOKE ;SHIFT IN THIS CHAR
1288      003720 105777 013610      TSTB   @RXCSR ;RXDONE ?
1289      003724 100401      BMI     64$
1290      003726 104000      HLT
1291      003730
1292      003730 017701 013601      64$:  MOV    @RXDBUF,R1 ;ACTUAL
1293      003734 020001      CMP     R0,R1 ;COMPARE EXPECTED VS. ACTUAL
1294      003736 001401      BEQ     65$
1295      003740 104002      HLT     2 ;RECEIVED DATA DID NOT MATCH
1296      ;EXPECTED DATA - CHECK MAINT DATA
1297      ;OR RECEIVER LOGIC
1298      003742
1299      003742 012767 000011 175170      65$:  MOV    #9,SHIFT ;# OF SHIFTS
1300      003750 012767 000652 175166      MOV    #652,TEMP1 ;DATA CHAR
1301      003756 004767 013256      JSR    PC,RPOKE ;SHIFT IN THIS CHAR
1302      ;NOW SHIFT IN A SECOND CHARACTER WITHOUT READING RXDBUF
1303      003762 012767 000011 175150      MOV    #9,SHIFT ;# OF SHIFTS
1304      003770 012767 000652 175146      MOV    #652,TEMP1 ;DATA CHAR
1305      003776 004767 013236      JSR    PC,RPOKE ;SHIFT IN THIS CHAR
1306      004002 012700 140125      MOV    #140000!125,R0 ;EXPECTED DATA PLUS
1307      ;RXERR & OVRUN
1308      004006 017701 013526      MOV    @RXDBUF,R1 ;ACTUAL
1309      004012 020001      CMP     R0,R1 ;COMPARE EXP VS. ACT
1310      004014 001401      BEQ     66$
1311      004016 104002      HLT     2 ;SPECIFICALLY LOOK AT RXERR &
1312      ;OVRUN BITS...THEY BOTH SHOULD BE SET
1313      004020
1314      004020 104400      66$:  SCOPE
1315      ;THIS TEST VERIFYS WORD LENGTH SELECT OF THE
1316      ;RECEIVER SECTION,IT USES THE ERROR FLAGS

```

```

1317      ; TO DETERMINE THAT IT WAS SELECTED CORRECTLY
1318      ; (OVRUN, RXERR)
1319      ; MODE: ISYMOD
1320      ; LENGTH: SEVEN
1321      ; CHAR: 52
1322
1323 004022 012767 000006 175076 TST6: MOV      #5, TSTNO      ; SAVE THIS
1324 004030 012767 004264 175060      MOV      #TST7, NEXT      ; GO TO THIS TEST WHEN THRU
1325 004036 052777 000400 013504      BIS      #MRESET, @TXCSR ; MASTER RESET
1326 004044 012777 000000 013472      MOV      #ISYMOD, @PARCSR ; SET THE MODE
1327 004052 052777 000400 013470      BIS      #MRESET, @TXCSR ; MASTER RESET
1328
1329      ; SET MAINT DATA, CLK, BREAK, & MAINTENANCE MODE
1330 004060 012777 064001 013462      MOV      #MTDATA, CLK, MINT, BREAK, @TXCSR
1331
1332      ; SET MODE, # OF BITS, PARITY SENSE, & LOAD SYNC REG
1333 004066 012777 004000 013450      MOV      #ISYMOD, SEVEN, NCPAR, @PARCSR
1334 004074 052777 000020 013432      BIS      #SYNSCH, @RXCSR ; SET SYNC SEARCH
1335      ; POKE CLK TO GET RECEIVER INTO SYNCHRONIZATION....
1336 004102 042777 020001 013440      BIC      #CLK, @TXCSR ; POKE CLK DOWN
1337 004110 052777 020000 013432      BIS      #CLK, @TXCSR ; POKE CLK UP
1338      ; POKE CLK TO GET LOGIC INTO SYNCHRONIZATION
1339 004116 042777 020000 013424      BIC      #CLK, @TXCSR ; POKE CLK DOWN
1340 004124 052777 020000 013416      BIS      #CLK, @TXCSR ; POKE CLK UP
1341 004132 016703 013402      MOV      RXDBUF, R3 ; SET UP FOR ERROR MESSAGE
1342 004136 012700 000052      MOV      #52, R0 ; EXPECTED
1343 004142 012767 000011 174770      MOV      #9, SHIFT ; # OF SHIFTS
1344 004150 012767 000524 174766      MOV      #524, TEMP1 ; DATA CHAR
1345 004156 004767 010056      JSR      PC, RPOKE ; SHIFT IN THIS CHAR
1346 004162 105777 013346      TSTB    @RXCSR ; RXDONE
1347 004166 100401      BMI     64$
1348 004170 104000      HLT
1349 004172
1350 004172 017701 013342      64$: MOV      @RXDBUF, R1 ; ACTUAL
1351 004176 020001      CMP     R0, R1 ; COMPARE EXPECTED VS. ACTUAL
1352 004200 001401      BEQ     65$
1353 004202 104002      HLT     2 ; RECEIVED DATA DID NOT MATCH
1354      ; EXPECTED DATA - CHECK MAINT DATA
1355      ; OR RECEIVER LOGIC
1356 004204
1357 004204 012767 000011 174726      65$: MOV      #9, SHIFT ; # OF SHIFTS
1358 004212 012767 000524 174724      MOV      #524, TEMP1 ; DATA CHAR
1359 004220 004767 013014      JSR      PC, RPOKE ; SHIFT IN THIS CHAR
1360      ; NOW SHIFT IN A SECOND CHARACTER WITHOUT READING RXDBUF
1361 004224 012767 000011 174706      MOV      #9, SHIFT ; # OF SHIFTS
1362 004232 012767 000524 174704      MOV      #524, TEMP1 ; DATA CHAR
1363 004240 004767 012774      JSR      PC, RPOKE ; SHIFT IN THIS CHAR
1364 004244 012700 140052      MOV      #140000, 52, R0 ; EXPECTED DATA PLUS
1365      ; RXERR & OVRUN
1366 004250 017701 013264      MOV      @RXDBUF, R1 ; ACTUAL
1367 004254 020001      CMP     R0, R1 ; COMPARE EXP VS. ACT
1368 004256 001401      BEQ     66$
1369 004260 104002      HLT     2 ; SPECIFICALLY LOOK AT RXERR &
1370      ; OVRUN BITS...THEY BOTH SHOULD BE SET
1371 004262
1372 004262 104400      66$: SCOPE

```

```

1373                                     ;: THIS TEST VERIFYS WORD LENGTH SELECT OF THE
1374                                     ;: RECEIVER SECTION, IT USES THE ERROR FLAGS
1375                                     ;: TO DETERMINE THAT IT WAS SELECTED CORRECTLY
1376                                     ;: (OVRUN, RXERR)
1377                                     ;: MODE: ISYMOD
1378                                     ;: LENGTH: SEVEN
1379                                     ;: CHAR: 177
1380
1381 004264 012767 000007 174634 TST7: MOV      #7, TSTNO          ;SAVE THIS
1382 004272 012767 004526 174616      MOV      #TSTB, NEXT          ;GO TO THIS TEST WHEN THRU
1383 004300 052777 000400 013242      BIS      #MRESET, @TXCSR      ;MASTER RESET
1384 004306 012777 000000 013230      MOV      #ISYMOD, @PARCSR      ;SET THE MODE
1385 004314 052777 000400 013226      BIS      #MRESET, @TXCSR      ;MASTER RESET
1386
1387                                     ;SET MAINT DATA, CLK, BREAK, & MAINTENANCE MODE
1388 004322 012777 064001 013220      MOV      #MTDATA!CLK!MINT!BREAK, @TXCSR
1389
1390                                     ;SET MODE, # OF BITS, PARITY SENSE, & LOAD SYNC REG
1391 004330 012777 004000 013206      MOV      #ISYMOD!SEVEN!NOPAR!0, @PARCSR
1392 004336 052777 000020 013170      BIS      #SYNSCH, @RXCSR      ;SET SYNC SEARCH
1393                                     ;POKE CLK TO GET RECEIVER INTO SYNCRIZATION....
1394 004344 042777 020000 013176      BIC      #CLK, @TXCSR      ;POKE CLK DOWN
1395 004352 052777 020000 013170      BIS      #CLK, @TXCSR      ;POKE CLK UP
1396                                     ;POKE CLK TO GET LOGIC INTO SYNCRONIZATION
1397 004360 042777 020000 013162      BIC      #CLK, @TXCSR      ;POKE CLK DOWN
1398 004366 052777 020000 013154      BIS      #CLK, @TXCSR      ;POKE CLK UP
1399 004374 016703 013140              MOV      RXDBUF, R3          ;SET UP FOR ERROR MESSAGE
1400 004400 012700 000177              MOV      #177, R0          ;EXPECTED
1401 004404 012767 000011 174526      MOV      #9, SHIFT          ;# OF SHIFTS
1402 004412 012767 000776 174524      MOV      #776, TEMP1        ;DATA CHAR
1403 004420 004767 012614              JSR      PC, RPOKE          ;SHIFT IN THIS CHAR
1404 004424 105777 013104              TSTB      @RXCSR      ;RXDONE
1405 004430 100401                    BMI      64$
1406 004432 104000                    HLT
1407 004434                    64$:
1408 004434 017701 013100              MOV      @RXDBUF, R1          ;ACTUAL
1409 004440 020001                    CMP      R0, R1          ;COMPARE EXPECTED VS. ACTUAL
1410 004442 001401                    BEQ      65$
1411 004444 104002                    HLT      2
1412                                     ;RECEIVED DATA DID NOT MATCH
1413                                     ;EXPECTED DATA - CHECK MAINT DATA
1414                                     ;OR RECEIVER LOGIC
1415
1416 004446 012767 000011 174464      MOV      #9, SHIFT          ;# OF SHIFTS
1417 004454 012767 000776 174462      MOV      #776, TEMP1        ;DATA CHAR
1418 004462 004767 012552              JSR      PC, RPOKE          ;SHIFT IN THIS CHAR
1419                                     ;NOW SHIFT IN A SECOND CHARACTER WITHOUT READING RXDBUF
1420 004466 012767 000011 174444      MOV      #9, SHIFT          ;# OF SHIFTS
1421 004474 012767 000776 174442      MOV      #776, TEMP1        ;DATA CHAR
1422 004502 004767 012532              JSR      PC, RPOKE          ;SHIFT IN THIS CHAR
1423 004506 012700 140177              MOV      #140000!177, R0      ;EXPECTED DATA PLUS
1424                                     ;RXERR & OVRUN
1425 004512 017701 013022              MOV      @RXDBUF, R1          ;ACTUAL
1426 004516 020001                    CMP      R0, R1          ;COMPARE EXP VS. ACT
1427 004520 001401                    BEQ      66$
1428 004522 104002                    HLT      2
1429                                     ;SPECIFICALLY LOOK AT RXERR &
1430                                     ;OVRUN BITS...THEY BOTH SHOULD BE SET

```

```

1429 004524 66$:
1430 004524 104400
1431
1432
1433
1434
1435
1436
1437
1438
1439 004526 012767 000010 174372 TSTB: MOV #8,TSTNO ;SAVE THIS
1440 004534 012767 004770 174354 MOV #TST9,NEXT ;GO TO THIS TEST WHEN THRU
1441 004542 052777 000400 013000 BIS #MRESET,@TXCSR ;MASTER RESET
1442 004550 012777 000000 012766 MOV #ISYMOD,@PARCSR ;SET THE MODE
1443 004556 052777 000400 012764 BIS #MRESET,@TXCSR ;MASTER RESET
1444
1445 ;SET MAINT DATA,CLK,BREAK,&MAINTENANCE MODE
1446 004564 012777 064001 012756 MOV #MTDATA!CLK!MINT!BREAK,@TXCSR
1447
1448 ;SET MODE, # OF BITS,PARITY SENSE &LOAD SYNC REG
1449 004572 012777 004000 012744 MOV #ISYMOD!SEVEN!NOPAR!0,@PARCSR
1450 004600 052777 000020 012726 BIS #SYNSCH,@RXCSR ;SET SYNC SEARCH
1451 ;POKE CLK TO GET RECEIVER INTO SYNCROIZATION....
1452 004606 042777 020000 012734 BIC #CLK,@TXCSR ;POKE CLK DOWN
1453 004614 052777 020000 012726 BIS #CLK,@TXCSR ;POKE CLK UP
1454 ;POKE CLK TO GET LOGIC INTO SYNCRONIZATION
1455 004622 042777 020000 012720 BIC #CLK,@TXCSR ;POKE CLK DOWN
1456 004630 052777 020000 012712 BIS #CLK,@TXCSR ;POKE CLK UP
1457 004636 016703 012676 MOV RXDBUF,R3 ;SET UP FOR ERROR MESSAGE
1458 004642 012700 000000 MOV #0,R0 ;EXPECTED
1459 004646 012767 000011 174264 MOV #9,SHIFT ;# OF SHIFTS
1460 004654 012767 000400 174262 MOV #400,TEMP1 ;DATA CHAR
1461 004662 004767 012352 JSR PC,RPOKE ;SHIFT IN THIS CHAR
1462 004666 105777 012642 TSTB @RXCSR ;RXDONE
1463 004672 100401 BMI 64$
1464 004674 104000 HLT ;RXDONE SHOULD BE SET
1465
1466 004676 017701 012636 64$: MOV @RXDBUF,R1 ;ACTUAL
1467 004702 020001 CMP R0,R1 ;COMPARE EXPECTED VS. ACTUAL
1468 004704 001401 BEQ 65$
1469 004706 104002 HLT 2 ;RECEIVED DATA DID NOT MATCH
1470 ;EXPECTED DATA - CHECK MAINT DATA
1471 ;OR RECEIVER LOGIC
1472
1473 004710 65$: MOV #9,SHIFT ;# OF SHIFTS
1474 004710 012767 000011 174222 MOV #400,TEMP1 ;DATA CHAR
1475 004716 012767 000400 174220 JSR PC,RPOKE ;SHIFT IN THIS CHAR
1476 004724 004767 012310 ;NOW SHIFT IN A SECOND CHARACTER WITHOUT READING RXDBUF
1477 004730 012767 000011 174202 MOV #9,SHIFT ;# OF SHIFTS
1478 004736 012767 000400 174200 MOV #400,TEMP1 ;DATA CHAR
1479 004744 004767 012270 JSR PC,RPOKE ;SHIFT IN THIS CHAR
1480 004750 012700 140003 MOV #140000!0,R0 ;EXPECTED DATA PLUS
1481 ;RXERR & OVRRUN
1482 004754 017701 012560 MOV @RXDBUF,R1 ;ACTUAL
1483 004760 020001 CMP R0,R1 ;COMPARE EXP VS. ACT
1484 004762 001401 BEQ 66$

```

E03

DZDUB-C MACY11 27(1006) 01-OCT-76 09:17 PAGE 33
 DZDUBC.P11 21-MAY-76 00:00

SEQ 0030

```

1485 004764 104002          HLT      2          ;SPECIFICALLY LOOK AT RXERR &
1486                                     ;OVRUN BITS...THEY BOTH SHOULD BE SET
1487 004766                66$:
1488 004766 104400          SCOPE
1489                                     ;:THIS TEST VERIFYS WORD LENGTH SELECT OF THE
1490                                     ;:RECEIVER SECTION,IT USES THE ERROR FLAGS
1491                                     ;:TO DETERMINE THAT IT WAS SELECTED CORRECTLY
1492                                     ;:(OVRUN,RXERR)
1493                                     ;:MODE:ISYMOD
1494                                     ;:LENGTH:EIGHT
1495                                     ;:CHAR:125
1496                                     ;:
1497 004770 012767 000011 174130 TST9:  MOV      #9,TSTNO          ;SAVE THIS
1498 004776 012767 005232 174112      MOV      #TST10,NEXT        ;GO TO THIS TEST WHEN THRU
1499 005004 052777 000400 012536      BIS      #MRESET,ATXCSR      ;MASTER RESET
1500 005012 012777 000000 012524      MOV      #ISYMOD,APARCSR     ;SET THE MODE
1501 005020 052777 000400 012522      BIS      #MRESET,ATXCSR      ;MASTER RESET
1502
1503                                     ;SET MAINT DATA,CLK,BREAK,&MAINTENANCE MODE
1504 005026 012777 064001 012514      MOV      #MTDATA!CLK!MINT!BREAK,ATXCSR
1505
1506                                     ;SET MODE ,# OF BITS,PARITY SENSE,&LOAD SYNC REG
1507 005034 012777 006000 012502      MOV      #ISYMOD!EIGHT!NOPAR!0,APARCSR
1508 005042 052777 000020 012464      BIS      #SYNSCH,ARXCSR      ;SET SYNC SEARCH
1509                                     ;POKE CLK TO GET RECEIVER INTO SYNCROIZATION....
1510 005050 042777 020000 012472      BIC      #CLK,ATXCSR      ;POKE CLK DOWN
1511 005056 052777 020000 012464      BIS      #CLK,ATXCSR      ;POKE CLK UP
1512                                     ;POKE CLK TO GET LOGIC INTO SYNCHRONIZATION
1513 005064 042777 020000 012456      BIC      #CLK,ATXCSR      ;POKE CLK DOWN
1514 005072 052777 020000 012450      BIS      #CLK,ATXCSR      ;POKE CLK UP
1515 005100 016703 012434          MOV      RXDBUF,R3          ;SET UP FOR ERROR MESSAGE
1516 005104 012700 000125          MOV      #125,R0          ;EXPECTED
1517 005110 012767 000012 174022      MOV      #10,SHIFT        ;# OF SHIFTS
1518 005116 012767 001252 174020      MOV      #1252,TEMP1      ;DATA CHAR
1519 005124 004767 012110          JSR      PC,RPOKE          ;SHIFT IN THIS CHAR
1520 005130 105777 012400          TSTB      ARXCSR      ;RXDONE
1521 005134 100401          BMI      64$
1522 005136 104000          HLT
1523                                     ;RXDONE SHOULD BE SET
1524 005140 017701 012374          64$:  MOV      ARXDBUF,R1          ;ACTUAL
1525 005144 020001          CMP      R0,R1          ;COMPARE EXPECTED VS. ACTUAL
1526 005146 001401          BEQ      65$
1527 005150 104002          HLT      2
1528                                     ;RECEIVED DATA DID NOT MATCH
1529                                     ;EXPECTED DATA - CHECK MAINT DATA
1530                                     ;OR RECEIVER LOGIC
1531 005152                65$:
1532 005152 012767 000012 173760      MOV      #10,SHIFT        ;# OF SHIFTS
1533 005160 012767 001252 173756      MOV      #1252,TEMP1      ;DATA CHAR
1534 005166 004767 012046          JSR      PC,RPOKE          ;SHIFT IN THIS CHAR
1535                                     ;NOW SHIFT IN A SECOND CHARACTER WITHOUT READING RXDBUF
1536 005172 012767 000012 173740      MOV      #10,SHIFT        ;# OF SHIFTS
1537 005200 012767 001252 173736      MOV      #1252,TEMP1      ;DATA CHAR
1538 005206 004767 012026          JSR      PC,RPOKE          ;SHIFT IN THIS CHAR
1539 005212 012700 140125          MOV      #140000!125,R0      ;EXPECTED DATA PLUS
1540 005216 017701 012316          MOV      ARXDBUF,R1          ;ACTUAL

```

F03

DZDUB-C MACY11 27(1006) 31-OCT-76 09:17 PAGE 34
DZDUBC.P11 21-MAY-76 00:00

SEQ 0031

```

1541 005222 020001      CMP      R0,R1      ;COMPARE EXP VS. ACT
1542 005224 001401      BEQ      66$
1543 005226 104002      HLT      2
1544                                     ;SPECIFICALLY LOOK AT RXERR &
1545                                     ;OVRUN BITS...THEY BOTH SHOULD BE SET
1545 005230                                     66$:
1546 005230 104400      SCOPE
1547                                     ;:THIS TEST VERIFYS WORD LENGTH SELECT OF THE
1548                                     ;:RECEIVER SECTION,IT USES THE ERROR FLAGS
1549                                     ;:TO DETERMINE THAT IT WAS SELECTED CORRECTLY
1550                                     ;:(OVRUN,RXERR)
1551                                     ;:MODE:ISYMOD
1552                                     ;:LENGTH:EIGHT
1553                                     ;:CHAR:252
1554
1555 005232 012767 000012 173666 TST10: MOV      #10,TSTNO      ;SAVE THIS
1556 005240 012767 005474 173650      MOV      #TST11,NEXT      ;GO TO THIS TEST WHEN THRU
1557 005246 052777 000400 012274      BIS      #MRESET,RTXCSR      ;MASTER RESET
1558 005254 012777 000000 012262      MOV      #ISYMOD,PARCSR      ;SET THE MODE
1559 005262 052777 000400 012260      BIS      #MRESET,RTXCSR      ;MASTER RESET
1560
1561                                     ;SET MAINT DATA,CLK,BREAK,&MAINTENANCE MODE
1562 005270 012777 064001 012252      MOV      #MTDATA!CLK!MINT!BREAK,RTXCSR
1563
1564                                     ;SET MODE, # OF BITS,PARITY SENSE,&LOAD SYNC REG
1565 005276 012777 006000 012240      MOV      #ISYMOD!EIGHT!NOPAR!0,PARCSR
1566 005304 052777 000020 012222      BIS      #SYNSCH,RTXCSR      ;SET SYNC SEARCH
1567                                     ;POKE CLK TO GET RECEIVER INTO SYNCROIZATION....
1568 005312 042777 020000 012230      BIC      #CLK,RTXCSR      ;POKE CLK DOWN
1569 005320 052777 020000 012222      BIS      #CLK,RTXCSR      ;POKE CLK UP
1570                                     ;POKE CLK TO GET LOGIC INTO SYNCHRONIZATION
1571 005326 042777 020000 012214      BIC      #CLK,RTXCSR      ;POKE CLK DOWN
1572 005334 052777 020000 012206      BIS      #CLK,RTXCSR      ;POKE CLK UP
1573 005342 016703 012172      MOV      RXDBUF,R3      ;SET UP FOR ERROR MESSAGE
1574 005346 012700 000252      MOV      #252,R0      ;EXPECTED
1575 005352 012767 000012 173560      MOV      #10,SHIFT      ;# OF SHIFTS
1576 005360 012767 001524 173556      MOV      #1524,TEMP1      ;DATA CHAR
1577 005366 004767 011646      JSR      PC,RPOKE      ;SHIFT IN THIS CHAR
1578 005372 105777 012136      TSTB      RTXCSR      ;RXDONE
1579 005376 104001      BMI      64$
1580 005400 104000      HLT
1581                                     ;RXDONE SHOULD BE SET
1581 005402                                     64$:
1582 005402 017701 012132      MOV      #RXDBUF,R1      ;ACTUAL
1583 005406 020001      CMP      R0,R1      ;COMPARE EXPECTED VS. ACTUAL
1584 005410 001401      BEQ      65$
1585 005412 104002      HLT      2
1586                                     ;RECEIVED DATA DID NOT MATCH
1587                                     ;EXPECTED DATA - CHECK MAINT DATA
1588                                     ;OR RECEIVER LOGIC
1588 005414                                     65$:
1589 005414 012767 000012 173516      MOV      #10,SHIFT      ;# OF SHIFTS
1590 005422 012767 001524 173514      MOV      #1524,TEMP1      ;DATA CHAR
1591 005430 004767 011604      JSR      PC,RPOKE      ;SHIFT IN THIS CHAR
1592                                     ;NOW SHIFT IN A SECOND CHARACTER WITHOUT READING RXDBUF
1593 005434 012767 000012 173476      MOV      #10,SHIFT      ;# OF SHIFTS
1594 005442 012767 001524 173474      MOV      #1524,TEMP1      ;DATA CHAR
1595 005450 004767 011564      JSR      PC,RPOKE      ;SHIFT IN THIS CHAR
1596 005454 012700 140252      MOV      #140000!252,R0      ;EXPECTED DATA PLUS

```

```

1597
1598 005460 017701 012054      MOV    2RXDBUF,R1      ;RXERR & OVRRUN
1599 005464 020001      CMP    R0,R1      ;ACTUAL
1600 005466 001401      BEQ    66$      ;COMPAPE EXP VS. ACT
1601 005470 104002      HLT    2      ;SPECIFICALLY LOOK AT RXERR &
1602                                     ;OVRRUN BITS...THEY BOTH SHOULD BE SET
1603 005472      66$:
1604 005472 104400      SCOPE
1605                                     ::THIS TEST VERIFYS WORD LENGTH SELECT OF THE
1606                                     ::RECEIVER SECTION,IT USES THE ERROR FLAGS
1607                                     ::TO DETERMINE THAT IT WAS SELECTED CORRECTLY
1608                                     ::(OVRRUN,RXERR)
1609                                     ::MODE:ISYMOD
1610                                     ::LENGTH:EIGHT
1611                                     ::CHAR:377
1612
1613 005474 012767 000013 173424  TST11: MOV    #11,TSTNO      ;SAVE THIS
1614 005502 012767 005736 173406      MOV    #TST12,NEXT      ;GO TO THIS TEST WHEN THRU
1615 005510 052777 000400 012032      BIS    #MRESET,2TXCSR      ;MASTER RESET
1616 005516 012777 000000 012020      MOV    #ISYMOD,2PARCSR      ;SET THE MODE
1617 005524 052777 000400 012016      BIS    #MRESET,2TXCSR      ;MASTER RESET
1618
1619                                     ;SET MAINT DATA,CLK,BREAK,&MAINTENANCE MODE
1620 005532 012777 064001 012010      MOV    #MTDATA!CLK!MINT!BREAK,2TXCSR
1621
1622                                     ;SET MODE ,# OF BITS,PARITY SENSE &LOAD SYNC REG
1623 005540 012777 006000 011776      MOV    #ISYMOD!EIGHT!NOPAR!0,2PARCSR
1624 005546 052777 000020 011760      BIS    #SYNSCH,2RXCSR      ;SET SYNC SEARCH
1625                                     ;POKE CLK TO GET RECEIVER INTO SYNCROIZATION....
1626 005554 042777 020000 011766      BIC    #CLK,2TXCSR      ;POKE CLK DOWN
1627 005562 052777 020000 011760      BIS    #CLK,2TXCSR      ;POKE CLK UP
1628                                     ;POKE CLK TO GET LOGIC INTO SYNCRONIZATION
1629 005570 042777 020000 011752      BIC    #CLK,2TXCSR      ;POKE CLK DOWN
1630 005576 052777 020000 011744      BIS    #CLK,2TXCSR      ;POKE CLK UP
1631 005604 016703 011730      MOV    RXDBUF,R3      ;SET UP FOR ERROR MESSAGE
1632 005610 012700 000377      MOV    #377,R0      ;EXPECTED
1633 005614 012767 000012 173316      MOV    #10,SHIFT      ;# OF SHIFTS
1634 005622 012767 001776 173314      MOV    #1776,TEMP1      ;DATA CHAR
1635 005630 004767 011404      JSR    PC,RPOKE      ;SHIFT IN THIS CHAR
1636 005634 105777 011674      TSTB   2RXCSR      ;RXDONE
1637 005640 100401      BMI    64$
1638 005642 104000      HLT
1639
1640 005644 017701 011670      64$: MOV    2RXDBUF,R1      ;ACTUAL
1641 005650 020001      CMP    R0,R1      ;COMPARE EXPECTED VS. ACTUAL
1642 005652 001401      BEQ    65$
1643 005654 104002      HLT    2      ;RECEIVED DATA DID NOT MATCH
1644                                     ;EXPECTED DATA - CHECK MAINT DATA
1645                                     ;OR RECEIVER LOGIC
1646
1647 005656 012767 000012 173254      65$: MOV    #10,SHIFT      ;# OF SHIFTS
1648 005664 012767 001776 173252      MOV    #1776,TEMP1      ;DATA CHAR
1649 005672 004767 011342      JSR    PC,RPOKE      ;SHIFT IN THIS CHAR
1650                                     ;NOW SHIFT IN A SECOND CHARACTER WITHOUT READING RXDBUF
1651 005676 012767 000012 173234      MOV    #10,SHIFT      ;# OF SHIFTS
1652 005704 012767 001776 173232      MOV    #1776,TEMP1      ;DATA CHAR

```

```

1653 005712 004767 011322      JSR    PC,RPOKE      ;SHIFT IN THIS CHAR
1654 005716 012700 140377      MOV     #140000!377,R0 ;EXPECTED DATA PLUS
1655                                ;RXERR & OVRUN
1656 005722 017701 011612      MOV     @RXDBUF,R1    ;ACTUAL
1657 005726 020001                CMP     R0,R1      ;COMPARE EXP VS. ACT
1658 005730 001401                BEQ     66$
1659 005732 104002                HLT     2            ;SPECIFICALLY LOOK AT RXERR &
1660                                ;OVRUN BITS...THEY BOTH SHOULD BE SET
1661 005734                66$:
1662 005734 104400                SCOPE
1663                                ;:THIS TEST VERIFYS WORD LENGTH SELECT OF THE
1664                                ;:RECEIVER SECTION,IT USES THE ERROR FLAGS
1665                                ;:TO DETERMINE THAT IT WAS SELECTED CORRECTLY
1666                                ;:(OVRUN,RXERR)
1667                                ;:MODE:ISYMOD
1668                                ;:LENGTH:EIGHT
1669                                ;:CHAR:0
1670
1671 005736 012767 000014 173162  TST12: MOV     #12,TSTNO      ;SAVE THIS
1672 005744 012767 006200 173144      MOV     #TST13,NEXT    ;GO TO THIS TEST WHEN THRU
1673 005752 052777 000400 011570      BIS     #MRESET,@TXCSR ;MASTER RESET
1674 005760 012777 000000 011556      MOV     #ISYMOD,@PARCSR ;SET THE MODE
1675 005766 052777 000400 011554      BIS     #MRESET,@TXCSR ;MASTER RESET
1676
1677                                ;SET MAINT DATA,CLK,BREAK,&MAINTENANCE MODE
1678 005774 012777 064001 011546      MOV     #MTDATA!CLK!MINT!BREAK,@TXCSR
1679
1680                                ;SET MODE, # OF BITS,PARITY SENSE &LOAD SYNC REG
1681 006002 012777 006000 011534      MOV     #ISYMOD!EIGHT!NOPAR!0,@PARCSR
1682 006010 052777 000020 011516      BIS     #SYNSCH,@RXCSR ;SET SYNC SEARCH
1683                                ;POKE CLK TO GET RECEIVER INTO SYNCROIZATION....
1684 006016 042777 020000 011524      BIC     #CLK,@TXCSR    ;POKE CLK DOWN
1685 006024 052777 020000 011516      BIS     #CLK,@TXCSR    ;POKE CLK UP
1686                                ;POKE CLK TO GET LOGIC INTO SYNCRONIZATION
1687 006032 042777 020000 011510      BIC     #CLK,@TXCSR    ;POKE CLK DOWN
1688 006040 052777 020000 011502      BIS     #CLK,@TXCSR    ;POKE CLK UP
1689 006046 016703 011466                MOV     RXDBUF,R3    ;SET UP FOR ERROR MESSAGE
1690 006052 012700 000000                MOV     #0,R0      ;EXPECTED
1691 006056 012767 000012 173054      MOV     #10,SHIFT    ;# OF SHIFTS
1692 006064 012767 001000 173052      MOV     #1000,TEMP1 ;DATA CHAR
1693 006072 004767 011142                JSR     PC,RPOKE      ;SHIFT IN THIS CHAR
1694 006076 105777 011432                TSTB    @RXCSR ;RXDONE
1695 006102 100401                BMI     64$
1696 006104 104000                HLT
1697                                64$:
1698 006106 017701 011426                MOV     @RXDBUF,R1    ;ACTUAL
1699 006112 020001                CMP     R0,R1      ;COMPARE EXPECTED VS. ACTUAL
1700 006114 001401                BEQ     65$
1701 006116 104002                HLT     2            ;RECEIVED DATA DID NOT MATCH
1702                                ;EXPECTED DATA - CHECK MAINT DATA
1703                                ;OR RECEIVER LOGIC
1704                                65$:
1705 006120 012767 000012 173012      MOV     #10,SHIFT    ;# OF SHIFTS
1706 006126 012767 001000 173010      MOV     #1000,TEMP1 ;DATA CHAR
1707 006134 004767 011100                JSR     PC,RPOKE      ;SHIFT IN THIS CHAR
1708                                ;NOW SHIFT IN A SECOND CHARACTER WITHOUT READING RXDBUF

```

DZDUB-C MACY11 27(1006) 01-OCT-76 09:17 PAGE 37
 DZDUBC.P11 21-MAY-76 00:00

SEQ 0034

```

1709 006140 012767 000012 172772      MOV      #10,SHIFT      ; # OF SHIFTS
1710 006146 012767 001000 172770      MOV      #1000,TEMP1    ; DATA CHAR
1711 006154 004767 011060              JSR      PC,RPOKE      ; SHIFT IN THIS CHAR
1712 006160 012700 140000              MOV      #140000!0,R0      ; EXPECTED DATA PLUS
1713                                ; RXERR & OVRUN
1714 006164 017701 011350              MOV      @RXDBUF,R1      ; ACTUAL
1715 006170 020001              CMP      R0,R1      ; COMPARE EXP VS. ACT
1716 006172 001401              BEQ      66$
1717 006174 104002              HLT      2      ; SPECIFICALLY LOOK AT RXERR &
                                ; OVRUN BITS...THEY BOTH SHOULD BE SET
1718
1719                                66$:
1720 006176 104400              SCOPE
1721                                ; THIS TEST VERIFYS WORD LENGTH SELECT OF THE
1722                                ; RECEIVER SECTION, IT USES THE ERROR FLAGS
1723                                ; TO DETERMINE THAT IT WAS SELECTED CORRECTLY
1724                                ; (OVRUN, RXERR)
1725                                ; MODE:SYNEXT
1726                                ; LENGTH:FIVE
1727                                ; CHAR:25
1728
1729 006200 012767 000015 172720      TST13: MOV      #13,TSTNC      ; SAVE THIS
1730 006206 012767 006426 172702      MOV      #TST14,NEXT      ; GO TO THIS TEST WHEN THRU
1731 006214 052777 000400 011326      BIS      #MRESET,@TXCSR    ; MASTER RESET
1732 006222 012777 020000 011314      MOV      #SYNEXT,@PARCSR    ; SET THE MODE
1733 006230 052777 000400 011312      BIS      #MRESET,@TXCSR    ; MASTER RESET
1734
1735                                ; SET MAINT DATA,CLK,BREAK,&MAINTEN " MODE
1736 006236 012777 064001 011304      MOV      #MTDATA!CLK!MINT!BREAK,@TXCSR
1737
1738                                ; SET MODE , # OF BITS,PARITY SENSE,&LOAD SYNC REG
1739 006244 012777 020000 011272      MOV      #SYNEXT!FIVE!NOPAR!0,@PARCSR
1740 006252 052777 000020 011254      BIS      #SYNSCH,@TXCSR    ; SET SEARCH SYNC
1741                                ; POKE CLK TO GET LOGIC INTO SYNCRONIZATION
1742 006260 042777 020000 011262      BIC      #CLK,@TXCSR      ; POKE CLK DOWN
1743 006266 052777 020000 011254      BIS      #CLK,@TXCSR      ; POKE CLK UP
1744 006274 016703 011240              MOV      @RXDBUF,R3      ; SET UP FOR ERROR MESSAGE
1745 006300 012700 000025              MOV      #25,R0      ; EXPECTED
1746 006304 012767 000005 172626      MOV      #5,SHIFT      ; # OF SHIFTS
1747 006312 012767 000025 172624      MOV      #25,TEMP1      ; DATA CHAR
1748 006320 004767 010714              JSR      PC,RPOKE      ; SHIFT IN THIS CHAR
1749 006324 105777 011204              TSTB      @RXCSR      ; RXDONE
1750 006330 100401              BMI      64$
1751 006332 104000              HLT
                                ; RXDONE SHOULD BE SET
1752                                64$:
1753 006334 017701 011200              MOV      @RXDBUF,R1      ; ACTUAL
1754 006340 020001              CMP      R0,R1      ; COMPARE EXPECTED VS. ACTUAL
1755 006342 001401              BEQ      65$
1756 006344 104002              HLT      2      ; RECEIVED DATA DID NOT MATCH
                                ; EXPECTED DATA - CHECK MAINT DATA
                                ; OR RECEIVER LOGIC
1757
1758                                65$:
1759 006346 012767 000005 172564      MOV      #5,SHIFT      ; # OF SHIFTS
1760 006346 012767 000025 172562      MOV      #25,TEMP1      ; DATA CHAR
1761 006354 012767 000025 172562      JSR      PC,RPOKE      ; SHIFT IN THIS CHAR
1762 006362 004.67 010652              ; NOW SHIFT IN A SECOND CHARACTER WITHOUT READING RXDBUF
1763                                MOV      #5,SHIFT      ; # OF SHIFTS
1764 006366 012767 000005 172544

```

```

1765 006374 012767 000025 172542      MOV      #25,TEMP1      ;DATA CHAR
1766 006402 004767 010632              JSR      PC,RPOKE      ;SHIFT IN THIS CHAR
1767 006406 012700 140025              MOV      #140000!25,R0    ;EXPECTED DATA PLUS
1768                                ;RXERR & OVRUN
1769 006412 017701 011122              MOV      @RXDBUF,R1     ;ACTUAL
1770 006416 020001                      CMP      R0,R1      ;COMPARE EXP VS. ACT
1771 006420 001401                      BEQ      66$
1772 006422 104002                      HLT      2
1773                                ;SPECIFICALLY LOOK AT RXERR &
1774                                ;OVRUN BITS...THEY BOTH SHOULD BE SET
1775 006424 104400                      66$:
1776                                SCOPE
1777                                ;;THIS TEST VERIFYS WORD LENGTH SELECT OF THE
1778                                ;;RECEIVER SECTION,IT USES THE ERROR FLAGS
1779                                ;;TO DETERMINE THAT IT WAS SELECTED CORRECTLY
1780                                ;;(OVRUN,RXERR)
1781                                ;;MODE:SYNEXT
1782                                ;;LENGTH:FIVE
1783                                ;;CHAR:12
1784 006426 012767 000016 172472      TST14: MOV      #14,TSTNO      ;SAVE THIS
1785 006434 012767 006654 172454      MOV      #TST15,NEXT      ;GO TO THIS TEST WHEN THRU
1786 006442 052777 000400 011100      BIS      #MRESET,@TXCSR  ;MASTER RESET
1787 006450 012777 020000 011066      MOV      #SYNEXT,@PARCSR ;SET THE MODE
1788 006456 052777 000400 011064      BIS      #MRESET,@TXCSR  ;MASTER RESET
1789
1790                                ;SET MAINT DATA,CLK BREAK,&MAINTENANCE MODE
1791 006464 012777 064001 011056      MOV      #MTDATA!CLK!MINT!BREAK,@TXCSR
1792
1793                                ;SET MODE ,# OF BITS,PARITY SENSE,&LOAD SYNC REG
1794 006472 012777 020000 011044      MOV      #SYNEXT!FIVE!NOPAR!0,@PARCSR
1795 006500 052777 000020 011026      BIS      #SYNSCH,@RXCSR  ;SET SEARCH SYNC
1796                                ;POKE CLK TO GET LOGIC INTO SYNCHRONIZATION
1797 006506 042777 020000 011034      BIC      #CLK,@TXCSR      ;POKE CLK DOWN
1798 006514 052777 070000 011026      BIS      #CLK,@TXCSR      ;POKE CLK UP
1799 006522 016703 011012              MOV      RXDBUF,R3      ;SET UP FOR ERROR MESSAGE
1800 006526 012700 000012              MOV      #12,R0      ;EXPECTED
1801 006532 012767 000005 172400      MOV      #5,SHIFT      ;# OF SHIFTS
1802 006540 012767 000012 172376      MOV      #12,TEMP1      ;DATA CHAR
1803 006546 004767 010466              JSR      PC,RPOKE      ;SHIFT IN THIS CHAR
1804 006552 105777 010756              TSTB      @RXCSR      ;RXDONE
1805 006556 100401                      BMI      64$
1806 006560 104000                      HLT
1807                                ;RXDONE SHOULD BE SET
1808 006562 017701 010752      64$: MOV      @RXDBUF,R1     ;ACTUAL
1809 006566 020001                      CMP      R0,R1      ;COMPARE EXPECTED VS. ACTUAL
1810 006570 001401                      BEQ      65$
1811 006572 104002                      HLT      2
1812                                ;RECEIVED DATA DID NOT MATCH
1813                                ;EXPECTED DATA - CHECK MAINT DATA
1814                                ;OR RECEIVER LOGIC
1815 006574 012767 000005 172336      65$: MOV      #5,SHIFT      ;# OF SHIFTS
1816 006602 012767 000012 172334      MOV      #12,TEMP1      ;DATA CHAR
1817 006610 004767 010424              JSR      PC,RPOKE      ;SHIFT IN THIS CHAR
1818                                ;NOW SHIFT IN A SECOND CHARACTER WITHOUT READING RXDBUF
1819 006614 012767 000005 172316      MOV      #5,SHIFT      ;# OF SHIFTS
1820 006622 012767 000012 172314      MOV      #12,TEMP1      ;DATA CHAR

```

K03

 C2DJ8-C MACY11 27(1006) 01-OCT-76 09:17 PAGE 39
 02DU8C.P11 21-MAY-76 00:00

SEQ 0036

```

1821 006630 004767 010404 JSR PC,RPOKE ;SHIFT IN THIS CHAR
1822 006634 012700 140012 MOV #140000!12,R0 ;EXPECTED DATA PLUS
1823 ;RXERR & OVRUN
1824 006640 017701 010674 MOV @RXDBUF,R1 ;ACTUAL
1825 006644 020001 CMP R0,R1 ;COMPARE EXP VS. ACT
1826 006646 001401 BEQ 66$
1827 006650 104002 HLT 2 ;SPECIFICALLY LOOK AT RXERR &
1828 ;OVRUN BITS...THEY BOTH SHOULD BE SET
1829 006652 66$:
1830 006652 104400 SCOPE
1831 ;:THIS TEST VERIFYS WORD LENGTH SELECT OF THE
1832 ;:RECEIVER SECTION,IT USES THE ERROR FLAGS
1833 ;:TO DETERMINE THAT IT WAS SELECTED CORRECTLY
1834 ;:(OVRUN,RXERR)
1835 ;:MODE:SYNEXT
1836 ;:LENGTH:FIVE
1837 ;:CHAR:37
1838
1839 006654 012767 000017 172244 TST15: MOV #15,TSTNO ;SAVE THIS
1840 006662 012767 007102 172226 MOV #TST16,NEXT ;GO TO THIS TEST WHEN THRU
1841 006670 052777 000400 010652 BIS #MRESET,@TXCSR ;MASTER RESET
1842 006676 012777 020000 010640 MOV #SYNEXT,@PARCSR ;SET THE MODE
1843 006704 052777 000400 010636 BIS #MRESET,@TXCSR ;MASTER RESET
1844
1845 ;SET MAINT DATA,CLK,BREAK,&MAINTENANCE MODE
1846 006712 012777 064001 010630 MOV #MTDATA!CLK!MINT!BREAK,@TXCSR
1847
1848 ;SET MODE # OF BITS,PARITY SENSE,&LOAD SYNC REG
1849 006720 012777 020000 010616 MOV #SYNEXT!FIVE!NOPAR!0,@PARCSR
1850 006726 052777 000020 010600 BIS #SYNSCH,@RXCSR ;SET SEARCH SYNC
1851 ;POKE CLK TO GET LOGIC INTO SYNCHRONIZATION
1852 006734 042777 020000 010606 BIC #CLK,@TXCSR ;POKE CLK DOWN
1853 006742 052777 020000 010600 BIS #CLK,@TXCSR ;POKE CLK UP
1854 006750 016703 015564 MOV RXDBUF,R3 ;SET UP FOR ERROR MESSAGE
1855 006754 012700 000037 MOV #37,R0 ;EXPECTED
1856 006760 012767 000005 172152 MOV #5,SHIFT ;# OF SHIFTS
1857 006766 012767 000037 172150 MOV #37,TEMP1 ;DATA CHAR
1858 006774 004767 010240 JSR PC,RPOKE ;SHIFT IN THIS CHAR
1859 007000 105777 010530 TSTB @RXCSR ;RXDONE
1860 007004 100401 BMI 64$
1861 007006 104000 HLT ;RXDONE SHOULD BE SET
1862 007010 64$:
1863 007010 017701 010524 MOV @RXDBUF,R1 ;ACTUAL
1864 007014 020001 CMP R0,R1 ;COMPARE EXPECTED VS. ACTUAL
1865 007016 001401 BEQ 65$
1866 007020 104002 HLT 2 ;RECEIVED DATA DID NOT MATCH
1867 ;EXPECTED DATA - CHECK MAINT DATA
1868 ;OR RECEIVER LOGIC
1869 007022 65$:
1870 007022 012767 000005 172110 MOV #5,SHIFT ;# OF SHIFTS
1871 007030 012767 000037 172106 MOV #37,TEMP1 ;DATA CHAR
1872 007036 004767 010176 JSR PC,RPOKE ;SHIFT IN THIS CHAR
1873 ;NOW SHIFT IN A SECOND CHARACTER WITHOUT READING RXDBUF
1874 007042 012767 000005 172070 MOV #5,SHIFT ;# OF SHIFTS
1875 007050 012767 000037 172066 MOV #37,TEMP1 ;DATA CHAR
1876 007056 004767 010156 JSR PC,RPOKE ;SHIFT IN THIS CHAR

```

```

1877 007062 012700 140037      MOV      #140000!37,RO      ;EXPECTED DATA PLUS
1878                                ;RXERR & OVRRUN
1879 007066 017701 010446      MOV      @RXDBUF,R1      ;ACTUAL
1880 007072 020001      CMP      RO,R1      ;COMPARE EXP VS. ACT
1881 007074 001401      BEQ      66$
1882 007076 104002      HLT      2      ;SPECIFICALLY LOOK AT RXERR &
                                ;OVRRUN BITS...THEY BOTH SHOULD BE SET
1883
1884 007100      66$:
1885 007100 104400      SCOPE
1886                                ;:THIS TEST VERIFYS WORD LENGTH SELECT OF THE
1887                                ;:RECEIVER SECTION,IT USES THE ERROR FLAGS
1888                                ;:TO DETERMINE THAT IT WAS SELECTED CORRECTLY
1889                                ;:(OVRRUN,RXERR)
1890                                ;:MODE:SYNEXT
1891                                ;:LENGTH:FIVE
1892                                ;:CHAR:0
1893
1894 007102 012767 000020 172016  TST16: MOV      #16,TSTNO      ;SAVE THIS
1895 007110 012767 007330 172000      MOV      #TST17,NEXT      ;GO TO THIS TEST WHEN THRU
1896 007116 052777 000400 010424      BIS      #MRESET,@TXCSR ;MASTER RESET
1897 007124 012777 020000 010412      MOV      #SYNEXT,@PARCSR ;SET THE MODE
1898 007132 052777 000400 010410      BIS      #MRESET,@TXCSR ;MASTER RESET
1899
1900                                ;SET MAINT DATA,CLK,BREAK,&MAINTENANCE MODE
1901 007140 012777 064001 010402      MOV      #MTDATA!CLK!MINT!BREAK,@TXCSR
1902
1903                                ;SET MODE ,# OF BITS,PARITY SENSE,&LOAD SYNC REG
1904 007146 012777 020000 010370      MOV      #SYNEXT!FIVE!NOPAR!0,@PARCSR
1905 007154 052777 000020 010352      BIS      #SYNSCH,@RXCSR ;SET SEARCH SYNC
1906                                ;POKE CLK TO GET LOGIC INTO SYNCHRONIZATION
1907 007162 042777 020000 010360      BIC      #CLK,@TXCSR ;POKE CLK DOWN
1908 007170 052777 020000 010352      BIS      #CLK,@TXCSR ;POKE CLK UP
1909 007176 016703 010336      MOV      RXDBUF,R3      ;SET UP FOR ERROR MESSAGE
1910 007202 012700 000000      MOV      #0,RO      ;EXPECTED
1911 007206 012767 000005 171724      MOV      #5,SHIFT ;# OF SHIFTS
1912 007214 012767 000000 171722      MOV      #0,TEMP1 ;DATA CHAR
1913 007222 004767 010012      JSR      PC,RPOKE ;SHIFT IN THIS CHAR
1914 007236 105777 010302      TSTB     @RXCSR ;RXDONE
1915 007232 100401      EMT      64$
1916 007234 104000      HLT      ;RXDONE SHOULD BE SET
1917
1918 007236 017701 010276      64$: MOV      @RXDBUF,R1      ;ACTUAL
1919 007242 020001      CMP      RO,R1      ;COMPARE EXPECTED VS. ACTUAL
1920 007244 001401      BEQ      65$
1921 007246 104002      HLT      2      ;RECEIVED DATA DID NOT MATCH
                                ;EXPECTED DATA - CHECK MAINT DATA
                                ;OR RECEIVER LOGIC
1922
1923
1924 007250      65$:
1925 007250 012767 000005 171662      MOV      #5,SHIFT ;# OF SHIFTS
1926 007256 012767 000000 171660      MOV      #0,TEMP1 ;DATA CHAR
1927 007264 004767 007750      JSR      PC,RPOKE ;SHIFT IN THIS CHAR
1928                                ;NOW SHIFT IN A SECOND CHARACTER WITHOUT READING RXDBUF
1929 007270 012767 000005 171642      MOV      #5,SHIFT ;# OF SHIFTS
1930 007276 012767 000000 171640      MOV      #0,TEMP1 ;DATA CHAR
1931 007304 004767 007730      JSR      PC,RPOKE ;SHIFT IN THIS CHAR
1932 007310 012700 140000      MOV      #140000!0,RO ;EXPECTED DATA PLUS

```

M03

DZDUB-C MACY11 27(1006) 31-OCT-76 09:17 PAGE 41
 DZDUBC.P11 21-MAY-76 00:00

SEQ 0038

```

1933                                     ;RXERR & OVRRUN
1934 007314 017701 010220      MOV      @RXDBUF,R1      ;ACTUAL
1935 007320 020001      CMP      R0,R1      ;COMPARE EXP VS. ACT
1936 007322 001401      BEQ      66$
1937 007324 104002      HLT      2      ;SPECIFICALLY LOC AT RXERR &
                                     ;OVRRUN BITS...THEY BOTH SHOULD BE SET
1938
1939                                     66$:
1940 007326 104400      SCOPE
1941                                     ;THIS TEST VERIFYS WORD LENGTH SELECT OF THE
1942                                     ;RECEIVER SECTION,IT USES THE ERROR FLAGS
1943                                     ;TO DETERMINE THAT IT WAS SELECTED CORRECTLY
1944                                     ;(OVRRUN,RXERR)
1945                                     ;MODE:SYNEXT
1946                                     ;LENGTH:SIX
1947                                     ;CHAR:25
1948
1949 007330 012767 000021 171570  TST17: MOV      #17,TSTNO      ;SAVE THIS
1950 007336 012767 007556 171552      MOV      #TST18,NEXT      ;GO TO THIS TEST WHEN THRU
1951 007344 052777 000400 010176      BIS      #MRESET,@TXCSR ;MASTER RESET
1952 007352 012777 020000 010164      MOV      #SYNEXT,@PARCSR ;SET THE MODE
1953 007360 052777 000400 010162      BIS      #MRESET,@TXCSR ;MASTER RESET
1954
1955                                     ;SET MAINT DATA,CLK,BREAK,&MAINTENANCE MODE
1956 007366 012777 064001 010154      MOV      #MTDATA!CLK!MINT!BREAK,@TXCSR
1957
1958                                     ;SET MODE ,# OF BITS,PARITY SENSE,&LOAD SYNC REG
1959 007374 012777 022000 010142      MOV      #SYNEXT!SIX!NOPAR!0,@PARCSR
1960 007402 052777 000020 010124      BIS      #SYNSCH,@RXCSR ;SET SEARCH SYNC
1961                                     ;POKE CLK TO GET LOGIC INTO SYNCRONIZATION
1962 007410 042777 020000 010132      BIC      #CLK,@TXCSR      ;POKE CLK DOWN
1963 007416 052777 020000 010124      BIS      #CLK,@TXCSR      ;POKE CLK UP
1964 007424 016703 010110      MOV      RXDBUF,R3      ;SET UP FOR ERROR MESSAGE
1965 007430 012700 000025      MOV      #25,R0      ;EXPECTED
1966 007434 012767 000006 171476      MOV      #6,SHIFT      ;# OF SHIFTS
1967 007442 012767 000025 171474      MOV      #25,TEMP1      ;DATA CHAR
1968 007450 004767 007564      JSR      PC,RPOKE      ;SHIFT IN THIS CHAR
1969 007454 105777 010054      TSTB      @RXCSR ;RXDONE
1970 007460 100401      BMI      64$
1971 007462 104000      HLT      ;RXDONE SHOULD BE SET
1972
1973 007464 017701 010050      64$: MOV      @RXDBUF,R1      ;ACTUAL
1974 007470 020001      CMP      R0,R1      ;COMPARE EXPECTED VS. ACTUAL
1975 007472 001401      BEQ      65$
1976 007474 104002      HLT      2      ;RECEIVED DATA DID NOT MATCH
                                     ;EXPECTED DATA - CHECK MAINT DATA
                                     ;OR RECEIVER LOGIC
1977
1978                                     65$:
1979 007476 012767 000006 171434      MOV      #6,SHIFT      ;# OF SHIFTS
1980 007476 012767 000025 171432      MOV      #25,TEMP1      ;DATA CHAR
1981 007504 012767 000025 171432      JSR      PC,RPOKE      ;SHIFT IN THIS CHAR
1982 007512 004767 007522      ;NOW SHIFT IN A SECOND CHARACTER WITHOUT READING RXDBUF
1983                                     MOV      #6,SHIFT      ;# OF SHIFTS
1984 007516 012767 000006 171414      MOV      #25,TEMP1      ;DATA CHAR
1985 007524 012767 000025 171412      JSR      PC,RPOKE      ;SHIFT IN THIS CHAR
1986 007532 004767 007502      MOV      #140000!25,R0      ;EXPECTED DATA PLUS
1987 007536 012700 140025      ;RXERR & OVRRUN
1988

```

N03

DZDUB-C MACY11 27(1006) 31-OCT-76 09:17 PAGE 42
DZDUBC.P11 21-MAY-76 00:00

SEQ 0039

1989	007542	017701	007772		MOV	ARXDBUF,R1	;ACTUAL
1990	007546	020001			CMP	R0,R1	;COMPARE EXP VS. ACT
1991	007550	001401			BEQ	65\$	
1992	007552	104002			HLT	2	;SPECIFICALLY LOOK AT RXERR & ;OVRRUN BITS...THEY BOTH SHOULD BE SET
1993							
1994	007554			65\$:			
1995	007554	104400					
1996							
1997							
1998							
1999							
2000							
2001							
2002							
2003							
2004	007556	012767	000022	171342	TST18:	MOV	#18,TSTNO ;SAVE THIS
2005	007564	012767	010004	171324		MOV	#TST19,NEXT ;GO TO THIS TEST WHEN THRU
2006	007572	052777	000400	007750		BIS	#MRESET,ATXCSR ;MASTER RESET
2007	007600	012777	020000	007736		MOV	#SYNEXT,APARCSR ;SET THE MODE
2008	007606	052777	000400	007734		BIS	#MRESET,ATXCSR ;MASTER RESET
2009							
2010							
2011	007614	012777	064001	007726			
2012							
2013							
2014	007622	012777	022000	007714			
2015	007630	052777	000020	007676			
2016							
2017	007636	042777	020000	007704			
2018	007644	052777	020000	007676			
2019	007652	016703	007662				
2020	007656	012700	000052				
2021	007662	012767	000006	171250			
2022	007670	012767	000052	171246			
2023	007676	004767	007336				
2024	007702	105777	007626				
2025	007706	100401					
2026	007710	104000					
2027	007712						
2028	007712	017701	007622				
2029	007716	020001					
2030	007720	001401					
2031	007722	104002					
2032							
2033							
2034	007724						
2035	007724	012767	000006	171206			
2036	007732	012767	000052	171204			
2037	007740	004767	007274				
2038							
2039	007744	012767	000006	171166			
2040	007752	012767	000052	171164			
2041	007760	004767	007254				
2042	007764	012700	140052				
2043							
2044	007770	017701	007544				

```

SCOPE
;THIS TEST VERIFYS WORD LENGTH SELECT OF THE
;RECEIVER SECTION,IT USES THE ERROR FLAGS
;TO DETERMINE THAT IT WAS SELECTED CORRECTLY
;(OVRRUN,RXERR)
;MODE:SYNEXT
;LENGTH:SIX
;CHAR:52

;SET MAINT DATA,CLK,BREAK,&MAINTENANCE MODE
MOV #MTDATA!CLK!MINT!BREAK,ATXCSR

;SET MODE # OF BITS,PARITY SENSE,&LOAD SYNC REG
MOV #SYNEXT!SIX!NOPAR!0,APARCSR
BIS #SYNSCH,ATXCSR ;SET SEARCH SYNC

;POKE CLK TO GET LOGIC INTO SYNCHRONIZATION
BIC #CLK,ATXCSR ;POKE CLK DOWN
BIS #CLK,ATXCSR ;POKE CLK UP
MOV RXDBUF,R3 ;SET UP FOR ERROR MESSAGE
MOV #52,R0 ;EXPECTED
MOV #6,SHIFT ;# OF SHIFTS
MOV #52,TEMP1 ;DATA CHAR
JSR PC,RPOKE ;SHIFT IN THIS CHAR
TSTB ATXCSR ;RXDONE
BMI 64$
HLT ;RXDONE SHOULD BE SET

64$:
MOV ARXDBUF,R1 ;ACTUAL
CMP R0,R1 ;COMPARE EXPECTED VS. ACTUAL
BEQ 65$
HLT 2 ;RECEIVED DATA DID NOT MATCH
;EXPECTED DATA - CHECK MAINT DATA
;OR RECEIVER LOGIC

65$:
MOV #6,SHIFT ;# OF SHIFTS
MOV #52,TEMP1 ;DATA CHAR
JSR PC,RPOKE ;SHIFT IN THIS CHAR
;NOW SHIFT IN A SECOND CHARACTER WITHOUT READING RXDBUF
MOV #6,SHIFT ;# OF SHIFTS
MOV #52,TEMP1 ;DATA CHAR
JSR PC,RPOKE ;SHIFT IN THIS CHAR
MOV #140000!52,R0 ;EXPECTED DATA PLUS
;RXERR & OVRRUN
MOV ARXDBUF,R1 ;ACTUAL

```

```

2045 007774 020001      CMP      R0,R1      ;COMPARE EXP VS. ACT
2046 007776 001401      BEQ      66$
2047 010000 104002      HLT      2
2048                                     ;SPECIFICALLY LOOK AT RXERR 3
2049                                     ;OVRUN BITS...THEY BOTH SHOULD BE SET
2050 010002 104400      66$:
2051                                     SCOPE
2052                                     ::THIS TEST VERIFYS WORD LENGTH SELECT OF THE
2053                                     ::RECEIVER SECTION,IT USES THE ERPCR FLAGS
2054                                     ::TO DETERMINE THAT IT WAS SELECTED CORRECTLY
2055                                     ::(OVRUN,RXERR)
2056                                     ::MODE:SYNEXT
2057                                     ::LENGTH:SIX
2058                                     ::CHAR:77
2059 010004 012767 000023 171114 TST19: MOV      #19,TSTNO      ;SAVE THIS
2060 010012 012767 010232 171076      MOV      #TST20,NEXT      ;GO TO THIS TEST WHEN THRU
2061 010020 052777 000400 007522      BIS      #MRESET,@TXCSR ;MASTER RESET
2062 010026 012777 020000 007510      MOV      #SYNEXT,@PARCSR ;SET THE MODE
2063 010034 052777 000400 007506      BIC      #MRESET,@TXCSR ;MASTER RESET
2064
2065                                     ;SET MAINT DATA,CLK,BREAK,&MAINTENANCE MODE
2066 010042 012777 064001 007500      MOV      #MTDATA!CLK!MINT!BREAK,@TXCSR
2067
2068                                     ;SET MODE, # OF BITS,PARITY SENSE,&LOAD SYNC REG
2069 010050 012777 022000 007466      MOV      #SYNEXT!SIX!NOPAR!0,@PARCSR
2070 010056 052777 000020 007450      BIS      #SYNSCH,@RXCSR ;SET SEARCH SYNC
2071                                     ;POKE CLK TO GET LOGIC INTO SYNCHRONIZATION
2072 010064 042777 020000 007456      BIC      #CLK,@TXCSR ;POKE CLK DOWN
2073 010072 052777 020000 007450      BIS      #CLK,@TXCSR ;POKE CLK UP
2074 010100 016703 007434      MOV      #RXDBUF,R3 ;SET UP FOR ERROR MESSAGE
2075 010104 012700 000077      MOV      #77,R0 ;EXPECTED
2076 010110 012767 000006 171022      MOV      #6,SHIFT ;# OF SHIFTS
2077 010116 012767 000077 171020      MOV      #77,TEMP1 ;DATA CHAR
2078 010124 004767 007110      JSR      PC,RPOKE ;SHIFT IN THIS CHAR
2079 010130 105777 007400      TSTB     @RXCSR ;RXDONE
2080 010134 100401 64$
2081 010136 104000      HLT      ;RXDONE SHOULD BE SET
2082
2083 010140 017701 007374      64$: MOV      @RXDBUF,R1 ;ACTUAL
2084 010144 020001      CMP      R0,R1 ;COMPARE EXPECTED VS. ACTUAL
2085 010146 001401      BEQ      65$
2086 010150 104002      HLT      2
2087                                     ;RECEIVED DATA DID NOT MATCH
2088                                     ;EXPECTED DATA - CHECK MAINT DATA
2089                                     ;OR RECEIVER LOGIC
2090 010152 012767 000006 170760      65$: MOV      #6,SHIFT ;# OF SHIFTS
2091 010160 012767 000077 170756      MOV      #77,TEMP1 ;DATA CHAR
2092 010166 004767 007046      JSR      PC,RPOKE ;SHIFT IN THIS CHAR
2093                                     ;NOW SHIFT IN A SECOND CHARACTER WITHOUT READING RXDBUF
2094 010172 012767 000006 170740      MOV      #6,SHIFT ;# OF SHIFTS
2095 010200 012767 000077 170736      MOV      #77,TEMP1 ;DATA CHAR
2096 010206 004767 007026      JSR      PC,RPOKE ;SHIFT IN THIS CHAR
2097 010212 012700 140077      MOV      #140000!77,R0 ;EXPECTED DATA PLUS
2098                                     ;RXERR & OVRUN
2099 010216 017701 007316      MOV      @RXDBUF,R1 ;ACTUAL
2100 010222 020001      CMP      R0,R1 ;COMPARE EXP VS. ACT

```

```

2101 010224 001401      BEQ      66$
2102 010226 104002      HLT      2      ;SPECIFICALLY LOOK AT RXERR &
2103                                     ;OVRUN BITS...THEY BOTH SHOULD BE SET
2104 010230
2105 010230 104400      66$:
2106                                     SCOPE
2107                                     ;:THIS TEST VERIFYS WORD LENGTH SELECT OF THE
2108                                     ;:RECEIVER SECTION,IT USES THE ERROR FLAGS
2109                                     ;:TO DETERMINE THAT IT WAS SELECTED CORRECTLY
2110                                     ;:(OVRUN,RXERR)
2111                                     ;:MODE:SYNEXT
2112                                     ;:LENGTH:SIX
2113                                     ;:CHAR:0
2114 010232 012767 000024 170666 TST20. MOV      #20,TSTNO      ;SAVE THIS
2115 010234 012767 010460 170650      MOV      #TST21,NEXT      ;GO TO THIS TEST WHEN THRU
2116 010246 052777 000400 007274      BIS      #MRESET,@TXCSR ;MASTER RESET
2117 010254 012777 020000 007262      MOV      #SYNEXT,@PARCSR ;SET THE MODE
2118 010262 052777 000400 007260      BIS      #MRESET,@TXCSR ;MASTER RESET
2119
2120                                     ;SET MAINT DATA,CLK,BREAK,&MAINTENANCE MODE
2121 010270 012777 064001 007252      MOV      #MTDATA!CLK!MINT!BREAK,@TXCSR
2122
2123                                     ;SET MODE # OF BITS,PARITY SENSE,&LOAD SYNC REG
2124 010276 012777 022000 007240      MOV      #SYNEXT!SIX!NOPAR!0,@PARCSR
2125 010304 052777 000020 007222      BIS      #SYNSCH,@RXCSR ;SET SEAP H SYNC
2126                                     ;POKE CLK TO GET LOGIC INTO SYNCRONIZATI
2127 010312 042777 020000 007230      BIC      #CLK,@TXCSR ;POKE CLK DOWN
2128 010320 052777 020000 007222      BIS      #CLK,@TXCSR ;POKE CLK UP
2129 010326 016703 007206      MOV      RXDBUF,R3      ;SET UP FOR ERROR MESSAGE
2130 010332 012700 000000      MOV      #0,R0 ;EXPECTED
2131 010336 012767 000006 170574      MOV      #6,SHIFT ;# OF SHIFTS
2132 010344 012767 000000 170572      MOV      #0,TEMP1 ;DATA CHAR
2133 010352 004767 006662      JSR      PC,RPOKE ;SHIFT IN THIS CHAR
2134 010356 105777 007152      TSTB      @RXCSR ;RXDONE
2135 010362 100401      BMI      64$
2136 010364 104000      HLT
2137 010366
2138 010366 017701 007146      64$: MOV      @RXDBUF,R1 ;ACTUAL
2139 010372 020001      CMP      R0,R1 ;COMPARE EXPECTED VS. ACTUAL
2140 010374 001401      BEQ      65$
2141 010376 104002      HLT      2      ;RECEIVED DATA DID NOT MATCH
2142                                     ;EXPECTED DATA - CHECK MAINT DATA
2143                                     ;OR RECEIVER LOGIC
2144 010400
2145 010400 012767 000006 170532      65$: MOV      #6,SHIFT ;# OF SHIFTS
2146 010406 012767 000000 170530      MOV      #0,TEMP1 ;DATA CHAR
2147 010414 004767 006620      JSR      PC,RPOKE ;SHIFT IN THIS CHAR
2148                                     ;NOW SHIFT IN A SECOND CHARACTER WITHOUT READING RXDBUF
2149 010420 012767 000006 170512      MOV      #6,SHIFT ;# OF SHIFTS
2150 010426 012767 000000 170510      MOV      #0,TEMP1 ;DATA CHAR
2151 010434 004767 006600      JSR      PC,RPOKE ;SHIFT IN THIS CHAR
2152 010440 012700 140000      MOV      #140000!0,R0 ;EXPECTED DATA PLUS
2153                                     ;RXERR & OVRUN
2154 010444 017701 007070      MOV      @RXDBUF,R1 ;ACTUAL
2155 010450 020001      CMP      R0,R1 ;COMPARE EXP VS. ACT
2156 010452 001401      BEQ      66$

```

```

2157 010454 104002          HLT      2          ;SPECIFICALLY LOOK AT RXERR &
2158                                     ;OVRUN BITS...THEY BOTH SHOULD BE SET
2159 010456          66$:
2160 010456 104400          SCOPE
2161                                     ;:THIS TEST VERIFYS WORD LENGTH SELECT OF THE
2162                                     ;:RECEIVER SECTION,IT USES THE ERROR FLAGS
2163                                     ;:TO DETERMINE THAT IT WAS SELECTED CORRECTLY
2164                                     ;:(OVRUN,RXERR)
2165                                     ;:MODE:SYNEXT
2166                                     ;:LENGTH:SEVEN
2167                                     ;:CHAR:125
2168
2169 010460 012767 000025 170440 TST21: MOV      #21,TSTNO          ;SAVE THIS
2170 010466 012767 010706 170422      MOV      #TST22,NEXT        ;GO TO THIS TEST WHEN THRU
2171 010474 052777 000400 007046      BIS      #MRESET,@TXCSR    ;MASTER RESET
2172 010502 012777 020000 007034      MOV      #SYNEXT,@PARCSR   ;SET THE MODE
2173 010510 052777 000400 007032      BIS      #MRESET,@TXCSR    ;MASTER RESET
2174
2175                                     ;SET MAINT DATA,CLK,BREAK,&MAINTENANCE MODE
2176 010516 012777 064001 007024      MOV      #MTDATA!CLK!MINT!BREAK,@TXCSR
2177
2178                                     ;SET MODE ,# OF BITS,PARITY SENSE,&LOAD SYNC REG
2179 010524 012777 024000 007012      MOV      #SYNEXT!SEVEN!NOPAR!0,@PARCSR
2180 010532 052777 000020 006774      BIS      #SYNSCH,@RXCSR    ;SET SEARCH SYNC
2181                                     ;POKE CLK TO GET LOGIC INTO SYNCHRONIZATION
2182 010540 042777 020000 007002      BIC      #CLK,@TXCSR      ;POKE CLK DOWN
2183 010546 052777 020000 006774      BIS      #CLK,@TXCSR      ;POKE CLK UP
2184 010554 016703 006760          MOV      #RXDBUF,R3          ;SET UP FOR ERROR MESSAGE
2185 010560 012700 000125          MOV      #125,R0              ;EXPECTED
2186 010564 012767 000007 170346      MOV      #7,SHIFT          ;# OF SHIFTS
2187 010572 012767 000125 170344      MOV      #125,TEMP1        ;DATA CHAR
2188 010600 004767 006434          JSR      PC,RPOKE            ;SHIFT IN THIS CHAR
2189 010604 105777 006724          TSTB     @RXCSR              ;RXDONE
2190 010610 100401          BMI      64$
2191 010612 104000          HLT
2192 010614          64$:
2193 010614 017701 006720          MOV      @RXDBUF,R1          ;ACTUAL
2194 010620 020001          CMP      R0,R1          ;COMPARE EXPECTED VS. ACTUAL
2195 010622 001401          BEQ      65$
2196 010624 104002          HLT      2          ;RECEIVED DATA DID NOT MATCH
2197                                     ;EXPECTED DATA - CHECK MAINT DATA
2198                                     ;OR RECEIVER LOGIC
2199
2200 010626 012767 000007 170304      MOV      #7,SHIFT          ;# OF SHIFTS
2201 010634 012767 000125 170302      MOV      #125,TEMP1        ;DATA CHAR
2202 010642 004767 006372          JSR      PC,RPOKE            ;SHIFT IN THIS CHAR
2203                                     ;NOW SHIFT IN A SECOND CHARACTER WITHOUT READING RXDBUF
2204 010646 012767 000007 170264      MOV      #7,SHIFT          ;# OF SHIFTS
2205 010654 012767 000125 170262      MOV      #125,TEMP1        ;DATA CHAR
2206 010662 004767 006352          JSR      PC,RPOKE            ;SHIFT IN THIS CHAR
2207 010666 012700 140125          MOV      #140000!125,R0      ;EXPECTED DATA PLUS
2208                                     ;RXERR & OVRUN
2209 010672 017701 006642          MOV      @RXDBUF,R1          ;ACTUAL
2210 010676 020001          CMP      R0,R1          ;COMPARE EXP VS. ACT
2211 010700 001401          BEQ      66$
2212 010702 104002          HLT      2          ;SPECIFICALLY LOOK AT RXERR &

```

```

2213                                     ;OVRUN BITS...THEY BOTH SHOULD BE SET
2214 010704                               66$:
2215 010704 104400
2216                                     SCOPE
2217                                     ;:THIS TEST VERIFYS WORD LENGTH SELECT OF THE
2218                                     ;:RECEIVER SECTION,IT USES THE ERROR FLAGS
2219                                     ;:TO DETERMINE THAT IT WAS SELECTED CORRECTLY
2220                                     ;:(OVRUN,RXERR)
2221                                     ;:MODE:SYNEXT
2222                                     ;:LENGTH:SEVEN
2223                                     ;:CHAR:52
2224 010706 012767 000026 170212 TST2: MOV #22,TSTNO ;SAVE THIS
2225 010714 012767 011134 170174      MOV #TST2,NEXT ;GO TO THIS TEST WHEN THRU
2226 010722 052777 000400 006620      BIS #MRESET,ATXCSR ;MASTER RESET
2227 010730 012777 020000 006606      MOV #SYNEXT,APARCSR ;SET THE MODE
2228 010736 052777 000400 006604      BIS #MRESET,ATXCSR ;MASTER RESET
2229
2230                                     ;SET MAINT DATA,CLK,BREAK,&MAINTENANCE MODE
2231 010744 012777 064001 006576      MOV #MTDATA!CLK!MINT!BREAK,ATXCSR
2232
2233                                     ;SET MODE ,# OF BITS,PARITY SENSE,&LOAD SYNC REG
2234 010752 012777 024000 006564      MOV #SYNEXT!SEVEN!NOPAR!0,APARCSR
2235 010760 052777 000020 006546      BIS #SYNSCH,ARXCSR ;SET SEARCH SYNC
2236                                     ;POKE CLK TO GET LOGIC INTO SYNCHRONIZATION
2237 010766 042777 020000 006554      BIC #CLK,ATXCSR ;POKE CLK DOWN
2238 010774 052777 020000 006546      BIS #CLK,ATXCSR ;POKE CLK UP
2239 011002 016703 006532              MOV RXDBUF,RJ ;SET UP FOR ERROR MESSAGE
2240 011006 012700 000052              MOV #52,R0 ;EXPECTED
2241 011012 012767 000007 170120      MOV #7,SHIFT ;# OF SHIFTS
2242 011020 012767 000052 170116      MOV #52,TEMP1 ;DATA CHAR
2243 011026 004767 006206              JSR PC,APPOKE ;SHIFT IN THIS CHAR
2244 011032 105777 006476              TSTB ARXCSR ;RXDONE
2245 011036 100401                    BMI 64$
2246 011040 104000                    HLT
2247 011042                    64$:
2248 011042 017701 006472              MOV ARXDBUF,R1 ;ACTUAL
2249 011046 020001                    CMP R0,R1 ;COMPARE EXPECTED VS. ACTUAL
2250 011050 001401                    BEQ 65$
2251 011052 104002                    HLT 2
2252                                     ;RECEIVED DATA DID NOT MATCH
2253                                     ;EXPECTED DATA - CHECK MAINT DATA
2254                                     ;OR RECEIVER LOGIC
2255 011054                    65$:
2256 011054 012767 000007 170056      MOV #7,SHIFT ;# OF SHIFTS
2257 011062 012767 000052 170054      MOV #52,TEMP1 ;DATA CHAR
2258 011070 004767 006144              JSR PC,APPOKE ;SHIFT IN THIS CHAR
2259                                     ;NOW SHIFT IN A SECOND CHARACTER WITHOUT READING RXDBUF
2260 011074 012767 000007 170036      MOV #7,SHIFT ;# OF SHIFTS
2261 011102 012767 000052 170034      MOV #52,TEMP1 ;DATA CHAR
2262 011110 004767 006124              JSR PC,APPOKE ;SHIFT IN THIS CHAR
2263 011114 012700 140052              MOV #140000!52,R0 ;EXPECTED DATA PLUS
2264                                     ;RXERR & OVRUN
2265 011120 017701 006414              MOV ARXDBUF,R1 ;ACTUAL
2266 011124 020001                    CMP R0,R1 ;COMPARE EXP VS. ACT
2267 011126 001401                    BEQ 66$
2268 011130 104002                    HLT 2
2269                                     ;SPECIFICALLY LOOK AT RXERR &
2270                                     ;OVRUN BITS...THEY BOTH SHOULD BE SET

```

```

2269 011132          66$:
2270 011132 104400
2271
2272
2273
2274
2275
2276
2277
2278
2279 011134 012767 000027 167764 TST23: MOV #23,TSTNO ;SAVE THIS
2280 011142 012767 011362 167746 MOV #TST24,NEXT ;GO TO THIS TEST WHEN THRU
2281 011150 052777 000400 006372 BIS #MRESET,ATXCSR ;MASTER RESET
2282 011156 012777 020000 006360 MOV #SYNEXT,APARCSR ;SET THE MODE
2283 011164 052777 000400 006356 BIS #MRESET,ATXCSR ;MASTER RESET
2284
2285 ;SET MAINT DATA,CLK,BREAK,&MAINTENANCE MODE
2286 011172 012777 064001 006350 MOV #MTDATA!CLK!MINT!BREAK,ATXCSR
2287
2288 ;SET MODE, # OF BITS,PARITY SENSE,&LOAD SYNC REG
2289 011200 012777 024000 006336 MOV #SYNEXT!SEVEN!NOPAR!0,APARCSR
2290 011206 052777 000020 006320 BIS #SYNSCH,ATXCSR ;SET SEARCH SYNC
2291 ;POKE CLK TO GET LOGIC INTO SYNCHRONIZATION
2292 011214 042777 020000 006326 BIC #CLK,ATXCSR ;POKE CLK DOWN
2293 011222 052777 020000 006320 BIS #CLK,ATXCSR ;POKE CLK UP
2294 011230 016703 006304 MOV RXDBUF,R3 ;SET UP FOR ERROR MESSAGE
2295 011234 012700 000177 MOV #177,R0 ;EXPECTED
2296 011240 012767 000007 167672 MOV #7,SHIFT ;# OF SHIFTS
2297 011246 012767 000177 167670 MOV #177,TEMP1 ;DATA CHAR
2298 011254 004767 005760 JSR PC,RPOKE ;SHIFT IN THIS CHAR
2299 011260 105777 006250 TSTB ATXCSR ;RXDONE
2300 011264 100401 BMI B4$
2301 011266 104000 HLT ;RXDONE SHOULD BE SET
2302
2303 011270 017701 006244 64$: MOV ATXDBUF,R1 ;ACTUAL
2304 011274 020001 CMP R0,R1 ;COMPARE EXPECTED VS. ACTUAL
2305 011276 001401 BEQ B5$
2306 011300 104002 HLT 2 ;RECEIVED DATA DID NOT MATCH
2307 ;EXPECTED DATA - CHECK MAINT DATA
2308 ;OR RECEIVER LOGIC
2309
2310 011302 012767 000007 167630 65$: MOV #7,SHIFT ;# OF SHIFTS
2311 011310 012767 000177 167626 MOV #177,TEMP1 ;DATA CHAR
2312 011316 004767 005716 JSR PC,RPOKE ;SHIFT IN THIS CHAR
2313 ;NOW SHIFT IN A SECOND CHARACTER WITHOUT READING RXDBUF
2314 011322 012767 000007 167610 MOV #7,SHIFT ;# OF SHIFTS
2315 011330 012767 000177 167606 MOV #177,TEMP1 ;DATA CHAR
2316 011336 004767 005676 JSR PC,RPOKE ;SHIFT IN THIS CHAR
2317 011342 012700 140177 MOV #140000!177,R0 ;EXPECTED DATA PLUS
2318 ;RXERR & OVRUN
2319 011346 017701 006166 MOV ATXDBUF,R1 ;ACTUAL
2320 011352 020001 CMP R0,R1 ;COMPARE EXP VS. ACT
2321 011354 001401 BEQ B6$
2322 011356 104002 HLT 2 ;SPECIFICALLY LOOK AT RXERR &
2323 ;OVRUN BITS...THEY BOTH SHOULD BE SET
2324 011360 66$:

```

```

2325 011360 104400 SCOPE
2326 ::THIS TEST VERIFYS WORD LENGTH SELECT OF THE
2327 ::RECEIVER SECTION, IT USES THE ERROR FLAGS
2328 ::TO DETERMINE THAT IT WAS SELECTED CORRECTLY
2329 ::(OVRUN, RXERR)
2330 ::MODE:SYNEXT
2331 ::LENGTH:SEVEN
2332 ::CHAR:J
2333
2334 011362 012767 000030 167536 TST24: MOV #24, TSTNO ;SAVE THIS
2335 011370 012767 011610 167520 MOV #TST25, NEXT ;GO TO THIS TEST WHEN THRU
2336 011376 052777 000400 006144 BIS #MRESET, @TXCSR ;MASTER RESET
2337 011404 012777 020000 006132 MOV #SYNEXT, @PARCSR ;SET THE MODE
2338 011412 052777 000400 006130 BIS #MRESET, @TXCSR ;MASTER RESET
2339
2340 ;SET MAINT DATA, CLK, BREAK, & MAINTENANCE MODE
2341 011420 012777 064001 006122 MOV #MTDATA!CLK!MINT!BREAK, @TXCSR
2342
2343 ;SET MODE, # OF BITS, PARITY SENSE, & LOAD SYNC REG
2344 011426 012777 024000 006110 MOV #SYNEXT!SEVEN!NOPAR!0, @PARCSR
2345 011434 052777 000020 006072 BIS #SYNSCH, @RXCSR ;SET SEARCH SYNC
2346 ;POKE CLK TO GET LOGIC INTO SYNCHRONIZATION
2347 011442 042777 020000 006100 BIC #CLK, @TXCSR ;POKE CLK DOWN
2348 011450 052777 020000 006072 BIS #CLK, @TXCSR ;POKE CLK UP
2349 011456 016703 006056 MOV RXDBUF, R3 ;SET UP FOR ERROR MESSAGE
2350 011462 012700 000000 MOV #0, RO ;EXPECTED
2351 011466 012767 000007 167444 MOV #7, SHIFT ;# OF SHIFTS
2352 011474 012767 000000 167442 MOV #0, TEMP1 ;DATA CHAR
2353 011502 004767 005532 JSR PC, RPOKE ;SHIFT IN THIS CHAR
2354 011506 105777 006022 TSTB @RXCSR ;RXDONE
2355 011512 100401 BMI 64$
2356 011514 104000 HLT ;RXDONE SHOULD BE SET
2357 011516 64$:
2358 011516 017701 006016 MOV @RXDBUF, R1 ;ACTUAL
2359 011522 020001 CMP RO, R1 ;COMPARE EXPECTED VS. ACTUAL
2360 011524 001401 BEQ 65$
2361 011526 104002 HLT 2 ;RECEIVED DATA DID NOT MATCH
2362 ;EXPECTED DATA - CHECK MAINT DATA
2363 ;OR RECEIVER LOGIC
2364 011530 65$:
2365 011530 012767 000007 167402 MOV #7, SHIFT ;# OF SHIFTS
2366 011536 012767 000000 167400 MOV #0, TEMP1 ;DATA CHAR
2367 011544 004767 005470 JSR PC, RPOKE ;SHIFT IN THIS CHAR
2368 ;NOW SHIFT IN A SECOND CHARACTER WITHOUT READING RXDBUF
2369 011550 012767 000007 167362 MOV #7, SHIFT ;# OF SHIFTS
2370 011556 012767 000000 167360 MOV #0, TEMP1 ;DATA CHAR
2371 011564 004767 005450 JSR PC, RPOKE ;SHIFT IN THIS CHAR
2372 011570 012700 140000 MOV #140000!0, RO ;EXPECTED DATA PLUS
2373 ;RXERR & OVRUN
2374 011574 017701 005740 MOV @RXDBUF, R1 ;ACTUAL
2375 011600 020001 CMP RO, R1 ;COMPARE EXP VS. ACT
2376 011602 001401 BEQ 66$
2377 011604 104002 HLT 2 ;SPECIFICALLY LOOK AT RXERR &
2378 ;OVRUN BITS...THEY BOTH SHOULD BE SET
2379 011606 66$:
2380 011606 104400 SCOPE

```

```

2381      ;; THIS TEST VERIFYS WORD LENGTH SELECT OF THE
2382      ;; RECEIVER SECTION, IT USES THE ERROR FLAGS
2383      ;; TO DETERMINE THAT IT WAS SELECTED CORRECTLY
2384      ;; (OVRUN, RXERR)
2385      ;; MODE: SYNEXT
2386      ;; LENGTH: EIGHT
2387      ;; CHAR: 125
2388
2389 011610 012767 000031 167310 TST25: MOV    #25, TSTNO      ;SAVE THIS
2390 011616 012767 012036 167272      MOV    #TST26, NEXT      ;GO TO THIS TEST WHEN THRU
2391 011624 052777 000400 005716      BIS    #MRESET, @TXCSR ;MASTER RESET
2392 011632 012777 020000 005704      MOV    #SYNEXT, @PARCSR ;SET THE MODE
2393 011640 052777 000400 005702      BIS    #MRESET, @TXCSR ;MASTER RESET
2394
2395      ;SET MAINT DATA, CLK, BREAK, & MAINTENANCE MODE
2396 011646 012777 064001 005674      MOV    #MTDATA!CLK!MINT!BREAK, @TXCSR
2397
2398      ;SET MODE, # OF BITS, PARITY SENSE, & LOAD SYNC REG
2399 011654 012777 026000 005662      MOV    #SYNEXT!EIGHT!NOPAR!0, @PARCSR
2400 011662 052777 000020 005644      BIS    #SYNSCH, @RXCSR ;SET SEARCH SYNC
2401
2402      ;POKE CLK TO GET LOGIC INTO SYNCHRONIZATION
2403 011670 042777 020000 005652      BIC    #CLK, @TXCSR ;POKE CLK DOWN
2404 011676 052777 020000 005644      BIS    #CLK, @TXCSR ;POKE CLK UP
2405 011704 016703 005630          MOV    RXDBUF, R3 ;SET UP FOR ERROR MESSAGE
2406 011710 012700 000125          MOV    #125, R0 ;EXPECTED
2407 011714 012767 000010 167216      MOV    #8, SHIFT ;# OF SHIFTS
2408 011722 012767 000125 167214      MOV    #125, TEMP1 ;DATA CHAR
2409 011730 004767 005304          JSR    PC, RPOKE ;SHIFT IN THIS CHAR
2410 011734 105777 005574          TSTB   @RXCSR ;RXDONE
2411 011740 100401          BMI     64$
2412 011742 104000          HLT     ;RXDONE SHOULD BE SET
2413
2414 011744 017701 005570          64$: MOV    @RXDBUF, R1 ;ACTUAL
2415 011750 020001          CMP     R0, R1 ;COMPARE EXPECTED VS. ACTUAL
2416 011752 001401          BEQ     65$
2417 011754 104002          HLT     2 ;RECEIVED DATA DID NOT MATCH
2418      ;EXPECTED DATA - CHECK MAINT DATA
2419      ;OR RECEIVER LOGIC
2420
2421 011756 012767 000010 167154          65$: MOV    #8, SHIFT ;# OF SHIFTS
2422 011764 012767 000125 167152      MOV    #125, TEMP1 ;DATA CHAR
2423 011772 004767 005242          JSR    PC, RPOKE ;SHIFT IN THIS CHAR
2424      ;NOW SHIFT IN A SECOND CHARACTER WITHOUT READING RXDBUF
2425 011776 012767 000010 167134      MOV    #8, SHIFT ;# OF SHIFTS
2426 012004 012767 000125 167132      MOV    #125, TEMP1 ;DATA CHAR
2427 012012 004767 005222          JSR    PC, RPOKE ;SHIFT IN THIS CHAR
2428 012016 012700 140125          MOV    #140000!125, R0 ;EXPECTED DATA PLUS
2429      ;RXERR & OVRUN
2430 012022 017701 005512          MOV    @RXDBUF, R1 ;ACTUAL
2431 012026 020001          CMP     R0, R1 ;COMPARE EXP VS. ACT
2432 012030 001401          BEQ     66$
2433 012032 104002          HLT     2 ;SPECIFICALLY LOOK AT RXERR &
2434      ;OVRUN BITS...THEY BOTH SHOULD BE SET
2435
2436 012034 104400          66$: SCOPE
      ;; THIS TEST VERIFYS WORD LENGTH SELECT OF THE

```

```

2437      ;;RECEIVER SECTION,IT USES THE ERROR FLAGS
2438      ;;TO DETERMINE THAT IT WAS SELECTED CORRECTLY
2439      ;;(OVRUN,RXERR)
2440      ;;MODE:SYNEXT
2441      ;;LENGTH:EIGHT
2442      ;;CHAR:252
2443
2444      012036 012767 000032 167062 TST26: MOV     #26,TSTNO      ;SAVE THIS
2445      012044 012767 012264 167044      MOV     #TST27,NEXT      ;GO TO THIS TEST WHEN THRU
2446      012052 052777 000400 005470      BIS     #MRESET,@TXCSR ;MASTER RESET
2447      012060 012777 020000 005456      MOV     #SYNEXT,@PARCSR ;SET THE MODE
2448      012066 052777 000400 005454      BIS     #MRESET,@TXCSR ;MASTER RESET
2449
2450      ;SET MAINT DATA,CLK,BREAK,&MAINTENANCE MODE
2451      012074 012777 064001 005446      MOV     #MTDATA!CLK!MINT!BREAK,@TXCSR
2452
2453      ;SET MODE ,# OF BITS,PARITY SENSE,&LOAD SYNC REG
2454      012102 012777 026000 005434      MOV     #SYNEXT!EIGHT!NOPAR!0,@PARCSR
2455      012110 052777 000020 005416      BIS     #SYNSCH,@RXCSR ;SET SEARCH SYNC
2456      ;POKE CLK TO GET LOGIC INTO SYNCRONIZATION
2457      012116 042777 020000 005424      BIC     #CLK,@TXCSR ;POKE CLK DOWN
2458      012124 052777 020000 005416      BIS     #CLK,@TXCSR ;POKE CLK UP
2459      012132 016703 005402              MOV     RXDBUF,R3 ;SET UP FOR ERROR MESSAGE
2460      012136 012700 000252              MOV     #252,R0 ;EXPECTED
2461      012142 012767 000010 166770      MOV     #8,SHIFT ;# OF SHIFTS
2462      012150 012767 000252 166766      MOV     #252,TEMP1 ;DATA CHAR
2463      012156 004767 005056              JSR     PC,RPOKE ;SHIFT IN THIS CHAR
2464      012162 105777 005346              TSTB    @RXCSR ;RXDONE
2465      012166 100401                      BMI     64$
2466      012170 104000                      HLT
2467      012172
2468      012172 017701 005342      64$: MOV     @RXDBUF,R1 ;ACTUAL
2469      012176 020001              CMP     R0,R1 ;COMPARE EXPECTED VS. ACTUAL
2470      012200 001401              BEQ     65$
2471      012202 104002              HLT     2 ;RECEIVED DATA DID NOT MATCH
2472      ;EXPECTED DATA - CHECK MAINT DATA
2473      ;OR RECEIVER LOGIC
2474
2475      012204
2476      012204 012767 000010 166726      65$: MOV     #8,SHIFT ;# OF SHIFTS
2477      012212 012767 000252 166724      MOV     #252,TEMP1 ;DATA CHAR
2478      012220 004767 005014              JSR     PC,RPOKE ;SHIFT IN THIS CHAR
2479      ;NOW SHIFT IN A SECOND CHARACTER WITHOUT READING RXDBUF
2480      012224 012767 000010 166706      MOV     #8,SHIFT ;# OF SHIFTS
2481      012232 012767 000252 166704      MOV     #252,TEMP1 ;DATA CHAR
2482      012240 004767 004774              JSR     PC,RPOKE ;SHIFT IN THIS CHAR
2483      012244 012700 140252              MOV     #140000!252,R0 ;EXPECTED DATA PLUS
2484      ;RXERR & OVRUN
2485      012250 017701 005264      MOV     @RXDBUF,R1 ;ACTUAL
2486      012254 020001              CMP     R0,R1 ;COMPARE EXP VS. ACT
2487      012256 001401              BEQ     66$
2488      012260 104002              HLT     2 ;SPECIFICALLY LOOK AT RXERR &
2489      ;OVRUN BITS...THEY BOTH SHOULD BE SET
2490      012262 104400      66$:
2491      SCOPE
2492      ;;THIS TEST VERIFYS WORD LENGTH SELECT OF THE
2493      ;;RECEIVER SECTION,IT USES THE ERROR FLAGS

```

```

2493      ;; TO DETERMINE THAT IT WAS SELECTED CORRECTLY
2494      ;; (OVRUN, RXERR)
2495      ;; MODE: SYNEXT
2496      ;; LENGTH: EIGHT
2497      ;; CHAR: 377
2498
2499      012264 012767 000033 166634 TST27: MOV    #27, TSTNO      ;SAVE THIS
2500      012272 012767 012512 166616      MOV    #TST28, NEXT      ;GO TO THIS TEST WHEN THRU
2501      012300 052777 000400 005242      BIS    #MRESET, @TXCSR    ;MASTER RESET
2502      012306 012777 020000 005230      MOV    #SYNEXT, @PARCSR   ;SET THE MODE
2503      012314 052777 000400 005226      BIS    #MRESET, @TXCSR    ;MASTER RESET
2504
2505      ;SET MAINT DATA, CLK, BREAK, & MAINTENANCE MODE
2506      012322 012777 064001 005220      MOV    #MTDATA!CLK!MINT!BREAK, @TXCSR
2507
2508      ;SET MODE, # OF BITS, PARITY SENSE, & LOAD SYNC REG
2509      012330 012777 026000 005206      MOV    #SYNEXT!EIGHT!NOPAR!0, @PARCSR
2510      012336 052777 000020 005170      BIS    #SYNSCH, @RXCSR    ;SET SEARCH SYNC
2511      ;POKE CLK TO GET LOGIC INTO SYNCHRONIZATION
2512      012344 042777 020000 005176      BIC    #CLK, @TXCSR      ;POKE CLK DOWN
2513      012352 052777 020000 005170      BIS    #CLK, @TXCSR      ;POKE CLK UP
2514      012360 016703 005154              MOV    RXDBUF, R3        ;SET UP FOR ERROR MESSAGE
2515      012364 012700 000377              MOV    #377, R0          ;EXPECTED
2516      012370 012767 000010 166542      MOV    #8, SHIFT        ;# OF SHIFTS
2517      012376 012767 000377 166540      MOV    #377, TEMP1      ;DATA CHAR
2518      012404 004767 004630              JSR    PC, RPOKE        ;SHIFT IN THIS CHAR
2519      012410 105777 005120              TSTB    @RXCSR          ;RXDONE
2520      012414 100401 64$                BMI    64$
2521      012416 104000                    HLT
2522      012420
2523      012420 017701 005114              64$: MOV    @RXDBUF, R1      ;ACTUAL
2524      012424 020001                    CMP    R0, R1          ;COMPARE EXPECTED VS. ACTUAL
2525      012426 001401                    BEQ    65$
2526      012430 104002                    HLT    2              ;RECEIVED DATA DID NOT MATCH
2527
2528
2529
2530      012432 012767 000010 166500              65$: MOV    #8, SHIFT        ;# OF SHIFTS
2531      012440 012767 000377 166476              MOV    #377, TEMP1      ;DATA CHAR
2532      012446 004767 004566              JSR    PC, RPOKE        ;SHIFT IN THIS CHAR
2533
2534      ;NOW SHIFT IN A SECOND CHARACTER WITHOUT READING RXDBUF
2535      012452 012767 000010 166460              MOV    #8, SHIFT        ;# OF SHIFTS
2536      012460 012767 000377 166456              MOV    #377, TEMP1      ;DATA CHAR
2537      012466 004767 004546              JSR    PC, RPOKE        ;SHIFT IN THIS CHAR
2538      012472 012700 140377              MOV    #140000!377, R0  ;EXPECTED DATA PLUS
2539
2540
2541
2542
2543
2544      012476 017701 005036              MOV    @RXDBUF, R1      ;ACTUAL
2545      012502 020001                    CMP    R0, R1          ;COMPARE EXP VS. ACT
2546      012504 001401                    BEQ    66$
2547      012506 104002                    HLT    2              ;SPECIFICALLY LOOK AT RXERR &
2548
2549
2550
2551
2552
2553
2554
2555
2556
2557
2558
2559
2560
2561
2562
2563
2564
2565
2566
2567
2568
2569
2570
2571
2572
2573
2574
2575
2576
2577
2578
2579
2580
2581
2582
2583
2584
2585
2586
2587
2588
2589
2590
2591
2592
2593
2594
2595
2596
2597
2598
2599
2600
2601
2602
2603
2604
2605
2606
2607
2608
2609
2610
2611
2612
2613
2614
2615
2616
2617
2618
2619
2620
2621
2622
2623
2624
2625
2626
2627
2628
2629
2630
2631
2632
2633
2634
2635
2636
2637
2638
2639
2640
2641
2642
2643
2644
2645
2646
2647
2648
2649
2650
2651
2652
2653
2654
2655
2656
2657
2658
2659
2660
2661
2662
2663
2664
2665
2666
2667
2668
2669
2670
2671
2672
2673
2674
2675
2676
2677
2678
2679
2680
2681
2682
2683
2684
2685
2686
2687
2688
2689
2690
2691
2692
2693
2694
2695
2696
2697
2698
2699
2700
2701
2702
2703
2704
2705
2706
2707
2708
2709
2710
2711
2712
2713
2714
2715
2716
2717
2718
2719
2720
2721
2722
2723
2724
2725
2726
2727
2728
2729
2730
2731
2732
2733
2734
2735
2736
2737
2738
2739
2740
2741
2742
2743
2744
2745
2746
2747
2748
2749
2750
2751
2752
2753
2754
2755
2756
2757
2758
2759
2760
2761
2762
2763
2764
2765
2766
2767
2768
2769
2770
2771
2772
2773
2774
2775
2776
2777
2778
2779
2780
2781
2782
2783
2784
2785
2786
2787
2788
2789
2790
2791
2792
2793
2794
2795
2796
2797
2798
2799
2800
2801
2802
2803
2804
2805
2806
2807
2808
2809
2810
2811
2812
2813
2814
2815
2816
2817
2818
2819
2820
2821
2822
2823
2824
2825
2826
2827
2828
2829
2830
2831
2832
2833
2834
2835
2836
2837
2838
2839
2840
2841
2842
2843
2844
2845
2846
2847
2848
2849
2850
2851
2852
2853
2854
2855
2856
2857
2858
2859
2860
2861
2862
2863
2864
2865
2866
2867
2868
2869
2870
2871
2872
2873
2874
2875
2876
2877
2878
2879
2880
2881
2882
2883
2884
2885
2886
2887
2888
2889
2890
2891
2892
2893
2894
2895
2896
2897
2898
2899
2900
2901
2902
2903
2904
2905
2906
2907
2908
2909
2910
2911
2912
2913
2914
2915
2916
2917
2918
2919
2920
2921
2922
2923
2924
2925
2926
2927
2928
2929
2930
2931
2932
2933
2934
2935
2936
2937
2938
2939
2940
2941
2942
2943
2944
2945
2946
2947
2948
2949
2950
2951
2952
2953
2954
2955
2956
2957
2958
2959
2960
2961
2962
2963
2964
2965
2966
2967
2968
2969
2970
2971
2972
2973
2974
2975
2976
2977
2978
2979
2980
2981
2982
2983
2984
2985
2986
2987
2988
2989
2990
2991
2992
2993
2994
2995
2996
2997
2998
2999
3000

```

K04

 DZDUB-C MACY11 27(1006) 01-OCT-76 09:17 PAGE 52
 DZDUBC.P11 21-MAY-76 00:00

SEQ 0049

```

2549      ; (OVRUN, RXERR)
2550      ; MODE: SYNEXT
2551      ; LENGTH: EIGHT
2552      ; CHAR: 0
2553
2554 012512 012767 000034 166406 TST28: MOV #28, TSTNO ; SAVE THIS
2555 012520 012767 012740 166370      MOV #.EOP, NEXT ; GO TO THIS TEST WHEN THRU
2556 012526 052777 000400 005014      BIS #MRESET, @TXCSR ; MASTER RESET
2557 012534 012777 020000 005002      MOV #SYNEXT, @PARCSR ; SET THE MODE
2558 012542 052777 000400 005000      BIS #MRESET, @TXCSR ; MASTER RESET
2559
2560      ; SET MAINT DATA, CLK, BREAK, & MAINTENANCE MODE
2561 012550 012777 064001 004772      MOV #MTDATA!CLK!MINT!BREAK, @TXCSR
2562
2563      ; SET MODE, # OF BITS, PARITY SENSE, & LOAD SYNC REG
2564 012556 012777 026000 004760      MOV #SYNEXT!EIGHT!NOPAR!0, @PARCSR
2565 012564 052777 000020 004742      BIS #SYNSCH, @RXCSR ; SET SEARCH SYNC
2566      ; POKE CLK TO GET LOGIC INTO SYNCHRONIZATION
2567 012572 042777 020000 004750      BIC #CLK, @TXCSR ; POKE CLK DOWN
2568 012600 052777 020000 004742      BIS #CLK, @TXCSR ; POKE CLK UP
2569 012606 016703 004726          MOV RXDBUF, R3 ; SET UP FOR ERROR MESSAGE
2570 012612 012700 000000          MOV #0, R0 ; EXPECTED
2571 012616 012767 000010 166314      MOV #8, SHIFT ; # OF SHIFTS
2572 012624 012767 000000 166312      MOV #0, TEMP1 ; DATA CHAR
2573 012632 004767 004402          JSR PC, RPOKE ; SHIFT IN THIS CHAR
2574 012636 105777 004672          TSTB @RXCSR ; RXDONE
2575 012642 100401          BMI 64$
2576 012644 104000          HLT ; RXDONE SHOULD BE SET
2577 012646
2578 012646 017701 004666      64$: MOV @RXDBUF, R1 ; ACTUAL
2579 012652 020001          CMP R0, R1 ; COMPARE EXPECTED VS. ACTUAL
2580 012654 001401          BEQ 65$
2581 012656 104002          HLT 2 ; RECEIVED DATA DID NOT MATCH
2582      ; EXPECTED DATA - CHECK MAINT DATA
2583      ; OR RECEIVER LOGIC
2584
2585 012660      65$: MOV #8, SHIFT ; # OF SHIFTS
2586 012660 012767 000010 166252      MOV #0, TEMP1 ; DATA CHAR
2587 012674 004767 004340          JSR PC, RPOKE ; SHIFT IN THIS CHAR
2588      ; NOW SHIFT IN A SECOND CHARACTER WITHOUT READING RXDBUF
2589 012700 012767 000010 166232      MOV #8, SHIFT ; # OF SHIFTS
2590 012706 012767 000000 166230      MOV #0, TEMP1 ; DATA CHAR
2591 012714 004767 004320          JSR PC, RPOKE ; SHIFT IN THIS CHAR
2592 012720 012700 140000          MOV #140000!0, R0 ; EXPECTED DATA PLUS
2593      ; RXERR & OVRUN
2594 012724 017701 004610          MOV @RXDBUF, R1 ; ACTUAL
2595 012730 020001          CMP R0, R1 ; COMPARE EXP VS. ACT
2596 012732 001401          BEQ 66$
2597 012734 104002          HLT 2 ; SPECIFICALLY LOOK AT RXERR &
2598      ; OVRUN BITS...THEY BOTH SHOULD BE SET
2599 012736      66$:
2600 012736 104400          SCOPE

```

```

2601
2602
2603      ;END OF PASS
2604      ;TYPE NAME OF TEST
2605      ;UPDATE PASS COUNT
2606      ;CHECK FOR EXIT TO ACT-11
2607      ;RESTART TEST
2608      012740 104402      .EOP:  TYPE
2609      012742 016102      MEPASS
2610      012744 104410 013176  CONVRT ,OUTCRY
2611      012750 104402 015623  TYPE ,DEVICE
2612      012754 105767 166222  TSTB MULTD
2613      012760 001511      BEQ CCC
2614      012762 005767 166230  TST ACTREG
2615      012766 001007      BNE RUNIT
2616      012770 104402 015635  TYPE ,MCOW
2617      012774 016700 166216  MOV ACTREG,RO
2618      013000 000000      HALT
2619      ;SELECT SWITCHES & HIT CONTINUE (PUT SW00 =1)
2620      013002 000167 166252  JMP .START
2621      013006 062767 000010 166170 RUNIT: ADD #10,BASEADD
2622      013014 062767 000010 166170 ZERO: ADD #10,BASEIV
2623      013022 000241      CLC
2624      013024 006167 166170  ROL ROTADD
2625      013030 103410      BCS 2$
2626
2627      013032 036767 166162 166156  BIT ROTADD,ACTREG
2628      013040 001762      BEQ RUNIT
2629      013042 004767 000034  JSR PC,REPLAY
2630      013046 000167 000174  JMP RESTRT
2631      013052 012767 000001 166140 2$: MOV #1,ROTADD
2632
2633      013060 016767 166122 166116  MOV KEEPADD,BASEADD
2634      013066 016767 166122 166116  MOV KEEPIV,BASEIV
2635      013074 004767 000002  JSR PC,REPLAY
2636      013100 000441      BR CCC
2637      013102 016767 166076 004126 REPLAY: MOV BASEADD,DUBASE
2638      013110 004767 003770  JSR PC,DUADDR
2639      013114 016767 166072 004436  MOV BASEIV,DURIV
2640      013122 062767 000002 166062  ADD #2,BASEIV
2641      013130 016767 166056 004424  MOV BASEIV,DURIS
2642      013136 062767 000002 166046  ADD #2,BASEIV
2643      013144 016767 166042 004412  MOV BASEIV,DUTIV
2644      013152 062767 000002 166032  ADD #2,BASEIV
2645      013160 016767 166026 004400  MOV BASEIV,DUTIS
2646      013166 016767 004366 166016  MOV DURIV,BASEIV
2647      013174 000207      RTS PC
2648
2649      013176 000001      OUTCRY: 1
2650      013200 006 002      .BYTE 6,2
2651      013202 017534      RXCSR
2652
2653      013204      CCC:
2654      013204 005067 165724  CLR LSTERR
2655      013210 005067 166010  CLR ERRFLG
2656      013214 005267 165710  INC PASCNT

```

M04

DZDUB-C MACY11 27(1006) 01-OCT-76 09:17 PAGE 54
 DZDUBC.P11 21-MAY-76 00:00

SEQ 0051

```

2657 013220 016777 165704 165654      MOV    PASCNT,ALIGHTS      ;DISPLAY PASS COUNT
2658 013226 013701 000042      MOV    A#42,R1          ;CHECK FOR ACT-11 OR DDP
2659 013232 001405              BEQ    RESTRT          ;IF NOT, CONTINUE TESTING
2660 013234 000005              RESET
2661 013236 004711              LOGICAL: JSR    PC,(R1)
2662 013240 000240              NOP
2663 013242 000240              NOP
2664 013244 000240              NOP
2665 013246 012767 000340 164522 RESTRT: MOV    #340,PS          ;PREVENT INTERRUPTS (PRIO: 7)
2666 013254 104413              CKSWR          ;CHECK FOR IG
2667 013256 012767 002350 165630      MOV    #TST1,RTRN
2668 013264 000167 167060      JMP     TST1
2669
2670                                ;SCOPE LOOP AND ITERATION HANDLER
2671
2672 013270      .SCOPE:
2673      ;**** START OF CODE FOR THE X OR TESTER ****
2674 013270 000424      BR      4$
2675
2676 013272 013746 000004              MOV    A#4,-(SP)          ;IF RUNNING ON THE X OR TESTER CHANGE
2677 013276 012737 013316 0000C4      MOV    #1$ ,A#4          ;THIS INSTRUCTION TO A "NOP"(NOP=240)
2678 013304 005737 177060              TST    A#177060          ;SAVE CONTENTS OF ERROR VECTOR
2679 013310 012637 000004              MOV    (SP)+,A#4          ;SET FOR TIME OUT
2680 013314 000404              BR      2$
2681 013316 022626              1$: CMP    (SP)+,(SP)+          ;TIME OUT ON X OR ?
2682 013320 012637 000004              MOV    (SP)+,A#4          ;RESTORE ERROR VECTOR
2683 013324 000403              BR      3$
2684 013326 016767 165564 165560 2$: MOV    NEXT,RTRN          ;GO TO NEXT TEST
2685 013334 016716 165554 3$: MOV    RTRN,(SP)          ;CLEAR THE STACK AFTER A TIMEOUT
2686 013340 000002              RTI          ;RESTORE ERROR VECTOR
2687 013342              4$:      ;**** END OF CODE FOR THE X OR TESTER ****
2688 013342 104413              CKSWR          ;CHECK FOR IG
2689 013344 032777 040000 165526      BIT     #SW14,ASWR          ;LOOP ON CURRENT TEST ?
2690 013352 001407              TTST: BEQ    1$
2691 013354 000432              BR      3$
2692 013356 105777 165522              TSTB   ATKCSR          ;TEST TTY FLAG
2693 013362 100027              BPL     3$
2694 013364 017700 165516              MOV    ATKDBR,RO          ;CLR DONE BIT
2695 013370 000412              BR      2$
2696 013372 032777 004000 165500 1$: BIT     #SW11,ASWR          ;IF A TTY KEY IS STRUCK GO TO NEXT TST
2697 013400 001006              BNE     2$
2698 013402 005267 165516              INC     LPCNT
2699 013406 026767 165512 165506      CMP     LPCNT,ICOUNT          ;CHECK FOR ITERATION CNT FINISH
2700 013414 101412              BLOS   3$
2701 013416 105067 165602 2$: CLRB   ERRFLG
2702 013422 005067 165476              CLR     LPCNT
2703 013426 012767 000005 165466      MOV    #5,ICOUNT          ;SET UP ITERATION COUNT
2704 013434 016767 165456 165452      MOV    NEXT,RTRN          ;SET UP NEXT TEST IN RTRN
2705 013442 016716 165446 3$: MOV    RTRN,(SP)          ;SET UP STACK FOR RTI
2706 013446 000002              RTI
2707 013450 001407      BRW:   1407          ;RESTORE "BEQ 1$" INSTRUCTION
2708 013452 000432      BRX:   432          ;RESTORE "BR 3$" INSTRUCTION
2709
2710                                ;CHECK FOR FREEZE ON CURRENT DATA
2711
2712 013454 104413      .SCOPE1: CKSWR          ;CHECK FOR IG

```

N04

DZDUB-C MACY11 27(1006) 01-OCT-76 09:17 PAGE 55
DZDUBC.P11 21-MAY-76 00:00

SEQ 0052

2713	013456	032777	001000	165414	B1T	#SW09, @SWR	
2714	013464	001402			BEQ	1\$	
2715	013466	016716	165426		MOV	LOCK, (SP)	
2716	013472	000002			RTI		
2717							
2718							
2719							
2720	013474	010546			.TYPE:	MOV	R5, -(SP)
2721	013476	017605	000002			MOV	@2(SP), R5
2722	013502	062766	000002	C00002		ADD	#2, 2(SP)
2723	013510	105715			1\$:	TSTB	(R5)
2724	013512	001406				BEQ	3\$
2725	013514	105777	165370		2\$:	TSTB	@TPCSR
2726	013520	100375				BPL	2\$
2727	013522	112577	165364			MOVB	(R5)+, @TPDBR
2728	013526	000770				BR	1\$
2729	013530	012605			3\$:	MOV	(SP)+, R5
2730	013532	000002				RTI	
2731							
2732							
2733							
2734	013534	010346			.INSTR:	MOV	R3, -(SP)
2735	013536	010446				MOV	R4, -(SP)
2736	013540	017667	000004	000010		MOV	@4(SP), MSG
2737	013546	062766	000002	000004		ADD	#2, 4(SP)
2738	013554	104402			.INST1:	TYPE	
2739	013556	000000			.MSG:	0	
2740	013560	012704	016670			MOV	#INBUF, R4
2741	013564	012703	000007			MOV	#7, R3
2742	013570	105777	165310		1\$:	TSTB	@TKCSR
2743	013574	100375				BPL	1\$
2744	013576	117714	165304			MOVB	@TKDBR, (R4)
2745	013602	142714	000200			BICB	#200, (R4)
2746	013606	121427	000025			CMPB	(R4), #25
2747	013612	001003				BNE	200\$
2748	013614	104402	016012			TYPE, MCRLF	
2749	013620	000755				BR	.INST1
2750	013622	122427	000015		200\$:	CMPB	(R4)+, #15
2751	013626	001423				BEQ	INSTR2
2752	013630	117777	165252	165254		MOVB	@TKDBR, @TPDBR
2753	013636	105777	165246		2\$:	TSTB	@TPCSR
2754	013642	100375				BPL	2\$
2755	013644	005303				DEC	R3
2756	013646	001350				BNE	1\$
2757	013650	000402				BR	.INSTG
2758	013652	010346			.INSTE:	MOV	R3, -(SP)
2759	013654	010446				MOV	R4, -(SP)
2760	013656	104402			.INSTG:	TYPE	
2761	013660	016006				MQM	
2762	013662	005737	015150			TST	@RDSW
2763	013666	001402				BEQ	400\$
2764	013670	104402	016012			TYPE, MCRLF	
2765	013674	000727			400\$:	BR	.INST1
2766	013676	012604			INSTR2:	MOV	(SP)+, R4
2767	013700	012603				MOV	(SP)+, R3
2768	013702	000002				RTI	

;LOOK FOR "0"

;TEST DONE BIT

;TYPE CHAR
;DO IT AGAIN UNTIL "0" IS SEEN

;IS IT <1U>

```

2769
2770
2771
2772
2773 013704 010546
2774 013706 010446
2775 013710 016605 000004
2776 013714 012567 000170
2777 013720 012567 000166
2778 013724 012567 000164
2779 013730 112567 000162
2780 013734 112567 000157
2781 013740 010566 000004
2782 013744 005005
2783 013746 012704 016670
2784 013752 122714 000015
2785 013756 001420
2786 013760 121427 000060
2787 013764 002415
2788 013766 121427 000067
2789 013772 003012
2790 013774 142714 000060
2791 014000 152405
2792 014002 122714 000015
2793 014006 001414
2794 014010 006305
2795 014012 006305
2796 014014 006305
2797 014016 000760
2798 014020 122714 000015
2799 014024 001003
2800 014026 005737 015150
2801 014032 001023
2802 014034 104404
2803 014036 000742
2804
2805
2806 014040 020567 000046
2807 014044 101365
2808 014046 020567 000036
2809 014052 103762
2810 014054 136705 000036
2811 014060 001357
2812
2813
2814
2815 014062 016704 000026
2816 014066 010524
2817 014070 062705 000002
2818 014074 105367 000017
2819 014100 001372
2820 014102 012604
2821 014104 012605
2822 014106 000002
2823 014110 000000
2824 014112 000000

;CONVERT ASCII STRING TO OCTAL

.PARAM: MOV R5, -(SP)
        MOV R4, -(SP)
        MOV 4(SP), R5
        MOV (R5)+, LOLIM
        MOV (R5)+, HILIM
        MOV (R5)+, DEVADR
        MOV (R5)+, LOBITS
        MOV (R5)+, ADCNT
        MOV PS, 4(SP)
PARAM1: CLR R5
        MOV #INBUF, R4
        CMPB #1, (R4)
        BEQ PARERR
1$: CMPB (R4), #60
        BLT PARERR
        CMPB (R4), #67
        BGT PARERR
        BICB #60, (R4)
        BISB (R4)+, R5
        CMPB #15, (R4)
        BEQ LIMITS
        ASL R5
        ASL R5
        ASL R5
        BR 1$
PARERR: CMPB #15, (R4)
        BNE 120$
        TST #RDSW
        BNE PARTI
120$: INSTER
        BR PARAM1

;IS FIRST CHARACTER A (CR)
;IS CKSWR ROUTINE BEING USED

;TEST TO SEE IF NUMBER IS WITHIN LIMITS
LIMITS: CMP R5, HILIM
        BHI PARERR
        CMP R5, LOLIM
        BLO PARERR
        BITB LOBITS, R5
        BNE PARERR

;STORE NUMBER AT SPECIFIED ADDRESS
1$: MOV DEVADR, R4
        MOV R5, (R4)+
        ADD #2, R5
        DECB ADCNT
        BNE 1$
PARTI: MOV (SP)+, R4
        MOV (SP)+, R5
        RTI
LOLIM: 0
HILIM: 0

```

```

2625 014114 000000          DEVADR: 0
2626 014116 000000          LOBITS: 0
2627          014117          ADRCNT=LOBITS+1
2628
2629          ;SAVE PC OF TEST THAT FAILED AND RD-R5
2630
2631 014120 016667 000004 165046 .SAV05: MOV      4(SP),SAVPC
2632
2633          ;SAVE RD-R5
2634
2635 014126 010567 165036      SV05:  MOV      R5,SAVR5
2636 014132 010467 165030      MOV      R4,SAVR4
2637 014136 010367 165022      MOV      R3,SAVR3
2638 014142 010267 165014      MOV      R2,SAVR2
2639 014146 010167 165006      MOV      R1,SAVR1
2640 014152 010067 165000      MOV      R0,SAVR0
2641 014156 000002          RTI
2642
2643          ;RESTORE RD-R5
2644
2645 014160 016700 164772      .RESC5: MOV      SAVR0,R0
2646 014164 016701 164770      MOV      SAVR1,R1
2647 014170 016702 164766      MOV      SAVR2,R2
2648 014174 016703 164764      MOV      SAVR3,R3
2649 014200 016704 164762      MOV      SAVR4,R4
2650 014204 016705 164760      MOV      SAVR5,R5
2651 014210 000002          RTI
2652
2653          ;CONVERT OCTAL NUMBER TO ASCII AND OUTPUT TO TELEPRINTER
2654
2655 014212 104402      .CONVR: TYPE
2656 014214 016012      MCRLF
2657 014216 010046      .CNVRT: MOV      R0,-(SP)
2658 014220 010146      MOV      R1,-(SP)
2659 014222 010346      MOV      R3,-(SP)
2660 014224 010446      MOV      R4,-(SP)
2661 014226 010546      MOV      R5,-(SP)
2662 014230 017601 000012      MOV      212(SP),R1
2663 014234 016767 002470 164706      MOV      TEMP,TEMP3
2664 014242 062766 000002 000012      ADD      #2,12(SP)
2665 014250 012167 000154      MOV      (R1)+,WRDCNT
2666 014254 112167 000152      15:  MOV8    (R1)+,CHRCNT
2667 014260 112167 000147      MOV8    (R1)+,SPACNT
2668 014264 013167 000144      MOV      2(R1)+,BINWRD
2669 014270 016704 000140      25:  MOV      BINWRD,R4
2670 014274 116705 000132      MOV8    CHRCNT,R5
2671 014300 012700 016730      MOV      #TEMP,R0
2672 014304 010403      35:  MOV      R4,R3
2673 014306 042703 177770      BIC      #177770,R3
2674 014312 062703 000060      ADD      #060,R3
2675 014316 110320      MOV8    R3,(R0)+
2676 014320 006204      ASR      R4
2677 014322 042704 100000      BIC      #100000,R4
2678 014326 006204      ASR      R4
2679 014330 006204      ASR      R4
2680 014332 005305      DEC      R5

```

```

;SHIFT FOR NEXT #
;CLUGE TO STOP BIT 15 PROPAGATING.
;DITTO
;DITTO

```

2881	014334	001363			BNE	35	
2882	014336	012703	016770		MOV	#DATA, R3	
2883	014342	114023		45:	MOV	-(R0), (R3)+	
2884	014344	105367	000062		DECB	CHRCNT	
2885	014350	001374			BNE	45	
2886	014352	105767	000055		TSTB	SPACNT	
2887	014356	001405			SEQ	65	
2888	014360	112723	000040	55:	MOV	#040, (R3)+	
2889	014364	105357	000043		DECB	SPACNT	
2890	014370	001373			BNE	55	
2891	014372	105013		65:	CLRB	(R3)	
2892	014374	104402			TYPE		
2893	014376	016770			#DATA		
2894	014400	005367	000024		DEC	WRDCNT	
2895	014404	001323			BNE	15	
2896	014406	016767	164536 002314		MOV	TEMP3, TEMP	
2897	014414	012605			MOV	(SP)+, R5	
2898	014416	012604			MOV	(SP)+, R4	
2899	014420	012603			MOV	(SP)+, R3	
2900	014422	012601			MOV	(SP)+, R1	
2901	014424	012600			MOV	(SP)+, R0	
2902	014426	000002			RTI		
2903	014430	000000			WRDCNT:	0	
2904	014432	000000			CHRCNT:	0	
2905		014433			SPACNT=CHRCNT+1		
2906	014434	000000			BINWRD:	0	
2907							
2908							
2909							
2910							
2911							
2912							
2913	014436	017605	000000		.SETFLG: MOV	2(SP), R5	
2914	014442	122767	000116 002220		CMPB	#'N, INBUF	; IS IT "N" ?
2915	014450	001002			BNE	15	
2916	014452	105015			CLRB	(R5)	; 000
2917	014454	000406			BR	25	
2918	014456	122767	000131 002204	15:	CMPB	#'Y, INBUF	; IS IT "Y" ?
2919	014464	001005			BNE	35	
2920	014466	112715	177777		MOV	#-1, (R5)	; 377
2921	014472	062716	000002	25:	ADD	#2, (SP)	
2922	014476	000002			RTI		
2923	014500	104404		35:	INSTR		; RETRY
2924	014502	000755			BR	.SETFLG	
2925							
2926							
2927							
2928							
2929							
2930	014504	011646		.TRPSR:	MOV	(SP), -(SP)	; GET PC OF RETURN
2931	014506	162716	000002		SUB	#2, (SP)	; =PC OF TRAP
2932	014512	017616	000000		MOV	2(SP), (SP)	; GET TRP
2933	014516	000316		TRPOK:	ASL	(SP)	; MULTIPLY TRAP ARG BY 2
2934	014520	042716	177001		BIC	#177001, (SP)	; CLEAR UNWANTED BITS
2935	014524	062716	001226		ADD	#.TRPTAB, (SP)	; POINTER TO SUBROUTINE ADDRESS
2936	014530	017616	000000		MOV	2(SP), (SP)	; SUBROUTINE ADDRESS

```

2937 014534 000136          JMP      2(SP)+          ;GO TO SUBROUTINE
2938
2939          ;ERROR HANDLER
2940
2941 014536 104413          .HLT:  CKSWR          ;CHECK FOR IG
2942 014540 032777 020000 164332  BIT      #SW13,2SWR          ;INHIBIT ERROR TYPE OUT ?
2943 014546 001061          BNE      HALTS
2944 014550 021667 164360          CMP      (SP),LSTERR
2945 014554 001404          BEQ      1$
2946 014556 011667 164352          MOV      (SP),LSTERR
2947 014562 105067 164436          CLR     ERRFLG
2948 014566 104406          1$:  SAVOS
2949 014570 011605          MOV      (SP),R5
2950 014572 162705 000002          SUB      #2,R5
2951 014576 011504          MOV      (R5),R4
2952 014600 006304          ASL      R4
2953 014602 061504          ADD      (R5),R4
2954 014604 006304          ASL      R4
2955 014606 042704 177001          BIC      #177001,R4
2956 014612 062704 017504          ADD      #.ERRTAB,R4
2957 014616 012467 000040          MOV      (R4)+,ERRMSG
2958 014622 012467 000046          MOV      (R4)+,DATAHD
2959 014626 011467 000054          MOV      (R4),DATABP
2960 014632 105767 164366          TSTB    ERRFLG
2961 014636 001403          BEQ      TYPMSG
2962 014640 005767 000042          TST     DATABP
2963 014644 001014          BNE      TYPDAT
2964 014646 104410          TYPMSG: CONVRT
2965 014650 015000          ERTAB0
2966 014652 112767 177777 164344  MOVB    #-1,ERRFLG
2967 014660 104402          TYPE
2968 014662 000000          ERRMSG: 0
2969 014664 005767 000004          TST     DATAHD
2970 014670 001402          BEQ      TYPDAT
2971 014672 104402          TYPE
2972 014674 000000          DATAHD: 0
2973 014676 005767 000004          TYPDAT: TST     DATABP
2974 014702 001402          BEQ      RESREG
2975 014704 104410          CONVRT
2976 014706 000000          DATABP: 0
2977 014710 104407          RESREG: RESOS
2978 014712 005777 164162          HALTS:  TST     2SWR
2979 014716 100005          BPL      EXITER
2980 014720 010046          PUSHRO
2981 014722 016600 000002          MOV      2(SP),R0
2982 014726 000000          HALT
2983 014730 012600          POPRO
2984 014732 104413          EXITER: CKSWR          ;CHECK FOR IG
2985 014734 005267 164172          INC      ERRCNT
2986 014740 032777 000400 164132  BIT      #SW08,2SWR          ;LOOP ON ERROR ?
2987 014746 001007          BNE      1$
2988 014750 032777 002000 164122  BIT      #SW10,2SWR          ;ESCAPE TO NEXT ON ERROR ?
2989 014756 001407          BEQ      2$
2990 014760 016767 164132 164126  MOV      NEXT,RTRN          ;SET UP FOR NEXT TEST
2991 014766 012706 001100          1$:  MOV      #STACK,SP          ;REINITIALIZE SP
2992 014772 000177 164116          JMP      2RTN

```

```

2993 014776 000002      25: R11
2994 015000 000001      ERTAB0: 1
2995 015002 006        .BYTE 6,2
2996 015004 001174      SAVPC
2997                                     ;ENTER HERE ON POWER FAILURE
2998
2999
3000 015006 010046      .PFAIL: MOV R0,-(SP) ;SAVE R0-R5 ON PROCESSOR STACK
3001 015010 010146      MOV R1,-(SP)
3002 015012 010246      MOV R2,-(SP)
3003 015014 010346      MOV R3,-(SP)
3004 015016 010446      MOV R4,-(SP)
3005 015020 010546      MOV R5,-(SP)
3006 015022 016746 162776 MOV 24,-(SP)
3007 015026 010667 164140 MOV SP,SAVSP ;SAVE STACK POINTER
3008 015032 012767 015044 162764 MOV #RESTART,24 ;SET UP FOR POWER UP TRAP
3009 015040 000000      HALT ;HALT ON POWER DOWN NORMAL
3010 015042 000777      15: BR 15
3011
3012                                     ;PROCESSOR WILL TRAP HERE WHEN POWER IS RESTORED
3013
3014 015044 016706 164122 RESTAR: MOV SAVSP,SP ;RESTORE STACK POINTER
3015 015050 012605      MOV (SP)+,R5 ;RESTORE R0-R5
3016 015052 012604      MOV (SP)+,R4
3017 015054 012603      MOV (SP)+,R3
3018 015056 012602      MOV (SP)+,R2
3019 015060 012601      MOV (SP)+,R1
3020 015062 012600      MOV (SP)+,R0
3021 015064 012767 015006 162732 MOV #.PFAIL,24 ;SET UP FOR POWER FAILURE
3022 015072 012767 000340 162676 MOV #340,PS
3023 015100 012706 001100 MOV #STACK,SP
3024 015104 005067 001620 CLR TEMP
3025 015110 005267 001614 15: INC TEMP
3026 015114 001375      BNE 15
3027 015116 104410      CONVRT
3028 015120 015142      PFTAB
3029 015122 104402      TYPE
3030 015124 016015      MPFAIL
3031 015126 005067 164072 CLR ERRFLG
3032 015132 005067 163776 CLR LSTERR
3033 015136 000177 163752 JMP JRTN
3034 015142 000001      PFTAB: 1
3035 015144 006        .BYTE 6,2
3036 015146 001114      RTRN
3037
3038
3039                                     ;CHECK SWITCH REGISTER ROUTINE. CHECKS FOR 1G TO ALLOW CHANGING
3040                                     ;OF LOC.176.
3041                                     ;LOCATIONS USED:
3042 015150 000000      RDSW: .WORD 0
3043
3044
3045 015152 005737 000042 .CKSWR: TST #42
3046 015156 001042      BNE OUT
3047 015160 022767 000176 163712 CMP #SWREG,SWR ;SOFTWARE SWITCH REGISTER PRESENT
3048 015166 001036      BNE OUT ;NO, GET OUT

```

G05

DZDUB-C MACY11 27(1006) 01-OCT-76 09:17 PAGE 61
DZDUBC.P11 21-MAY-76 00:00

SEQ 0058

3049	015170	105777	163710		TSTB	2TKCSR		: ES WAIT FOR
3050	015174	100033			BPL	OUT		: READY GET CHARACTER
3051	015175	017767	163704	176352	MOV	2TKDBR, .MSG		: AND STRIP OFF
3052	015204	042767	177600	176344	BIC	#177600, .MSG		: THE GARBAGE
3053	015212	122767	000007	176336	CMPB	#7, .MSG		: IS IT A (TG)
3054	015220	001021			BNE	OUT		
3055	015222	104402	015300		TYPE, SCNTG			
3056	015226	005137	015150		.CNTLU: COM	2#RDSW		
3057	015232	104402	015305		TYPE, SMSWR			
3058	015236	104411	015272		CNVRT, SWREGC			
3059	015242	104403	015315		INST, SMNEW			
3060	015246	104405			PARAM			
3061	015250	000000			0			
3062	015252	177777			177777			
3063	015254	000176			SWREG			
3064	015256	000	001		.BYTE	0, 1		
3065	015260	104402	016012		TYPE, MCRLF			
3066	015264	005037	015150		OUT: CLR	2#RDSW		
3067	015270	000002			RTI			
3068	015272	000001			SWREGC: 1			
3069	015274	006	002		.BYTE	6, 2		
3070	015276	000176			SWREG			
3071	015300	005015	043536	000	CNTG: .ASCIZ	<15><12>/TG/		
3072	015305	015	051412	051127	SMSWR: .ASCIZ	<15><12>/SWR= /		
3073	015312	020075	000					
3074	015315	040	047040	053505	SMNEW: .ASCIZ	/ NEW= /		
3075	015322	020075	000					
3076	015326	005015	042012	030525	.EVEN			
3077	015326	005015	042012	030525	MTITLE: .ASCIZ	<15><12><12>/DU11 DZDUB-C TAPE 8 /<15><12>		
3078	015334	020061	055104	052504				
3079	015342	026502	020103	040524				
3080	015350	042520	041040	006440				
3081	015356	000012						
3082	015360	005015	042526	052103	MVECTO: .ASCIZ	<15><12>/VECTOR ADDRESS-/		
3083	015366	051117	040440	042104				
3084	015374	042522	051523	000055				
3085	015402	005015	05146	020124	MREGAD: .ASCIZ	<15><12>/1ST DEVICE: RECEIVER CONTROL REGISTER ADDRESS-/		
3086	015410	042504	044526	042503				
3087	015416	020072	042522	042503				
3088	015424	053111	051105	041440				
3089	015432	047117	051124	046117				
3090	015440	051040	043505	051511				
3091	015446	042524	020122	042101				
3092	015454	051104	051505	026523				
3093	015462	000						
3094	015463	015	040412	042522	MMULT: .ASCIZ	<15><12>/ARE YOU RUNNING MULTIPLE DEVICES ? (Y OR N)-/		
3095	015470	054440	052517	051040				
3096	015476	047125	044516	043516				
3097	015504	046440	046125	044524				
3098	015512	046120	020105	042504				
3099	015520	044526	042503	020123				
3100	015526	020077	054450	047440				
3101	015534	020122	024516	000055				
3102	015542	005015	040514	052123	MLASTD: .ASCIZ	<15><12>/LAST DEVICE: RECEIVER CONTROL REGISTER ADDRESS-/		
3103	015550	042040	053105	041511				
3104	015556	035105	042522	042503				

3105	015564	053111	051105	041440	
3106	015572	047117	051124	046117	
3107	015600	051040	043505	051511	
3108	015606	042524	020122	042101	
3109	015614	051104	051505	026523	
3110	015622	000			
3111	015623	075	042504	044526	DEVICE: .ASCIZ /=DEVICE /
3112	015630	042503	020040	000	
3113	015635	015	044012	053517	MCOW: .ASCIZ <15><12>/HOW NOW BROWN COW? ...SELECT SOMETHING TO RUN JACTREG/
3114	015642	047040	053517	041040	
3115	015650	047522	047127	041440	
3116	015656	053517	020077	027056	
3117	015664	051456	046105	041505	
3118	015672	020124	047523	042515	
3119	015700	044124	047111	020107	
3120	015706	047524	051040	047125	
3121	015714	040040	041501	051124	
3122	015722	043505	000		
3123	015725	015	047412	052125	MRANGE: .ASCIZ <15><12>/OUT OF RANGE:RETYPE LAST DEVICE RXCSR ADDRESS-/
3124	015732	047440	020106	040522	
3125	015740	043516	035105	042522	
3126	015746	054524	042520	046040	
3127	015754	051501	020124	042504	
3128	015762	044526	042503	051040	
3129	015770	041530	051123	040440	
3130	015776	042104	042522	051523	
3131	016004	000055			
3132	016006	020040	000077		MQM: .ASCIZ / ?/
3133	016012	005015	000		MCRLF: .ASCIZ <15><12>
3134	016015	040	050040	053517	MPFAIL: .ASCIZ / POWER FAILURE, PROGRAM RESTART AT TEST IN PROGRESS/
3135	016022	051105	043040	044501	
3136	016030	052514	042522	020054	
3137	016036	051120	043517	040522	
3138	016044	020115	042522	052123	
3139	016052	051101	020124	052101	
3140	016060	052040	051505	020124	
3141	016066	047111	050040	047522	
3142	016074	051107	051505	000123	
3143	016102	005015	047105	020104	MEPASS: .ASCIZ <15><12>/END OF PASS TAPE B/
3144	016110	043117	050040	051501	
3145	016116	020123	040524	042520	
3146	016124	041040	000		
3147	016127	015	051012	000	MR: .ASCIZ <15><12>/R/
3148	016133	015	052012	051505	MTSTPC: .ASCIZ <15><12>/TEST PC-/
3149	016140	020124	041520	000055	
3150	016146	005015	047514	045503	MLOCK: .ASCIZ <15><12>/LOCK ON SELECTED TEST? (Y OR N)-/
3151	016154	047440	020116	042523	
3152	016162	042514	052103	042105	
3153	016170	052040	051505	037524	
3154	016176	024040	020131	051117	
3155	016204	047040	026451	000	
3156	016211	015	042012	020125	MLEVEL: .ASCIZ <15><12>/DU PRIORITY LEVEL-/
3157	016216	051120	047511	044522	
3158	016224	054524	046040	053105	
3159	016232	046105	000055		
3160	016236	005015	020043	043117	MSYNC: .ASCIZ <15><12>/# OF SYNC CHARS SELECTED (1 OR 2)-/

DZDUB-C MACY11 27(1006) 01-OCT-76 09:17 PAGE 63
 DZDUBC.P11 21-MAY-76 00:00

SEQ 0060

3161	016244	051440	047131	020103	
3162	016252	044103	051101	020123	
3163	016260	042523	042514	052103	
3164	016266	042105	024040	030440	
3165	016274	047440	020122	024462	
3166	016302	000055			
3167	016304	005015	051511	051440	MWIRE6: .ASCIZ <15><12>/IS SEC XMIT JUMPER #6 IN? (Y OR N)-/
3168	016312	041505	054040	044515	
3169	016320	020124	052512	050115	
3170	016326	051105	021440	020066	
3171	016334	047111	020077	054450	
3172	016342	047440	020122	024516	
3173	016350	000055			
3174	016352	005015	051511	051440	MWIRE5: .ASCIZ <15><12>/IS SEC REC JUMPER #5 IN? (Y OR N)-/
3175	016360	041505	051040	041505	
3176	016366	045040	046525	042520	
3177	016374	020122	032443	044440	
3178	016402	037516	024040	020131	
3179	016410	051117	047040	026451	
3180	016416	000			
3181	016417	015	044412	020123	MWIRE4: .ASCIZ <15><12>/IS OPT CLR ENABLE JUMPER #4 IN? (Y OR N)-/
3182	016424	050117	020124	046103	
3183	016432	020122	047105	041101	
3184	016440	042514	045040	046525	
3185	016446	042520	020122	032043	
3186	016454	044440	037516	024040	
3187	016462	020131	051117	047040	
3188	016470	026451	000		
3189	016473	015	040412	042522	MEXTJ: .ASCII <15><12>/ARE YOU RUNNING IN MAINT MODE EXTERNAL?/
3190	016500	054440	052517	051040	
3191	016506	047125	044516	043516	
3192	016514	044440	020116	040515	
3193	016522	047111	020124	047515	
3194	016530	042504	042440	052130	
3195	016536	051105	040516	037514	
3196	016544	005015	040401	042116	.ASCII <15><12><1>/AND DO YOU HAVE THE EXTERNAL MODEM BYPASS/
3197	016552	027040	027056	027056	
3198	016560	042040	020117	047531	
3199	016566	020125	040510	042526	
3200	016574	052040	042510	042440	
3201	016602	052130	051105	040516	
3202	016610	020114	047515	042504	
3203	016616	020115	054502	040520	
3204	016624	051523			
3205	016626	005015	045001	046525	.ASCIZ <15><12><1>/JUMPER CONNECTOR ON ?(Y OR N)-/
3206	016634	042520	020122	047503	
3207	016642	047116	041505	047524	
3208	016650	020122	047117	037440	
3209	016656	054450	047440	020122	
3210	016664	024516	000055		
3211					.EVEN
3212					
3213					;BUFFERS FOR INPUT-OUTPUT
3214					
3215	016670	000040			INBUF: .BLKB 40
3216	016730	000040			TEMP: .BLKB 40

```

3217 016770 000040      MDATA: .BLKB 40
3218                      ;*****
3219                      ;UTILITIES
3220                      ;*****
3221
3222                      ;THIS UTILITY CALCULATES PRIORITY LEVEL
3223 017030 006367 000044  DULEV: ASL      DUPRT      ;SHIFT LEFT
3224 017034 006367 000040      ASL      DUPRT
3225 017040 006367 000034      ASL      DUPRT
3226 017044 006367 000030      ASL      DUPRT
3227 017050 006367 000024      ASL      DUPRT
3228 017054 016767 000020 000020 MOV      DUPRT,LESS1 ;MOVE THIS TO LESS1
3229 017062 162767 000001 000012 SUB      #1,LESS1 ;CREATE LESS1
3230 017070 042767 000037 000004 BIC      #37,LESS1 ;CLEAR TNZVC
3231 017076 000207      PTS      PC
3232 017100 000240      DUPRT: LEVEL5
3233 017102 000200      LESS1: LEVEL4 ;LEVEL TO ALLOW INTERRUPTS
3234
3235                      ;NEW DU ADDRESSES
3236 017104 016767 000126 000422 DUADDR: MOV      DUBASE,RXCSR ;XXX0
3237 017112 005267 000120      INC      DUBASE
3238 017116 016767 000114 000412 MOV      DUBASE,HRXCSR ;XXX1
3239 017124 005267 000106      INC      DUBASE
3240 017130 016767 000102 000402 MOV      DUBASE,RXDBUF ;XXX2
3241 017136 016767 000074 000400 MOV      DUBASE,PARCSR ;XXX2
3242 017144 005267 000066      INC      DUBASE
3243 017150 016767 000062 000364 MOV      DUBASE,HRXDBUF ;XXX3
3244 017156 016767 000054 000362 MOV      DUBASE,HPARCSR ;XXX3
3245 017164 005267 000046      INC      DUBASE
3246 017170 016767 000042 000352 MOV      DUBASE,TXCSR ;XXX4
3247 017176 005267 000034      INC      DUBASE
3248 017202 016767 000030 000342 MOV      DUBASE,HTXCSR ;XXX5
3249 017210 005267 000022      INC      DUBASE
3250 017214 016767 000016 000332 MOV      DUBASE,TXDBUF ;XXX6
3251 017222 005267 000010      INC      DUBASE
3252 017226 016767 000004 000322 MOV      DUBASE,HTXDBUF ;XXX7
3253 017234 000207      RTS      PC
3254 017236 000000      DUBASE: 0
3255
3256                      ;THIS UTILITY POKES THE MAINT DATA BASED UPON THE
3257                      ;INFORMATION CONTAINED IN TEMP1 AND IT IS
3258                      ;SHIFTED IN BY THE CONTENTS OF SHIFT
3259 017240 042777 040000 000302 RPOKE: BIC      #MTDATA,HTXCSR
3260 017246 005067 161674      CLR      TEMP2
3261 017252 006067 161666      ROR      TEMP1 ;FORCE CARRY
3262 017256 006067 161664      ROR      TEMP2 ;PICK UP CARRY IN BIT 15
3263 017262 006267 161660      ASR      TEMP2 ;SHIFT INTO BIT 14
3264 017266 042767 100000 161652 BIC      #BIT15,TEMP2 ;CLR BIT 15
3265 017274 056777 161646 000246 BIS      TEMP2,HTXCSR ;POKE MAINT DATA
3266 017302 042777 020000 000240 BIC      #CLK,HTXCSR ;POKE CLK
3267 017310 052777 020000 000232 BIS      #CLK,HTXCSR
3268 017316 005367 161616      DEC      SHIFT
3269 017322 001346      BNE      RPOKE
3270 017324 000207      RTS      PC
3271
3272 017326 016767 161612 161612 ODD8:  ;THIS ROUTINE CALCULATES ODD PARITY FOR AN 8 BIT CHAR
      MOV      TEMP1,TEMP2 ;SAVE TEMP1

```

K05

DZDUB-C MACY11 27(1006) 31-OCT-76 09:17 PAGE 65
 DZDUBC.P11 21-MAY-76 00:00

SEQ 0062

```

3273 017334 005067 161610 CLR TEMP3
3274 017340 012727 000010 MOV #8.,(PC)+
3275 017344 000000 4$: 0
3276 017346 006067 161574 1$: ROR TEMP2
3277 017352 005567 161572 ADC TEMP3
3278 017356 005367 177762 DEC 4$
3279 017362 001371 BNE 1$
3280 017364 006067 161560 ROR TEMP3
3281 017370 103404 BCS 2$
3282 017372 052767 000400 161544 BIS #BIT8,TEMP1 ;SET ODD PARITY
3283 017400 000403 BR 3$
3284 017402 042767 000400 161534 2$: BIC #BIT8,TEMP1 ;CLR EVEN PARITY
3285 :TEMP1 NOW HAS ODD PARITY CHARACTER
3286 017410 000207 3$: RTS PC
3287
3288 :THIS ROUTINE CALCULATES EVEN PARITY FOR AN 8 BIT CHARACTER
3289 017412 016767 161526 161526 EVEN8: MOV TEMP1,TEMP2 ;SAVE TEMP1
3290 017420 005067 161524 CLR TEMP3
3291 017424 012727 000010 MOV #8.,(PC)+
3292 017430 000000 4$: 0
3293 017432 006067 161510 1$: ROR TEMP2
3294 017436 005567 161506 ADC TEMP3
3295 017442 005367 177762 DEC 4$
3296 017446 001371 BNE 1$
3297 017450 006067 161474 ROR TEMP3
3298 017454 103004 BCC 2$
3299 017456 052767 000400 161460 BIS #BIT8,TEMP1 ;SET EVEN PARITY
3300 017464 000403 BR 3$
3301 017466 042767 000400 161450 2$: BIC #BIT8,TEMP1 ;CLR ODD PARITY
3302 :TEMP1 NOW HAS EVEN PARITY CHARACTER
3303 017474 000207 3$: RTS PC
3304
3305 017476 062716 000002 TRPREG: ADD #2,(SP) ;ALLOW IT TO "CRUNCH" INTO HLT BACK
3306 ;IN MAIN PART OF THE PROGRAM
3307 017502 000002 RTI
3308 ;ERROR HLT TABLE
3309 017504 017570 .ERRTAB: EMO ;HLT 0 BIT ERROR (GENERAL)
3310 017506 000000 0
3311 017510 000000 0
3312 017512 017604 EM1 ;HLT 1 REGISTER ERROR
3313 017514 017755 DH1
3314 017516 017776 DT1
3315 017520 017646 EM2 ;HLT 2 RECEIVER ERROR
3316 017522 017755 DH1
3317 017524 017776 DT1
3318 017526 017710 EM3 ;HLT 3 TRANSMITTER ERROR
3319 017530 017755 DH1
3320 017532 017776 DT1
3321 :DEFAULT DU ADDRESSES
3322 017534 160040 RXCSR: 160040
3323 017536 160041 HRXCSR: 160041
3324 017540 160042 RXDBUF: 160042
3325 017542 160043 HRXDBUF: 160043
3326 017544 160042 PARCSR: 160042
3327 017546 160043 HPARCSR: 160043
3328 017550 160044 TXCSR: 160044

```

3329	017552	160045			HTXCSR: 160045
3330	017554	160046			TXDBUF: 160046
3331	017553	160047			HTXDBUF: 160047
3332					:DEFAULT DU VECTORS
3333	017560	000770			DURIV: 770 ;REC INTR VECTOR
3334	017562	000772			DURIS: 772 ;REC INTR STATUS
3335	017564	000774			DUTIV: 774 ;XMIT INTR VECTOR
3336	017566	000776			DUTIS: 776 ;XMIT INTR STATUS
3337					:ERROR MESSAGES
3338	017570	036440	042440	051122	EM0: .ASCIZ / = ERROR PC/
3339	017576	051117	050040	000103	
3340	017604	036440	051040	043505	EM1: .ASCIZ / = REGISTER ERROR PC/<15><12><1>/REGISTER /
3341	017612	051511	042524	020122	
3342	017620	051105	047522	020122	
3343	017626	041520	005015	051001	
3344	017634	043505	051511	042524	
3345	017642	020122	000040		
3346	017646	036440	051040	041505	EM2: .ASCIZ / = RECEIVER ERROR PC/<15><12><1>/REGISTER /
3347	017654	044505	042526	020122	
3348	017662	051105	047522	020122	
3349	017670	041520	005015	051001	
3350	017676	043505	051511	042524	
3351	017704	020122	000040		
3352	017710	036440	052040	040522	EM3: .ASCIZ / = TRANSMITTER ERROR PC/<15><12><1>/REGISTER /
3353	017716	051516	044515	052124	
3354	017724	051105	042440	051122	
3355	017732	051117	050040	006503	
3356	017740	000412	042522	044507	
3357	017746	052123	051105	020040	
3358	017754	000			
3359					:DATA HEADERS FOR ERROR MESSAGES
3360	017755	105	050130	041505	DH1: .ASCIZ /EXPECTED ACTUAL/
3361	017762	042524	020104	040440	
3362	017770	052103	040525	000114	
3363					.EVEN
3364					:DATA TABLES FOR ERROR MESSAGES
3365	017776	000003			DT1: 3
3366	020000	006	004		.BYTE 6,4
3367	020002	001164			SAVR3 :REGISTER
3368	020004	006	004		.BYTE 6,4
3369	020006	001156			SAVR0 :EXPECTED DATA
3370	020010	006	002		.BYTE 6,2
3371	020012	001160			SAVR1 :ACTUAL DATA
3372		000001			.END

DZDUB-C MACY11 27(1006) 31-OCT-76 09:17 PAGE 69

DZDUBC.P11 21-MAY-76 00:00

CROSS REFERENCE TABLE -- USER SYMBOLS

SEO 0065

[illegible]

DZDUB-C MACY11 27(1506) 31-OCT-76 09:17 PAGE 71
DZDUBC.P11 21-MAY-76 00:00 CROSS REFERENCE TABLE -- USER SYMBOLS

JNCE	001362	941	844#											
OPTCLR	001201	761#	979											
OUT	015264	3046	3048	3050	3054	3066#								
OUTCRY	013176	2610	2649#											
OUTMUL	002024	904	929	940#										
JVRRUN=	040000	661#												
PARAM =	104405	802#	876	887	908	933	943	1014	3060					
PARAM1	013744	2781#	2802											
PARCSR	017544	1036#	1043#	1094#	1101#	1152#	1159#	1210#	1217#	1268#	1275#	1326#	1333#	1384#
		1391#	1442#	1449#	1500#	1507#	1558#	1565#	1616#	1623#	1674#	1681#	1732#	1739#
		1787#	1794#	1842#	1849#	1897#	1904#	1952#	1959#	2007#	2014#	2062#	2069#	2117#
		2124#	2172#	2179#	2227#	2234#	2282#	2289#	2337#	2344#	2392#	2399#	2447#	2454#
		2502#	2509#	2557#	2564#	3241#	3326#							
PAREN =	001000	665#												
PARER =	010000	663#												
PARERR	014020	2784	2786	2788	2797#	2807	2809	2811						
PAPTI	014102	2800	2820#											
PASCHT	001130	735#	833#	2656#	2657									
PFTAB	015142	3028	3034#											
POPR0 =	012600	609#	2983											
POP1SP=	005726	607#												
POP2SP=	022626	611#												
PS =	177776	601#	828#	987#	2665#	3022#								
PUSHRO=	010046	608#	2980											
PUSH1S=	005746	606#												
PUSH2S=	024646	610#												
RDSM	015150	2762	2799	3042#	3056#	3066#								
REACT=	004000	647#												
REPLAY	013102	2629	2635	2637#										
RESREG	014710	2974	2977#											
RESTAR	015044	3008	3014#											
RESTRT	013246	2630	2659	2665#										
RESOS =	104407	806#	2977											
RIN=	040000	644#												
RINTEN=	000100	652#												
ROTAD0	001220	775#	903#	915#	917	919#	924	927#	2624#	2627	2631#			
RP0KE	017240	1055	1069	1073	1113	1127	1131	1171	1185	1189	1229	1243	1247	1287
		1301	1305	1345	1359	1363	1403	1417	1421	1461	1475	1479	1519	1533
		1537	1577	1591	1595	1635	1649	1653	1693	1707	1711	1748	1762	1766
		1803	1817	1821	1858	1872	1876	1913	1927	1931	1968	1982	1986	2023
		2037	2041	2078	2092	2096	2133	2147	2151	2188	2202	2206	2243	2257
		22												

[illegible]

DZDUB-C MACY11 27(1006) 31-OCT-76 09:17 PAGE 73
DZDUBC.P11 21-MAY-76 00:00 CROSS REFERENCE TABLE -- USER SYMBOLS

[illegible]

DZDUB-C MACY11 27(1006) 31-OCT-76 09:17 PAGE 74
DZDUBC.P11 21-MAY-76 00:00 CROSS REFERENCE TABLE -- USER SYMBOLS

TST25	011610	2335	2389#											
TST26	012036	2390	2444#											
TST27	012264	2445	2499#											
TST28	012512	2500	2554#	2602										
TST29	= ***** U	2555												
TST3	003054	1092	1149#											
TST4	003316	1150	1207#											
TST5	003560	1208	1265#											
TST6	004022	1266	1323#											
TST7	004264	1324	1381#											
TST8	004526	1382	1439#											
TST9	004770	1440	1497#											
TTST	013352	994#	995#	1005#	1006#	1008#	1009#	2690#						
TXCSR	017550	1035#	1037#	1040#	1046#	1047#	1049#	1050#	1093#	1095#	1098#	1104#	1105#	1107#
		1108#	1151#	1153#	1156#	1162#	1163#	1165#	1166#	1209#	1211#	1214#	1220#	1221#
		1223#	1224#	1267#	1269#	1272#	1278#	1279#	1281#	1282#	1325#	1327#	1330#	1336#
		1337#	1339#	1340#	1383#	1385#	1388#	1394#	1395#	1397#	1398#	1441#	1443#	1446#
		1452#	1453#	1455#	1456#	1499#	1501#	1504#	1510#	1511#	1513#	1514#	1557#	1559#
		1562#	1568#	1569#	1571#	1572#	1615#	1617#	1620#	1626#	1627#	1629#	1630#	1673#
		1675#	1678#	1684#	1685#	1687#	1688#	1731#	1733#	1736#	1742#	1743#	1786#	1788#
		1791#	1797#	1798#	1841#	1843#	1846#	1852#	1853#	1896#	1898#	1901#	1907#	1908#
		1951#	1953#	1956#	1962#	1963#	2006#	2008#	2011#	2017#	2018#	2061#	2063#	2066#
		2072#	2073#	2116#	2118#	2121#	2127#	2128#	2171#	2173#	2176#	2182#	2183#	2226#
		2228#	2231#	2237#	2238#	2281#	2283#	2286#	2292#	2293#	2336#	2338#	2341#	2347#
		2348#	2391#	2393#	2396#	2402#	2403#	2446#	2448#	2451#	2457#	2458#	2501#	2503#
		2506#	2512#	2513#	2556#	2558#	2561#	2567#	2568#	3246#	3259#	3265#	3266#	3267#
		3328#												
TXDBUF	017554	3250#	3330#											
TXDONE=	000200	684#												
TXINTE=	000100	685#												
TYPDAT	014676	2963	2970	2973#										
TYPE =	104402	796#	842	1022	2608	2611	2616	2738	2748	2760	2764	2855	2892	2967
		2971	3029	3055	3057	3065								
TYPMMSG	014646	2961	2964#											
USER =	000050	691#												
VOID =	000001	658#												
MRDCNT	014430	2865#	2894#	2903#										
ZERO	013014	2622#												
SCNTG	015300	3055	3071#											

G06

DZDUB-C MACY11 27(1006) 01-OCT-76 09:17 PAGE 75

DZDUBC.P11 21-MAY-76 00:00

CROSS REFERENCE TABLE -- USER SYMBOLS

SEQ 0071

.CNTLU	015226	817	3056#			
.CNVRT	014216	811	2857#			
.CONVR	014212	809	2855#			
.EOP	012740	2555	2608#			
.EART	017504	2956	3309#			
.HLT	014536	702	2941#			
.INSTE	013652	801	2758#			
.INSTG	013656	2757	2760#			
.INSTR	013534	799	2734#			
.INST1	013554	2738#	2749	2765		
.MSG	013556	2736*	2739#	3051*	3052*	3053
.PARAM	013704	803	2772#			
.PFAIL	015006	700	830	3000#	3021	
.RESOS	014160	807	2845#			
.SAVOS	014120	805	2631#			
.SCOPE	013270	793	2672#			
.SCOPI	013454	795	2712#			
.SETFL	014436	813	2913#	2924		
.START	001260	712	828#	838	2620	
.TRPSR	014504	704	2930#			
.TRPTA	001226	789#	2935			
.TYPE	013474	797	2720#			

02DUB-C MACY11 27(1006) 01-OCT-76 09:17 PAGE 77

020000C.P11 21-MAY-76 00:00

CROSS REFERENCE TABLE -- MACRO NAMES

SEQ 0072

HLT	612#	1058	1063	1079	1116	1121	1137	1174	1179	1195	1232	1237	1253	1290	1295
	1311	1348	1353	1369	1406	1411	1427	1464	1469	1485	1522	1527	1543	1580	1585
	1601	1638	1643	1659	1696	1701	1717	1751	1756	1772	1806	1811	1827	1861	1866
	1882	1916	1921	1937	1971	1976	1992	2026	2031	2047	2081	2086	2102	2136	2141
	2157	2191	2196	2212	2246	2251	2267	2301	2306	2322	2356	2361	2377	2411	2416
	2432	2466	2471	2487	2521	2526	2542	2576	2581	2597					
PRGENO	552#	2601													
PRGFRT	552#	553													
PUSSYF	552#														
RSETUP	552#	1035	1093	1151	1209	1267	1325	1383	1441	1499	1557	1615	1673	1731	1786
	1841	1896	1951	2006	2061	2116	2171	2226	2281	2336	2391	2446	2501	2556	
TSETUP	552#														
\$BEGIN	552#	984													
\$BINAR	552#														
\$BUFFE	552#	3212													
\$CABLE	552#														
\$CATCH	552#	695													
\$CLRVE	552#	844													
\$CONVR	552#	2852													
\$DNA	552#														
\$EOP	552#	2601													
\$GETFL	552#	895	968	972	976	980	999								
\$GETPA	552#	874	885	905	931	940	1012								
\$GETSY	552#	950													
\$HEADE	552#	553													
\$HLT	552#	2938													
\$INSTR	552#	2731													
\$ISOB	552#														
\$MATCH	552#														
\$MRR	552#														
\$MRRW	552#														
\$MRW	552#														
\$MSG	552#	3077													
\$PARAM	552#	2769													
\$PFAIL	552#	2997													
\$POKE	552#														
\$POKER	552#	1048	1106	1164	1222	1280	1338	1396	1454	1512	1570	1528	1686	1741	1796
	1851	1906	1961	2016	2071	2126	2181	2236	2291	2346	2401	2456	2511	2566	
\$RCNET	552#														
\$RECAC	552#														
\$REG	552#	2828													
\$RESET	552#	1035	1037	1093	1095	1151	1153	1209	1211	1267	1269	1325	1327	1383	1385
	1441	1443	1499	1501	1557	1559	1615	1617	1673	1675	1731	1733	1786	1788	1841
	1843	1896	1898	1951	1953	2006	2008	2061	2063	2116	2118	2171	2173	2226	2228
	2281	2283	2336	2338	2391	2393	2446	2448	2501	2503	2556	2558			
\$RXACT	552#														
\$SCOPE	552#	2669													
\$SCOPI	552#	2709													
\$SETFL	552#	2907													
\$SETVE	552#	696													
\$START	552#	820													
\$STRIP	552#														
\$SYMB0	552#	565													
\$SYNCR	552#	1044	1102	1160	1218	1276	1334	1392	1450	1508	1566	1624	1682		
\$TRAPS	552#	784													
\$TRPAR	552#														

I06

DZDUB-C MACY11 27(1006) 01-OCT-76 09:17 PAGE 78

DZDUBC.P11 21-MAY-76 00:00

CROSS REFERENCE TABLE -- MACRO NAMES

SEQ 0073

\$TRPDE	552#	792	794	796	798	800	802	804	806	808	810	812	814	816	
\$TRPSR	552#	2925													
\$TSTNO	552#	1033	1091	1149	1207	1265	1323	1381	1439	1497	1555	1613	1671	1729	1784
	1839	1894	1949	2004	2059	2114	2169	2224	2279	2334	2389	2444	2499	2554	
\$TYPE	552#	2717													
\$UNIBU	552#														
\$VARIA	552#	715													
\$WORDF	552#														
\$WORDO	552#	1025	1083	1141	1199	1257	1315	1373	1431	1489	1547	1605	1663	1721	1776
	1831	1886	1941	1996	2051	2106	2161	2216	2271	2326	2381	2436	2491	2546	
\$WORDP	552#														

. ABS. 020014 C00

ERRORS DETECTED: 0
DEFAULT GLOBALS GENERATED: 0

DZDUBC,DZDUBCV/CRF/SOL=HELLO.P11,PARA.P11,KEET.P11,DZDUBC.P11
RUN-TIME: 23 34 3 SECONDS
RUN-TIME RATIO: 228/60=3.7
CORE USED: 18K (35 PAGES)

Spooler runtime 10 seconds, 47 KCS, 300 disk reads, 3 disk writes, 73 pages:

Page 17-76 11/11/98 File Loc: PC-9 0079 (002) 000000

[illegible]