


DRAWING 6 OF 15

THIS DRAWING AND SPECIFICATIONS, HEREIN, ARE THE PROPERTY OF DIGITAL EQUIPMENT CORPORATION AND SHALL NOT BE REPRODUCED OR COPIED OR USED IN WHOLE OR IN PART AS THE BASIS FOR THE MANUFACTURE OR SALE OF ITEMS WITHOUT WRITTEN PERMISSION. COPYRIGHT © 1982, DIGITAL EQUIPMENT CORPORATION

REVISIONS

| CHK | CHANGE NO. | REV |
|---|---|---|
| | M8061-MP003 | B |
| | M. MLYNARCZYK | |

digital

| | | | |
|---|---|---|---|
| DRN. T. GIORGIO | DATE 04-MAR-82 | ENG. M. MLYNARCZYK | DATE 9MAR82 |
| CHK'D. R.W. CAUNTER | DATE 9MAR82 | BOARD LOCATION: SHEET 1 OF 1 | |
| SUDCOM:(BOUEN,SCRATCH)RLV6.DRW 03-MAR-82 14:34 | | NEXT HIGHER ASSEMBLY: B-DD-M8061-0 | |
| FIRST USED ON OPTION/MODEL: RLV12 | | | |

TITLE: FIFO BUFFER REGISTER

| SIZE | CODE | NUMBER | REV. |
|---|---|---|---|
| D | CS | M8061-0-RLV6 | B |




DRAWING 7 OF 15

| SIZE | CODE | NUMBER | REV. |
|---|---|---|---|
| D | CS | M8061-0-RLV7 | C |


CONTROL STORE SEQUENCER
M8061-0-RLV8
DRAWING 8 OF 15
8 MIX 74LS151 E78
8 MIX 74LS151 E64
74LS04 E71
74S08 E47
74S74 E55
74S74 E99
74S04 E53
74S157 E41
4x2 MIX
RLV7 MS CLK H
RLV7 CRC ERR H
RLV7 CMP RSLT H
RLV7 MUX DATA H
RLV7 BMPR FLAG H
RLV4 UC OFLW H
RLV5 LIM 0/128 H
RLV5 LIM 127/255 H
RLV4 INITO L
RLV7 A MS CLK H
C HIGH
RLV8 T FLAG L
RLV8 T FLAG H
RLV8 T FLAG X L
RLV8 INSTR 1 H
RLV8 INSTR 0 H
RLV8 INSTR 2 H
RLV8 INSTR 4 H
RLV8 SI H
RLV8 SO H
RLV8 FE L
RLV8 RE L
RLV1 DEV SEL H
RLV3 CRDT H
RLV8 ZERO L
RLV8 T MUX SEL 3 L
RLV8 T MUX SEL 0 H
RLV8 T MUX SEL 1 H
RLV8 T MUX SEL 2 H
RLV8 INSTR 3 L
RLV8 INSTR 9 H
RLV8 CONST 8 H
RLV8 CONST 4 H
RLV8 CONST 7 H
RLV8 CONST 6 H
RLV8 CONST 5 H
RLV8 CONST 3 H
RLV8 CONST 2 H
RLV8 CONST 1 H
RLV8 CONST 0 H
RLV8 US CRT 0 H
RLV8 US CRT 1 H
RLV8 PR ADD 0 H
RLV8 PR ADD 1 H
RLV8 PR ADD 2 H
RLV8 PR ADD 3 H
RLV8 PR ADD 4 H
RLV8 PR ADD 5 H
RLV8 PR ADD 6 H
RLV8 PR ADD 7 H
RLV8 PR ADD 8 H
RLV8 PR ADD 9 H
RLV8 PR OUT 0 H
RLV8 PR OUT 1 H
RLV8 PR OUT 2 H
RLV8 PR OUT 3 H
RLV8 PR OUT 4 H
RLV8 PR OUT 5 H
RLV8 PR OUT 6 H
RLV8 PR OUT 7 H
RLV8 PR OUT 8 H
RLV8 PR OUT 9 H
RLV8 PR OUT 10 H
RLV8 PR OUT 11 H
RLV8 PR OUT 12 H
RLV8 PR OUT 13 H
RLV8 PR OUT 14 H
RLV8 PR OUT 15 H
RLV8 PR OUT 16 H
RLV8 PR OUT 17 H
RLV8 PR OUT 18 H
RLV8 PR OUT 19 H
RLV8 PR OUT 20 H
RLV8 PR OUT 21 H
RLV8 PR OUT 22 H
RLV8 PR OUT 23 H
RLV8 LD CTRL A H
RLV8 LD CTRL B H
RLV8 LD CTRL C H
RLV8 CONST 11 H
RLV8 CONST 10 H
RLV8 CONST 9 H
RLV8 CONST 8 H
RLV8 CONST 7 H
-RLV8 T FLAG X H
-RLV9 SET CRDT L
RLV4 INIT H
RLV8 FATAL PLS H
RLV8 FATAL ERR H
C HIGH
R18 100Ω
1K X 8 PROM 82S181 E20
1K X 8 PROM 82S181 E21
1K X 8 PROM 82S181 E22
MICROPROGRAM 2911 E13
MICROPROGRAM 2911 E12
MICROPROGRAM 2911 E11
8 D FLOP 74LS273 E26
8 D FLOP 74LS273 E27
8 D FLOP 74LS273 E28
REG EN
STACK CONTROL
DIRECT INPUTS
ADR
OUTPUTS
SEL
CLK
CLR
EN
M8061-0-RLV8
B-DD-M8061-0
RLV12
REVISIONS
DRAWN T. BIORDIO
CHK'D R.W. CAUNTER
NEXT HIGHER ASSEMBLY: 03-MAR-82 14:43
SUBCOMP: <BDWEW.SCRATCH>RLV8.DRW
FIRST USED ON OPTION/MODEL:
BOARD LOCATION:
SHEET 1 OF 1
SIZE D CODE CS NUMBER M8061-0-RLV8 REV. B
TITLE: CONTROL STORE SEQUENCER
digital




DRAWING 9 OF 15

"THIS DRAWING AND SPECIFICATIONS, WHEREIN, ARE THE PROPERTY OF DIGITAL EQUIPMENT CORPORATION AND SHALL NOT BE REPRODUCED OR COPIED OR USED IN WHOLE OR IN PART AS THE BASIS FOR THE MANUFACTURE OR SALE OF ITEMS WITHOUT WRITTEN PERMISSION. COPYRIGHT © 1982, DIGITAL EQUIPMENT CORPORATION"

| REVISIONS | | |
|---|---|---|
| CHK | CHANGE NO. | REV |
| M.HLYNARCZYK | M8061-MR003 | B |

| | | | |
|---|---|---|---|
| DRN. T. GIORGIO | DATE 04-MAR-82 | ENG. M.HLYNARCZYK | DATE 9MAR82 |
| CHK'D R.W. CAUNTER | DATE 9MAR82 | BOARD LOCATION: | |
| SUDCOM:<BOWEN.SCRATCH>RLV9.DRW 04-MAR-82 08:02 | | SHEET 1 OF 1 | |
| FIRST USED ON OPTION/MODEL: RLV12 | | NEXT HIGHER ASSEMBLY: B-DD-M8061-0 | |

TITLE: RLV12 CONTROL SIGNALS

| SIZE | CODE | NUMBER | REV. |
|---|---|---|---|
| D | CS | M8061-0-RLV9 | B |




DRAWING 18 OF 15

"THIS DRAWING AND SPECIFICATIONS, HEREIN, ARE THE PROPERTY OF DIGITAL EQUIPMENT CORPORATION AND SHALL NOT BE REPRODUCED OR COPIED OR USED IN WHOLE OR IN PART AS THE BASIS FOR THE MANUFACTURE OR SALE OF ITEMS WITHOUT WRITTEN PERMISSION. COPYRIGHT © 1982 DIGITAL EQUIPMENT CORPORATION"

| REVISIONS | | |
|---|---|---|
| CHK | CHANGE NO. | REV |
| M. HLYNARCZYK | M8061-HR003 | B |

| | | | | | |
|---|---|---|---|---|---|
| DRW. T. GIORGIO | DATE 04-MAR-82 | ENG. M. HLYNARCZYK | DATE 9MAR82 | TITLE: WRITE ENCODE CIRCUIT | |
| CHK'D R.W. CAUNTER | DATE 9MAR82 | BOARD LOCATION: SHEET 1 OF 1 | | | |
| SUDCOM::[BOWEN,SCRATCH]RLVA.DRW 04-MAR-82 07:58 | | NEXT HIGHER ASSEMBLY: B-DD-M8061-0 | | SIZE D / CODE CS / NUMBER M8061-0-RLVA / REV. B | |
| FIRST USED ON OPTION/MODEL: RLV12 | | | | | |




DRAWING 11 OF 15

"THIS DRAWING AND SPECIFICATIONS, HEREIN, ARE THE PROPERTY OF DIGITAL EQUIPMENT CORPORATION AND SHALL NOT BE REPRODUCED OR COPIED OR USED IN WHOLE OR IN PART AS THE BASIS FOR THE MANUFACTURE OR SALE OF ITEMS WITHOUT WRITTEN PERMISSION. COPYRIGHT © 1982, DIGITAL EQUIPMENT CORPORATION"

| REVISIONS | | |
|---|---|---|
| CHK | CHANGE NO. | REV |
| DW | M8061-M8093 | B |
| W. MLYNARCZYK | | |

digital

| | | | | | |
|---|---|---|---|---|---|
| DRN. T. GIORGIO | DATE 04-MAR-82 | ENG. W. MLYNARCZYK | DATE 9MAR82 | TITLE: READ CIRCUIT | |
| CHK'D R.W. CAUNTER | DATE 9MAR82 | BOARD LOCATION: SHEET 1 OF 1 | | | |
| SUDCOM:<BOWEN.SCRATCH>RLVB.DRW 03-MAR-82 14:50 | | NEXT HIGHER ASSEMBLY: B-DD-M8061-0 | | SIZE D | CODE CS |
| FIRST USED ON OPTION/MODEL: RLV12 | | | | NUMBER M8061-0-RLVB | REV. B |




DRAWING 12 OF 15

"THIS DRAWING AND SPECIFICATIONS, HEREIN, ARE THE PROPERTY OF DIGITAL EQUIPMENT CORPORATION AND SHALL NOT BE REPRODUCED OR COPIED OR USED IN WHOLE OR IN PART AS THE BASIS FOR THE MANUFACTURE OR SALE OF ITEMS WITHOUT WRITTEN PERMISSION. COPYRIGHT © 1982, DIGITAL EQUIPMENT CORPORATION"

| REVISIONS | | |
|---|---|---|
| CHK | CHANGE NO. | REV |
| [illegible] | M8061-MA0003 | C |
| M. MLYNARCZYK | | |
| [illegible] 12APR82 | | |

DRN. T. GIORGIO — DATE 03-MAR-82 — ENG. M. MLYNARCZYK — DATE 9MAR82

CHK'D. R.W. CAUNTER — DATE 9MAR82 — BOARD LOCATION: — SHEET 1 OF 1

SUDCOM:<BOWEN.SCRATCH>RLVC.DRW 03-MAR-82 14:55 — NEXT HIGHER ASSEMBLY: B-DD-M8061-0 — FIRST USED ON OPTION/MODEL: RLV12

TITLE: CURRENT PUMP/VCO

| SIZE | CODE | NUMBER | REV. |
|---|---|---|---|
| D | CS | M8061-0-RLVC | C |




DRAWING 13 OF 15

"THIS DRAWING AND SPECIFICATIONS, HEREIN, ARE THE PROPERTY OF DIGITAL EQUIPMENT CORPORATION AND SHALL NOT BE REPRODUCED OR COPIED OR USED IN WHOLE OR IN PART AS THE BASIS FOR THE MANUFACTURE OR SALE OF ITEMS WITHOUT WRITTEN PERMISSION. COPYRIGHT © 1982, DIGITAL EQUIPMENT CORPORATION"

| REVISIONS | | |
|---|---|---|
| CHK | CHANGE NO. | REV |
| W.L.F. | W80611-0-RLVD#1 | B |
| W. HLYNARCZYK | | |

| | | | |
|---|---|---|---|
| DRN. T. GIORGIO | DATE 04-MAR-82 | ENG. W. HLYNARCZYK | DATE 9MAR82 |
| CHK'D. R.W. CAUNTER | DATE 9MAR82 | BOARD LOCATION: | |
| SUDCON:<BOWEN,SCRATCH>RLV0.DRW 03-MAR-82 15:01 | | SHEET 1 OF 1 | |
| FIRST USED ON OPTION/MODEL: RLV12 | | NEXT HIGHER ASSEMBLY: B-DD-M8061-0 | |

TITLE: -5V CHARGE PUMP

| SIZE | CODE | NUMBER | REV. |
|---|---|---|---|
| D | CS | M8061-0-RLVD | B |

MR




DRAWING 14 OF 15

"THIS DRAWING AND SPECIFICATIONS, HEREIN, ARE THE PROPERTY OF DIGITAL EQUIPMENT CORPORATION AND SHALL NOT BE REPRODUCED OR COPIED OR USED IN WHOLE OR IN PART AS THE BASIS FOR THE MANUFACTURE OR SALE OF ITEMS WITHOUT WRITTEN PERMISSION. COPYRIGHT © 1982, DIGITAL EQUIPMENT CORPORATION"

| REVISIONS | | | |
|---|---|---|---|
| CHK | CHANGE NO. | REV |
| M.W.Z. | M8061-WR003 | B |
| J. [illegible] | [illegible] | |
| M. MLYNARCZYK | | |

| | | | |
|---|---|---|---|
| digital | DRN. T. GIORGIO | DATE 04-MAR-82 | ENG. M. MLYNARCZYK |
| | CHK'D. R.W. CAUNTER | DATE 9MAR82 | BOARD LOCATION: |
| SUDCOM::[BOWEN.SCRATCH]RLVE.DRW | 03-MAR-82 15:09 | | SHEET 1 OF 1 |
| FIRST USED ON OPTION/MODEL: RLV12 | | | NEXT HIGHER ASSEMBLY: B-DD-M8061-0 |

DATE 9MAR82

TITLE: DRIVE BUS INTERFACE

| SIZE | CODE | NUMBER | REV. |
|---|---|---|---|
| D | CS | M8061-0-RLVE | B |




DRAWING 15 OF 15

"THIS DRAWING AND SPECIFICATIONS, HEREIN, ARE THE PROPERTY OF DIGITAL EQUIPMENT CORPORATION AND SHALL NOT BE REPRODUCED OR COPIED OR USED IN WHOLE OR IN PART AS THE BASIS FOR THE MANUFACTURE OR SALE OF ITEMS WITHOUT WRITTEN PERMISSION. COPYRIGHT © 1982, DIGITAL EQUIPMENT CORPORATION"

| REVISIONS | | |
|---|---|---|
| CHK | CHANGE NO. | REV |
| TWC | M8061-MR003 | B |
| H. HLYNARCZYK | | |

| | | | | | |
|---|---|---|---|---|---|
| digital | DRN. T. GIORGIO | DATE 04-MAR-82 | ENG. H. HLYNARCZYK | DATE 9MAR82 | TITLE: CAPS |
| | CHK'D A. W. CAUNTER | DATE 9MAR82 | BOARD LOCATION: SHEET 1 OF 1 | | |
| SUDCON:<BOWEN,SCRATCH>RLVF.DRW 03-MAR-82 15:18 | | | NEXT HIGHER ASSEMBLY: B-DD-M8061-0 | | |
| FIRST USED ON OPTION/MODEL: RLV12 | | | | | |

| SIZE | CODE | NUMBER | REV. |
|---|---|---|---|
| D | CS | M8061-0-RLVF | B |

THIS DRAWING AND SPECIFICATIONS, HEREIN, ARE THE PROPERTY OF DIGITAL EQUIPMENT CORPORATION AND SHALL NOT BE REPRODUCED OR COPIED OR USED IN WHOLE OR IN PART AS THE BASIS FOR THE MANUFACTURE OR SALE OF ITEMS WITHOUT WRITTEN PERMISSION.
COPYRIGHT © 1981 DIGITAL EQUIPMENT CORPORATION




DETAIL "A"
SCALE: NONE




VIEW B-B
SCALE: NONE
(WITH STRAIN RELIEF REMOVED, ITEM #8)




VIEW A-A
SCALE: NONE
(WITH ITEM #3 & ITEM #4 ASSEMBLED)







| LEGEND | | |
|---|---|---|
| NUMBER | DIM "X" VARIATION | DIM "Y" (PRECUT) REF |
| BC80M-06 | 6FT-0IN ±2IN | 6FT-8.0 IN |
| BC80M-10 | 10FT-0IN ±2IN | 10FT-8.0 IN |
| BC80M-15 | 15FT-0IN ±2IN | 15FT-8.0 IN |
| BC80M-25 | 25FT-0IN ±3IN | 25FT-10.5 IN |
| BC80M-50 | 50FT-0IN ±3IN | 50FT-10.5 IN |
| BC80M-A0 | 100FT-0IN ±3IN | 100FT-10.5 IN |
| BC80M-12 | 12FT-0IN ±2IN | 12FT-8.0 IN |

NOTES:

FOR NOTES SEE SHEET 2

FOR WIRE TABLE SEE SHEET 2

CAUTION: OFF SHEET PARTS LIST EXISTS.
SEE K-PL-BC80M-0-DBP

| REVISION HISTORY | | | |
|---|---|---|---|
| DATE | ECO NUMBER | REV | |
| 7-APR-81 | INITIAL | A | B FITCH |
| 29-JUN-81 | BC80M-MR001 | B | B FITCH |
| 2-SEP-81 | BC80M-MR001 | C | B FITCH |

UNLESS OTHERWISE SPECIFIED DIMENSIONS ARE IN INCHES AND THE FOLLOWING TOLERANCES APPLY (PER DEC STD 114)

INCHES TOLERANCES: X = ± .1, XX = ± .02, XXX = ± .005
ANGLES ± 0° 30'
SURFACE QUALITY: MICROINCHES
APPLICABLE DIMENSION RANGE (CHECK ONE)
DIMENSION RANGE IN INCHES: OVER 0 TO 6.0; OVER 6.0 TO 12.0; OVER 12.0 TO 48.0; OVER 48.0 TO 96.0
± .02 | ± .05 | ± .08 | ± .10
± .004 | ± .005 | ± .012 | ± .016 | ± .024 | ± .04
QUANTITY & VARIATION
THIRD ANGLE PROJECTION
DO NOT SCALE DRAWING
REMOVE BURRS AND BREAK SHARP CORNERS
MATERIAL: SEE PARTS LIST
FINISH

| | | |
|---|---|---|
| DRN | Jim Dunbar | DATE 15 JULY 81 |
| CHK'D | Jim Hurd | DATE 3-Sept-81 |
| DES. ENG. | Robert Fitch | DATE 14-SEP-81 |
| PROJ. ENG. | Robert Fitch | DATE 14-SEP-81 |
| MFG. | | DATE |
| NEXT HIGHER ASSY | | |

TITLE: I/O CABLE (BC80M)
digital
DOCUMENT NUMBER: CODE DUA, NUMBER BC80M-0-0, REV C
SCALE — SHEET — OF 2

BC80M-0-0 C

"THIS DRAWING AND SPECIFICATIONS, HEREIN, ARE THE PROPERTY OF DIGITAL EQUIPMENT CORPORATION AND SHALL NOT BE REPRODUCED OR COPIED OR USED IN WHOLE OR IN PART AS THE BASIS FOR THE MANUFACTURE OR SALE OF ITEMS WITHOUT WRITTEN PERMISSION.
COPYRIGHT © 1981 DIGITAL EQUIPMENT CORPORATION"



## WIRE TABLE

| ITEM NO. | WIRE LENGTH TO CABLE JACKET | DESCRIPTION TWP | COLOR | FROM CONN | FROM TERM | TO CONN | TO TERM | SIGNAL NAME | REMARKS |
|---|---|---|---|---|---|---|---|---|---|
| 1 | | — | ——— | P1-1 | —— | P2-A | —— | ——— | NO CONN |
| | | — | ——— | P1-2 | —— | P2-B | —— | ——— | |
| | 2.50 | TWP | RED | P1-3 | —— | P2-C | ITEM*11 | DRV ERR + | ——— |
| | 2.50 | | WHT/RED | P1-4 | —— | P2-D | | DRV ERR − | ——— |
| | 2.38 | TWP | RED | P1-5 | —— | P2-E | | DRV RDY + | ——— |
| | 2.38 | | WHT/GRN | P1-6 | —— | P2-F | | DRV RDY − | ——— |
| | 2.25 | TWP | RED | P1-7 | —— | P2-H | | SEC PLS + | ——— |
| | 2.25 | | WHT/ORN | P1-8 | —— | P2-J | ITEM*11 | SEC PLS − | ——— |
| | ——— | — | ——— | P1-9 | —— | P2-K | —— | ——— | NO CONN |
| | ——— | — | ——— | P1-10 | —— | P2-L | —— | ——— | |
| | 2.00 | TWP | RED | P1-11 | —— | P2-M | ITEM*11 | STAT CLK + | ——— |
| | 2.00 | | WHT/YEL | P1-12 | —— | P2-N | ITEM*11 | STAT CLK − | ——— |
| | ——— | — | ——— | P1-13 | —— | P2-P | —— | ——— | NO CONN |
| | ——— | — | ——— | P1-14 | —— | P2-R | —— | ——— | |
| | 1.75 | TWP | RED | P1-15 | —— | P2-S | ITEM*11 | STAT IN + | ——— |
| | 1.75 | | WHT/BLK/RED | P1-16 | —— | P2-T | ITEM*11 | STAT IN − | ——— |
| | ——— | — | ——— | P1-17 | —— | P2-U | —— | ——— | NO CONN |
| | ——— | — | ——— | P1-18 | —— | P2-V | —— | ——— | |
| | 1.62 | TWP | RED | P1-19 | —— | P2-W | ITEM*11 | READ DATA+ | ——— |
| | 1.62 | | WHT/BLK/ORN | P1-20 | —— | P2-X | | READ DATA− | ——— |
| | 1.50 | TWP | RED | P1-21 | —— | P2-Y | | DRIVE CMND+ | ——— |
| 1 | 1.50 | | WHT/BLK/BLU | P1-22 | —— | P2-Z | ITEM*11 | DRIVE CMND− | ——— |

## WIRE TABLE

| ITEM NO. | WIRE LENGTH TO CABLE JACKET | DESCRIPTION TWP | COLOR | FROM CONN | FROM TERM | TO CONN | TO TERM | SIGNAL NAME | REMARKS |
|---|---|---|---|---|---|---|---|---|---|
| 1 | | — | ——— | P1-23 | —— | P2-AA | —— | ——— | NO CONN |
| | | — | ——— | P1-24 | —— | P2-BB | —— | ——— | |
| | .38 | TWP | RED | P1-25 | —— | P2-CC | ITEM*11 | WRT DATA − | ——— |
| | .38 | | WHT/BLK/BRN | P1-26 | —— | P2-DD | ITEM*11 | WRT DATA + | ——— |
| | ——— | — | ——— | P1-27 | —— | P2-EE | —— | ——— | NO CONN |
| | ——— | — | ——— | P1-28 | —— | P2-FF | —— | ——— | |
| | 1.25 | TWP | RED | P1-29 | —— | P2-HH | ITEM*11 | SYS CLK − | ——— |
| | 1.25 | | WHT/GRN/RED | P1-30 | —— | P2-JJ | ITEM*11 | SYS CLK + | ——— |
| | ——— | — | ——— | P1-31 | —— | P2-KK | —— | ——— | NO CONN |
| | ——— | — | ——— | P1-32 | —— | P2-LL | —— | ——— | |
| | .13 | TWP | RED | P1-33 | —— | P2-MM | ITEM*11 | WRT GATE − | ——— |
| | .13 | | WHT/GRN/BLU | P1-34 | —— | P2-NN | | WRT GATE + | ——— |
| | 1.00 | TWP | RED | P1-35 | —— | P2-PP | | DRV SEL1 − | ——— |
| | 1.00 | | WHT/GRN/YEL | P1-36 | —— | P2-RR | | DRV SEL1 + | ——— |
| | .88 | TWP | RED | P1-37 | —— | P2-SS | | DRV SELØ − | ——— |
| | .88 | | WHT/GRN/BRN | P1-38 | —— | P2-TT | | DRV SELØ + | ——— |
| | .75 | TWP | YEL | P1-39 | —— | P2-UU | ITEM*11 | DC OK | ——— |
| | ——— | | WHT | ——— | —— | ——— | —— | ——— | SEE NOTE 1 |
| 1 | 1.75 | — | BLK | P1-40 | —— | P2-VV | ITEM*12 | GND | SEE NOTE 1 |




SECTION C-C
SCALE: NONE

NOTES:

1. THE DRAIN WIRE AND INNER GND WIRE MUST BE PREPARED AS FOLLOWS BEFORE TERMINATING CABLE TO PLUG ON BOTH ENDS OF WIRE.
   A. CUT BACK THE CENTER BLACK GND WIRE 0.4±0.1 INCH ABOVE JACKET, STRIP END 0.25 ± .06 INCH.
   B. FIND AND SEPARATE THE SOLID WHITE AND YELLOW PAIRED WIRES. CUT THE WHITE WIRE FLUSH WITH JACKET. STRIP END OF LOOSE WHITE WIRE 0.25 ± .06 INCH
   C. POSITION STRIPPED END OF WHITE WIRE PARALLEL TO THE STRIPPED END OF THE BLACK GND WIRE. WRAP THE DRAIN WIRE AROUND THE STRIPPED END OF THE BLACK AND WHITE WIRE 2-4 TIMES. SOLDER WIRE SPLICE AND CUT OFF END OF DRAIN FLUSH WITH SPLICE.
   D. COVER SPLICE WITH 0.5 ± .06 INCH OF SHRINK TUBING, ITEM 4, TWIST THE WHITE AND YELLOW WIRES (PREVIOUSLY SEPARATED) BACK TOGETHER FOR APPROXIMATELY (3) THREE INCHES.
2. SCREWS (2 X 3LG SELFTAPPING) ARE PART OF PLUG HOUSING AND CAMSHAFT KIT(ITEM#2).
3. REF ONLY CONTACT(DEC PART NO.12111591-27) FOR REPLACEMENT ONLY.
4. PRIOR TO SNAPPING SIDES OF PLUG HOUSING TOGETHER CARE SHOULD BE TAKEN TO ASSURE THAT ALL WIRES ARE SUFFICENTLY WITHIN HOUSING TO PREVENT PINCHING OF INDIVIDUAL STRANDS.
5. CABLE TO BE MARKED WITH PART NUMBER BC80M AND REV IN AREA SHOWN.
6. * DENOTES CAVITIES NOT TO BE USED OR DESIGNATED BY LETTERS.

| REVISION HISTORY | | |
|---|---|---|
| DATE | ECO NUMBER | REV. |
| | | |

DRD 137A

TITLE I/O CABLE (BC80M)

| DOCUMENT NUMBER | | | |
|---|---|---|---|
| SIZE | CODE | NUMBER | REV. |
| D | UA | BC80M-0-0 | C |
| SCALE — | | SHEET 2 OF 2 | |

MR