

RK11/C/D

ZRKJE0

RK11 BASIC LOGIC TEST #1

ABSTRACT :

This program is part 1 of 2 and it checks only the drive-independent logic of the RK11 controller, no drive is needed. After this test run part 2 (ZRKKxx).

OPERATING PROCEDURES :

.R ZRKJE0

The program will print:

END PASS # 1

END PASS # 2

SWITCH SETTINGS :

SW15= 1 halt on error

SW14= 1 loop on test

SW13= 1 inhibit error typeout

SW12= 1 loop on error

SW11= 1 inhibit iterations

SW10= 1 testing on simulator

SW09= 1 loop on specific error

SW08= 1 loop on test as per SW<07-00>

use "CONTROL G" to enter software SWR at loc. 176